101LABS® Cisco CCNP

LEARN • BY • DOING

Paul Browning
Farai Tafa

https://t.me/learningnets

101 Labs – Cisco CCNP

Hands-on Practical Labs for the SWITCH, ROUTE and TSHOOT Exams

Paul Browning, LLB (Hons), CCNP, MCSE
Farai Tafa, dual CCIE

https://t.me/learningnets

https://t.me/learningnets

This study guide and/or material is not sponsored by, endorsed by or affiliated with Cisco Systems, Inc. Cisco®, Cisco Systems®, CCDA™, CCNA™, CCDP™, CCNP™, CCIE™, CCSI™, the Cisco Systems logo, and the CCIE logo are trademarks or registered trademarks of Cisco Systems, Inc., in the United States and certain other countries. All other trademarks are trademarks of their respective owners.

101 Labs is a registered trademark.

Copyright Notice

Copyright © 2019 Paul Browning, all rights reserved. No portion of this book may be reproduced mechanically, electronically, or by any other means, including photocopying without written permission of the publisher.

https://www.101labs.net

ISBN: 9781091835412

Published by:

Reality Press Ltd.

Legal Notice

The advice in this book is designed to help you achieve the standard of Cisco Certified Network Professional, which is Cisco's advanced internetworking examination. A CCNP is able to carry out advanced router and switch installations and troubleshooting for small to enterprise-level networks. Before you carry out more complex operations, it is advisable to seek the advice of experts or Cisco Systems, Inc.

The practical scenarios in this book are meant only to illustrate a technical point and should be used only on your privately owned equipment and never on a live network.

https://t.me/learningnets

Table of Contents

Introduction – 101 Labs 2
101 Labs – Cisco CCNP 3
    Doing the Labs 3
101 Labs – Cisco CCNP Video Course 5
    Instructions 5
    Also from Reality Press Ltd. 5
CCNP Lab 001: VLANs, VTP, DTP and STP 6
CCNP Lab 002: VLANs, VTP, DTP and STP 13
CCNP Lab 003: LACP, PAgP, Multiple STP 21
CCNP Lab 004: MLS, EtherChannels and Security 31
CCNP Lab 005: DHCP, Source Guard and 802.1X 42
CCNP Lab 006: HSRP and Switch Security 47
CCNP Lab 007: HSRP and STP Convergence 55
CCNP Lab 008: SNMP, Logging and Management 64
CCNP Lab 009: QoS, Voice and Video Support 72
CCNP Lab 010: Router, Port and VLAN ACLs 81
CCNP Lab 011: Private Vlans 89
CCNP Lab 012: RIPv2 Lab 96
CCNP Lab 013: RIPv2 Redistribution into EIGRP 115
CCNP Lab 014: EIGRP Multi-Technology 126
CCNP Lab 015: EIGRP Multi-Technology Lab 133
CCNP Lab 016: EIGRP Multi-Technology Lab 140
CCNP Lab 017: EIGRP Multi-Technology Lab 150
CCNP Lab 018: EIGRP Multi-Technology Lab 159
CCNP Lab 019: EIGRP Multi-Technology Lab 168
CCNP Lab 020: EIGRP Multi-Technology Lab 176
CCNP Lab 021: EIGRP Multi-Technology Lab 187
CCNP Lab 022: EIGRP Multi-Technology Lab 196

https://t.me/learningnets

CCNP Lab 023: EIGRP Multi-Technology Lab 202
CCNP Lab 024: OSPF Multi-Technology Lab 209
CCNP Lab 025: OSPF Multi-Technology Lab 217
CCNP Lab 026: OSPF Multi-Technology Lab 228
CCNP Lab 027: OSPF Multi-Technology Lab 237
CCNP Lab 028: OSPF Multi-Technology Lab 249
CCNP Lab 029: OSPF Multi-Technology Lab 257
CCNP Lab 030: OSPF Multi-Technology Lab 266
CCNP Lab 031: OSPF Multi-Technology Lab 278
CCNP Lab 032: OSPF Multi-Technology Lab 290
CCNP Lab 033: OSPF Multi-Technology Lab 300
CCNP Lab 034: Border Gateway Protocol Lab 311
CCNP Lab 035: Border Gateway Protocol Lab 322
CCNP Lab 036: Border Gateway Protocol Lab 332
CCNP Lab 037: Border Gateway Protocol Lab 344
CCNP Lab 038: Border Gateway Protocol Lab 352
CCNP Lab 039: Border Gateway Protocol Lab 361
CCNP Lab 040: Border Gateway Protocol Lab 372
CCNP Lab 041: Border Gateway Protocol Lab 384
CCNP Lab 042: Border Gateway Protocol Lab 392
CCNP Lab 043: Border Gateway Protocol Lab 402
CCNP Lab 044: IPv6 RIPng Lab 413
CCNP Lab 045: IPv6 RIPng and OSPFv3 Lab 422
CCNP Lab 046: IPv6 OSPFv3 Lab 435
CCNP Lab 047: IPv6 MP-BGP Lab 445
CCNP Lab 048: LLDP and DHCPv6 455
CCNP Lab 049: IPv6 Tunnels and OSPFv3 Lab 468
CCNP Lab 050: IPv6 Tunnels and Security Lab 475
CCNP Lab 051: IPv6 Tunnels and MP-BGP Lab 483
CCNP Lab 052: IPv6 Tunnels and MP-BGP Lab 488
CCNP Lab 053: IPv6 GRE Tunnels and RIPng Lab 498

https://t.me/learningnets

CCNP Lab 054: Cisco IOS IP SLA and FHRP Lab 504
CCNP Lab 055: Cisco IOS EOT and FHRP Lab 513
CCNP Lab 056: Cisco IOS IP SLA and BGP Lab 519
CCNP Lab 057: Cisco Policy-Based Routing Lab 525
CCNP Lab 058: Cisco Policy-Based Routing Lab 532
CCNP Lab 059: Cisco Policy-Based Routing Lab 539
CCNP Lab 060: Cisco IOS PBR, SLA and EOT Lab 546
CCNP Lab 061: Cisco IOS GLBP Lab 556
CCNP Lab 062: Cisco IOS GLBP Lab 563
CCNP Lab 063: Cisco IOS IP SLA and GLBP Lab 571
CCNP Lab 064: Embedded Event Manager Lab 582
CCNP Lab 065: Embedded Event Manager Lab 587
CCNP Lab 066: Syslog and NTP Lab 591
CCNP Lab 067: SNMP Traps and Informs Lab 596
CCNP Lab 068: NetFlow and Accounting Lab 601
CCNP Lab 069: Cisco IOS NBAR Lab 606
CCNP Lab 070: Cisco IOS RITE and SPAN Lab 612
CCNP Lab 071: Cisco IOS RITE and RSPAN Lab 616
CCNP Lab 072: Syslog and SNMP Lab 622
CCNP Lab 073: Multicast - PIM Dense Mode Lab 628
CCNP Lab 074: Multicast - PIM Sparse Mode Lab 634
CCNP Lab 075: Multicast - PIM Auto RP Lab 641
CCNP Lab 076: Branch Office Connectivity Lab 649
CCNP Lab 077: Branch Office Connectivity Lab 660
CCNP Lab 078: PPP over Ethernet (PPPoE) Lab 668
CCNP Lab 079: PPP over Ethernet (PPPoE) Lab 673
CCNP Lab 080: Branch Office Connectivity Lab 681
CCNP Lab 081: CCNP Multi-Technology Lab 687
CCNP Lab 082: CCNP Multi-Technology Lab 704
CCNP Lab 083: CCNP Multi-Technology Lab 723
CCNP Lab 084: CCNP Multi-Technology Lab 739

https://t.me/learningnets

CCNP Lab 085: CCNP Multi-Technology Lab 758
CCNP Lab 086: Troubleshooting Lab 781
CCNP Lab 087: Troubleshooting Lab 784
CCNP Lab 088: Troubleshooting Lab 788
CCNP Lab 089: Troubleshooting Lab 791
CCNP Lab 090: Troubleshooting Lab 795
CCNP Lab 091: Troubleshooting Lab 799
CCNP Lab 092: Troubleshooting Lab 803
CCNP Lab 093: Troubleshooting Lab 806
CCNP Lab 094: Troubleshooting Lab 809
CCNP Lab 095: Troubleshooting Lab 813
CCNP Lab 096: Troubleshooting Lab 817
CCNP Lab 097: Troubleshooting Lab 821
CCNP Lab 098: Troubleshooting Lab 824
CCNP Lab 099: Troubleshooting Lab 827
CCNP Lab 100: Troubleshooting Lab 831
CCNP Lab 101: EIGRP and OSPF VRF Lite Lab 834

https://t.me/learningnets

Introduction – 101 Labs

Welcome to your 101 Labs book.

When I started teaching IT courses back in 2002, I was shocked to discover that most training manuals were almost exclusively dedicated to theoretical knowledge. Apart from a few examples of commands to use or configuration guidelines, you were left to plow through without ever knowing how to apply what you learned to live equipment or to the real world.

Fast forward 17 years and little has changed. I still wonder how, when around 50% of your exam marks are based on hands-on skills and knowledge, most books give little or no regard to equipping you with the skills you need to both pass the exam and then make money in your chosen career as a network, security, or cloud engineer (or whichever career path you choose).

101 Labs is NOT a theory book: it's here to transform what you have learned in your study guides into valuable skills you will be using from day one on your job as a network engineer. Farai and I don't teach DHCP, for example; instead, we show you how to configure a DHCP server, which addresses you shouldn't use, and which parameters you can allocate to hosts. If the protocol isn't working, we show you what the probable cause is. Sound useful? We certainly hope so.

We choose the most relevant parts of the exam syllabus and use free software or free trials (whenever possible) to walk you through configuration and troubleshooting commands step by step. As your confidence grows, we increase the difficulty level. If you want to be an exceptional IT engineer, you can make your own labs up, add other technologies, try to break them, fix them, and do it all over again.

We recommend you get some hands-on time with live Cisco equipment because it differs from network simulation tools. See below for more information.

Paul Browning

https://t.me/learningnets

101 Labs – Cisco CCNP

This book is designed to cement the theory you have read in your CCNP study guide or video training course. If you haven't studied any theory yet, then please check out our website https://www.howtonetwork.com, which also features practice exams. Our CCNP Simplified range of study guides for the ROUTE, SWITCH, and TSHOOT exams is still available on Amazon but has not been updated for the latest versions because so few students have decided to take the exams after passing the CCNA. The guides still contain around 85% of the current exam topics and so are well worth checking out.

The goal of this book is to dramatically improve your hands-on skills and speed, enabling you to succeed in the practical portions of the CCNP exams and also to transfer your skills to the real world as a CCNP-level network engineer. We don't have space here to cover theory at all, so please refer to your CCNP study guide to get a good understanding of the learning points behind each lab. Every lab is designed to cover a particular theoretical issue, such as the configuration requirements of RIP passive interfaces.

If you want to become CCNP Routing and Switching (CCNP RS) certified, you must pass three exams:

300-101 ROUTE – Implementing Cisco IP Routing (ROUTE)

300-115 SWITCH – Implementing Cisco IP Switched Networks (SWITCH)

300-135 TSHOOT – Troubleshooting and Maintaining Cisco IP Networks (TSHOOT)

It's been a very painstaking process to decide which subjects to include in this guide. You must have a very deep understanding of core topics (such as OSPF), so they're a no-brainer, but others mentioned only in passing in the exam syllabus are still included. In the exam, you are told you need to 'describe' a certain technology (such as RIPng), but it's hard to describe any technology you have never configured, so configuration exercises are included. We've removed topics which were removed from the latest exam syllabus, such as QoS. Others we have added or left because they are either specifically mentioned in the syllabus or alluded to. We've added bonus labs to the resources page just in case you want to learn the technology (such as QoS).

Cisco also inserts test questions that are not marked, so don't sweat it if something out of the ordinary appears. (I took a Cisco switching exam once, and an EIGRP routing question appeared on the screen!) Do your best to answer it and move on. Remember also that Cisco reserves the right to add questions about any topic even if it's not listed in the syllabus, and we simply can't anticipate those in this book.

https://t.me/learningnets

The main lab topic is mentioned in the title, but most labs feature several other protocols and services, so don't worry if you can't see a specific topic listed. Passive interfaces are included in the syllabus, for example, and although we don't list a specific lab for this, we do configure them several times throughout this guide. The same goes for NTP, DHCP, and other services and protocols.

It's also worth noting that once we show you how to configure a certain service or protocol a few times, we stop walking you through the steps in subsequent labs—to save valuable space. Anyway, you can always flick back a few pages to see how it's done. Also, at over 1100 pages, this book simply had to be trimmed down to save trees, so all running configurations and basic configs for the troubleshooting labs and bonus labs are now only downloadable from https://www.101labs.net/resources.

We've done our best to keep the topology as simple as possible, but many advanced topics require multiple routers and switches. If possible, use GNS3 so you can quickly add routers and interfaces to match our topology. If you have a different setup or live rack, then, of course, you need to make adjustments—for example, our serial interface is S1/0, but your rack might be S0/1/0. At the CCNP level, you should be able to deal with this easily. We are working on a downloadable vRack as I write this introduction, so please come to https://www.101labs.net to see if it's live. You should be able to run all your labs inside our VM. You always need to use your own IOS with GNS3 because Cisco own the copyright to these.

Before you start configuring the labs in this guide, it's very important that you have a strong grasp of all the current CCNA-level subjects because we jump right into CCNP level from Lab 1. If you need to brush up on your hands-on CCNA skills, please check out our book 101 Labs – Cisco CCNA (the new edition has a red-and-white cover). You will find there are many topic overlaps between CCNA and CCNP, and it will provide you with a very solid base from which to start these labs.

Please do check out our resources page, which will cover any additional information you need, the running configurations for all your labs, and other stuff which will help you:

https://www.101labs.com/resources

Doing the Labs

Up until recently, all CCNP students used home racks to study for their exams. There were no online rental CCNP racks, and CCIE-level racks were usually too expensive and overkill for CCNP level. Cisco has made its network simulation tool Packet Tracer free to download now, but it is completely unsuitable for CCNP-level study. Many

https://t.me/learningnets

commands you will need are not supported, and important debugs won't work. You must avoid it for CCNP labs, and none of the labs in this guide will work in Packet Tracer, so please don't try.

GNS3 has made a big difference to Cisco students, allowing them to study from home using the software and any IOS image they could get their hands on. A huge limitation was a lack of Layer 2 support, meaning that STP, VLANs, SPAN, etc., couldn't be used on the platform. This has now changed, so please refer to www.gns3.com for details and instructions if you want to use it to complete the labs.

There is a live rack on https://www.101labs.com if you need to use it. It's available for members only. See below for details. Please also visit our website for any vRack solutions we have devised for you to use.

You can also use a home rack if you have the equipment. For around $500 you should be able to obtain switches and routers and all cables. Either buy the equipment individually or buy a pre-created CCNP rack from sellers you can find on sites such as eBay and Amazon. You should be able to sell it once you have finished with it.

It's very important to note that you need to match our interface numbers and cabling. If you make any changes when you create your own rack or GNS3 topology, then you will need to note which interface numbers you use. We used GNS3 for almost all of our labs, but for some, we jumped onto our live racks.

If you get stuck or things aren't working, we recommend you take a break and come back to the lab later with a clear mind.

Please bear in mind that some Cisco IOS commands change over time. We have found this in technology such as IP SLA, where the configuration command 'ip sla monitor 1' has changed to 'ip sla 1' (other configuration commands and show commands have changed as well). Commands can even vary between platforms, so if a particular command isn't working, check your documentation. Some IOS releases support advanced routing and security features. If you don't see whether a command is available, then check the Cisco website.

Best of luck with your studies,

Paul Browning, CCNP

Farai Tafa, CCIE (RS & SP) 14811

https://t.me/learningnets

101 Labs – Cisco CCNP Video Course

All of our 101 Labs books have a walkthrough video for each lab, hosted on https://www.101labs.net. We only mention this in case you want an extra boost. We add a new certification every two months, and each course comes with 200 exam-style questions. Please use the below coupon code to get a discount off your joining fee:

101ccnp

Instructions

1. Please follow the labs from start to finish. If you get stuck, do the next lab and come back to the problem lab later. There is a good chance you will work out the solution as you gain confidence and experience in configuring the software and using the commands.
2. You can take the labs in any order, but we've done our best to group them into SWITCH, ROUTE, and TSHOOT, although some topics may be included in later labs for better flow. For best results, do ALL the labs several times over before attempting the exam.
3. There are resources as well as configuration files for all the labs at www.101labs.net/resources.
4. Please DO NOT configure these labs on a live network or on equipment belonging to private companies or individuals.
5. Please DO NOT attempt to configure these labs on Packet Tracer. They simply will not work due to limitations of the software (it really only supports CCNA level).
6. You MUST be reading or have read a CCNP study guide or watched a theory video course. Apart from some configuration tips and suggestions, we don't explain much theory in this book; it's all hands-on labs. We presume you know (for example) when you need to use a crossover cable (router to router or PC to router or switch to switch) or a straight-through (PC to switch or router to switch). We don't point this out in most of the network diagrams.
7. It's impossible for us to give individual support to the thousands of readers of this book (sorry!), so please don't contact us for tech support. Each lab has been tested by several tech editors from beginner to expert.

https://t.me/learningnets

Also from Reality Press Ltd.

Cisco CCNA Simplified

Cisco CCDA Simplified

Cisco CCDP Simplified

Cisco CCNA in 60 Days

IP Subnetting – Zero to Guru

101 Labs – CompTIA A+ (due 2019)

101 Labs – CompTIA Network+

101 Labs – IP Subnetting

101 Labs – Cisco CCNP (due 2019)

101 Labs – Wireshark WCNA (due 2019)

https://t.me/learningnets

CCNP Lab 001: VLANs, VTP, DTP and STP

Lab Objective:

The focus of this lab is to understand basic VLAN, VTP, DTP and STP implementation and configuration in Cisco IOS Catalyst switches.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please begin each and every lab by shutting down all interfaces on all switches and then manually re-enabling only the interfaces that are illustrated in this topology.

Task 1

Enable and configure VTP on the switches illustrated in the topology as follows:

- All switches should reside in VTP domain 'SWITCH'
- All switches should run VTP version 2
- All switches should allow VLAN creation, deletion and modification
- All switches should use a VTP password of 'CCNP'

Task 2

Configure trunking on the switches as follows:

- Configure ALS1 so that its interfaces will only trunk if the upstream switch is trunking
- Configure ALS2 so that its interfaces will only trunk if the upstream switch is trunking
- Configure DLS1 so that its interfaces will actively attempt to become trunk links

https://t.me/learningnets

- Configure DLS2 so that its interfaces will actively attempt to become trunk links

Task 3

Configure the following VLANs only on switch DLS1:

- VLAN 100 name USER-VLAN
- VLAN 200 name FILE-VLAN

Configure switch DLS1 so that Cisco IOS software automatically elects it as the root bridge for both VLANs without explicitly specifying a priority value. Ensure that switch DLS2 is also automatically elected backup root bridge for both VLANs.

Task 4

Configure Spanning Tree on switches ALS1 and ALS2 as follows:

- Port Fa0/7 on ALS1 and port Fa0/9 on ALS2 should be forwarding for VLAN 100
- Port Fa0/9 on ALS1 and port Fa0/7 on ALS2 should be forwarding for VLAN 200

Task 5

Configure your 802.1D network to improve convergence as follows:

- Backup ports on Access layer switches should transition to forwarding in 1 to 5 seconds following the failure of the primary link to the root bridge
- In the event of an indirect link failure, the network should converge within 30 seconds instead of the typical 50 seconds

Lab Validation:

Task 1

DLS1(config)#**vtp domain SWITCH**
Changing VTP domain name from null to SWITCH
DLS1(config)#**vtp version 2**
DLS1(config)#**vtp password CCNP**
Setting device VLAN database password to CCNP

DLS2(config)#**vtp domain SWITCH**
Changing VTP domain name from null to SWITCH

https://t.me/learningnets

DLS2(config)#**vtp version 2**
DLS2(config)#**vtp password CCNP**
Setting device VLAN database password to CCNP

ALS1(config)#**vtp domain SWITCH**
Changing VTP domain name from null to SWITCH
ALS1(config)#**vtp version 2**
ALS1(config)#**vtp password CCNP**
Setting device VLAN database password to CCNP

ALS2(config)#**vtp domain SWITCH**
Changing VTP domain name from null to SWITCH
ALS2(config)#**vtp version 2**
ALS2(config)#**vtp password CCNP**
Setting device VLAN database password to CCNP

Task 2

ALS1(config)#**interface range f0/7 , f0/9**
ALS1(config-if-range)#**switchport mode dynamic auto**

ALS2(config)#**interface range f0/7 , f0/9**
ALS2(config-if-range)#**switchport mode dynamic auto**

DLS1(config)#**int range f0/7 , f0/9 , f0/11**
DLS1(config-if-range)#**switchport mode dynamic desirable**

DLS2(config)#**int range f0/7 , f0/9 , f0/11**
DLS2(config-if-range)#**switchport mode dynamic desirable**

Verify your configuration using the **show interfaces trunk** command as follows:

DLS2#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 desirable n-802.1q trunking 1
Fa0/9 desirable n-802.1q trunking 1
Fa0/11 desirable n-isl trunking 1

DLS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 desirable n-802.1q trunking 1
Fa0/9 desirable n-802.1q trunking 1
Fa0/11 desirable n-isl trunking 1

ALS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan

https://t.me/learningnets

Fa0/7 auto 802.1q trunking 1
Fa0/9 auto 802.1q trunking 1

ALS2#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 auto 802.1q trunking 1
Fa0/9 auto 802.1q trunking 1

NOTE: Catalyst 3550 series switches (which are used in the racks) support both ISL and 802.1Q and will attempt to negotiate an ISL trunk first. However, the modern Catalyst switches only support 802.1Q and will dynamically negotiate an 802.1Q trunk.

Task 3

DLS1(config)#**vlan 100**
DLS1(config-vlan)#**name USER-VLAN**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 200**
DLS1(config-vlan)#**name FILE-VLAN**
DLS1(config-vlan)#**exit**
DLS1(config)#**spanning-tree vlan 100 root primary**
DLS1(config)#**spanning-tree vlan 200 root primary**

DLS2(config)#**spanning-tree vlan 100 root secondary**
DLS2(config)#**spanning-tree vlan 200 root secondary**

Verify your configuration using the **show spanning-tree root** command as follows:

DLS1#**show spanning-tree root**

Root Hello Max Fwd
Vlan Root ID Cost Time Age Dly Root Port
---------- ---------- ---------- ----- --- --- ----------
VLAN0100 24676 000f.2303.2d80 0 2 20 15
VLAN0200 24776 000f.2303.2d80 0 2 20 15

DLS2#**show spanning-tree root**

Root Hello Max Fwd
Vlan Root ID Cost Time Age Dly Root Port
---------- ---------- ---------- ----- --- --- ----------
VLAN0100 24676 000f.2303.2d80 19 2 20 15 Fa0/11
VLAN0200 24776 000f.2303.2d80 19 2 20 15 Fa0/11

ALS1#**show spanning-tree root**

Root Hello Max Fwd

https://t.me/learningnets

Vlan Root ID Cost Time Age Dly Root Port
---------- ---------- ---- ---- --- --- ----------
VLAN0100 24676 000f.2303.2d80 19 2 20 15 Fa0/7
VLAN0200 24776 000f.2303.2d80 19 2 20 15 Fa0/7

ALS2#**show spanning-tree root**

Root Hello Max Fwd
Vlan Root ID Cost Time Age Dly Root Port
---------- ---------- ---- ---- --- --- ----------
VLAN0100 24676 000f.2303.2d80 19 2 20 15 Fa0/9
VLAN0200 24776 000f.2303.2d80 19 2 20 15 Fa0/9

Task 4

ALS1(config)#**interface fa 0/7**
ALS1(config-if)#**spanning-tree vlan 200 cost 40**

ALS2(config)#**interface fa 0/9**
ALS2(config-if)#**spanning-tree vlan 200 cost 40**

NOTE: When selecting a root port, Spanning Tree considers the following:

- Lowest Root Bridge ID
- Lowest Root Path Cost to Root Bridge
- Lowest Sender Bridge ID
- Lowest Sender Port ID

By default, no additional configuration is required to ensure that Fa0/7 and Fa0/9 on switches ALS1 and ALS2, respectively, are the root ports (forwarding) for VLAN 100. However, to ensure that Fa0/9 and Fa0/7 on switches ALS1 and ALS2, respectively, are root ports (forwarding) for VLAN 200, you must increase the cost of the current root ports Fa0/7 and Fa0/9 on switches ALS1 and ALS2, respectively, to make these less desirable (blocking) for VLAN 200.

This value must be higher than the cumulative cost of 19 + 19, which is 38. Any cost value above number 38 on Fa0/7 and Fa0/9 on switches ALS1 and ALS2 for VLAN 200 will satisfy the requirements of this task. Before the change, the current STP status shows the following:

ALS1#**show spanning-tree interface fastethernet 0/7**

Vlan Role Sts Cost Prio.Nbr Type
---------- ---- --- --------- -------- ----------
VLAN0001 Desg FWD 19 128.7 P2p

https://t.me/learningnets

VLAN0100 Root FWD 19 128.7 P2p
VLAN0200 Root FWD 19 128.7 P2p
ALS1#
ALS1#**show spanning-tree interface fastethernet 0/9**
Vlan Role Sts Cost Prio.Nbr Type
---------- ---- --- -------- -------- ----------
VLAN0001 Desg FWD 19 128.9 P2p
VLAN0100 Altn BLK 19 128.9 P2p
VLAN0200 Altn BLK 19 128.9 P2p
ALS2#**show spanning-tree interface fastethernet 0/7**
Vlan Role Sts Cost Prio.Nbr Type
---------- ---- --- -------- -------- ----------
VLAN0001 Root FWD 19 128.7 P2p
VLAN0100 Altn BLK 19 128.7 P2p
VLAN0200 Altn BLK 19 128.7 P2p
ALS2#
ALS2#**show spanning-tree interface fastethernet 0/9**
Vlan Role Sts Cost Prio.Nbr Type
---------- ---- --- -------- -------- ----------
VLAN0001 Altn BLK 19 128.9 P2p
VLAN0100 Root FWD 19 128.9 P2p
VLAN0200 Root FWD 19 128.9 P2p

Following the changing of the cost on the current root ports, the topology is now as follows:

ALS1#**show spanning-tree interface fastethernet 0/7**
Vlan Role Sts Cost Prio.Nbr Type
---------- ---- --- -------- -------- ----------
VLAN0001 Desg FWD 19 128.7 P2p
VLAN0100 Root FWD 19 128.7 P2p
VLAN0200 Altn BLK 40 128.7 P2p
ALS1#
ALS1#**show spanning-tree interface fastethernet 0/9**
Vlan Role Sts Cost Prio.Nbr Type
---------- ---- --- -------- -------- ----------
VLAN0001 Desg FWD 19 128.9 P2p
VLAN0100 Altn BLK 19 128.9 P2p

https://t.me/learningnets

VLAN0200 Root FWD 19 128.9 P2p

ALS2#**show spanning-tree interface fastethernet 0/7**

Vlan Role Sts Cost Prio.Nbr Type
---------------- ---- --- --------- -------- ----------------
VLAN0001 Root FWD 19 128.7 P2p
VLAN0100 Altn BLK 19 128.7 P2p
VLAN0200 Root FWD 19 128.7 P2p
ALS2#
ALS2#**show spanning-tree interface fastethernet 0/9**

Vlan Role Sts Cost Prio.Nbr Type
---------------- ---- --- --------- -------- ----------------
VLAN0001 Altn BLK 19 128.9 P2p
VLAN0100 Root FWD 19 128.9 P2p
VLAN0200 Altn BLK 40 128.9 P2p

Task 5

This task requires the implementation of STP backbonefast and uplinkfast. Backbonefast is configured on ALL switches in the network as follows:

DLS1(config)#**spanning-tree backbonefast**

DLS2(config)#**spanning-tree backbonefast**

ALS1(config)#**spanning-tree backbonefast**

ALS2(config)#**spanning-tree backbonefast**

However, uplinkfast is configured only on access switches in the network as follows:

ALS1(config)#**spanning-tree uplinkfast**

ALS2(config)#**spanning-tree uplinkfast**

Verify backbonefast by shutting down the Fa0/11 link between DLS1 and DLS2. This will then generate RLQs which allow for the faster recovergence of the STP domain. You can verify backbonefast operation using the IOS **show spanning-tree backbonefast** command as follows:

DLS2(config)#**int fastethernet 0/11**
DLS2(config-if)#**shut**
DLS2(config-if)#**end**
DLS2#
DLS2#**show spanning-tree backbonefast**
BackboneFast is enabled

https://t.me/learningnets

BackboneFast statistics

Number of transition via backboneFast (all VLANs) : 0
Number of inferior BPDUs received (all VLANs) : 0
Number of RLQ request PDUs received (all VLANs) : 2
Number of RLQ response PDUs received (all VLANs) : 0
Number of RLQ request PDUs sent (all VLANs) : 0
Number of RLQ response PDUs sent (all VLANs) : 2

On the downstream switch, for example ALS1, the same command shows the following:

ALS1#**show spanning-tree backbonefast**
BackboneFast is enabled

BackboneFast statistics

Number of transition via backboneFast (all VLANs) : 3
Number of inferior BPDUs received (all VLANs) : 3
Number of RLQ request PDUs received (all VLANs) : 0
Number of RLQ response PDUs received (all VLANs) : 3
Number of RLQ request PDUs sent (all VLANs) : 3
Number of RLQ response PDUs sent (all VLANs) : 0

Verify backbonefast by shutting down a trunk link on one of the access switches. This will then generate dummy frames, which are sent to the Multicast address 01-00.0C-CD-CD-CD.You can verify uplinkfast operation using the **show spanning-tree uplinkfast** command as follows:

ALS1(config)#**int fastethernet 0/7**
ALS1(config-if)#**shut**
ALS1(config-if)#**end**
ALS1#
ALS1#**show spanning-tree uplinkfast**
UplinkFast is enabled

Station update rate set to 150 packets/sec.

UplinkFast statistics

Number of transitions via uplinkFast (all VLANs) : 2
Number of proxy multicast addresses transmitted (all VLANs) : 4

Name Interface List
---

https://t.me/learningnets

VLAN0001 Fa0/9(fwd)
VLAN0100 Fa0/9(fwd)
VLAN0200 Fa0/9(fwd)

https://t.me/learningnets

CCNP Lab 002: VLANs, VTP, DTP and STP

Lab Objective:

The focus of this lab is to understand basic VLAN, VTP, DTP and STP implementation and configuration in Cisco IOS Catalyst switches.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please begin each and every lab by shutting down all interfaces on all switches and then manually re-enabling only the interfaces that are illustrated in this topology.

Task 1

Disable VTP on all switches. All switches should support the configuration, modification and deletion of VLANs.

Task 2

Configure trunking on the switches so that all ports are explicitly trunking and DTP should never be used on any of these ports.

Task 3

Configure VLANs 100 and 200 on all switches and use the default IOS VLAN names. Explicitly configure switch DLS1 with a priority of 8192 so it is elected root for both of these VLANs. Additionally, also explicitly configure switch DLS2 so it is elected backup root for both VLANs.

Task 4

Configure Spanning Tree so that it will remain root bridge in the event that another switch is inadvertently misconfigured with a lower priority for VLANs 100 and 200. Test and verify your configuration by specifying a priority of 0 for VLAN 100 on any

https://t.me/learningnets

switch within the STP network.

Task 5

Configure the trunk links on switch DLS2 so that they will be disabled automatically in the event that they do not receive BPDUs. Test and verify your configuration by disabling default BPDU transmission from one of the upstream switches.

Task 6

Ports FastEthernet0/1 through FastEthernet0/5 on switches ALS1 and ALS2 will be connected to hosts in the future. These hosts will reside in VLAN 100. Using only **TWO** commands, perform the following activities on these ports:

- Assign all of these individual ports to VLAN 100
- Configure the ports as static access port
- Enable PortFast for all the ports
- Disable bundling, i.e. EtherChannel, for these ports

Lab Validation:

Task 1

DLS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

DLS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

ALS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

ALS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

Task 2

DLS1(config)#**interface range fa0/7, fa0/9, fa0/11**
DLS1(config-if-range)#**switchport trunk encapsulation dot1q**
DLS1(config-if-range)#**switchport mode trunk**
DLS1(config-if-range)#**switchport nonegotiate**

DLS2(config)#**interface range fa0/7, fa0/9, fa0/11**
DLS2(config-if-range)#**switchport trunk encapsulation dot1q**
DLS2(config-if-range)#**switchport mode trunk**
DLS2(config-if-range)#**switchport nonegotiate**

https://t.me/learningnets

NOTE: If using the H2N racks, the ALS switches are 2950 switches and therefore support only 802.1Q encapsulation. There is no need to specify trunk encapsulation.

ALS1(config)#**interface range faste 0/7 , faste 0/9 , faste 0/11**
ALS1(config-if-range)#**switchport mode trunk**
ALS1(config-if-range)#**switchport nonegotiate**

ALS2(config)#**interface range faste 0/7 , faste 0/9 , faste 0/11**
ALS2(config-if-range)#**switchport mode trunk**
ALS2(config-if-range)#**switchport nonegotiate**

Verify your configuration using the **show interfaces trunk** command:

DLS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 on 802.1q trunking 1
Fa0/9 on 802.1q trunking 1
Fa0/11 on 802.1q trunking 1

DLS2#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 on 802.1q trunking 1
Fa0/9 on 802.1q trunking 1
Fa0/11 on 802.1q trunking 1

ALS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 on 802.1q trunking 1
Fa0/9 on 802.1q trunking 1
Fa0/11 on 802.1q trunking 1

ALS2#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 on 802.1q trunking 1
Fa0/9 on 802.1q trunking 1
Fa0/11 on 802.1q trunking 1

Task 3

DLS1(config)#**vlan 100**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 200**
DLS1(config-vlan)#**exit**
DLS1(config)#**spanning-tree vlan 100 prior 8192**

https://t.me/learningnets

DLS1(config)#**spanning-tree vlan 200 prior 8192**

DLS2(config)#**vlan 100**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 200**
DLS2(config-vlan)#**exit**
DLS2(config)#**spanning-tree vlan 100 priority 16384**
DLS2(config)#**spanning-tree vlan 200 priority 16384**

ALS1(config)#**vlan 100**
ALS1(config-vlan)#**exit**
ALS1(config)#**vlan 200**
ALS1(config-vlan)#**exit**

ALS2(config)#**vlan 100**
ALS2(config-vlan)#**exit**
ALS2(config)#**vlan 200**
ALS2(config-vlan)#**exit**

Verify your configuration using the **show spanning-tree root** command:

DLS1#**show spanning-tree root**

Root Hello Max Fwd
Vlan Root ID Cost Time Age Dly Root Port
---------- ---------- ---------- ----- --- --- ----------
VLAN0100 8292 000f.2303.2d80 0 2 20 15
VLAN0200 8392 000f.2303.2d80 0 2 20 15

DLS2#**show spanning-tree root**

Root Hello Max Fwd
Vlan Root ID Cost Time Age Dly Root Port
---------- ---------- ---------- ----- --- --- ----------
VLAN0100 8292 000f.2303.2d80 19 2 20 15 Fa0/11
VLAN0200 8392 000f.2303.2d80 19 2 20 15 Fa0/11

ALS1#**show spanning-tree root**

Root Hello Max Fwd
Vlan Root ID Cost Time Age Dly Root Port
---------- ---------- ------ ----- --- --- ----------
VLAN0100 8292 000f.2303.2d80 19 2 20 15 Fa0/7
VLAN0200 8392 000f.2303.2d80 19 2 20 15 Fa0/7

ALS2#**show spanning-tree root**

https://t.me/learningnets

Root Hello Max Fwd
Vlan Root ID Cost Time Age Dly Root Port
---------- ---------- ---- ---- --- --- ----------
VLAN0100 8292 000f.2303.2d80 19 2 20 15 Fa0/9
VLAN0200 8392 000f.2303.2d80 19 2 20 15 Fa0/9

Task 4

This task requires identifying designated ports and configuring the root guard feature on them. The root guard feature prevents a designated port from becoming a root port.

If a port on which the root guard feature receives a superior BPDU, it moves the port into a root-inconsistent state, thus maintaining the current root bridge status quo. Use the **show spanning-tree vlan** command to determine the current Spanning Tree port states as follows:

DLS1#**show spanning-tree vlan 100**

VLAN0100

...

Interface Role Sts Cost Prio.Nbr Type
---------- ---- --- --------- -------- ----------
Fa0/7 Desg FWD 19 128.7 P2p
Fa0/9 Desg FWD 19 128.9 P2p
Fa0/11 Desg FWD 19 128.11 P2p

DLS2#**show spanning-tree vlan 100**

VLAN0100

...

Interface Role Sts Cost Prio.Nbr Type
---------- ---- --- --------- -------- ----------
Fa0/7 Desg FWD 19 128.7 P2p
Fa0/9 Desg FWD 19 128.9 P2p
Fa0/11 Root FWD 19 128.11 P2p

ALS1#**show spanning-tree vlan 100**

VLAN0100

...

Interface Role Sts Cost Prio.Nbr Type
---------- ---- --- --------- -------- ----------
Fa0/7 Root FWD 19 128.7 P2p
Fa0/9 Altn BLK 19 128.9 P2p

https://t.me/learningnets

Technet24

Fa0/11 Desg FWD 19 128.11 P2p

ALS2#**show spanning-tree vlan 100**

VLAN0100

...

Interface Role Sts Cost Prio.Nbr Type

---------- ---- --- --------- -------- ----------

Fa0/7 Altn BLK 19 128.7 P2p
Fa0/9 Root FWD 19 128.9 P2p
Fa0/11 Altn BLK 19 128.11 P2p

Following this, enable the root guard feature on all designated ports using the spanning-tree guard root interface configuration command. Referencing the list above, root guard would be enabled on the following interfaces or ports:

- Switch DSL1: Fa0/7, Fa0/9, Fa0/11
- Switch DLS2: Fa0/7, Fa0/9
- Switch ALS1: Fa0/11
- Switch ALS2: None - because this switch has no designated ports

This task is completed by enabling root guard on the ports above as follows:

DLS1(config)#**interface range fa0/7, fa0/9, fa0/11**
DLS1(config-if-range)#**spanning-tree guard root**

DLS2(config)#**interface range fa0/7, fa0/9**
DLS2(config-if-range)#**spanning-tree guard root**

ALS1(config)#**interface fastethernet 0/11**
ALS1(config-if)#**spanning-tree guard root**

Test your solution by setting the priority of a VLAN to 0 or 4096 and then verifying the port state on the adjacent segment designated bridge. For example, if you changed the priority of VLAN 100 on switch ALS2 to 0, all peer ports enabled for root guard with which this switch connects will be placed into a root inconsistent state as follows:

ALS2(config)#**spanning-tree vlan 100 priority 0**

DLS1#
*Mar 1 01:21:28.851: %SPANTREE-2-ROOTGUARD_BLOCK: Root guard blocking port FastEthernet0/9 on VLAN0100.

DLS2#
*Mar 1 01:21:31.535: %SPANTREE-2-ROOTGUARD_BLOCK: Root guard blocking port FastEthernet0/7 on VLAN0100.

https://t.me/learningnets

ALS1#
*Mar 1 01:24:39.903: %SPANTREE-2-ROOTGUARD_BLOCK: Root guard blocking port FastEthernet0/11 on VLAN0100.

Aside from the logged message, you can also use the **show spanning-tree inconsistentports** and the **show spanning-tree interface** commands to view root inconsistent ports:

DLS1#**show spanning-tree inconsistentports**

Name Interface Inconsistency
---------- ---------- ----------
VLAN0001 FastEthernet0/7 Root Inconsistent
VLAN0001 FastEthernet0/9 Root Inconsistent
VLAN0001 FastEthernet0/11 Root Inconsistent
VLAN0100 FastEthernet0/9 Root Inconsistent

DLS1#**show spanning-tree interface fastethernet 0/9**

Vlan Role Sts Cost Prio.Nbr Type
---------- ---- --- --------- -------- ----------
VLAN0100 Desg BKN*19 128.9 P2p *ROOT_Inc

Task 5

This task requires the configuration of Loop Guard on switch DLS2. The Loop Guard detects root ports and blocked ports, and ensures they continue to receive BPDUs. When enabled, should one of these ports stop receiving BPDUs, it is moved into a loop-inconsistent state.

DLS2(config)#**interface range faste 0/7 , faste 0/9 , faste 0/11**
DLS2(config-if-range)#**spanning-tree guard loop**

NOTE: The Loop Guard feature can also be enabled globally as follows:

DLS2(config)#**spanning-tree loopguard default**

Test this configuration by filtering BPDUs from one of the connected switches as follows:

DLS1(config)#**interface fastethernet 0/11**
DLS1(config-if)#**spanning-tree bpdufilter enable**

After this configuration, the following log messages are printed on the console of ALS1:

DLS2#
01:41:26: %SPANTREE-2-LOOPGUARD_BLOCK: Loop guard blocking port FastEthernet0/11 on VLAN0100.
01:41:28: %SPANTREE-2-LOOPGUARD_BLOCK: Loop guard blocking port

https://t.me/learningnets
Technet24

FastEthernet0/11 on VLAN0200.

Aside from the logged message, you can also use the **show spanning-tree inconsistentports** and the **show spanning-tree interface** commands to view root inconsistent ports:

DLS2#**show spanning-tree inconsistentports**

Name Interface Inconsistency
---------- ---------- ----------
VLAN0100 FastEthernet0/9 Loop Inconsistent
VLAN0200 FastEthernet0/9 Loop Inconsistent

Number of inconsistent ports (segments) in the system : 2

DLS2#**show spanning-tree interface fastethernet 0/11**

Vlan Role Sts Cost Prio.Nbr Type
---------- ---- --- --------- -------- ----------
VLAN0100 Desg BKN*19 128.9 P2p *LOOP_Inc
VLAN0200 Desg BKN*19 128.9 P2p *LOOP_Inc

Task 6

While seemingly difficult, this task is actually very simple and requires the configuration of the **switchport access vlan** and **switchport host** commands. The **switchport host** command is an inbuilt Cisco IOS macro that performs three actions under the specified port(s):

- It configures the switchport for access mode
- It enables portfast
- It disables Etherchannel capabilities for the port

This task is completed as follows:

ALS1(config)#**interface range fastethernet 0/1 - 5**
ALS1(config-if-range)#**switchport access vlan 100**
ALS1(config-if-range)#**switchport host**
switchport mode will be set to access
spanning-tree portfast will be enabled
channel group will be disabled

ALS1(config-if-range)#**end**

ALS2(config)#**interface range fastethernet 0/1 - 5**
ALS2(config-if-range)#**switchport access vlan 100**
ALS2(config-if-range)#**switchport host**

https://t.me/learningnets

switchport mode will be set to access
spanning-tree portfast will be enabled
channel group will be disabled

ALS2(config-if-range)#**end**

Verify your configuration by looking at the switch interface configuration or using **the show interfaces <interface> switchport** command:

ALS1#**show running-config interface fastethernet 0/1**
Building configuration...

Current configuration : 109 bytes
!
interface FastEthernet0/1
switchport access vlan 100
switchport mode access
spanning-tree portfast
end

ALS1#**show interfaces fastethernet 0/1 switchport**
Name: Fa0/1
Switchport: Enabled
Administrative Mode: static access
Operational Mode: static access
Administrative Trunking Encapsulation: dot1q
Operational Trunking Encapsulation: native
Negotiation of Trunking: Off
Access Mode VLAN: 100 (VLAN0100)
Trunking Native Mode VLAN: 1 (default)
Voice VLAN: none
Administrative private-vlan host-association: none
Administrative private-vlan mapping: none
Administrative private-vlan trunk native VLAN: none
Administrative private-vlan trunk encapsulation: dot1q
Administrative private-vlan trunk normal VLANs: none
Administrative private-vlan trunk private VLANs: none
Operational private-vlan: none
Trunking VLANs Enabled: ALL
Pruning VLANs Enabled: 2-1001
Capture Mode Disabled
Capture VLANs Allowed: ALL

https://t.me/learningnets

Technet24

Protected: false
Appliance trust: none

https://t.me/learningnets

CCNP Lab 003: LACP, PAgP, Multiple STP

Lab Objective:

The focus of this lab is to understand EtherChannel (LACP, PAgP) and Multiple Spanning Tree (MST) implementation and configuration in Cisco IOS Catalyst switches.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please begin each and every lab by shutting down all interfaces on all switches and then manually re-enabling only the interfaces that are illustrated in this topology.

Task 1

Disable VTP on all switches. All switches should support the configuration, modification and deletion of VLANs.

Task 2

Configure EtherChannel trunks on the switches illustrated in the topology. Only switches DLS1 and DLS2 should actively initiate channel establishment; switches ALS1 and ALS2 should be configured as passive links that will should not actively attempt to establish an EtherChannel. Please note that depending upon your switch model, you may have to choose between ISL and dot1q encapsulation manually (as we do in the solution). The EtherChannels should be configured as follows:

- The two ports between DLS1 and DLS2 belong to channel group 1 and use mode on
- The two ports between DLS1 and ALS1 belong to channel group 2 and use LACP
- The two ports between DLS1 and ALS2 belong to channel group 3 and use PAgP

https://t.me/learningnets

- The two ports between DLS2 and ALS1 belong to channel group 4 and use LACP
- The two ports between DLS2 and ALS2 belong to channel group 5 and use PAgP

Task 3

Following the EtherChannel configuration, protect the switched network from any future misconfigurations by ensuring misconfigured EtherChannels are automatically disabled. Additionally, configure the switches to automatically bring up EtherChannels that were disabled due to misconfigurations after 10 minutes.

Task 4

Configure VLANs 100, 200, 300, 400, 500, 600, 700, and 800 all switches. Use the default VLAN names or specify your own names, if so desired.

Task 5

Selecting your own name and revision number, configure Multiple STP as follows:

- VLANs 100 and 200 will be mapped to MST Instance # 1: Switch DLS1 should be root
- VLANs 300 and 400 will be mapped to MST Instance # 2: Switch DLS2 should be root
- VLANs 500 and 600 will be mapped to MST Instance # 3: Switch ALS1 should be root
- VLANs 700 and 800 will be mapped to MST Instance # 4: Switch ALS2 should be root

Task 6

Configure Spanning Tree so that interface cost values appear to the 802.1t (long) version

Lab Validation:

Task 1

DLS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

DLS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

ALS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

https://t.me/learningnets

Technet24

ALS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

Task 2

DLS1(config)#**interface range fa 0/11 - 12**
DLS1(config-if-range)#**switchport**
DLS1(config-if-range)#**switchport mode trunk**
DLS1(config-if-range)#**switchport trunk encapsulation dot1q**
DLS1(config-if-range)#**switchport mode trunk**
DLS1(config-if-range)#**channel-group 1 mode on**
Creating a port-channel interface Port-channel 1
DLS1(config-if-range)#**exit**
DLS1(config)#**interface range fa 0/7 - 8**
DLS1(config-if-range)#**switchport**
DLS1(config-if-range)#**switchport trunk encapsulation dot1q**
DLS1(config-if-range)#**switchport mode trunk**
DLS1(config-if-range)#**channel-group 2 mode active**
Creating a port-channel interface Port-channel 2
DLS1(config-if-range)#**exit**
DLS1(config)#**interface range fa 0/9 - 10**
DLS1(config-if-range)#**switchport**
DLS1(config-if-range)#**switchport trunk encapsulation dot1q**
DLS1(config-if-range)#**switchport mode trunk**
DLS1(config-if-range)#**channel-group 3 mode desirable**
Creating a port-channel interface Port-channel 3
DLS1(config-if-range)#exit

DLS2(config)#**interface range fa 0/11 - 12**
DLS2(config-if-range)#**switchport**
DLS2(config-if-range)#**switchport trunk encapsulation dot1q**
DLS2(config-if-range)#**switchport mode trunk**
DLS2(config-if-range)#**channel-group 1 mode on**
Creating a port-channel interface Port-channel 1
DLS2(config-if-range)#**exit**
DLS2(config)#**interface range fa 0/9 - 10**
DLS2(config-if-range)#**switchport**
DLS2(config-if-range)#**switchport trunk encapsulation dot1q**
DLS2(config-if-range)#**switchport mode trunk**
DLS2(config-if-range)#**channel-group 4 mode active**

https://t.me/learningnets

Creating a port-channel interface Port-channel 4
DLS2(config-if-range)#**exit**
DLS2(config)#**interface range fa 0/7 - 8**
DLS2(config-if-range)#**switchport**
DLS2(config-if-range)#**switchport trunk encapsulation dot1q**
DLS2(config-if-range)#**switchport mode trunk**
DLS2(config-if-range)#**channel-group 5 mode desirable**
Creating a port-channel interface Port-channel 5
DLS2(config-if-range)#**exit**

ALS1(config)#**interface range f0/7 - 8**
ALS1(config-if-range)#**switchport mode trunk**
ALS1(config-if-range)#**channel-group 2 mode passive**
Creating a port-channel interface Port-channel 2
ALS1(config-if-range)#**exit**
ALS1(config)#**interface range fa 0/9 - 10**
ALS1(config-if-range)#**switchport mode trunk**
ALS1(config-if-range)#**channel-group 4 mode passive**
Creating a port-channel interface Port-channel 4
ALS1(config-if-range)#**exit**

ALS2(config)#**interface range f0/9 - 10**
ALS2(config-if-range)#**switchport mode trunk**
ALS2(config-if-range)#**channel-group 3 mode auto**
Creating a port-channel interface Port-channel 3
ALS2(config-if-range)#**exit**
ALS2(config)#**interface range f0/7 - 8**
ALS2(config-if-range)#**switchport mode trunk**
ALS2(config-if-range)#**channel-group 5 mode auto**
Creating a port-channel interface Port-channel 5
ALS2(config-if-range)#**exit**

Verify your configuration using the **show etherchannel summary** and the **show interfaces trunk** Cisco IOS Catalyst switch commands

DLS1#**show etherchannel summary**
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

https://t.me/learningnets

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 3
Number of aggregators: 3

Group Port-channel Protocol Ports
------+-------------+-----------+---
1 Po1(SD) - Fa0/11(D) Fa0/12(D)
2 Po2(SU) LACP Fa0/7(P) Fa0/8(P)
3 Po3(SU) PAgP Fa0/9(P) Fa0/10(P)

DLS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Po2 on 802.1q trunking 1
Po3 on 802.1q trunking 1

DLS2#**show etherchannel summary**
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 3
Number of aggregators: 3

Group Port-channel Protocol Ports
------+-------------+-----------+---
1 Po1(SD) - Fa0/11(D) Fa0/12(D)
4 Po4(SU) LACP Fa0/9(P) Fa0/10(P)
5 Po5(SU) PAgP Fa0/7(P) Fa0/8(P)

DLS2#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Po4 on 802.1q trunking 1
Po5 on 802.1q trunking 1

https://t.me/learningnets

ALS1#**show etherchannel summary**
Flags: D - down P - in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
u - unsuitable for bundling
U - in use f - failed to allocate aggregator
d - default port

Number of channel-groups in use: 2
Number of aggregators: 2

Group Port-channel Protocol Ports
------+-------------+-----------+---
2 Po2(SU) LACP Fa0/7(Pd) Fa0/8(P)
4 Po4(SU) LACP Fa0/9(Pd) Fa0/10(P)

ALS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Po2 on 802.1q trunking 1
Po4 on 802.1q trunking 1

ALS2#**show etherchannel summary**
Flags: D - down P - in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
u - unsuitable for bundling
U - in use f - failed to allocate aggregator
d - default port

Number of channel-groups in use: 2
Number of aggregators: 2

Group Port-channel Protocol Ports
------+-------------+-----------+---
3 Po3(SU) PAgP Fa0/9(P) Fa0/10(Pd)
5 Po5(SU) PAgP Fa0/7(P) Fa0/8(Pd)

ALS2#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Po3 on 802.1q trunking 1
Po5 on 802.1q trunking 1

https://t.me/learningnets

Technet24

Task 3

This task calls for the configuration of the EtherChannel guard feature. This feature places the port(s) into an err-disabled state if EtherChannel configurations are mismatched, e.g. EtherChannel parameters are not the same, which can result in loops within the network.

The second part of this task requires the configuration of the errdisable recovery feature for EtherChannel misconfigurations. The feature's timer should be set to 600 seconds (10 mins).

DLS1(config)#**spanning-tree etherchannel guard misconfig**
DLS1(config)#**errdisable recovery cause channel-misconfig**
DLS1(config)#**errdisable recovery interval 600**

DLS2(config)#**spanning-tree etherchannel guard misconfig**
DLS2(config)#**errdisable recovery cause channel-misconfig**
DLS2(config)#**errdisable recovery interval 600**

ALS1(config)#**spanning-tree etherchannel guard misconfig**
ALS1(config)#**errdisable recovery cause channel-misconfig**
ALS1(config)#**errdisable recovery interval 600**

ALS2(config)#**spanning-tree etherchannel guard misconfig**
ALS2(config)#**errdisable recovery cause channel-misconfig**
ALS2(config)#**errdisable recovery interval 600**

You can use the **show spanning-tree summary** command to verify that the EtherChannel guard feature has been enabled. You can use the **show errdisable recovery** command to verify configured errdisable recovery feature settings:

DLS1#**show spanning-tree summary**
Switch is in pvst mode
Root bridge for: none
Extended system ID is enabled
Portfast Default is disabled
PortFast BPDU Guard Default is disabled
Portfast BPDU Filter Default is disabled
Loopguard Default is disabled
EtherChannel misconfig guard is enabled
UplinkFast is disabled
BackboneFast is disabled
Configured Pathcost method used is short

DLS1#**show errdisable recovery**

https://t.me/learningnets

ErrDisable Reason Timer Status
---------------- --------------
arp-inspection Disabled
bpduguard Disabled
channel-misconfig Enabled
dhcp-rate-limit Disabled
dtp-flap Disabled
gbic-invalid Disabled
l2ptguard Disabled
link-flap Disabled
mac-limit Disabled
link-monitor-fail Disabled
loopback Disabled
oam-remote-failur Disabled
pagp-flap Disabled
port-mode-failure Disabled
psecure-violation Disabled
security-violatio Disabled
sfp-config-mismat Disabled
storm-control Disabled
udld Disabled
unicast-flood Disabled
vmps Disabled

Timer interval: 600 seconds

Interfaces that will be enabled at the next timeout:

Task 4

DLS1(config)#**vlan 100**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 200**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 300**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 400**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 500**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 600**

https://t.me/learningnets

Technet24

DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 700**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 800**
DLS1(config-vlan)#**exit**

DLS2(config)#**vlan 100**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 200**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 300**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 400**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 500**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 600**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 700**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 800**
DLS2(config-vlan)#**exit**

ALS1(config)#**vlan 100**
ALS1(config-vlan)#**exit**
ALS1(config)#**vlan 200**
ALS1(config-vlan)#**exit**
ALS1(config)#**vlan 300**
ALS1(config-vlan)#**exit**
ALS1(config)#**vlan 400**
ALS1(config-vlan)#**exit**
ALS1(config)#**vlan 500**
ALS1(config-vlan)#**exit**
ALS1(config)#**vlan 600**
ALS1(config-vlan)#**exit**
ALS1(config)#**vlan 700**
ALS1(config-vlan)#**exit**
ALS1(config)#**vlan 800**
ALS1(config-vlan)#**exit**

ALS2(config)#**vlan 100**

https://t.me/learningnets

ALS2(config-vlan)#**exit**
ALS2(config)#**vlan 200**
ALS2(config-vlan)#**exit**
ALS2(config)#**vlan 300**
ALS2(config-vlan)#**exit**
ALS2(config)#**vlan 400**
ALS2(config-vlan)#**exit**
ALS2(config)#**vlan 500**
ALS2(config-vlan)#**exit**
ALS2(config)#**vlan 600**
ALS2(config-vlan)#**exit**
ALS2(config)#**vlan 700**
ALS2(config-vlan)#**exit**
ALS2(config)#**vlan 800**
ALS2(config-vlan)#**exit**

Task 5

DLS1(config)#**spanning-tree mst configuration**
DLS1(config-mst)#**name CCNP**
DLS1(config-mst)#**revision 0**
DLS1(config-mst)#**instance 1 vlan 100, 200**
DLS1(config-mst)#**instance 2 vlan 300, 400**
DLS1(config-mst)#**instance 3 vlan 500, 600**
DLS1(config-mst)#**instance 4 vlan 700, 800**
DLS1(config-mst)#**show current**
Current MST configuration
Name [CCNP]
Revision 0 Instances configured 5

Instance Vlans mapped
-------- ---
0 1-99,101-199,201-299,301-399,401-499,501-599,601-699,701-799
801-4094
1 100,200
2 300,400
3 500,600
4 700,800

DLS1(config-mst)#**exit**

https://t.me/learningnets

Technet24

DLS1(config)#**spanning-tree mst 1 priority 0**
DLS1(config)#**spanning-tree mode mst**

DLS2(config)#**spanning-tree mst configuration**
DLS2(config-mst)#**name CCNP**
DLS2(config-mst)#**revision 0**
DLS2(config-mst)#**instance 1 vlan 100, 200**
DLS2(config-mst)#**instance 2 vlan 300, 400**
DLS2(config-mst)#**instance 3 vlan 500, 600**
DLS2(config-mst)#**instance 4 vlan 700, 800**
DLS2(config-mst)#**show current**
Current MST configuration
Name [CCNP]
Revision 0 Instances configured 5

Instance Vlans mapped
-------- ---
0 1-99,101-199,201-299,301-399,401-499,501-599,601-699,701-799
801-4094
1 100,200
2 300,400
3 500,600
4 700,800

DLS2(config-mst)#**exit**
DLS2(config)#**spanning-tree mst 2 priority 0**
DLS2(config)#**spanning-tree mode mst**

ALS1(config)#**spanning-tree mst configuration**
ALS1(config-mst)#**name CCNP**
ALS1(config-mst)#**revision 0**
ALS1(config-mst)#**instance 1 vlan 100, 200**
ALS1(config-mst)#**instance 2 vlan 300, 400**
ALS1(config-mst)#**instance 3 vlan 500, 600**
ALS1(config-mst)#**instance 4 vlan 700, 800**
ALS1(config-mst)#**show current**
Current MST configuration
Name [CCNP]
Revision 0 Instances configured 5

Instance Vlans mapped

https://t.me/learningnets

-------- --
0 1-99,101-199,201-299,301-399,401-499,501-599,601-699,701-799
801-4094
1 100,200
2 300,400
3 500,600
4 700,800

ALS1(config-mst)#**exit**
ALS1(config)#**spanning-tree mst 3 priority 0**
ALS1(config)#**spanning-tree mode mst**
ALS2(config)#**spanning-tree mst configuration**
ALS2(config-mst)#**name CCNP**
ALS2(config-mst)#**revision 0**
ALS2(config-mst)#**instance 1 vlan 100, 200**
ALS2(config-mst)#**instance 2 vlan 300, 400**
ALS2(config-mst)#**instance 3 vlan 500, 600**
ALS2(config-mst)#**instance 4 vlan 700, 800**
ALS2(config-mst)#**show current**
Current MST configuration
Name [CCNP]
Revision 0 Instances configured 5
Instance Vlans mapped
-------- --
0 1-99,101-199,201-299,301-399,401-499,501-599,601-699,701-799
801-4094
1 100,200
2 300,400
3 500,600
4 700,800

ALS2(config-mst)#**exit**
ALS2(config)#**spanning-tree mst 4 priority 0**
ALS2(config)#**spanning-tree mode mst**

Following this configuration, use the **show spanning-tree mst** command to verify MST:

DLS1#**show spanning-tree mst 1**

MST1 vlans mapped: 100,200

https://t.me/learningnets

Technet24

Bridge address 000f.2303.2d80 priority 1 (0 sysid 1)
Root this switch for MST1

Interface Role Sts Cost Prio.Nbr Type
---------- ---- --- -------- -------- ----------
Po1 Desg FWD 100000 128.68 P2p
Po2 Desg FWD 100000 128.69 P2p Pre-STD-Rx
Po3 Desg FWD 100000 128.70 P2p Pre-STD-Rx

DLS1#**show spanning-tree mst 2**

MST2 vlans mapped: 300,400
Bridge address 000f.2303.2d80 priority 32770 (32768 sysid 2)
Root address 000b.fd67.6500 priority 2 (0 sysid 2)
port Po1 cost 100000 rem hops 19

Interface Role Sts Cost Prio.Nbr Type
---------- ---- --- -------- -------- ----------
Po1 Root FWD 100000 128.68 P2p
Po2 Altn BLK 100000 128.69 P2p Pre-STD-Rx
Po3 Altn BLK 100000 128.70 P2p Pre-STD-Rx

DLS1#**show spanning-tree mst 3**

MST3 vlans mapped: 500,600
Bridge address 000f.2303.2d80 priority 32771 (32768 sysid 3)
Root address 0007.8432.dd00 priority 3 (0 sysid 3)
port Po2 cost 100000 rem hops 19

Interface Role Sts Cost Prio.Nbr Type
---------- ---- --- -------- -------- ----------
Po1 Altn BLK 100000 128.68 P2p
Po2 Root FWD 100000 128.69 P2p Pre-STD-Rx
Po3 Desg FWD 100000 128.70 P2p Pre-STD-Rx

DLS1#**show spanning-tree mst 4**

MST4 vlans mapped: 700,800
Bridge address 000f.2303.2d80 priority 32772 (32768 sysid 4)
Root address 0009.b79f.7d80 priority 4 (0 sysid 4)
port Po3 cost 100000 rem hops 19

Interface Role Sts Cost Prio.Nbr Type
---------- ---- --- -------- -------- ----------
Po1 Altn BLK 100000 128.68 P2p
Po2 Desg LRN 100000 128.69 P2p Pre-STD-Rx

https://t.me/learningnets

Po3 Root FWD 100000 128.70 P2p Pre-STD-Rx

Task 6

By default, the 802.1D specification assigns a 16-bit (short) default port cost values to each port that is based on the bandwidth. The 802.1t standard assigns a 32-bit (long) default port cost values to each port using a formula that is based on the bandwidth of the port. The formula for obtaining default 32-bit port costs is to divide the bandwidth of the port by 200,000,000. To complete this task you will need to change the default 802.1D cost method as follows:

DLS1(config)#**spanning-tree pathcost method long**

DLS2(config)#**spanning-tree pathcost method long**

ALS1(config)#**spanning-tree pathcost method long**

ALS2(config)#**spanning-tree pathcost method long**

Verify the current cost method using the **show spanning-tree pathcost method** command

DLS1#**show spanning-tree pathcost method**
Spanning tree default pathcost method used is long

DLS1(config)#**spanning-tree pathcost method long**

https://t.me/learningnets

Technet24

CCNP Lab 004: MLS, EtherChannels and Security

Lab Objective:

The focus of this lab is to understand how to implement and verify MLS, routed EtherChannels as well as some of the different Cisco IOS Catalyst series switch security features.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please begin each and every lab by shutting down all interfaces on all switches and then manually re-enabling only the interfaces that are illustrated in this topology.

Task 1

Disable VTP on all switches. All switches should support the configuration, modification and deletion of VLANs.

Task 2

Configure the following VLANs on the switches:

DLS1 and ALS1: VLAN 100
DLS2 and ALS2: VLAN 200

Configure the following SVIs on the switches:

DLS1 SVI 100 - IP Address 100.1.1.1/30
ALS1 SVI 100 - IP Address 100.1.1.2/30
DLS2 SVI 200 - IP Address 200.1.1.1/30
ALS2 SVI 200 - IP Address 200.1.1.2/30

Switches ALS1 and ALS2 should have their default gateway point to switches DLS1 and DLS2 respectively. There should be no default gateway configured on switches DLS1 and DLS2.

https://t.me/learningnets

Technet24

Task 3

Configure the ports between the access and distribution layer switches as static access ports. These should be assigned to the VLANs configured on the switches. Configure a routed EtherChannel between DLS1 and DLS2. Use any channel protocol. Assign switch DLS1 IP address 172.16.1.1/30 and switch DLS2 IP address 172.16.1.2/30.

Task 4

Using a routing protocol of your choice, configure switches DLS1 and DLS2 so that switches ALS1 and ALS2 have IP connectivity to each other. For efficiency, enable CEF. Verify your configuration and validate connectivity using PING and Telnet.

Task 5

At the VLAN level, implement filtering for VLAN 100 as follows:

- Drop all TCP packets
- Drop all UDP packets
- Forward all other non-IP packets
- Forward all other IP packets

At the VLAN level, implement filtering for VLAN 200 as follows:

- Forward all ICMP packets
- Forward all MAC packets from the MAC address of ALS2
- Drop all other IP packets
- Drop all other non-IP packets

Verify that you can still ping between switches ALS1 and ALS2; however, you should not be able to Telnet between switches ALS1 and ALS2. Verify your configuration.

Task 6

Configure Dynamic ARP Inspection for VLAN 100 such that the switch compares the ARP body for invalid and unexpected IP addresses, which includes 0.0.0.0, 255.255.255.255, all IP Multicast addresses, and a valid source MAC and explicitly denies them. Allow logging for DAI. Verify that switch ALS1 can still ping switch ALS2 after this configuration.

Lab Validation:

Task 1

DLS1(config)#**vtp mode transparent**

https://t.me/learningnets

Setting device to VTP TRANSPARENT mode.

DLS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

ALS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

ALS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

Task 2

DLS1(config)#**vlan 100**
DLS1(config-vlan)#**exit**
DLS1(config)#**interface vlan 100**
DLS1(config-if)#**ip address 100.1.1.1 255.255.255.252**
DLS1(config-if)#**exit**

DLS2(config)#**vlan 200**
DLS2(config-vlan)#**exit**
DLS2(config)#**interface vlan 200**
DLS2(config-if)#**ip address 200.1.1.1 255.255.255.252**
DLS2(config-if)#**exit**

ALS1(config)#**vlan 100**
ALS1(config-vlan)#**exit**
ALS1(config)#**interface vlan 100**
ALS1(config-if)#**ip address 100.1.1.1 255.255.255.252**
ALS1(config-if)#**exit**
ALS1(config)#**ip default-gateway 100.1.1.2**

ALS2(config)#**vlan 200**
ALS2(config-vlan)#**exit**
ALS2(config)#**interface vlan 200**
ALS2(config-if)#**ip address 200.1.1.2 255.255.255.252**
ALS2(config-if)#**exit**
ALS2(config)#**ip default-gateway 200.1.1.1**

Task 3

DLS1(config)#**interface fastethernet 0/7**
DLS1(config-if)#**switchport access vlan 100**
DLS1(config-if)#**switchport mode access**
DLS1(config-if)#**exit**
DLS1(config)#**interface range fastethernet 0/11 - 12**

https://t.me/learningnets

Technet24

DLS1(config-if-range)#**no switchport**
DLS1(config-if-range)#**channel-group 1 mode active**
Creating a port-channel interface Port-channel 1

DLS1(config-if-range)#**exit**
DLS1(config)#**interface port-channel 1**
DLS1(config-if)#**ip address 172.16.1.1 255.255.255.252**
DLS1(config-if)#**exit**

DLS2(config)#**interface fastethernet 0/7**
DLS2(config-if)#**switchport access vlan 200**
DLS2(config-if)#**switchport mode access**
DLS2(config-if)#**exit**
DLS2(config)#**interface range fastethernet 0/11 - 12**
DLS2(config-if-range)#**no switchport**
DLS2(config-if-range)#**channel-group 1 mode active**
Creating a port-channel interface Port-channel 1

DLS2(config-if-range)#**exit**
DLS2(config)#**interface port-channel 1**
DLS2(config-if)#**ip address 172.16.1.2 255.255.255.252**
DLS2(config-if)#**exit**

ALS1(config)#**interface fastethernet 0/7**
ALS1(config-if)#**switchport access vlan 100**
ALS1(config-if)#**switchport mode access**
ALS1(config-if)#**exit**

ALS2(config)#**interface fastethernet 0/7**
ALS2(config-if)#**switchport access vlan 200**
ALS2(config-if)#**switchport mode access**

Verify your EtherChannel configuration using the **show etherchannel** suite of commands. You can also ping between the switches to verify configuration and connectivity:

DLS2#**show etherchannel 1 summary**
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

M - not in use, minimum links not met

https://t.me/learningnets

u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
------+-------------+-----------+---
1 Po1(RU) LACP Fa0/11(P) Fa0/12(P)

DLS2#**ping 172.16.1.1**

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 172.16.1.1, timeout is 2 seconds:

.!!!!

Success rate is 80 percent (4/5), round-trip min/avg/max = 1/3/4 ms

Task 4

DLS1(config)#**ip routing**
DLS1(config)#**ip cef**
DLS1(config)#**router eigrp 1**
DLS1(config-router)#**network 0.0.0.0 255.255.255.255**
DLS1(config-router)#**no auto-summary**
DLS1(config-router)#**exit**

DLS2(config)#**ip routing**
DLS2(config)#**ip cef**
DLS1(config)#**router eigrp 1**
DLS1(config-router)#**network 0.0.0.0 255.255.255.255**
DLS1(config-router)#**no auto-summary**
DLS1(config-router)#**exit**

Use the appropriate commands to verify correct operation for the routing protocol you selected.

DLS1#**show ip eigrp neighbors**
EIGRP-IPv4:(1) neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 172.16.1.2 Po1 13 00:06:37 4 300 0 2

DLS1#**show ip route eigrp**

200.1.1.0/30 is subnetted, 1 subnets

https://t.me/learningnets

Technet24

D 200.1.1.0 [90/15616] via 172.16.1.2, 00:01:15, Port-channel1

Use the show ip cef command to view FIB information and entries:

DLS1#**show ip cef detail**

IPv4 CEF is enabled and running

VRF Default:

17 prefixes (17/0 fwd/non-fwd)

Table id 0

Database epoch: 0 (17 entries at this epoch)

0.0.0.0/0, epoch 0, flags default route handler

no route

0.0.0.0/32, epoch 0, flags receive

Special source: receive

receive

100.1.1.0/30, epoch 0, flags attached, connected, cover dependents, need deagg

Covered dependent prefixes: 4

need deagg: 3

notify cover updated: 1

attached to Vlan100

100.1.1.0/32, epoch 0, flags receive

Dependent covered prefix type cover need deagg cover 100.1.1.0/30

Interface source: Vlan100

receive for Vlan100

100.1.1.1/32, epoch 0, flags receive

Dependent covered prefix type cover need deagg cover 100.1.1.0/30

Interface source: Vlan100

receive for Vlan100

100.1.1.2/32, epoch 0, flags attached

Adj source: IP adj out of Vlan100, addr 100.1.1.2 01D83DC0

Dependent covered prefix type adjfib cover 100.1.1.0/30

attached to Vlan100

100.1.1.3/32, epoch 0, flags receive

https://t.me/learningnets

Dependent covered prefix type cover need deagg cover 100.1.1.0/30
Interface source: Vlan100
receive for Vlan100
172.16.1.0/30, epoch 0, flags attached, connected, cover dependents, need deagg
Covered dependent prefixes: 4
need deagg: 3
notify cover updated: 1
attached to Port-channel1
172.16.1.0/32, epoch 0, flags receive
Dependent covered prefix type cover need deagg cover 172.16.1.0/30
Interface source: Port-channel1
receive for Port-channel1
172.16.1.1/32, epoch 0, flags receive
Dependent covered prefix type cover need deagg cover 172.16.1.0/30
Interface source: Port-channel1
receive for Port-channel1
172.16.1.2/32, epoch 0, flags attached
Adj source: IP adj out of Port-channel1, addr 172.16.1.2 01D83F40
Dependent covered prefix type adjfib cover 172.16.1.0/30
attached to Port-channel1
172.16.1.3/32, epoch 0, flags receive
Dependent covered prefix type cover need deagg cover 172.16.1.0/30
Interface source: Port-channel1
receive for Port-channel1
200.1.1.0/30, epoch 0
nexthop 172.16.1.2 Port-channel1
224.0.0.0/4, epoch 0
Special source: drop
drop
224.0.0.0/24, epoch 0, flags receive
Special source: receive

https://t.me/learningnets

Technet24

receive

240.0.0.0/4, epoch 0

Special source: drop

drop

255.255.255.255/32, epoch 0, flags receive

Special source: receive

receive

Finally, use a simple ping to verify connectivity between switches ALS1 and ALS2:

ALS1#**ping 200.1.1.2**

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 200.1.1.2, timeout is 2 seconds:

..!!!

Success rate is 60 percent (3/5), round-trip min/avg/max = 1/3/4 ms

And finally, Telnet between the switches:

ALS1#**telnet 200.1.1.2**
Trying 200.1.1.2 ... Open

Password required, but none set

[Connection to 200.1.1.2 closed by foreign host]
ALS1#

Task 5

This task requires a little thought. When configuring VACLs, if the configured VLAN map has a match clause for the type of packet, which can either be IP or MAC, and the packet does not match the type, the default is to drop the packet. However, if there is no match clause in the VLAN map for that type of packet, and no action specified, the packet is forwarded. This task is completed as follows:

DLS1(config)#**ip access-list extended ALLOW-TCP**

DLS1(config-ext-nacl)#**permit tcp any any**

DLS1(config-ext-nacl)#**exit**

DLS1(config)#**ip access-list extended ALLOW-UDP**

DLS1(config-ext-nacl)#**permit udp any any**

DLS1(config-ext-nacl)#**exit**

DLS1(config)#**vlan access-map VLAN-100 10**

https://t.me/learningnets

DLS1(config-access-map)#**match ip address ALLOW-TCP**

DLS1(config-access-map)#**action drop**

DLS1(config-access-map)#**exit**

DLS1(config)#**vlan access-map VLAN-100 20**

DLS1(config-access-map)#**match ip address ALLOW-UDP**

DLS1(config-access-map)#**action drop**

DLS1(config-access-map)#**exit**

DLS1(config)#**vlan access-map VLAN-100 30**

DLS1(config-access-map)#**action forward**

DLS1(config-access-map)#**exit**

DLS1(config)#**vlan filter VLAN-100 vlan-list 100**

The configuration of the VACL on switch DLS2 follows similar logic. To determine the MAC address of switch ALS1, simply use the **show arp** command on switch DLS2.

DLS2(config)#**ip access-list extended ALLOW-ICMP**

DLS2(config-ext-nacl)#**permit icmp any any**

DLS2(config-ext-nacl)#**exit**

DLS2(config)#**mac access-list extended SWITCH-ALS2**

DLS2(config-ext-macl)#**permit host 0009.b79f.7d80 any**

DLS2(config-ext-macl)#**exit**

DLS2(config)#**vlan access-map VLAN-200 10**

DLS2(config-access-map)#**match ip address ALLOW-ICMP**

DLS2(config-access-map)#**action forward**

DLS2(config-access-map)#**exit**

DLS2(config)#**vlan access-map VLAN-200 20**

DLS2(config-access-map)#**match mac address SWITCH-ALS2**

DLS2(config-access-map)#**action forward**

DLS2(config-access-map)#**exit**

DLS2(config)#**vlan filter VLAN-200 vlan-list 200**

Following completion, verify the switch VACL configuration using the **show vlan access-map** and **show vlan filter** commands on switches DLS1 and DSL2. The output of the **show vlan access-map** command is shown below:

https://t.me/learningnets

Technet24

DLS2#**show vlan filter**
VLAN Map VLAN-200 is filtering VLANs:
200

The output of the **show vlan filter** command is shown below:

DLS2#**show vlan access-map**
Vlan access-map “VLAN-200” 10
Match clauses:
ip address: ALLOW-ICMP
Action:
forward
Vlan access-map “VLAN-200” 20
Match clauses:
mac address: SWITCH-ALS2
Action:
forward

Next, verify that the Access layer switches ALS1 and ALS2 can still ping each other:

ALS1#**ping 200.1.1.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 200.1.1.2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms

Finally, ensure that Telnet no longer works because of the applied VACL:

ALS1#**telnet 200.1.1.2**
Trying 200.1.1.2 ...
% Connection timed out; remote host not responding

ALS1#

Task 6

Dynamic ARP Inspection (DAI) depends on the entries in the DHCP Snooping binding database to verify IP-to-MAC address bindings in incoming ARP requests and ARP responses. However, when DHCP Snooping is disabled or in non-DHCP environments, you must use ARP ACLs to permit or to deny packets. The first part of this task entails configuring an ARP ACL for switch ALS1 in VLAN 100. This is completed as follows:

DLS1(config)#**arp access-list VLAN-100-DAI-ACL**
DLS1(config-arp-nacl)#**permit ip host 100.1.1.2 mac host 0007.8432.dd00 log**
DLS1(config-arp-nacl)#**exit**

https://t.me/learningnets

DLS1(config)#**ip arp inspection filter VLAN-100-DAI-ACL vlan 100 static**
DLS1(config)#**ip arp inspection vlan 100**
DLS1(config)#**ip arp inspection vlan 100 logging acl-match matchlog**

NOTE: The additional **static** keyword is used to treat implicit denies in the ARP ACL as explicit denies and to drop packets that do not match any previous clauses in the ACL.

The second part of the task is to configure the interface on DLS1 that is connected to ALS1 as untrusted (which means packets are inspected by DAI). Additionally, the task calls for comparing invalid and unexpected IP addresses, which includes 0.0.0.0, 255.255.255.255, all IP Multicast addresses and source MACs. This task is completed as follows:

DLS1(config)#**ip arp inspection validate ip src-mac**

Use the **show ip arp inspection** commands to verify your configuration:

DLS1#**show ip arp inspection vlan** 100

Source Mac Validation : Enabled
Destination Mac Validation : Disabled
IP Address Validation : Enabled

Vlan Configuration Operation ACL Match Static ACL
---- ------------- --------- --------- ----------
100 Enabled Active VLAN-100-DAI-ACL Yes

Vlan ACL Logging DHCP Logging Probe Logging
---- ----------- ------------ -------------
100 Acl-Match Deny Off

Finally, verify that switch ALS1 can still ping switch ALS2 using a simple ping as follows:

ALS1#**ping 200.1.1.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 200.1.1.2, timeout is 2 seconds:
!!!!!

You can test your configuration by changing the MAC address of SVI 100 on switch ALS1 and then attempting to ping switch ALS2. This is performed as follows:

ALS1(config)#**int vlan 100**
ALS1(config-if)#**mac-address 0009.b79f.7d80**
ALS1(config-if)#**end**
ALS1#**sh run int vlan 100**

https://t.me/learningnets

Technet24

Building configuration...

Current configuration : 110 bytes
!
interface Vlan100
mac-address 0009.b79f.7d80
ip address 100.1.1.2 255.255.255.252
no ip route-cache
end

ALS1#**ping 200.1.1.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 200.1.1.2, timeout is 2 seconds:
.....
Success rate is 0 percent (0/5)

On switch DLS1, use the **show ip arp inspection** command to see dropped packet statistics:

DLS1#**show ip arp inspection**

Source Mac Validation : Enabled
Destination Mac Validation : Disabled
IP Address Validation : Enabled

Vlan Configuration Operation ACL Match Static ACL
---- ------------- -------- -------- ----------
100 Enabled Active VLAN-100-DAI-ACL Yes

Vlan ACL Logging DHCP Logging Probe Logging
---- ----------- ----------- ------------
100 Acl-Match Deny Off

Vlan Forwarded Dropped DHCP Drops ACL Drops
---- --------- ------- ---------- ---------
100 0 12 0 12

Vlan DHCP Permits ACL Permits Probe Permits Source MAC Failures
---- ------------ ----------- ------------ ------------------
100 0 0 0 0

Vlan Dest MAC Failures IP Validation Failures Invalid Protocol Data
---- ----------------- ---------------------- --------------------

Vlan Dest MAC Failures IP Validation Failures Invalid Protocol Data
---- ----------------- ---------------------- --------------------

https://t.me/learningnets

100 0 0 0

When you change the MAC address of SVI 100 on ALS1 back to what it should be, you will see statistics for forwarded packets as well:

DLS1#**show ip arp inspection**

Source Mac Validation : Enabled
Destination Mac Validation : Disabled
IP Address Validation : Enabled

Vlan Configuration Operation ACL Match Static ACL
---- ------------- --------- --------- ----------
100 Enabled Active VLAN-100-DAI-ACL Yes

Vlan ACL Logging DHCP Logging Probe Logging
---- ----------- ------------ -------------
100 Acl-Match Deny Off

Vlan Forwarded Dropped DHCP Drops ACL Drops
---- --------- ------- ---------- ---------
100 2 18 0 18

Vlan DHCP Permits ACL Permits Probe Permits Source MAC Failures
---- ------------ ----------- ------------ -------------------
100 0 2 0 0

Vlan Dest MAC Failures IP Validation Failures Invalid Protocol Data
---- ----------------- ---------------------- --------------------

Vlan Dest MAC Failures IP Validation Failures Invalid Protocol Data
---- ----------------- ---------------------- --------------------
100 0 0 0 0

https://t.me/learningnets

Technet24

CCNP Lab 005: DHCP, Source Guard and 802.1X

Lab Objective:

The focus of this lab is to understand how to implement and verify Cisco IOS DHCP features and security, IP Source Guard and IEEE 802.1X port-based security.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please begin each and every lab by shutting down all interfaces on all switches and then manually re-enabling only the interfaces that are illustrated in this topology.

Task 1

Disable VTP on all switches. All switches should support the configuration, modification and deletion of VLANs.

Task 2

Configure VLAN 100 on switches ALS1 and DLS1 and then configure SVI 100 on switch DLS1. This SVI should be assigned the address 100.1.1.1/24.

Configure VLAN 200 on switches DLS1 and DLS2 and then configure SVI 200 on switch DLS1 and DLS2. Assign these interfaces the IP addresses 200.1.1.1/30 and 200.1.1.2/30, respectively.

Task 3

Configure the ports between DLS1 and ALS1 and between ALS1 and R1 as access ports in VLAN 100. Next, configure the ports between the DLS1 and DLS2 as access ports in VLAN 200. Verify that DLS1 and DLS2 can ping each other across VLAN 200.

Task 4

Configure Cisco IOS DHCP Server functionality on switch DLS2 as follows:

https://t.me/learningnets

Technet24

- Network/Mask: 100.1.1.0/24
- Excluded Addresses: 100.1.1.1 - 100.1.1.5
- Default Gateway: 100.1.1.1
- Domain Name: 101labs.net
- Lease Expiration: 8 hours

Task 5

Configure Cisco IOS DHCP Relay Agent on switch DLS1. This should point to switch DLS2, which will be providing DHCP services for the 100.1.1.0/24 network.

Ensure that the network is appropriately configured so that the DHCP server can assign addresses to hosts on the 100.1.1.0/24 network.

Task 6

Configure DHCP Snooping on switch DLS1. The port connected to the DHCP server should be trusted. All other port should be considered untrusted. Enable IP Source Guard for VLAN 100.

Task 7

Configure router R1 to receive addressing via DHCP. Verify that DHCP Snooping and IP Source Guard are functioning correctly using the appropriate commands.

Lab Validation:

Task 1

DLS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

DLS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

ALS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

ALS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

Task 2

DLS1(config)#**vlan 100**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 200**
DLS1(config-vlan)#**exit**
DLS1(config)#**interface vlan 100**

https://t.me/learningnets

DLS1(config-if)#**ip address 100.1.1.1 255.255.255.0**
DLS1(config-if)#**exit**
DLS1(config)#**interface vlan 200**
DLS1(config-if)#**ip address 200.1.1.1 255.255.255.252**
DLS1(config-if)#**exit**

DLS2(config)#**vlan 200**
DLS2(config-vlan)#**exit**
DLS2(config)#**interface vlan 200**
DLS2(config-if)#**ip address 200.1.1.2 255.255.255.252**
DLS2(config-if)#**exit**

ALS1(config)#**vlan 100**
ALS1(config-vlan)#**exit**

Task 3

DLS1(config)#**interface fastethernet 0/7**
DLS1(config-if)#**switchport mode access**
DLS1(config-if)#**switchport access vlan 100**
DLS1(config-if)#**exit**
DLS1(config)#**interface fastethernet0/11**
DLS1(config-if)#**switchport mode access**
DLS1(config-if)#**switchport access vlan 200**
DLS1(config-if)#**exit**

DLS2(config)#**interface fastethernet0/11**
DLS2(config-if)#**switchport mode access**
DLS2(config-if)#**switchport access vlan 200**
DLS2(config-if)#**exit**

ALS1(config)#**interface fastethernet 0/1**
ALS1(config-if)#**switchport mode access**
ALS1(config-if)#**switchport access vlan 100**
ALS1(config-if)#**exit**
ALS1(config)#**interface fastethernet 0/7**
ALS1(config-if)#**switchport mode access**
ALS1(config-if)#**switchport access vlan 100**
ALS1(config-if)#**exit**

Finally, verify your configuration by pinging between switches DLS1 and DLS2:

DLS1#**ping 200.1.1.2**

Type escape sequence to abort.

https://t.me/learningnets

Technet24

Sending 5, 100-byte ICMP Echos to 200.1.1.2, timeout is 2 seconds:
.!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 1/3/4 ms

Task 4

DLS2(config)#**ip dhcp excluded-address 100.1.1.1 100.1.1.5**
DLS2(config)#**ip dhcp pool VLAN-100-POOL**
DLS2(dhcp-config)#**network 100.1.1.0 255.255.255.0**
DLS2(dhcp-config)#**default-router 100.1.1.1**
DLS2(dhcp-config)#**domain-name 101labs.net**
DLS2(dhcp-config)#**lease 0 8 0**
DLS2(dhcp-config)#**exit**

Task 5

The first part of this task is straightforward and is completed as follows:

DLS1(config)#**interface vlan 100**
DLS1(config-if)#**ip helper-address 200.1.1.2**
DLS1(config-if)#**exit**

To complete the second part of the question, you need to ensure that switch DLS2 has IP reachability to the 100.1.1.0/24 subnet. Use either static routes or dynamic protocols. In this example, a simple default route pointing to switch DLS1 is configured on switch DLS2:

DLS2(config)#**ip routing**

DLS2(config)#**ip route 0.0.0.0 0.0.0.0 vlan 200 200.1.1.1**

Additionally, you need to enable IP routing on switch DLS1 (if not enabled by default)

DLS1(config)#**ip routing**

Following this, verify connectivity using a simple ping:

DLS2#**ping 100.1.1.1**

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 100.1.1.1, timeout is 2 seconds:

!!!!!

Success rate is 100 percent (5/5), round-trip min/avg/max = 4/4/4 ms

Task 6

This task requires a little thought. DHCP Snooping is required on VLANs 100 and 200. The port connected to switch DLS2 should be trusted because this is connected to the

https://t.me/learningnets

DHCP server. All other ports should be considered untrusted. This task is completed on switch DLS1 as follows:

DLS1(config)#**ip dhcp snooping**
DLS1(config)#**ip dhcp snooping vlan 100**
DLS1(config)#**ip dhcp snooping vlan 200**
DLS1(config)#**interface fastethernet 0/11**
DLS1(config-if)#**ip dhcp snooping trust**

Verify DHCP Snooping configuration using the **show ip dhcp snooping** commands:

DLS1#**show ip dhcp snooping**
Switch DHCP snooping is enabled
DHCP snooping is configured on following VLANs:
100,200
DHCP snooping is operational on following VLANs:
100,200
DHCP snooping is configured on the following L3 Interfaces:

Insertion of option 82 is enabled
circuit-id format: vlan-mod-port
remote-id format: MAC
Option 82 on untrusted port is not allowed
Verification of hwaddr field is enabled
Verification of giaddr field is enabled
DHCP snooping trust/rate is configured on the following Interfaces:

Interface Trusted Rate limit (pps)
------------------------ ------- ----------------
FastEthernet0/11 yes unlimited

The second part of this task is to enable IP Source Guard. IOS IP Source Guard is a feature that restricts IP traffic on untrusted Layer 2 ports by filtering the traffic based on the DHCP snooping binding database or manually configured IP source bindings.

This feature is used to prevent IP spoofing attacks. Any traffic coming into the interface with a source IP address other than that assigned via DHCP or static configuration will be filtered out on the untrusted Layer 2 ports. This task is completed as follows:

DLS1(config)#**interface fastethernet 0/7**
DLS1(config-if)#**ip verify source**
DLS1(config-if)#**exit**

Task 7

This task requires the router to be configured as a DHCP client. This is completed as

https://t.me/learningnets
Technet24

follows:

```
R1(config)#interface fastethernet 0/0
R1(config-if)#ip address dhcp
R1(config-if)#exit
R1(config)#
*Apr 10 01:33:28.183: %DHCP-6-ADDRESS_ASSIGN: Interface FastEthernet0/0
assigned DHCP address 100.1.1.6, mask 255.255.255.0, hostname R1
```

Following successful DHCP assignment, verify DHCP Snooping configuration using the show ip dhcp snooping commands on switch DLS1:

```
DLS1#show ip dhcp snooping binding
MacAddress IpAddress Lease(sec) Type VLAN Interface
------------------ --------------- ---------- ------------ ---- --------------------
00:0F:23:5E:EC:80 100.1.1.6 28602 dhcp-snooping 100 FastEthernet0/7
Total number of bindings: 1
```

Finally, verify IP Source Guard using the **show ip source binding** commands on switch DLS1:

```
DLS1#show ip source binding dhcp-snooping
MacAddress IpAddress Lease(sec) Type VLAN Interface
------------------ --------------- ---------- ------------ ---- --------------------
00:0F:23:5E:EC:80 100.1.1.6 28421 dhcp-snooping 100 FastEthernet0/7
Total number of bindings: 1
```

https://t.me/learningnets

CCNP Lab 006: HSRP and Switch Security

Lab Objective:

The focus of this lab is to understand basic HSRP and common security technology implementation and configuration in Cisco IOS Catalyst switches.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please begin each and every lab by shutting down all interfaces on all switches and then manually re-enabling only the interfaces that are illustrated in this topology.

Task 1

Disable VTP on all switches and create the following VLANs:

- DLS1: VLAN 100 and VLAN 200
- DLS2: VLAN 100 and VLAN 200
- ALS1: VLAN 100
- ALS2: VLAN 200

Task 2

Disable DTP and 802.1Q configure trunking on all switches as follows:

- The trunk links on switch DLS1 should only allow VLANs 1, 100 and 200
- The trunk links on switch DLS2 should only allow VLANs 1, 100 and 200
- The trunk links on switch ALS1 should only allow VLANs 1 and 100
- The trunk links on switch ALS2 should only allow VLANs 1 and 200

https://t.me/learningnets

Task 3

Configure the following SVIs and interfaces on the switches in the topology:

- DLS1: Interface VLAN 100: IP address 100.1.1.1/24
- DLS1: Interface VLAN 200: IP address 200.1.1.1/24

- DLS2: Interface VLAN 100: IP address 100.1.1.2/24
- DLS2: Interface VLAN 200: IP address 200.1.1.2/24

- ALS1: Interface VLAN 100: IP address 100.1.1.3/24
- ALS2: Interface VLAN 100: IP address 200.1.1.3/24

Task 4

Configure Cisco HSRP version 1 with preemption on switches DLS1 and DLS2 as follows:

- DLS1: VLAN 100: HSRP IP address 100.1.1.254, group 1, priority 105, password HSRP1
- DLS1: VLAN 200: HSRP IP address 200.1.1.254, group 2, priority 100, password HSRP2

- DLS2: VLAN 100: HSRP IP address 100.1.1.254, group 1, priority 100, password HSRP1
- DLS2: VLAN 200: HSRP IP address 200.1.1.254, group 2, priority 105, password HSRP2

Task 5

To allow for faster convergence, enable RPVST+. In addition to this, ensure that your Layer 2 and Layer 3 topologies are consistent, i.e. the primary gateway should be the root for the corresponding VLAN. Finally, ensure that switches ALS1 and ALS2 can also ping each other.

Task 6

Configure port security on all trunk links on switches DLS1 and DLS2. The switch port security configuration should allow a maximum of 10 addresses. When this limit has been reached, the switch should drop packets with unknown MAC addresses, until the number is of MAC addresses is below the limit. Additionally, the switch should send out an SNMP trap and a Syslog message, and the violation counter should be

https://t.me/learningnets

Technet24

incremented.

Lab Validation:

Task 1

DLS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.
DLS1(config)#**vlan 100**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 200**
DLS1(config-vlan)#**exit**

DLS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.
DLS2(config)#**vlan 100**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 200**
DLS2(config-vlan)#**exit**

ALS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.
ALS1(config)#**vlan 100**
ALS1(config-vlan)#**exit**

ALS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.
ALS2(config)#**vlan 200**
ALS2(config-vlan)#**exit**

Task 2

DLS1(config)#**interface range fasteth 0/7 , fasteth 0/9 , fasteth 0/11**
DLS1(config-if-range)#**switchport**
DLS1(config-if-range)#**switchport trunk encapsulation dot1q**
DLS1(config-if-range)#**switchport mode trunk**
DLS1(config-if-range)#**switchport trunk allowed vlan 1,100,200**
DLS1(config-if-range)#**switchport nonegotiate**
DLS1(config-if-range)#**exit**

DLS2(config)#**interface range fasteth 0/7 , fasteth 0/9 , fasteth 0/11**
DLS2(config-if-range)#**switchport**
DLS2(config-if-range)#**switchport trunk encapsulation dot1q**
DLS2(config-if-range)#**switchport mode trunk**

https://t.me/learningnets

DLS2(config-if-range)#**switchport trunk allowed vlan 1,100,200**
DLS2(config-if-range)#**switchport nonegotiate**
DLS2(config-if-range)#**exit**

ALS1(config)#**interface range fastethernet 0/7 , fastethernet 0/9**
ALS1(config-if-range)#**switchport mode trunk**
ALS1(config-if-range)#**switchport trunk allowed vlan 1,100**
ALS1(config-if-range)#**exit**

ALS2(config)#**interface range fastethernet 0/7 , fastethernet 0/9**
ALS2(config-if-range)#**switchport mode trunk**
ALS2(config-if-range)#**switchport trunk allowed vlan 1,200**
ALS2(config-if-range)#**exit**

Verify your configuration using the **show interfaces trunk** command:

DLS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 on 802.1q trunking 1
Fa0/11 on 802.1q trunking 1

Port Vlans allowed on trunk
Fa0/7 1,100,200
Fa0/11 1,100,200

Port Vlans allowed and active in management domain
Fa0/7 1,100,200
Fa0/11 1,100,200

Port Vlans in spanning tree forwarding state and not pruned
Fa0/7 1,100,200
Fa0/11 200

Task 3

DLS1(config)#**interface vlan 100**
DLS1(config-if)#**ip add 100.1.1.1 255.255.255.0**
DLS1(config-if)#**exit**
DLS1(config)#**interface vlan 200**
DLS1(config-if)#**ip add 200.1.1.1 255.255.255.0**
DLS1(config-if)#**exit**
DLS1(config)#**ip routing**

DLS2(config)#**interface vlan 100**
DLS2(config-if)#**ip address 100.1.1.2 255.255.255.0**

https://t.me/learningnets

Technet24

DLS2(config-if)#**exit**
DLS2(config)#**interface vlan 200**
DLS2(config-if)#**ip address 200.1.1.2 255.255.255.0**
DLS2(config-if)#**exit**
DLS2(config)#**ip routing**

ALS1(config)#**interface vlan 100**
ALS1(config-if)#**ip add 100.1.1.3 255.255.255.0**
ALS1(config-if)#**exit**
ALS1(config)#**ip routing**

ALS2(config)#**interface vlan 200**
ALS2(config-if)#**ip address 200.1.1.3 255.255.255.0**
ALS2(config-if)#**exit**
ALS2(config)#**ip routing**

Task 4

When completing this task, keep in mind that the default priority value for HSRP is 100 and so no explicit configuration is required to specify this value. However, unlike VRRP, preemption for HSRP is disabled by default and must be explicitly configured. Additionally, by default, when HSRP is enabled, version 1 is enabled. This task is completed as follows:

DLS1(config)#**interface vlan 100**
DLS1(config-if)#**standby 1 ip 100.1.1.254**
DLS1(config-if)#**standby 1 priority 105**
DLS1(config-if)#**standby 1 preempt**
DLS1(config-if)#**standby 1 authentication text HSRP1**
DLS1(config-if)#**exit**
DLS1(config)#**interface vlan 200**
DLS1(config-if)#**standby 2 ip 200.1.1.254**
DLS1(config-if)#**standby 2 preempt**
DLS1(config-if)#**standby 2 authentication text HSRP2**
DLS1(config-if)#**exit**

DLS2(config)#**interface vlan 100**
DLS2(config-if)#**standby 1 ip 100.1.1.254**
DLS2(config-if)#**standby 1 preempt**
DLS2(config-if)#**standby 1 authentication text HSRP1**
DLS2(config-if)#**exit**

https://t.me/learningnets

DLS2(config)#**interface vlan 200**

DLS2(config-if)#**standby 2 ip 200.1.1.254**

DLS2(config-if)#**standby 2 priority 105**

DLS2(config-if)#**standby 2 preempt**

DLS2(config-if)#**standby 2 authentication text HSRP2**

DLS2(config-if)#**exit**

Next, although not explicitly stated, configure the default gateway for switches ALS1 and ALS2 as the HSRP virtual IP (VIP) address so that they can reach other.

ALS1(config)#**ip default-gateway 100.1.1.254**

ALS2(config)#**ip default-gateway 200.1.1.254**

Verify your configuration using the **show standby** commands on switches DLS1 and DLS2:

DLS1#**show stand brief**

P indicates configured to preempt.

|

Interface Grp Prio P State Active Standby Virtual IP

Vl100 1 105 P Active local 100.1.1.2 100.1.1.254

Vl200 2 100 P Standby 200.1.1.2 local 200.1.1.254

DLS2#**show standby**

Vlan100 - Group 1

State is Standby

9 state changes, last state change 00:01:42

Virtual IP address is 100.1.1.254

Active virtual MAC address is 0000.0c07.ac01

Local virtual MAC address is 0000.0c07.ac01 (v1 default)

Hello time 3 sec, hold time 10 sec

Next hello sent in 2.620 secs

Authentication text “HSRP1”

Preemption enabled

Active router is 100.1.1.1, priority 105 (expires in 8.612 sec)

Standby router is local

https://t.me/learningnets

Technet24

Priority 100 (default 100)

IP redundancy name is “hsrp-Vl100-1” (default)

Vlan200 - Group 2

State is Active

5 state changes, last state change 00:14:18

Virtual IP address is 200.1.1.254

Active virtual MAC address is 0000.0c07.ac02

Local virtual MAC address is 0000.0c07.ac02 (v1 default)

Hello time 3 sec, hold time 10 sec

Next hello sent in 0.244 secs

Authentication text “HSRP2”

Preemption enabled

Active router is local

Standby router is 200.1.1.1, priority 100 (expires in 9.836 sec)

Priority 105 (configured 105)

IP redundancy name is “hsrp-Vl200-2” (default)

Task 5

The first part of this task is simple. RPVST+ is enabled on all switches as follows:

DLS1(config)#**spanning-tree mode rapid-pvst**

DLS2(config)#**spanning-tree mode rapid-pvst**

ALS1(config)#**spanning-tree mode rapid-pvst**

ALS2(config)#**spanning-tree mode rapid-pvst**

The second part of this task entails adjusting the default root bridges for the respective VLANs. Given that switch DLS1 is the primary gateway for VLAN 100, it should be root for that VLAN. Given that switch DLS2 is the primary gateway for VLAN 200, it should be root for that VLAN. These two switches should be configured as the secondary or backup root bridge for the other VLAN. This task is completed as follows:

DLS1(config)#**spanning-tree vlan 100 priority 4096**
DLS1(config)#**spanning-tree vlan 200 priority 8192**

DLS2(config)#**spanning-tree vlan 100 priority 8192**
DLS2(config)#**spanning-tree vlan 200 priority 4096**

Following this, verify your configuration using the **show spanning-tree** commands:

https://t.me/learningnets

DLS1#**show spanning-tree summary**
Switch is in rapid-pvst mode
Root bridge for: VLAN0100
Extended system ID is enabled
Portfast Default is disabled
PortFast BPDU Guard Default is disabled
Portfast BPDU Filter Default is disabled
Loopguard Default is disabled
EtherChannel misconfig guard is enabled
UplinkFast is disabled
BackboneFast is disabled
Configured Pathcost method used is short

Name Blocking Listening Learning Forwarding STP Active
---------- -------- --------- -------- ---------- ----------
VLAN0001 1 0 0 1 2
VLAN0100 0 0 0 2 2
VLAN0200 0 0 0 2 2
---------- -------- --------- -------- ---------- ----------
3 vlans 1 0 0 5 6

DLS2#**show spanning-tree summary**
Switch is in rapid-pvst mode
Root bridge for: VLAN0200
Extended system ID is enabled
Portfast Default is disabled
PortFast BPDU Guard Default is disabled
Portfast BPDU Filter Default is disabled
Loopguard Default is disabled
EtherChannel misconfig guard is enabled
UplinkFast is disabled
BackboneFast is disabled
Configured Pathcost method used is short

Name Blocking Listening Learning Forwarding STP Active
---------- -------- --------- -------- ---------- ----------
VLAN0001 0 0 0 2 2
VLAN0100 0 0 0 2 2
VLAN0200 0 0 0 2 2
---------- -------- --------- -------- ---------- ----------
3 vlans 0 0 0 6 6

https://t.me/learningnets
Technet24

The final task calls for verifying that switches ALS1 and ALS2 can ping each other:

ALS1#**ping 200.1.1.3**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 200.1.1.2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/1/4 ms

ALS2#**ping 100.1.1.3**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 100.1.1.2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 4/4/4 ms

Task 6

DLS1(config)#**interface range fasteth 0/7 , fasteth 0/9 , fasteth 0/11**
DLS1(config-if-range)#**switchport port-security**
DLS1(config-if-range)#**switchport port-security maximum 10**
DLS1(config-if-range)#**switchport port-security violation restrict**
DLS1(config-if-range)#**switchport port-security mac-address sticky**
DLS1(config-if-range)#**exit**

DLS2(config)#**interface range fasteth 0/7 , fasteth 0/9 , fasteth 0/11**
DLS2(config-if-range)#**switchport port-security**
DLS2(config-if-range)#**switchport port-security maximum 10**
DLS2(config-if-range)#**switchport port-security violation restrict**
DLS2(config-if-range)#**switchport port-security mac-address sticky**
DLS2(config-if-range)#**exit**

Following this configuration, use the **show port-security** commands for verification:

DLS1#**show port-security**
Secure Port MaxSecureAddr CurrentAddr SecurityViolation Security Action
(Count) (Count) (Count)

Fa0/7 10 0 1 Restrict
Fa0/9 10 0 1 Restrict
Fa0/11 10 0 1 Restrict

Total Addresses in System (excluding one mac per port) : 0
Max Addresses limit in System (excluding one mac per port) : 5120

https://t.me/learningnets

DLS2#**show port-security**
Secure Port MaxSecureAddr CurrentAddr SecurityViolation Security Action
(Count) (Count) (Count)

Fa0/7 10 1 0 Restrict
Fa0/9 10 1 0 Restrict
Fa0/11 10 0 0 Restrict

Total Addresses in System (excluding one mac per port) : 0
Max Addresses limit in System (excluding one mac per port) : 5120

https://t.me/learningnets

Technet24

CCNP Lab 007: HSRP and STP Convergence

Lab Objective:

The focus of this lab is to understand basic HSRP and STP convergence tweaking implementation and configuration in Cisco IOS Catalyst switches.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please begin each and every lab by shutting down all interfaces on all switches and then manually re-enabling only the interfaces that are illustrated in this topology.

Task 1

Disable VTP on all switches and create the following VLANs:

- DLS1: VLAN 100 and VLAN 200
- DLS2: VLAN 100 and VLAN 200
- ALS1: VLAN 100
- ALS2: VLAN 200

Task 2

Disable DTP and configure trunking on all switches as follows:

- The trunk links on switch DLS1 should only allow VLANs 1, 100 and 200
- The trunk links on switch DLS2 should only allow VLANs 1, 100 and 200
- The trunk links on switch ALS1 should only allow VLANs 1 and 100
- The trunk links on switch ALS2 should only allow VLANs 1 and 200

https://t.me/learningnets

Technet24

Task 3

Configure the following SVIs and interfaces on the switches in the topology:

- DLS1: Interface VLAN 100: IP address 100.1.1.1/24
- DLS1: Interface VLAN 200: IP address 200.1.1.1/24
- DLS1: Interface Loopback0: IP address 192.1.1.1/24

- DLS2: Interface VLAN 100: IP address 100.1.1.2/24
- DLS2: Interface VLAN 200: IP address 200.1.1.2/24

- ALS1: Interface VLAN 100: IP address 100.1.1.3/24
- ALS2: Interface VLAN 100: IP address 200.1.1.3/24

Task 4

Configure HSRP with preemption and MD5 authentication on DLS1 and DLS2 as follows:

- DLS1: VLAN 100: HSRP IP address 100.1.1.254, group 1, priority 200, MD5 password: ONE
- DLS1: VLAN 200: HSRP IP address 200.1.1.254, group 2, priority 200, MD5 password: TWO

- DLS2: VLAN 100: HSRP IP address 100.1.1.254, group 1, priority 150, MD5 password: ONE
- DLS2: VLAN 200: HSRP IP address 200.1.1.254, group 2, priority 150 MD5 password: TWO

Task 5

In the future, switch DLS1 will be configured to track an uplink port to the WAN routers. To test this solution, configure HSRP on switch DLS1 to track the Loopback0 interface. Should Loopback0 be shut down, ensure switch DLS2 becomes the active gateway for both groups.

Task 6

To allow for faster 802.1D convergence, configure the lowest possible diameter that will allow all devices in the network to communicate. In addition to this, ensure that your Layer 2 and Layer 3 topologies are consistent, i.e. the primary gateway should be the root for the corresponding VLAN. Finally, ensure that switches ALS1 and ALS2 can

https://t.me/learningnets

also ping each other.

Lab Validation:

Task 1

DLS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.
DLS1(config)#**vlan 100**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 200**
DLS1(config-vlan)#**exit**

DLS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.
DLS2(config)#**vlan 100**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 200**
DLS2(config-vlan)#**exit**

ALS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.
ALS1(config)#**vlan 100**
ALS1(config-vlan)#**exit**

ALS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.
ALS2(config)#**vlan 200**
ALS2(config-vlan)#**exit**

Task 2

DLS1(config)#**interface range fasteth 0/7 , fasteth 0/9 , fasteth 0/11**
DLS1(config-if-range)#**switchport**
DLS1(config-if-range)#**switchport trunk encapsulation dot1q**
DLS1(config-if-range)#**switchport mode trunk**
DLS1(config-if-range)#**switchport trunk allowed vlan 1,100,200**
DLS1(config-if-range)#**switchport nonegotiate**
DLS1(config-if-range)#**exit**

DLS2(config)# **interface range fasteth 0/7 , fasteth 0/9 , fasteth 0/11**DLS2(config-if-range)#**switchport**
DLS2(config-if-range)#**switchport trunk encapsulation dot1q**
DLS2(config-if-range)#**switchport mode trunk**

https://t.me/learningnets

Technet24

DLS2(config-if-range)#**switchport trunk allowed vlan 1,100,200**
DLS2(config-if-range)#**switchport nonegotiate**
DLS2(config-if-range)#**exit**

ALS1(config)#**interface range fastethernet 0/7 , fastethernet 0/9**
ALS1(config-if-range)#**switchport mode trunk**
ALS1(config-if-range)#**switchport trunk allowed vlan 1,100**
ALS1(config-if-range)#**exit**

ALS2(config)#**interface range fastethernet 0/7 , fastethernet 0/9**
ALS2(config-if-range)#**switchport mode trunk**
ALS2(config-if-range)#**switchport trunk allowed vlan 1,200**
ALS2(config-if-range)#**exit**

Verify your configuration using the **show interfaces trunk** command:

ALS2#show interfaces trunk

Port Mode Encapsulation Status Native vlan
Fa0/7 on 802.1q trunking 1
Fa0/9 on 802.1q trunking 1

Port Vlans allowed on trunk
Fa0/7 1,200
Fa0/9 1,200

Port Vlans allowed and active in management domain
Fa0/7 1,200
Fa0/9 1,200

Port Vlans in spanning tree forwarding state and not pruned
Fa0/7 1,200
Fa0/9 200

Task 3

DLS1(config)#**interface vlan 100**
DLS1(config-if)#**ip add 100.1.1.1 255.255.255.0**
DLS1(config-if)#**exit**
DLS1(config)#**interface vlan 200**
DLS1(config-if)#**ip add 200.1.1.1 255.255.255.0**
DLS1(config-if)#**exit**
DLS1(config)#**int loopback 0**
DLS1(config-if)#**ip add 192.1.1.1 255.255.255.0**
DLS1(config-if)#**exit**

https://t.me/learningnets

DLS2(config)#**interface vlan 100**
DLS2(config-if)#**ip address 100.1.1.2 255.255.255.0**
DLS2(config-if)#**exit**
DLS2(config)#**interface vlan 200**
DLS2(config-if)#**ip address 200.1.1.2 255.255.255.0**
DLS2(config-if)#**exit**

ALS1(config)#**interface vlan 100**
ALS1(config-if)#**ip add 100.1.1.3 255.255.255.0**
ALS1(config-if)#**exit**

ALS2(config)#**interface vlan 200**
ALS2(config-if)#**ip address 200.1.1.3 255.255.255.0**
ALS2(config-if)#**exit**

Task 4

When configuring HSRP MD5 authentication, you can reference a key chain, which contains the keys and key strings, or specify the key string directly with the HSRP configuration. Both methods are illustrated. The configuration on switch DLS1 has been implemented as follows:

DLS1(config)#**key chain HSRP-GROUP-ONE**
DLS1(config-keychain)#**key 1**
DLS1(config-keychain-key)#**key-string ONE**
DLS1(config-keychain-key)#**exit**
DLS1(config-keychain)#**exit**
DLS1(config)#**interface vlan 100**
DLS1(config-if)#**standby 1 ip 100.1.1.254**
DLS1(config-if)#**standby 1 priority 200**
DLS1(config-if)#**standby 1 preempt**
DLS1(config-if)#**standby 1 authentication md5 key-chain HSRP-GROUP-ONE**
DLS1(config-if)#**exit**
DLS1(config)#**interface vlan 200**
DLS1(config-if)#**standby 2 ip 200.1.1.254**
DLS1(config-if)#**standby 2 priority 200**
DLS1(config-if)#**standby 2 preempt**
DLS1(config-if)#**standby 2 authentication md5 key-string TWO**
DLS1(config-if)#**exit**

The configuration on switch DLS2 has been implemented as follows:

DLS2(config)#**key chain HSRP-GROUP-ONE**

https://t.me/learningnets

Technet24

DLS2(config-keychain)#**key 1**

DLS2(config-keychain-key)#**key-string ONE**

DLS2(config-keychain-key)#**exit**

DLS2(config-keychain)#**exit**

DLS2(config)#**interface vlan 100**

DLS2(config-if)#**standby 1 ip 100.1.1.254**

DLS2(config-if)#**standby 1 preempt**

DLS2(config-if)#**standby 1 priority 150**

DLS2(config-if)#**standby 1 authentication md5 key-chain HSRP-GROUP-ONE**

DLS2(config-if)#**exit**

DLS2(config)#**interface vlan 200**

DLS2(config-if)#**standby 2 ip 200.1.1.254**

DLS2(config-if)#**standby 2 preempt**

DLS2(config-if)#**standby 2 priority 150**

DLS2(config-if)#**standby 2 authentication md5 key-string TWO**

DLS2(config-if)#**exit**

Following this configuration, use the **show standby** commands to verify HSRP:

DLS1#**show standby brief**

P indicates configured to preempt.

|

Interface Grp Prio P State Active Standby Virtual IP

Vl100 1 200 P Active local 100.1.1.2 100.1.1.254

Vl200 2 200 P Active local 200.1.1.2 200.1.1.254

DLS2#**show standby**

Vlan100 - Group 1

State is Standby

4 state changes, last state change 00:01:46

Virtual IP address is 100.1.1.254

Active virtual MAC address is 0000.0c07.ac01

Local virtual MAC address is 0000.0c07.ac01 (v1 default)

Hello time 3 sec, hold time 10 sec

Next hello sent in 1.776 secs

Authentication MD5, key-chain "HSRP-GROUP-ONE"

Preemption enabled

https://t.me/learningnets

Active router is 100.1.1.1, priority 200 (expires in 7.776 sec)
Standby router is local
Priority 150 (configured 150)
IP redundancy name is “hsrp-Vl100-1” (default)
Vlan200 - Group 2
State is Standby
4 state changes, last state change 00:03:23
Virtual IP address is 200.1.1.254
Active virtual MAC address is 0000.0c07.ac02
Local virtual MAC address is 0000.0c07.ac02 (v1 default)
Hello time 3 sec, hold time 10 sec
Next hello sent in 0.828 secs
Authentication MD5, key-string “TWO”
Preemption enabled
Active router is 200.1.1.1, priority 200 (expires in 8.452 sec)
Standby router is local
Priority 150 (configured 150)
IP redundancy name is “hsrp-Vl200-2” (default)

Task 5

To complete this task, you need to configure HSRP tracking so that the priority of switch DLS1 is decremented to a value less than 150 when Loopback0 is disabled - allowing switch DLS2 to assume primary gateway functionality. This task is completed as follows:

DLS1(config)#**track 500 interface loopback 0 line-protocol**
DLS1(config-track)#**exit**
DLS1(config)#**interface vlan 100**
DLS1(config-if)#**standby 1 track 500 decrement 51**
DLS1(config-if)#**exit**
DLS1(config)#**interface vlan 200**
DLS1(config-if)#**standby 2 track 500 decrement 51**
DLS1(config-if)#**exit**

Following this configuration, use the show track command to verify object tracking:

DLS1#**show track 500**

Track 500

Interface Loopback0 line-protocol

Line protocol is Up

https://t.me/learningnets

Technet24

1 change, last change 00:01:51

Tracked by:

HSRP Vlan100 1

HSRP Vlan200 2

Additionally, use the **show standby** commands to verify HSRP tracking configuration:

DLS1#**show standby vlan 100**

Vlan100 - Group 1

State is Active

2 state changes, last state change 00:22:23

Virtual IP address is 100.1.1.254

Active virtual MAC address is 0000.0c07.ac01

Local virtual MAC address is 0000.0c07.ac01 (v1 default)

Hello time 3 sec, hold time 10 sec

Next hello sent in 0.908 secs

Authentication MD5, key-chain "HSRP-GROUP-ONE"

Preemption enabled

Active router is local

Standby router is 100.1.1.2, priority 150 (expires in 8.900 sec)

Priority 200 (configured 200)

Track object 500 state Up decrement 51

IP redundancy name is "hsrp-Vl100-1" (default)

Test the configuration by shutting down the Loopback0 interface on switch DLS1:

DLS1(config)#**interface loopback 0**

DLS1(config-if)#**shutdown**

DLS1(config-if)#

*Mar 1 00:51:16.799: %HSRP-5-STATECHANGE: Vlan200 Grp 2 state Active -> Speak

*Mar 1 00:51:17.159: %HSRP-5-STATECHANGE: Vlan100 Grp 1 state Active -> Speak

*Mar 1 00:51:18.627: %LINK-5-CHANGED: Interface Loopback0, changed state to administratively down

https://t.me/learningnets

*Mar 1 00:51:19.627: %LINEPROTO-5-UPDOWN: Line protocol on Interface Loopback0, changed state to down

*Mar 1 00:51:26.799: %HSRP-5-STATECHANGE: Vlan200 Grp 2 state Speak -> Standby

*Mar 1 00:51:27.159: %HSRP-5-STATECHANGE: Vlan100 Grp 1 state Speak -> Standby

Again, the **show standby** commands can be used to verify HSRP tracking configuration:

DLS1#**show standby vlan 100**
Vlan100 - Group 1
State is Standby
4 state changes, last state change 00:01:07
Virtual IP address is 100.1.1.254
Active virtual MAC address is 0000.0c07.ac01
Local virtual MAC address is 0000.0c07.ac01 (v1 default)
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.716 secs
Authentication MD5, key-chain "HSRP-GROUP-ONE"
Preemption enabled
Active router is 100.1.1.2, priority 150 (expires in 7.720 sec)
Standby router is local
Priority 149 (configured 200)
Track object 500 state Down decrement 51
IP redundancy name is "hsrp-Vl100-1" (default)

The **show track** command can be used to determine the state of the tracked object:

DLS1#**show track**
Track 500
Interface Loopback0 line-protocol
Line protocol is Down (hw admin-down)
2 changes, last change 00:01:42
Tracked by:
HSRP Vlan100 1
HSRP Vlan200 2

Task 6

Given the topology, the maximum diameter in any given situation would be 4. There are two ways the diameter can be influenced. These two methods are:

https://t.me/learningnets

Technet24

- Manually configuring STP parameters to force a diameter of 4
- Using the Cisco IOS macro to specify the diameter

The first method entails performing manual calculations using one of the following formulas:

Diameter = (Max Age + 2 - (4 * Hello)) / 2 or **Diameter = ((2 * Forward Delay) - (4 * Hello)) / 3**

The second method entails using the Cisco IOS macro, enabled by issuing the **spanning-tree vlan <number> root primary diameter <2-7>** global configuration command. The simplest method is to use the IOS macro on switch DLS1 which will be the root bridge for both VLANs.

DLS1(config)#**spanning-tree vlan 100 root primary diameter 4**
DLS1(config)#**spanning-tree vlan 200 root primary diameter 4**

When the diameter is changed, default STP timers are also adjusted. Use the **show spanning-tree** commands to verify the configuration:

DLS1#**show spanning-tree vlan 100**

VLAN0100
Spanning tree enabled protocol ieee
Root ID Priority 24676
Address 000f.2303.2d80
This bridge is the root
Hello Time 2 sec Max Age 14 sec Forward Delay 10 sec

Bridge ID Priority 24676 (priority 24576 sys-id-ext 100)
Address 000f.2303.2d80
Hello Time 2 sec Max Age 14 sec Forward Delay 10 sec
Aging Time 300

Interface Role Sts Cost Prio.Nbr Type
---------- ---- --- --------- -------- ----------
Fa0/7 Desg FWD 19 128.7 P2p
Fa0/9 Desg FWD 19 128.9 P2p
Fa0/11 Desg FWD 19 128.11 P2p

Using the manual method, we could confirm this calculation as follows:

Diameter = (Max Age + 2 - (4 * Hello)) / 2
Diameter = (14 + 2 - (4 * 2)) / 2
Diameter = (16 - 8)) / 2
Diameter = (8)) / 2

https://t.me/learningnets

Diameter = 4

The same result would be obtained using the alternate formula.

The final task is to ensure that switches ALS1 and ALS2 can ping each other. This requires that both switches be configured with default gateways (HSRP VIPs).

ALS1(config)#**ip default-gateway 100.1.1.254**

ALS2(config)#**ip default-gateway 200.1.1.254**

Finally, verify connectivity using a simple ping:

ALS1#**ping 200.1.1.3**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 200.1.1.2, timeout is 2 seconds:
..!!!
Success rate is 60 percent (3/5), round-trip min/avg/max = 1/3/4 ms

ALS2#**ping 100.1.1.3**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 100.1.1.2, timeout is 2 seconds:
..!!!
Success rate is 60 percent (3/5), round-trip min/avg/max = 1/3/4 ms

https://t.me/learningnets

Technet24

CCNP Lab 008: SNMP, Logging and Management

Lab Objective:

The focus of this lab is to understand basic SNMP, logging and switch management implementation and configuration in Cisco IOS Catalyst switches.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please begin each and every lab by shutting down all interfaces on all switches and then manually re-enabling only the interfaces that are illustrated in this topology.

Task 1

Configure VTP as following on the switches illustrated in the topology:

- Switches DLS1 and DLS2 should be VTP servers
- Switches ALS1 and ALS2 should be VTP clients
- The switches should reside in VTP domain 'CCNP'
- The VTP domain should be secured using the password 'CCNP'
- All switches should run VTP version 2

Task 2

Configure trunking on all switches and allow DTP to negotiate the trunking protocol. Assign the FastEthernet0/1 interface on switch ALS1 to VLAN 100.

https://t.me/learningnets

Technet24

Task 3

Configure switch DLS1 as the root bridge for VLAN 100, with switch DLS2 as the secondary (backup) root bridge. Next, configure the following SVIs and interfaces on the switches:

- DLS1: Interface VLAN 100: IP address 100.1.1.1/24
- DLS2: Interface VLAN 100: IP address 100.1.1.2/24
- ALS1: Interface VLAN 100: IP address 100.1.1.3/24
- ALS2: Interface VLAN 100: IP address 100.1.1.4/24

Finally, configure R1s FastEthernet 0/0 interface with the IP address 100.1.1.254.

Task 4

Configure SNMP on switches ALS1 and ALS2 as follows:

- Community string LEVEL1 should provide read-only access from 192.168.1.0/24
- Community string LEVEL2 should provide read-write access from 192.168.2.0/24
- SNMP traps for VTP should be sent to 10.1.1.253 using community LEVEL1
- SNMP traps for STP should be sent to 10.1.1.254 using community LEVEL2

Task 5

Configure logging on switches DLS1 and DLS2 as follows:

- Informational log messages should be sent to hosts 10.1.1.253 and 10.1.1.254
- Debugging log messages should be stored in the local buffer
- Log messages should include the date, time, millisecond values and local time zone
- Log messages should include a sequence number
- The local switch buffer size should be restricted to 10, 000

Task 6

For effective time management, configure Network Time Protocol as follows:

- Router R1 should be configured as the NTP server
- All switches should synchronize their time with router R1
- All network devices should reside in the EST (GMT -5) time zone

https://t.me/learningnets

- All network devices should adjust the time for daylight saving

Task 7

For effective configuration management, configure the Cisco IOS Command Scheduler to automatically save the configurations on switches DLS1 and DLS2 every 8 hours.

Lab Validation:

Task 1

DLS1(config)#**vtp mode server**
DLS1(config)#**vtp domain CCNP**
DLS1(config)#**vtp password CCNP**
DLS1(config)#**vtp version 2**

DLS2(config)#**vtp mode server**
DLS2(config)#**vtp domain CCNP**
DLS2(config)#**vtp password CCNP**
DLS2(config)#**vtp version 2**

ALS1(config)#**vtp version 2**
ALS1(config)#**vtp mode client**
ALS1(config)#**vtp domain CCNP**
ALS1(config)#**vtp password CCNP**

ALS2(config)#**vtp version 2**
ALS2(config)#**vtp mode client**
ALS2(config)#**vtp domain CCNP**
ALS2(config)#**vtp password CCNP**

NOTE: It is important to change the VTP version prior to configuring a switch as a VTP client. When the switch is in client mode, you cannot change the VTP version as shown below:

ALS2(config)#**vtp version 2**
Cannot modify version in VTP client mode

Task 2

DLS1(config)#**interface range fasteth 0/7, fasteth 0/9, fasteth 0/11**
DLS1(config-if-range)#**switchport**
DLS1(config-if-range)#**no shutdown**
DLS2(config-if-range)#**exit**

DLS2(config)#**interface range fasteth 0/7, fasteth 0/9, fasteth 0/11**
DLS2(config-if-range)#**switchport**

https://t.me/learningnets

Technet24

DLS2(config-if-range)#**no shutdown**
DLS2(config-if-range)#**exit**

ALS1(config)#**interface range fastethernet 0/7 , fastethernet 0/9**
ALS1(config-if-range)#**no shutdown**
ALS1(config)#**interface fastethernet 0/1**
ALS1(config-if)#**switchport mode access**
ALS1(config-if)#**switchport access vlan 100**
ALS1(config-if)#**no shutdown**

ALS2(config)#**interface range fastethernet 0/7 , fastethernet 0/9**
ALS2(config-if-range)#**no shutdown**

Following this, verify your configuration using the **show interfaces trunk** command:

DLS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 desirable n-802.1q trunking 1
Fa0/9 desirable n-802.1q trunking 1
Fa0/11 desirable n-isl trunking 1

ALS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 desirable 802.1q trunking 1
Fa0/9 desirable 802.1q trunking 1

Task 3

To complete this task, you first need to configure VLAN 100 on the VTP server devices prior to configuring the VLAN interfaces (SVIs) on the switches. This task is completed as follows:

DLS1(config)#**vlan 100**
DLS1(config-vlan)#**exit**
DLS1(config)#**spanning-tree vlan 100 priority 4096**
DLS1(config)#**interface vlan 100**
DLS1(config-if)#**ip address 100.1.1.1 255.255.255.0**
DLS1(config-if)#**exit**

DLS2(config)#**vlan 100**
DLS2(config-vlan)#**exit**
DLS2(config)#**spanning-tree vlan 100 priority 8192**
DLS2(config)#**interface vlan 100**
DLS2(config-if)#**ip address 100.1.1.2 255.255.255.0**

https://t.me/learningnets

DLS2(config-if)#**exit**

ALS1(config)#**interface vlan 100**
ALS1(config-if)#**ip address 100.1.1.3 255.255.255.0**
ALS1(config-if)#**exit**

ALS2(config)#**interface vlan 100**
ALS2(config-if)#**ip address 100.1.1.4 255.255.255.0**
ALS2(config-if)#**exit**

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip address 100.1.1.254 255.255.255.0**
R1(config-if)#**exit**

Next, verify your STP configuration using the **show spanning-tree** commands:

ALS2#**show spanning-tree vlan 100**

VLAN0100
Spanning tree enabled protocol ieee
Root ID Priority 4196
Address 000f.2303.2d80
Cost 19
Port 9 (FastEthernet0/9)
Hello Time 2 sec Max Age 20 sec Forward Delay 15 sec

Bridge ID Priority 32868 (priority 32768 sys-id-ext 100)
Address 0009.b79f.7d80
Hello Time 2 sec Max Age 20 sec Forward Delay 15 sec
Aging Time 300

Interface Role Sts Cost Prio.Nbr Type
---------------- ---- --- --------- -------- ----------------
Fa0/7 Altn BLK 19 128.7 P2p
Fa0/9 Root FWD 19 128.9 P2p

Finally, verify IP connectivity between the switches using a simple ping:

R1#**ping 100.1.1.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 100.1.1.0, timeout is 2 seconds:
.
Reply to request 1 from 100.1.1.1, 1 ms
Reply to request 1 from 100.1.1.4, 1 ms
Reply to request 1 from 100.1.1.3, 1 ms
Reply to request 1 from 100.1.1.2, 1 ms

https://t.me/learningnets

Technet24

Reply to request 2 from 100.1.1.1, 1 ms
Reply to request 2 from 100.1.1.4, 4 ms
Reply to request 2 from 100.1.1.3, 4 ms
Reply to request 2 from 100.1.1.2, 4 ms
Reply to request 3 from 100.1.1.1, 1 ms
Reply to request 3 from 100.1.1.4, 4 ms
Reply to request 3 from 100.1.1.3, 4 ms
Reply to request 3 from 100.1.1.2, 4 ms
Reply to request 4 from 100.1.1.1, 1 ms
Reply to request 4 from 100.1.1.4, 4 ms
Reply to request 4 from 100.1.1.3, 4 ms
Reply to request 4 from 100.1.1.2, 4 ms

Task 4

ALS1(config)#**access-list 1 permit 192.168.1.0 0.0.0.255**
ALS1(config)#**access-list 2 permit 192.168.2.0 0.0.0.255**
ALS1(config)#**snmp-server community LEVEL1 ro 1**
ALS1(config)#**snmp-server community LEVEL2 rw 2**
ALS1(config)#**snmp-server enable traps vtp**
ALS1(config)#**snmp-server enable traps stp**
ALS1(config)#**snmp-server host 10.1.1.253 traps version 2c LEVEL1 vtp**
ALS1(config)#**snmp-server host 10.1.1.254 traps version 2c LEVEL2 stp**

ALS2(config)#**access-list 1 permit 192.168.1.0 0.0.0.255**

ALS2(config)#**access-list 2 permit 192.168.2.0 0.0.0.255**

ALS2(config)#**snmp-server community LEVEL1 ro 1**

ALS2(config)#**snmp-server community LEVEL2 rw 2**

ALS2(config)#**snmp-server enable traps vtp**

ALS2(config)#**snmp-server enable traps stp**

ALS2(config)#**snmp-server host 10.1.1.253 traps version 2c LEVEL1 vtp**

ALS2(config)#**snmp-server host 10.1.1.254 traps version 2c LEVEL2 stp**

Verify your SNMP configuration using the **show snmp** commands:

ALS1#**show snmp**
Chassis: FAB0540Y20Z
0 SNMP packets input
0 Bad SNMP version errors
0 Unknown community name

https://t.me/learningnets

0 Illegal operation for community name supplied
0 Encoding errors
0 Number of requested variables
0 Number of altered variables
0 Get-request PDUs
0 Get-next PDUs
0 Set-request PDUs
0 SNMP packets output
0 Too big errors (Maximum packet size 1500)
0 No such name errors
0 Bad values errors
0 General errors
0 Response PDUs
0 Trap PDUs
SNMP global trap: disabled

SNMP logging: enabled
Logging to 10.1.1.253.162, 0/10, 0 sent, 0 dropped.
Logging to 10.1.1.254.162, 0/10, 0 sent, 0 dropped.

Task 5

DLS1(config)#**logging on**
DLS1(config)#**logging host 10.1.1.253**
DLS1(config)#**logging host 10.1.1.254**
DLS1(config)#**logging trap informational**
DLS1(config)#**logging buffered debugging**
DLS1(config)#**logging buffered 10000**
DLS1(config)#**service timestamps log datetime msec localtime**
DLS1(config)#**service sequence-numbers**
DLS1(config)#**exit**

DLS2(config)#**logging on**
DLS2(config)#**logging host 10.1.1.253**
DLS2(config)#**logging host 10.1.1.254**
DLS2(config)#**logging trap informational**
DLS2(config)#**logging buffered debugging**
DLS2(config)#**logging buffered 10000**
DLS2(config)#**service timestamps log datetime msec localtime**
DLS2(config)#**service sequence-numbers**
DLS2(config)#**exit**

https://t.me/learningnets

Technet24

Verify your configuration using the **show logging** commands:

DLS2#**show logging**

Syslog logging: enabled (0 messages dropped, 14 messages rate-limited, 0 flushes, 0 overruns, xml disabled, filtering disabled)

No Active Message Discriminator.

No Inactive Message Discriminator.

Console logging: disabled

Monitor logging: level debugging, 0 messages logged, xml disabled,

filtering disabled

Buffer logging: level debugging, 3 messages logged, xml disabled,

filtering disabled

Exception Logging: size (4096 bytes)

Count and timestamp logging messages: disabled

File logging: disabled

Persistent logging: disabled

Trap logging: level informational, 87 message lines logged

Logging to 10.1.1.253 (udp port 514, audit disabled,

authentication disabled, encryption disabled, link up),

3 message lines logged,

0 message lines rate-limited,

0 message lines dropped-by-MD,

xml disabled, sequence number disabled

filtering disabled

Logging to 10.1.1.254 (udp port 514, audit disabled,

authentication disabled, encryption disabled, link up),

3 message lines logged,

0 message lines rate-limited,

0 message lines dropped-by-MD,

xml disabled, sequence number disabled

filtering disabled

Log Buffer (10000 bytes):

https://t.me/learningnets

000082: *Mar 1 00:51:56.759: %SYS-5-CONFIG_I: Configured from console by console

000083: *Mar 1 00:51:57.759: %SYS-6-LOGGINGHOST_STARTSTOP: Logging to host 10.1.1.253 Port 514 started - CLI initiated

000084: *Mar 1 00:52:00.759: %SYS-6-LOGGINGHOST_STARTSTOP: Logging to host 10.1.1.254 Port 514 started - CLI initiated

Task 6

R1(config)#**ntp master**
R1(config)#**clock summer-time EST recurring**
R1(config)#**clock timezone EST -5**
May 1 01:40:00.000: %SYS-6-CLOCKUPDATE: System clock has been updated from 03:34:46 EST Wed Apr 10 2002 to 21:40:00 EST Sat Apr 30 2011

DLS1(config)#**ntp server 100.1.1.254**
DLS1(config)#**clock summer-time EST recurring**
DLS1(config)#**clock timezone EST -5**

DLS2(config)#**ntp server 100.1.1.254**
DLS2(config)#**clock summer-time EST recurring**
DLS2(config)#**clock timezone EST -5**

ALS1(config)#**ntp server 100.1.1.254**
ALS1(config)#**clock summer-time EST recurring**
ALS1(config)#**clock timezone EST -5**

ALS2(config)#**ntp server 100.1.1.254**
ALS2(config)#**clock summer-time EST recurring**
ALS2(config)#**clock timezone EST -5**

Following this configuration, use the **show ntp status** and **show ntp associations** commands to validate NTP. The **show ntp status** command shows whether or not the device is synchronized with the specified NTP server, the server stratum and server IP address. This command also includes the time received from the server. On the NTP master, the local Loopback address 127.127.7.1 is used as the NTP server IP address. This can be viewed below:

R1#**show ntp status**
Clock is synchronized, stratum 8, reference is 127.127.7.1
nominal freq is 250.0000 Hz, actual freq is 250.0000 Hz, precision is 2**16
reference time is D1673875.D60DC757 (21:40:05.836 EST Sat Apr 30 2011)
clock offset is 0.0000 msec, root delay is 0.00 msec
root dispersion is 15875.02 msec, peer dispersion is 15875.02 msec

https://t.me/learningnets

Technet24

All other devices show the IP address of the NTP server, which is 100.1.1.254, as shown below:

DLS1#**show ntp status**
Clock is synchronized, stratum 9, reference is 100.1.1.254
nominal freq is 250.0000 Hz, actual freq is 249.9999 Hz, precision is 2**18
reference time is D167397B.173143D3 (21:44:27.090 EST Sat Apr 30 2011)
clock offset is 0.0928 msec, root delay is 2.50 msec
root dispersion is 1750.17 msec, peer dispersion is 875.05 msec

The **show ntp associations [detail]** command provides information about each NTP server, including the stratum information as shown below:

DLS1#**show ntp associations detail**
100.1.1.254 configured, our_master, sane, valid, stratum 8
ref ID 127.127.7.1, time D16739B5.D60C5557 (21:45:25.836 EST Sat Apr 30 2011)
our mode client, peer mode server, our poll intvl 64, peer poll intvl 64
root delay 0.00 msec, root disp 375.03, reach 77, sync dist 752.274
delay 2.50 msec, offset 1.0837 msec, dispersion 375.99
precision 2**16, version 3
org time D16739BB.172AB9E9 (21:45:31.090 EST Sat Apr 30 2011)
rcv time D16739BB.173610D7 (21:45:31.090 EST Sat Apr 30 2011)
xmt time D16739BB.168E92A1 (21:45:31.088 EST Sat Apr 30 2011)
filtdelay = 2.50 2.50 2.50 2.52 2.52 2.50 0.00 0.00
filtoffset = 1.08 0.09 0.08 0.06 0.04 0.02 0.00 0.00
filterror = 0.02 0.99 1.01 1.02 1.04 1.05 16000.0 16000.0

Task 7

DLS1(config)#**kron policy-list Save-Configuration**
DLS1(config-kron-policy)#**cli write memory**
DLS1(config-kron-policy)#**exit**
DLS1(config)#**kron occurrence Auto-Management in 8:00 recurring**
DLS1(config-kron-occurrence)#**policy-list Save-Configuration**
DLS1(config-kron-occurrence)#**exit**

Following this configuration, use the **show kron schedule** command for validation:

DLS1#**show kron schedule**
Kron Occurrence Schedule
Auto-Management inactive, will run again in 0 days 07:58:25

https://t.me/learningnets

CCNP Lab 009: QoS, Voice and Video Support

Lab Objective:

The focus of this lab is to understand Quality of Service (QoS) implementation and configuration for voice and video services in Cisco IOS Catalyst switches.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please begin each and every lab by shutting down all interfaces on all switches and then manually re-enabling only the interfaces that are illustrated in this topology.

Task 1

Configure VTP on all switches illustrated in the network topology as follows:

- Switches DLS1 and ALS1 should reside in VTP domain ONE
- Switch DLS1 should be configured as a VTP server and ALS1 as a VTP client
- Switches DLS1 and ALS1 should secure VTP using a password of ONE
- Both switches should run VTP version 2

- Switches DLS2 and ALS2 should reside in VTP domain TWO
- Switch DLS2 should be configured as a VTP server and ALS2 as a VTP client
- Switches DLS2 and ALS2 should secure VTP using a password of TWO
- Both switches should run VTP version 2

Task 2

Configure an 802.1Q trunk between DLS1 and ALS1 as well as between DLS2 and ALS2. Next, configure a PAgP Layer 3 EtherChannel between switches DLS1 and DLS2. Use the 192.168.0.0/30 subnet for the EtherChannel.

https://t.me/learningnets

Task 3

Configure VLANs and the following SVIs and interfaces on the switches in the topology:

- DLS1: VLAN 100 - name DATA; VLAN 101 - name VOICE
- DLS1: Interface VLAN 100: IP address 100.1.1.1/24
- DLS1: Interface VLAN 101: IP address 101.1.1.1/24

- DLS2: VLAN 200 - name DATA; VLAN 201 - name VOICE
- DLS2: Interface VLAN 200: IP address 200.1.1.1/24
- DLS2: Interface VLAN 201: IP address 201.1.1.1/24

Task 4

Configure Cisco IOS DHCP on switch DLS1 to provide IP addressing information to both the DATA and VOICE VLANs. The first 5 addresses should be excluded from the DHCP scopes. The Cisco IP phones that will be assigned to the VOICE VLANs on the switches will need to communicate with a Cisco Unified Communications Manager with the IP address 192.168.0.254. This address should be included in the VOICE DHCP scopes. The DHCP scopes should be configured for a lease time of 5 days, use the domain name 101labs.net and use servers 172.16.1.253 and 172.16.2.254 for name resolution.

Configure switch DLS2 to forward DHCP requests to servers 192.168.1.254 and 192.168.2.254

Task 5

Configure OSPF on switches DLS1 and DLS2 so that switches ALS1 and ALS2 have IP reachability to each other.

Task 6

Configure Quality of Service on switches DLS1 and DLS2 as follows:

- All markings for packets received across the Layer 3 EtherChannel should be trusted
- All markings for packets received from their access switches should be trusted

Task 7

Configure voice support and Quality of Service on switch ALS1. Ports FastEthernet0/1-0/5 will be connected to Cisco IP phones. The phones will use VLAN 101 and the users

https://t.me/learningnets

Technet24

connected to the phone LAN port should use VLAN 100. The switch should trust QoS markings from the phones only.

Configure voice support and Quality of Service on switch ALS2. Ports FastEthernet0/1 - 0/5 will be connected to Cisco IP phones. The phones will use VLAN 201 and the users connected to the phone LAN port should use VLAN 200. The switch should trust QoS markings from both the phones as well as the user devices connected to the phones.

Task 8

On switches ALS1 and ALS2, ports FastEthernet0/10 - 12 will be connected to non-trusted video endpoints. To ensure that these do not affect other services, e.g. voice, configure the switches to ignore any CoS values in frames received on these ports and assign a default CoS value of 3.

Lab Validation:

Task 1

DLS1(config)#**vtp domain ONE**
DLS1(config)#**vtp password ONE**
DLS1(config)#**vtp version 2**

DLS2(config)#**vtp domain TWO**
DLS2(config)#**vtp password TWO**
DLS2(config)#**vtp version 2**

ALS1(config)#**vtp version 2**
ALS1(config)#**vtp domain ONE**
ALS1(config)#**vtp password ONE**
ALS1(config)#**vtp mode client**

ALS2(config)#**vtp domain TWO**
ALS2(config)#**vtp password TWO**
ALS2(config)#**vtp version 2**
ALS2(config)#**vtp mode client**

Task 2

DLS1(config)#**interface fastethernet 0/7**
DLS1(config-if)#**switchport**
DLS1(config-if)#**switchport trunk encapsulation dot1q**
DLS1(config-if)#**switchport mode trunk**
DLS1(config-if)#**no shutdown**
DLS1(config-if)#**exit**
DLS1(config)#**interface range fastethernet 0/11 - 12**

https://t.me/learningnets

DLS1(config-if-range)#**no switchport**
DLS1(config-if-range)#**channel-group 1 mode desirable**
Creating a port-channel interface Port-channel 1

DLS1(config-if-range)#**no shutdown**
DLS1(config-if-range)#**exit**
DLS1(config)#**interface port-channel 1**
DLS1(config-if)#**ip address 192.168.0.1 255.255.255.252**
DLS1(config-if)#**exit**

DLS2(config)#**interface fastethernet 0/7**
DLS2(config-if)#**switchport**
DLS2(config-if)#**switchport trunk encapsulation dot1q**
DLS2(config-if)#**switchport mode trunk**
DLS2(config-if)#**no shutdown**
DLS2(config-if)#**exit**
DLS2(config)#**interface range fastethernet 0/11 - 12**
DLS2(config-if-range)#**no switchport**
DLS2(config-if-range)#**channel-group 1 mode desirable**
Creating a port-channel interface Port-channel 1

DLS2(config-if-range)#**no shutdown**
DLS2(config-if-range)#**exit**
DLS2(config)#**interface port-channel 1**
DLS2(config-if)#**ip address 192.168.0.2 255.255.255.252**
DLS2(config-if)#**exit**

ALS1(config)#**interface fastethernet 0/7**
ALS1(config-if)#**no shutdown**
ALS1(config-if)#**switchport mode trunk**
ALS1(config-if)#**exit**

ALS2(config)#**interface fastethernet 0/7**
ALS2(config-if)#**no shutdown**
ALS2(config-if)#**switchport mode trunk**
ALS2(config-if)#**exit**

Verify trunking status and configuration using the **show interfaces trunk** command:

ALS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 on 802.1q trunking 1

ALS2#**show interfaces trunk**

https://t.me/learningnets

Technet24

Port Mode Encapsulation Status Native vlan
Fa0/7 on 802.1q trunking 1

Verify EtherChannel status and configuration using the **show etherchannel** commands:

DLS1#**show etherchannel summary**
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
------+-------------+-----------+---
1 Po1(RU) PAgP Fa0/11(P) Fa0/12(P)

And finally, verify IP connectivity between switches DLS1 and DLS2 using a simple ping:

DLS1#**ping 192.168.0.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.0.2, timeout is 2 seconds:
.!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 1/3/4 ms

Task 3

DLS1(config)#**vlan 100**
DLS1(config-vlan)#**name DATA**
DLS1(config-vlan)#**exit**
DLS1(config)#**vlan 101**
DLS1(config-vlan)#**name VOICE**
DLS1(config-vlan)#**exit**
DLS1(config)#**interface vlan 100**
DLS1(config-if)#**ip address 100.1.1.1 255.255.255.0**
DLS1(config-if)#**exit**
DLS1(config)#**interface vlan 101**

https://t.me/learningnets

DLS1(config-if)#**ip address 101.1.1.1 255.255.255.0**
DLS1(config-if)#**exit**

DLS2(config)#**vlan 200**
DLS2(config-vlan)#**name DATA**
DLS2(config-vlan)#**exit**
DLS2(config)#**vlan 201**
DLS2(config-vlan)#**name VOICE**
DLS2(config-vlan)#**exit**
DLS2(config)#**interface vlan 200**
DLS2(config-if)#**ip address 200.1.1.1 255.255.255.0**
DLS2(config-if)#**exit**
DLS2(config)#**interface vlan 201**
DLS2(config-if)#**ip address 201.1.1.1 255.255.255.0**
DLS2(config-if)#**exit**

Task 4

While the other DHCP configuration tasks are simple, when configuring the Cisco Unified Communications Manager (CUCM) address in DHCP, you can use either DHCP option 66 (name) or DHCP option 150 (IP address). This task is completed as follows on switch DLS1:

DLS1(config)#**ip dhcp excluded-address 100.1.1.1 100.1.1.5**
DLS1(config)#**ip dhcp excluded-address 101.1.1.1 101.1.1.5**
DLS1(config)#**ip dhcp pool DATA**
DLS1(dhcp-config)#**network 100.1.1.0 255.255.255.0**
DLS1(dhcp-config)#**default-router 100.1.1.1**
DLS1(dhcp-config)#**lease 5 0 0**
DLS1(dhcp-config)#**domain-name 101labs.net**
DLS1(dhcp-config)#**dns-server 172.16.1.254 172.16.2.254**
DLS1(dhcp-config)#**exit**
DLS1(config)#**ip dhcp pool VOICE**
DLS1(dhcp-config)#**network 101.1.1.0 255.255.255.0**
DLS1(dhcp-config)#**lease 5 0 0**
DLS1(dhcp-config)#**domain-name 101labs.net**
DLS1(dhcp-config)#**lease 5 0 0**
DLS1(dhcp-config)#**dns-server 172.16.1.254 172.16.2.254**
DLS1(dhcp-config)#**option 150 ip 192.168.0.254**
DLS1(dhcp-config)#**exit**

The second part of this task calls for the configuration of the Cisco IOS DHCP Relay

https://t.me/learningnets

Technet24

Agent, configured using **the ip helper-address** command. This task is completed as follows:

DLS2(config)#**interface vlan 200**

DLS2(config-if)#**ip helper-address 192.168.1.254**

DLS2(config-if)#**ip helper-address 192.168.2.254**

DLS2(config-if)#**exit**

DLS2(config)#**interface vlan 201**

DLS2(config-if)#**ip helper-address 192.168.1.254**

DLS2(config-if)#**ip helper-address 192.168.2.254**

DLS2(config-if)#**exit**

You can verify the helper addresses configured on a per-interface basis by looking at the device configuration or using the **show ip interface** command:

DLS2#**show ip interface vlan 200**
Vlan200 is up, line protocol is up
Internet address is 200.1.1.1/24
Broadcast address is 255.255.255.255
Address determined by setup command
MTU is 1500 bytes
Helper addresses are 192.168.1.254
192.168.2.254
Directed broadcast forwarding is disabled
Outgoing access list is not set
Inbound access list is not set

Task 5

DLS1(config)#**ip routing**
DLS1(config)#**router ospf 1**
DLS1(config-router)#**network 100.1.1.0 0.0.0.255 area 0**
DLS1(config-router)#**network 101.1.1.0 0.0.0.255 area 0**
DLS1(config-router)#**network 192.168.0.0 0.0.0.3 area 0**
DLS1(config-router)#**exit**

DLS2(config)#**ip routing**

DLS2(config)#**router ospf 2**

DLS2(config-router)#**network 200.1.1.0 0.0.0.255 area 0**

DLS2(config-router)#**network 201.1.1.0 0.0.0.255 area 0**

https://t.me/learningnets

DLS2(config-router)#**network 192.168.0.0 0.0.0.3 area 0**

DLS2(config-router)#**exit**

Verify your configuration using the **show ip ospf** and **show ip route** commands:

DLS1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface

201.1.1.1 1 FULL/BDR 00:00:32 192.168.0.2 Port-channel1

DLS1#**show ip route ospf**

O 201.1.1.0/24 [110/2] via 192.168.0.2, 00:01:47, Port-channel1

O 200.1.1.0/24 [110/2] via 192.168.0.2, 00:01:47, Port-channel1

Task 6

When configuring QoS on Catalyst switches, first QoS must be enabled globally. When this is done, by default, all interfaces are untrusted and a trust state must be explicitly configured. When configuring trust states, configure the switch to trust CoS only on trunks or ports connected to Cisco IP phones; and to trust DSCP or IP Precedence on Layer 3 (routed) ports or ports connected to non-Cisco IP phones, e.g. ports connected to workstations only.

DLS1(config)#**mls qos**
DLS1(config-if)#**interface fastethernet 0/7**
DLS1(config-if)#**mls qos trust cos**
DLS1(config-if)#**exit**
DLS1(config)#**interface range fastethernet 0/11 - 12**
DLS1(config-if-range)#**mls qos trust dscp**
DLS1(config-if-range)#**end**

NOTE: Depending on the switch platform, when configuring QoS for EtherChannels, you must configure it on a per-port basis. It is imperative to ensure that all ports have the same configuration, otherwise, some of the ports will not be included in the EtherChannel bundle.

DLS2(config)#**mls qos**
DLS2(config)#**interface fastethernet 0/7**
DLS2(config-if)#**mls qos trust cos**
DLS2(config-if)#**exit**
DLS2(config)#**interface range fastethernet 0/11 - 12**
DLS2(config-if-range)#**mls qos trust dscp**
DLS2(config-if-range)#**end**

Verify your configuration using the **show mls qos** commands:

https://t.me/learningnets

Technet24

DLS2#**show mls qos**
QoS is enabled

DLS2#**show mls qos interface fastethernet 0/7**
FastEthernet0/7
QoS is disabled. pass-through mode
When QoS is enabled, following settings will be applied
trust state: trust cos
trust mode: trust cos
COS override: dis
default COS: 0
DSCP Mutation Map: Default DSCP Mutation Map
Trust device: none

Task 7

ALS1(config)#**interface range fastethernet 0/1 - 5**
ALS1(config-if-range)#**switchport mode access**
ALS1(config-if-range)#**switchport access vlan 100**
ALS1(config-if-range)#**switchport voice vlan 101**
ALS1(config-if-range)#**mls qos trust cos**
ALS1(config-if-range)#**mls qos trust device cisco-phone**
ALS1(config-if-range)#**exit**

By default, the Cisco IP phone does not trust traffic received from its LAN port and resets the QoS values to 0 (default). To allow the Cisco IP phone to trust the connected devices QoS settings, the trust boundary must be extended to the device. This task is completed as follows:

ALS2(config)#**interface range fastethernet 0/1 - 5**
ALS2(config-if-range)#**switchport mode access**
ALS2(config-if-range)#**switchport access vlan 200**
ALS2(config-if-range)#**switchport voice vlan 201**
ALS2(config-if-range)#**mls qos trust cos**
ALS2(config-if-range)#**switchport priority extend trust**
ALS2(config-if-range)#**exit**

Verify the configuration using the **show mls qos** commands:

ALS1#**show mls qos interface fastethernet 0/1**
FastEthernet0/1
trust state: not trusted
trust mode: trust cos

https://t.me/learningnets

COS override: dis
default COS: 0
pass-through: none
trust device: cisco-phone

NOTE: The port trust state will be 'not trusted' until a Cisco IP phone is connected to the port

ALS2#**show mls qos interface fastethernet 0/1**
FastEthernet0/1
trust state: trust cos
trust mode: trust cos
COS override: dis
default COS: 0
pass-through: none
trust device: none

You can also use the **show interfaces switchport** command to verify QoS configuration:

ALS1#**show interfaces fastethernet 0/1 switchport**
Name: Fa0/1
Switchport: Enabled
Administrative Mode: static access
Operational Mode: down
Administrative Trunking Encapsulation: dot1q
Negotiation of Trunking: Off
Access Mode VLAN: 100 (DATA)
Trunking Native Mode VLAN: 1 (default)
Voice VLAN: 100 (DATA)
Administrative private-vlan host-association: none
Administrative private-vlan mapping: none
Administrative private-vlan trunk native VLAN: none
Administrative private-vlan trunk encapsulation: dot1q
Administrative private-vlan trunk normal VLANs: none
Administrative private-vlan trunk private VLANs: none
Operational private-vlan: none
Trunking VLANs Enabled: ALL
Pruning VLANs Enabled: 2-1001
Capture Mode Disabled
Capture VLANs Allowed: ALL
Protected: false

https://t.me/learningnets

Technet24

Appliance trust: none

ALS2#**show interfaces fastethernet 0/1 switchport**
Name: Fa0/1
Switchport: Enabled
Administrative Mode: static access
Operational Mode: down
Administrative Trunking Encapsulation: dot1q
Negotiation of Trunking: Off
Access Mode VLAN: 200 (DATA)
Trunking Native Mode VLAN: 1 (default)
Voice VLAN: 201 (VOICE)
Administrative private-vlan host-association: none
Administrative private-vlan mapping: none
Administrative private-vlan trunk native VLAN: none
Administrative private-vlan trunk encapsulation: dot1q
Administrative private-vlan trunk normal VLANs: none
Administrative private-vlan trunk private VLANs: none
Operational private-vlan: none
Trunking VLANs Enabled: ALL
Pruning VLANs Enabled: 2-1001
Capture Mode Disabled
Capture VLANs Allowed: ALL
Protected: false
Appliance trust: trusted

Task 8

By default, Cisco IOS Catalyst switches use a default CoS value of 0. To specify a default CoS value other than 0, you must explicitly configure the switch port using the **mls qos cos [override]** command. The **[override]** keyword overrides the configured trust state and assigns all traffic the configured CoS value.

ALS1(config)#**interface range fastethernet 0/10 - 12**
ALS1(config-if-range)#**switchport mode access**
ALS1(config-if-range)#**mls qos cos 3**
ALS1(config-if-range)#**mls qos cos override**
ALS1(config-if-range)#**exit**

ALS2(config)#**interface range fastethernet 0/10 - 12**
ALS2(config-if-range)#**switchport mode access**
ALS2(config-if-range)#**mls qos cos 3**

https://t.me/learningnets

ALS2(config-if-range)#**mls qos cos override**
ALS2(config-if-range)#**exit**

Again, use the **show mls qos** commands to verify this configuration:

ALS2#**show mls qos interface fastethernet 0/12**
FastEthernet0/12
trust state: not trusted
trust mode: not trusted
COS override: ena
default COS: 3
pass-through: none
trust device: none

https://t.me/learningnets

Technet24

CCNP Lab 010: Router, Port and VLAN ACLs

Lab Objective:

The focus of this lab is to understand basic RACL, PACL, and VACL implementation and configuration in Cisco IOS Catalyst switches.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please begin each and every lab by shutting down all interfaces on all switches and then manually re-enabling only the interfaces that are illustrated in this topology.

Task 1

Disable VTP on all switches.

Task 2

Configure 802.1Q trunks between DLS1 and ALS1 as well as between DLS2 and ALS2. Ensure that DTP is disabled on all trunk links.

Next, configure an LACP Layer 3 EtherChannel between switches DLS1 and DLS2. Use the 192.168.0.0/30 subnet for the EtherChannel.

Task 3

Configure the following SVIs and interfaces on the switches in the topology:

- DLS1: Interface VLAN 100: IP address 100.1.1.1/24
- ALS1: Interface VLAN 100: IP address 100.1.1.2/24

- DLS2: Interface VLAN 200: IP address 200.1.1.1/24
- ALS2: Interface VLAN 200: IP address 200.1.1.2/24

https://t.me/learningnets

Technet24

Task 4

Configure OSPF on switches DLS1 and DLS2 so that switches ALS1 and ALS2 have IP reachability to each other. Verify that switches ALS1 and ALS2 can ping each other.

Task 5

Configure an inbound RACL on switch DLS1s EtherChannel that allows OSPF and PING traffic anywhere. The RACL should also only allow TCP traffic if the session was initiated by any host residing on VLAN 100. In other words, switches DLS2 and ALS2 should not be able to initiate a Telnet (for example) connection to switches ALS1 and DLS1. However, switches ALS1 and DLS1 can Telnet to them. Test your configuration.

Task 6

Configure an inbound PACL on the trunk link between DLS1 and ALS1 that allows frames only sent by switch ALS1 to be forwarded. Verify that you can still ping ALS2 from ALS1. Additionally, in the event that routing fails on switch DLS1, ensure that non-IP packets can be bridged between VLAN 100 and switch DLS2.

Task 7

Configure a VACL on switch DLS2 for VLAN 200 that performs the following:

- It permits all non-IP traffic
- It denies all UDP traffic
- It permits all TCP traffic
- It permits all ICMP traffic
- It denies all other traffic

Lab Validation:

Task 1

DLS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

DLS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

ALS1(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

ALS2(config)#**vtp mode transparent**
Setting device to VTP TRANSPARENT mode.

https://t.me/learningnets

Task 2

DLS1(config)#**interface fastethernet 0/7**
DLS1(config-if)#**switchport**
DLS1(config-if)#**switchport trunk encapsulation dot1q**
DLS1(config-if)#**switchport mode trunk**
DLS1(config-if)#**switchport nonegotiate**
DLS1(config-if)#**exit**
DLS1(config)#**interface range fastethernet 0/11 - 12**
DLS1(config-if-range)#**no switchport**
DLS1(config-if-range)#**channel-group 1 mode active**
Creating a port-channel interface Port-channel 1
DLS1(config-if-range)#**exit**
DLS1(config)#**interface port-channel 1**
DLS1(config-if)#**ip address 192.168.0.1 255.255.255.252**
DLS1(config-if)#**exit**

DLS2(config)#**interface fastethernet 0/7**
DLS2(config-if)#**switchport**
DLS2(config-if)#**switchport trunk encapsulation dot1q**
DLS2(config-if)#**switchport mode trunk**
DLS2(config-if)#**switchport nonegotiate**
DLS2(config-if)#**exit**
DLS2(config)#**interface range fastethernet 0/11 - 12**
DLS2(config-if-range)#**no switchport**
DLS2(config-if-range)#**channel-group 1 mode active**
Creating a port-channel interface Port-channel 1
DLS2(config-if-range)#**exit**
DLS2(config)#**interface port-channel 1**
DLS2(config-if)#**ip address 192.168.0.2 255.255.255.252**
DLS2(config-if)#**exit**

ALS1(config)#**interface fastethernet 0/7**
ALS1(config-if)#**switchport mode trunk**
ALS1(config-if)#**switchport nonegotiate**
ALS1(config-if)#**exit**

ALS2(config)#**interface fastethernet 0/7**
ALS2(config-if)#**switchport mode trunk**
ALS2(config-if)#**switchport nonegotiate**
ALS2(config-if)#**exit**

https://t.me/learningnets

Verify your trunking configuration using the **show interfaces trunk** command:

ALS1#**show interfaces trunk**

Port Mode Encapsulation Status Native vlan
Fa0/7 on 802.1q trunking 1

Port Vlans allowed on trunk
Fa0/7 1-4094

Port Vlans allowed and active in management domain
Fa0/7 1

Port Vlans in spanning tree forwarding state and not pruned
Fa0/7 1

Use the show **etherchannel** commands to verify EtherChannel configuration:

DLS1#**show etherchannel summary**
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
------+-------------+-----------+---
1 Po1(RU) LACP Fa0/11(P) Fa0/12(P)

Finally, use a simple ping test to verify connectivity between switches DLS1 and DLS2:

DLS1#**ping 192.168.0.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 192.168.0.2, timeout is 2 seconds:
..!!!!!!!!
Success rate is 80 percent (8/10), round-trip min/avg/max = 4/4/4 ms

Task 3

DLS1(config)#**vlan 100**

https://t.me/learningnets

DLS1(config-vlan)#**exit**
DLS1(config)#**interface vlan 100**
DLS1(config-if)#**ip address 100.1.1.1 255.255.255.0**
DLS1(config-if)#**exit**

DLS2(config)#**vlan 200**
DLS2(config-vlan)#**exit**
DLS2(config)#**interface vlan 200**
DLS2(config-if)#**ip address 200.1.1.1 255.255.255.0**
DLS2(config-if)#**exit**

ALS1(config)#**vlan 100**
ALS1(config-vlan)#**exit**
ALS1(config)#**interface vlan 100**
ALS1(config-if)#**ip address 100.1.1.2 255.255.255.0**
ALS1(config-if)#**exit**

ALS2(config)#**vlan 200**
ALS2(config-vlan)#**exit**
ALS2(config)#**interface vlan 200**
ALS2(config-if)#**ip address 200.1.1.2 255.255.255.0**
ALS2(config-if)#**exit**

Verify connectivity between switches DLS1 and ALS1 using a simple ping:

ALS1#ping 100.1.1.1

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 100.1.1.1, timeout is 2 seconds:P SEP.!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 1/3/4 ms

Verify connectivity between switches DLS1 and ALS1 using a simple ping:

ALS2#ping 200.1.1.1

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 200.1.1.1, timeout is 2 seconds:
.!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 1/3/4 ms

Task 4

The first part of this task is straightforward and is completed as follows:

DLS1(config)#**ip routing**
DLS1(config)#**router ospf 1**
DLS1(config-router)#**network 0.0.0.0 255.255.255.255 area 0**

https://t.me/learningnets

Technet24

DLS1(config-router)#**exit**

DLS2(config)#**ip routing**

DLS2(config)#**router ospf 2**

DLS2(config-router)#**network 0.0.0.0 255.255.255.255 area 0**

DLS2(config-router)#**exit**

Verify OSPF configuration using the **show ip ospf** and **show ip route** commands:

DLS2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface

192.168.0.1 1 FULL/DR 00:00:31 192.168.0.1 Port-channel1

DLS2#**show ip route ospf**

100.0.0.0/24 is subnetted, 1 subnets

O 100.1.1.0 [110/2] via 192.168.0.1, 00:02:21, Port-channel1

In order to allow ALS1 and ALS2 to ping each other, both switches need a default gateway:

ALS1(config)#**ip default-gateway 100.1.1.1**

ALS2(config)#**ip default-gateway 200.1.1.1**

Finally, verify connectivity using a simple ping:

ALS2#ping 100.1.1.1

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 100.1.1.1, timeout is 2 seconds:

!!!!!

Success rate is 100 percent (5/5), round-trip min/avg/max = 4/4/4 ms

Task 5

The first two requirements are straightforward; however, the third; however, requires the use of the established keyword. This keyword matches on both the TCP ACK and RST bits. These bits are sent in response to an original SYN (hence are sent in response to an initiated connection). This task is completed as follows:

DLS1(config)#**ip access-list extended INBOUND**
DLS1(config-ext-nacl)#**permit ospf any any**
DLS1(config-ext-nacl)#**permit icmp any any**
DLS1(config-ext-nacl)#**permit tcp any any established**
DLS1(config-ext-nacl)#**exit**

https://t.me/learningnets

DLS1(config)#**interface port-channel 1**
DLS1(config-if)#**ip access-group INBOUND in**
DLS1(config-if)#**exit**

To verify your configuration, attempt to Telnet from switch ALS2 to switch ALS1:

ALS2#**ping 100.1.1.2**

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 100.1.1.1, timeout is 2 seconds:

!!!!!

Success rate is 100 percent (5/5), round-trip min/avg/max = 1/3/4 ms

ALS2#

ALS2#**telnet 100.1.1.2**

Trying 100.1.1.2 ...

% Destination unreachable; gateway or host down

Next, attempt to Telnet from switch ALS1 to switch ALS2:

ALS1#**ping 200.1.1.2**

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 200.1.1.2, timeout is 2 seconds:

!!!!!

Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms

ALS1#

ALS1#**telnet 200.1.1.2**

Trying 200.1.1.2 ... Open

Password required, but none set

[Connection to 200.1.1.2 closed by foreign host]

ALS1#

Task 6

The first part of this task requires the use of a MAC ACL. This is completed as follows:

DLS1(config)#**mac access-list extended HOST-ALS1-ONLY**
DLS1(config-ext-macl)#**permit host 0007.8432.dd00 any**
DLS1(config-ext-macl)#**exit**
DLS1(config)#**interface fastethernet 0/7**
DLS1(config-if)#**mac access-group HOST-ALS1-ONLY in**

https://t.me/learningnets

Technet24

DLS1(config-if)#**exit**

NOTE: You can use the **show arp** command to acquire the MAC address of switch ALS1.

Next, verify that following the PACL configuration, switch ALS1 can reach DLS2 and ALS2:

ALS1#**ping 200.1.1.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 200.1.1.2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 4/4/4 ms

The second part of this task requires the configuration of fallback bridging. Fallback bridging allows the bridging together of two or more VLANs or routed ports, allowing the switch to forward non-routable traffic within the bridge group. This task is completed as follows:

DLS1(config)#**bridge 1 protocol vlan-bridge**
DLS1(config)#**interface vlan 100**
DLS1(config-if)#**bridge-group 1**
DLS1(config-if)#**exit**
DLS1(config)#**interface port-channel 1**
DLS1(config-if)#**bridge-group 1**
DLS1(config-if)#**exit**

Verify your configuration using the **show bridge** commands:

DLS1#**show bridge group**

Bridge Group 1 is running the VLAN Bridge compatible Spanning Tree protocol

Port 57 (Vlan100) of bridge group 1 is forwarding
Port 56 (Port-channel1) of bridge group 1 is forwarding

Task 7

When configuring VACLs, if the VLAN map has at least one match clause for the type of packet (IP or MAC) and the packet does not match any of these match clauses, the default is to drop the packet. If there is no match clause for that type of packet in the VLAN map, the default is to forward the packet. This task is completed as follows:

DLS2(config)#**ip access-list extended ALLOW-ICMP-ONLY**
DLS2(config-ext-nacl)#**permit icmp any any**
DLS2(config-ext-nacl)#**exit**
DLS2(config)#**ip access-list extended ALLOW-TCP-ONLY**

https://t.me/learningnets

DLS2(config-ext-nacl)#**permit tcp any any**
DLS2(config-ext-nacl)#**exit**
DLS2(config)#**vlan access-map VLAN-200-FILTER 10**
DLS2(config-access-map)#**match ip address ALLOW-ICMP-ONLY**
DLS2(config-access-map)#**action forward**
DLS2(config-access-map)#**exit**
DLS2(config)#**vlan access-map VLAN-200-FILTER 20**
DLS2(config-access-map)#**match ip address ALLOW-TCP-ONLY**
DLS2(config-access-map)#**action forward**
DLS2(config-access-map)#**exit**
DLS2(config)#**vlan filter VLAN-200-FILTER vlan-list 200**

Use the **show vlan access-map** and **show vlan filter** commands to verify your configuration:

DLS2#**show vlan access-map**
Vlan access-map “VLAN-200-FILTER” 10
Match clauses:
ip address: ALLOW-ICMP ALLOW-ICMP-ONLY
Action:
forward
Vlan access-map “VLAN-200-FILTER” 20
Match clauses:
ip address: ALLOW-TCP ALLOW-TCP-ONLY
Action:
forward

DLS2#**show vlan filter**
VLAN Map VLAN-200-FILTER is filtering VLANs:
200

Finally, test your configuration using PING and Telnet from ALS1 to ALS2:

ALS1#**ping 200.1.1.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 200.1.1.2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms
ALS1#
ALS1#**telnet 200.1.1.2**
Trying 200.1.1.2 ... Open

Password required, but none set

https://t.me/learningnets

[Connection to 200.1.1.2 closed by foreign host]

https://t.me/learningnets

CCNP Lab 011: Private Vlans

Lab Objective:

The focus of this lab is to understand private VLANS. You will learn how to create primary, community and isolated VLANs. Understand the function of each type of VLAN, and how they are implemented in Cisco IOS. Please note that we used a virtual rack for this topology because our current lab doesn't support private VLANs (Cisco 3550 switches). GNS3 will work well if you use an L2 image (please check gns3.com for details).

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Create VLAN 100 as an isolated VLAN. Assign port eth 0/0 (connecting to

https://t.me/learningnets

FastEthernet0/0 of R1) and eth 0/1 (connecting to FastEthernet0/0 of R2) to VLAN 100. Assign IP 10.0.0.1/24 to R1 and 10.0.0.2/24 to R2

Make sure R1 can't ping R2 even though they are in the same VLAN and subnet.

Task 2

Create VLAN 200 as a community VLAN. Assign port eth 0/2 (connecting to FastEthernet 0/0 of R3) and port eth 0/3 (connecting to FastEthernet 0/0 of R4) to VLAN 200.

Make sure R3 can ping R4 but it can't ping R1 or R2 even though all 4 routers (R1 – R4) are in the same subnet.

Task 3

Create VLAN 300 as a primary VLAN. Devices in this VLAN should be able to communicate with all other devices in all other VLANs.

Assign port eth 1/0 (connecting to FastEthernet 0/0 of R5) to VLAN 300.

Make sure R5 can ping R1 – R4.

Task 4

Set a default route on R1 – R4 as 10.0.0.5 (LAN address of R5) and a route to 10.0.0.0/24 on R6 to go via 10.10.10.5.

Make sure all devices in the topology can ping R6's interface 10.10.10.6.

That signifies all devices have external access via R5 but can only communicate within the restrictions imposed by private VLANs when communicating locally.

Lab configuration and Verifications:

Task 1

L2SW(config)#**vtp mode transparent**
L2SW(config)#**vlan 100**
L2SW(config-vlan)#**private-vlan isolated**
L2SW(config-vlan)#**exit**
L2SW(config)#**vlan 200**
L2SW(config-vlan)#**private-vlan community**
L2SW(config-vlan)#**exit**
L2SW(config-vlan)#**private-vlan primary**
L2SW(config-vlan)#**private-vlan association 100,200**
L2SW(config-vlan)#**exit**
L2SW(config)#**interface eth 0/0**
L2SW(config-if)#**switchport mode private-vlan host**

https://t.me/learningnets

Technet24

L2SW(config-if)#**switchport private-vlan host-association 300 100**
L2SW(config)#**interface eth 0/1**
L2SW(config-if)#**switchport mode private-vlan host**
L2SW(config-if)#**switchport private-vlan host-association 300 100**

R1(config)#**int fastethernet0/0**
R1(config-if)#**ip add 10.0.0.1 255.255.255.0**
R1(config-if)#**no shutdown**

R2(config)#**int fastethernet0/0**
R2(config-if)#**ip add 10.0.0.2 255.255.255.0**
R2(config-if)#**no shutdown**

Private VLANs can only be configured in VTP transparent mode. There are 2 types of private VLANs; Primary and Secondary. Secondary VLANs can be of 2 types; Isolated and Community VLANs.

Devices in Isolated VLANs can't reach any device in the same subnet other than the devices in the Primary VLAN. This is useful especially in a scenario when you have a backup network in which all devices are connected to but you don't want devices to communicate on that network – often required as part of your security considerations.

Devices in Community VLANs can communicate with other devices in the same community VLAN and Primary VLAN but cannot with any other device in any other VLAN on the same layer 3 subnet.

The above configuration creates a Primary VLAN and tells the switch that it is associated with secondary VLANs 100, and 200.

VLAN 100 is isolated and VLAN 200 is created as a community VLAN.

We have configured ports connecting to R1 and R2 in VLAN 100 which is an isolated VLAN so they must not be able to communicate with each other.

L2SW#show vlan

VLAN Name Status Ports
---- -------------------------------- --------- -------------------------
1 default active Et0/0, Et0/1, Et0/2, Et0/3
Et1/0, Et1/1, Et1/2, Et1/3
Et2/0, Et2/1, Et2/2, Et2/3
Et3/0, Et3/1, Et3/2, Et3/3
100 VLAN0100 active
200 VLAN0200 active
300 VLAN0300 active
1002 fddi-default act/unsup

https://t.me/learningnets

1003 token-ring-default act/unsup
1004 fddinet-default act/unsup
1005 trnet-default act/unsup

VLAN Type SAID MTU Parent RingNo BridgeNo Stp BrdgMode Trans1 Trans2
---- ----- ---------- ----- ------ ------ -------- ---- -------- ------ ---
1 enet 100001 1500 - - - - - 0 0
100 enet 100100 1500 - - - - - 0 0
200 enet 100200 1500 - - - - - 0 0
300 enet 100300 1500 - - - - - 0 0
1002 fddi 101002 1500 - - - - - 0 0
1003 tr 101003 1500 - - - - - 0 0

VLAN Type SAID MTU Parent RingNo BridgeNo Stp BrdgMode Trans1 Trans2
---- ----- ---------- ----- ------ ------ -------- ---- -------- ------ ---
1004 fdnet 101004 1500 - - - ieee - 0 0
1005 trnet 101005 1500 - - - ibm - 0 0

Remote SPAN VLANs

Primary Secondary Type Ports
------- --------- ---------- ----------
300 100 isolated Et0/0, Et0/1
300 200 community

Verification:

R1#sh ip int brief
Interface IP-Address OK? Method Status Protocol
FastEthernet0/0 10.0.0.1 YES manual up up
FastEthernet0/1 unassigned YES unset administratively down down

R1#ping 10.0.0.2

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.0.2, timeout is 2 seconds:
.....
Success rate is 0 percent (0/5)

R2#sh ip int brief
Interface IP-Address OK? Method Status Protocol
FastEthernet0/0 10.0.0.2 YES manual up up
FastEthernet0/1 unassigned YES unset administratively down down

https://t.me/learningnets

Technet24

R2#ping 10.0.0.1

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.0.1, timeout is 2 seconds:
.....
Success rate is 0 percent (0/5)

Even though R2 is in the same subnet connected to same vlan 100, we can't ping R2 from R1 and vice versa because VLAN 100 is an isolated VLAN.

Task 2

L2SW(config-if)#**interface ethernet 0/2**
L2SW(config-if)#**switchport mode private-vlan host**
L2SW(config-if)#**switchport private-vlan host-association 300 200**
L2SW(config-if)#**interface ethernet 0/3**
L2SW(config-if)#**switchport mode private-vlan host**
L2SW(config-if)#**switchport private-vlan host-association 300 200**

VLAN 200 is already defined as a community VLAN as part of Task 1 solution (partial definition of private VLANs is not accepted by the switch so we created all VLANs in Task 1 solution).

These commands only inform the switch that ports eth 0/2 and eth 0/3 are part of private VLAN 200 and their primary VLAN is 300.

L2SW#show vlan

VLAN Name Status Ports
---- -------------------------------- --------- -------------------------
1 default active Et1/0, Et1/1, Et1/2, Et1/3
Et2/0, Et2/1, Et2/2, Et2/3
Et3/0, Et3/1, Et3/2, Et3/3
100 VLAN0100 active
200 VLAN0200 active
300 VLAN0300 active
1002 fddi-default act/unsup
1003 token-ring-default act/unsup
1004 fddinet-default act/unsup
1005 trnet-default act/unsup

VLAN Type SAID MTU Parent RingNo BridgeNo Stp BrdgMode Trans1 Trans2
---- ----- ---------- ----- ------ ------ -------- ---- -------- ------ ---
1 enet 100001 1500 - - - - - 0 0
100 enet 100100 1500 - - - - - 0 0

https://t.me/learningnets

200 enet 100200 1500 - - - - - 0 0
300 enet 100300 1500 - - - - - 0 0
1002 fddi 101002 1500 - - - - - 0 0
1003 tr 101003 1500 - - - - - 0 0
1004 fdnet 101004 1500 - - - ieee - 0 0

VLAN Type SAID MTU Parent RingNo BridgeNo Stp BrdgMode Trans1 Trans2
---- ----- ---------- ----- ------ ------ -------- ---- -------- ------ ---
1005 trnet 101005 1500 - - - ibm - 0 0

Remote SPAN VLANs

Primary Secondary Type Ports
------- --------- ---------- ----------------------------------
300 100 isolated Et0/0, Et0/1
300 200 community Et0/2, Et0/3

Verifications:

Ping results:

R3#ping 10.0.0.4

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.0.4, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 20/21/28 ms
R3#ping 10.0.0.1

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.0.1, timeout is 2 seconds:
.....
Success rate is 0 percent (0/5)
R3#ping 10.0.0.2

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.0.2, timeout is 2 seconds:
.....
Success rate is 0 percent (0/5)

Task 3

L2SW(config)#**int eth 1/0**
L2SW(config-if)#**switchport mode private-vlan promiscuous**
L2SW(config-if)#**switchport private-vlan mapping 300 100,200**

https://t.me/learningnets

Technet24

The port in primary VLAN must be in promiscuous mode for it to be able to communicate with other VLANs.

The mapping is primary-VLAN to list-of-secondary-vlans (isolated and community VLANs).

Verifications:

R5#ping 10.0.0.1

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.0.1, timeout is 2 seconds:
.!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 20/26/36 ms
R5#ping 10.0.0.2

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.0.2, timeout is 2 seconds:
.!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 8/13/24 ms
R5#ping 10.0.0.3

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.0.3, timeout is 2 seconds:
.!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 4/9/12 ms

R5#ping 10.0.0.4

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.0.4, timeout is 2 seconds:
.!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 8/13/28 ms

So R1 being in the Primary VLAN can ping every other device in the topology.

Task 4

R1(config)#ip route 0.0.0.0 0.0.0.0 10.0.0.5

R2(config)#ip route 0.0.0.0 0.0.0.0 10.0.0.5

R3(config)#ip route 0.0.0.0 0.0.0.0 10.0.0.5

R4(config)#ip route 0.0.0.0 0.0.0.0 10.0.0.5

R6(config)#ip route 10.0.0.0 255.255.255.0 10.10.10.5

Devices in both secondary VLANs have the same default gateway which is R5 (10.0.0.5).

https://t.me/learningnets

Verifications:

R1#ping 10.10.10.6

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.10.10.6, timeout is 2 seconds:
.!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 32/38/44 ms
R2#ping 10.10.10.6

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.10.10.6, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 12/24/36 ms
R3#ping 10.10.10.6

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.10.10.6, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 24/34/40 ms
R4#ping 10.10.10.6

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.10.10.6, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/20/28 ms
R5#ping 10.10.10.6

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.10.10.6, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 8/17/24 ms

https://t.me/learningnets

Technet24

CCNP Lab 012: RIPv2 Lab

Lab Objective:

The focus of this lab is to understand RIPv2 implementation and configuration in Cisco IOS routers. You will learn to implement RIPv2, route manipulation, summarization, filtering and authentication.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure RIPv2 on all routers in the topology and advertise connected networks, both

https://t.me/learningnets

Technet24

LAN and WAN.

Task 3

Configure R1 so that it should NOT have R2's LAN 150.2.2.0/24 in its routing table.

Task 4

Currently R1's preferred route to 150.3.3.0/24 is via R3 due to it having fewer hops.

R1#sh ip route 150.3.3.0
Routing entry for 150.3.3.0/24
Known via "rip", distance 120, metric 1
Redistributing via rip
Last update from 10.0.0.6 on Serial1/1, 00:00:17 ago
Routing Descriptor Blocks:
*** 10.0.0.6, from 10.0.0.6, 00:00:17 ago, via Serial1/1**
Route metric is 1, traffic share count is 1

Configure R1 so that the route to 150.3.3.0/24 does NOT go via R3

Task 5

Add the following loopbacks to R4:

Loopback0: 150.4.1.4/24
Loopback1: 150.4.2.4/24
Loopback2: 150.4.3.4/24

Advertise these new subnets into RIP. Summarize these subnets so that R2, R3, and R4 only receives 1 summary route for these subnets.

Task 6

Configure all routers in the topology to use md5 authentication with the password of 'cisco'

Lab configuration and Verifications:

Task 1

Router#**configure terminal**
R1(config)#**hostname R1**
R1(config)#**interface serial 1/0**
R1(config-if)# **ip address 10.0.0.1 255.255.255.252**
R1(config-if)# **no shutdown**
R1(config-if)#**interface serial 1/1**
R1(config-if)# **ip address 10.0.0.5 255.255.255.252**
R1(config-if)# **no shutdown**
R1(config-if)#**interface f0/0**

https://t.me/learningnets

R1(config-if)# **ip address 10.0.1.1 255.255.255.0**
R1(config-if)# **no shutdown**

Router#**configure terminal**
R2(config)#**hostname R2**
R2(config)#
R2(config)#**interface serial 1/0**
R2(config-if)# **ip address 10.0.0.2 255.255.255.252**
R2(config-if)# **no shutdown**
R2(config-if)#**interface serial 1/1**
R2(config-if)# **ip address 10.0.0.9 255.255.255.252**
R2(config-if)# **no shutdown**
R2(config-if)#**interface f0/0**
R2(config-if)# **ip address 150.2.2.2 255.255.255.0**
R2(config-if)# **no shutdown**

Router#**configure terminal**
Router(config)#**hostname R3**
R3(config)#**interface serial 1/0**
R3(config-if)# **ip address 10.0.0.6 255.255.255.252**
R3(config-if)# **no shutdown**
R3(config-if)#**interface serial 1/1**
R3(config-if)# **ip address 10.0.0.10 255.255.255.252**
R3(config-if)# **no shutdown**
R3(config-if)#**interface serial 1/2**
R3(config-if)# **ip address 10.0.0.13 255.255.255.252**
R3(config-if)# **no shutdown**
R3(config-if)#**interface f0/0**
R3(config-if)# **ip address 150.3.3.3 255.255.255.0**
R3(config-if)# **no shutdown**

R4#**configure terminal**
R4(config)#i**nterface serial 1/0**
R4(config-if)# **ip address 10.0.0.14 255.255.255.252**
R4(config-if)# **no shutdown**
R4(config-if)#**interface f0/0**
R4(config-if)# **ip address 10.0.1.4 255.255.255.0**
R4(config-if)# **no shutdown**

Task 2

R1(config)#**router rip**

https://t.me/learningnets

Technet24

R1(config-router)#**version 2**
R1(config-router)#**no auto-summary**
R1(config-router)#**network 10.0.0.0**

R2(config)#**router rip**
R2(config-router)#**version 2**
R2(config-router)#**no auto-summary**
R2(config-router)#**network 10.0.0.0**
R2(config-router)#**network 150.2.2.0**

R3(config)#**router rip**
R3(config-router)#**version 2**
R3(config-router)#**no auto-summary**
R3(config-router)#**network 10.0.0.0**
R3(config-router)#**network 150.3.3.0**

R4(config)#**router rip**
R4(config-router)#**version 2**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 10.0.0.0**

Explanation:

The network statement is the easiest way to advertise routes into RIP. RIP will automatically convert the configurations into classful boundaries, if we configure 'network 10.10.10.0' that will show up in configuration as 'network 10.0.0.0' hence it will advertise all the interfaces that have subnets of 10.0.0.0 class into RIP.

Additionally, we need to specify the version as 2, otherwise RIP version 1 will be assumed.

Auto-summary is the default option; it is a good idea to do a 'no auto-summary' to turn off any auto-summarization. Please check your platform and IOS release notes for any changes to this default.

Verifications:

Verify your configurations by looking at the RIP database.

R1#show ip rip database
10.0.0.0/8 auto-summary
10.0.0.0/30 directly connected, Serial1/0
10.0.0.4/30 directly connected, Serial1/1
10.0.0.8/30
[1] via 10.0.0.6, 00:00:09, Serial1/1
[1] via 10.0.0.2, 00:00:26, Serial1/0

https://t.me/learningnets

10.0.0.12/30
[1] via 10.0.1.4, 00:00:02, FastEthernet0/0
[1] via 10.0.0.6, 00:00:09, Serial1/1
10.0.1.0/24 directly connected, FastEthernet0/0
150.2.0.0/16 auto-summary
150.2.2.0/24
[1] via 10.0.0.2, 00:00:26, Serial1/0
150.3.0.0/16 auto-summary
150.3.3.0/24
[1] via 10.0.0.6, 00:00:09, Serial1/1

We can see directly connected networks in the RIP database as well as networks learned from other routers. The number in bracket is the metric which in this case is hops.

R2#sh ip rip database
10.0.0.0/8 auto-summary
10.0.0.0/30 directly connected, Serial1/0
10.0.0.4/30
[1] via 10.0.0.10, 00:00:22, Serial1/1
[1] via 10.0.0.1, 00:00:23, Serial1/0
10.0.0.8/30 directly connected, Serial1/1
10.0.0.12/30
[1] via 10.0.0.10, 00:00:22, Serial1/1
10.0.1.0/24
[1] via 10.0.0.1, 00:00:23, Serial1/0
150.2.0.0/16 auto-summary
150.2.2.0/24 directly connected, FastEthernet0/0
150.3.0.0/16 auto-summary
150.3.3.0/24
[1] via 10.0.0.10, 00:00:22, Serial1/1

R3#sh ip rip database
10.0.0.0/8 auto-summary
10.0.0.0/30
[1] via 10.0.0.9, 00:00:04, Serial1/1
[1] via 10.0.0.5, 00:00:20, Serial1/0
10.0.0.4/30 directly connected, Serial1/0
10.0.0.8/30 directly connected, Serial1/1
10.0.0.12/30 directly connected, Serial1/2
10.0.1.0/24

https://t.me/learningnets

[1] via 10.0.0.14, 00:00:17, Serial1/2
[1] via 10.0.0.5, 00:00:20, Serial1/0
150.2.0.0/16 auto-summary
150.2.2.0/24
[1] via 10.0.0.9, 00:00:04, Serial1/1
150.3.0.0/16 auto-summary
150.3.3.0/24 directly connected, FastEthernet0/0

R4#sh ip rip database
10.0.0.0/8 auto-summary
10.0.0.0/30
[1] via 10.0.1.1, 00:00:04, FastEthernet0/0
10.0.0.4/30
[1] via 10.0.1.1, 00:00:04, FastEthernet0/0
[1] via 10.0.0.13, 00:00:24, Serial1/0
10.0.0.8/30
[1] via 10.0.0.13, 00:00:24, Serial1/0
10.0.0.12/30 directly connected, Serial1/0
10.0.1.0/24 directly connected, FastEthernet0/0
150.2.0.0/16 auto-summary
150.2.2.0/24
[2] via 10.0.1.1, 00:00:04, FastEthernet0/0
[2] via 10.0.0.13, 00:00:24, Serial1/0
150.3.0.0/16 auto-summary
150.3.3.0/24
[1] via 10.0.0.13, 00:00:24, Serial1/0

Another way to verify will be by issuing 'show ip protocols'. This will establish if RIP is enabled, on which interface, which version, and whether or not it is auto summarizing.

R1#sh ip protocols
Routing Protocol is "rip"
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Sending updates every 30 seconds, next due in 20 seconds
Invalid after 180 seconds, hold down 180, flushed after 240
Redistributing: rip
Default version control: send version 2, receive version 2
Interface Send Recv Triggered RIP Key-chain
FastEthernet0/0 2 2

https://t.me/learningnets

Serial1/0 2 2
Serial1/1 2 2
Automatic network summarization is not in effect
Maximum path: 4
Routing for Networks:
10.0.0.0
Routing Information Sources:
Gateway Distance Last Update
10.0.0.2 120 00:00:00
10.0.0.6 120 00:00:13
10.0.1.4 120 00:00:25
Distance: (default is 120)

R2#sh ip protocols
Routing Protocol is “rip”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Sending updates every 30 seconds, next due in 9 seconds
Invalid after 180 seconds, hold down 180, flushed after 240
Redistributing: rip
Default version control: send version 2, receive version 2
Interface Send Recv Triggered RIP Key-chain
FastEthernet0/0 2 2
Serial1/0 2 2
Serial1/1 2 2
Automatic network summarization is not in effect
Maximum path: 4
Routing for Networks:
10.0.0.0
150.2.0.0
Routing Information Sources:
Gateway Distance Last Update
10.0.0.10 120 00:00:26
10.0.0.1 120 00:00:04
Distance: (default is 120)

R3#sh ip protocols
Routing Protocol is “rip”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set

https://t.me/learningnets

Technet24

Sending updates every 30 seconds, next due in 17 seconds
Invalid after 180 seconds, hold down 180, flushed after 240
Redistributing: rip
Default version control: send version 2, receive version 2
Interface Send Recv Triggered RIP Key-chain
FastEthernet0/0 2 2
Serial1/0 2 2
Serial1/1 2 2
Serial1/2 2 2
Automatic network summarization is not in effect
Maximum path: 4
Routing for Networks:
10.0.0.0
150.3.0.0
Routing Information Sources:
Gateway Distance Last Update
10.0.0.9 120 00:00:02
10.0.0.14 120 00:00:19
10.0.0.5 120 00:00:25
Distance: (default is 120)

R4#sh ip protocols
Routing Protocol is “rip”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Sending updates every 30 seconds, next due in 28 seconds
Invalid after 180 seconds, hold down 180, flushed after 240
Redistributing: rip
Default version control: send version 2, receive version 2
Interface Send Recv Triggered RIP Key-chain
FastEthernet0/0 2 2
Serial1/0 2 2
Automatic network summarization is not in effect
Maximum path: 4
Routing for Networks:
10.0.0.0
Routing Information Sources:
Gateway Distance Last Update
10.0.0.13 120 00:00:01

https://t.me/learningnets

10.0.1.1 120 00:00:06
Distance: (default is 120)

Now that the routes are converged we must be able to ping the remote networks from each router.

Testing from R1, we can ping networks on every other router

R1#ping 150.3.3.3

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/24/40 ms
R1#ping 150.2.2.2

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/25/40 ms
R1#ping 10.0.1.4

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.1.4, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 20/27/40 ms

Task 3

R1(config)#access-list 1 deny 150.2.2.0 0.0.0.255
R1(config)#access-list 1 permit any
R1(config)#router rip
R1(config-router)#distribute-list 1 in

Note: It is also possible to deny a prefix from one neighbor and allow it from other neighbors. In that case, just use interface name at the end of distribute-list statement. e.g., distribute-list in s1/0 – this will block the prefix due to be received from the neighbor connected to the s1/0 interface.

Task 4

R1(config)#access-list 2 permit 150.3.3.0 0.0.0.255
R1(config)#router rip
R1(config-router)#offset-list 2 in 5 serial 1/1

Offset-lists are used to add/subtract a number of hops from the received RIP metric.

We have created an ACL specifying the route we want to change, then using the offset-

https://t.me/learningnets

Technet24

list statement we called the ACL and added '5' hops to that route when it is received from Serial 1/1 where R3 is connected.

Now, when the route is received from R3, 5 hops are added (marking it as 6 hops away) whereas the same route from R2 and R4 will have lesser number of hops so those will be installed in the routing table.

Note: It might take up to 240 seconds for routes to update (that is RIPs default hold-down timer). You can clear the routing table by using 'clear ip route *' for an immediate update.

Verification:

R1#sh ip route 150.3.3.0
Routing entry for 150.3.3.0/24
Known via "rip", distance 120, metric 2
Redistributing via rip
Last update from 10.0.0.2 on Serial1/0, 00:00:04 ago
Routing Descriptor Blocks:
*** 10.0.0.2, from 10.0.0.2, 00:00:04 ago, via Serial1/0**
Route metric is 2, traffic share count is 1

Route 150.3.3.0/24 is going via R2 NOT R3 now.

Task 5

R4(config)#**interface loopback0**
R4(config-if)#**ip address 150.4.1.4 255.255.255.0**
R4(config-if)#**interface loopback1**
R4(config-if)#**ip address 150.4.2.4 255.255.255.0**
R4(config-if)#**interface loopback2**
R4(config-if)#**ip address 150.4.3.4 255.255.255.0**
!
R4(config)#**router rip**
R4(config-router)#**network 150.4.1.0**
R4(config-router)#**network 150.4.2.0**
R4(config-router)#**network 150.4.3.0**
!
R4(config)#**interface serial 1/0**
R4(config-if)#**ip summary-address rip 150.4.0.0 255.255.0.0**
!
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip summary-address rip 150.4.0.0 255.255.0.0**

https://t.me/learningnets

Task 6

R1(config)#**key chain RIP-KEYS**
R1(config-keychain)#**key 1**
R1(config-keychain-key)#**key-string cisco**
R1(config-keychain-key)#**accept-lifetime 13:11:00 4 Mar 2019 infinite**
R1(config-keychain-key)#**send-lifetime 13:11:00 4 Mar 2019 infinite**
!
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip rip authentication mode md5**
R1(config-if)#**ip rip authentication key-chain RIP-KEYS**
!
R1(config-if)#**interface serial 1/0**
R1(config-if)# **ip rip authentication mode md5**
R1(config-if)# **ip rip authentication key-chain RIP-KEYS**
R1(config-if)#**interface serial 1/1**
R1(config-if)# **ip rip authentication mode md5**
R1(config-if)# **ip rip authentication key-chain RIP-KEYS**

R2(config)#**key chain RIP-KEYS**
R2(config-keychain)#**key 1**
R2(config-keychain-key)#**key-string cisco**
R2(config-keychain-key)#**accept-lifetime 13:11:00 4 Mar 2019 infinite**
R2(config-keychain-key)#**send-lifetime 13:11:00 4 Mar 2019 infinite**
!
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip rip authentication mode md5**
R2(config-if)#**ip rip authentication key-chain RIP-KEYS**
!
R2(config-if)#**interface serial 1/0**
R2(config-if)# **ip rip authentication mode md5**
R2(config-if)# **ip rip authentication key-chain RIP-KEYS**
!
R2(config-if)#i**nterface serial 1/1**
R2(config-if)# **ip rip authentication mode md5**
R2(config-if)# **ip rip authentication key-chain RIP-KEYS**

R3(config)#**key chain RIP-KEYS**
R3(config-keychain)#**key 1**
R3(config-keychain-key)#**key-string cisco**
R3(config-keychain-key)#**accept-lifetime 13:11:00 4 Mar 2019 infinite**

https://t.me/learningnets

Technet24

R3(config-keychain-key)#**send-lifetime 13:11:00 4 Mar 2019 infinite**
!
R3(config)#**interface fastethernet 0/0**
R3(config-if)# **ip rip authentication mode md5**
R3(config-if)# **ip rip authentication key-chain RIP-KEYS**
!
R3(config-if)#**interface serial 1/0**
R3(config-if)# **ip rip authentication mode md5**
R3(config-if)# **ip rip authentication key-chain RIP-KEYS**
!
R3(config-if)#**interface serial 1/1**
R3(config-if)# **ip rip authentication mode md5**
R3(config-if)# **ip rip authentication key-chain RIP-KEYS**
!
R3(config-if)#**interface serial 1/2**
R3(config-if)# **ip rip authentication mode md5**
R3(config-if)# **ip rip authentication key-chain RIP-KEYS**

R4(config)#**key chain RIP-KEYS**
R4(config-keychain)#**key 1**
R4(config-keychain-key)#**key-string cisco**
R4(config-keychain-key)#**accept-lifetime 13:11:00 4 Mar 2019 infinite**
R4(config-keychain-key)#**send-lifetime 13:11:00 4 Mar 2019 infinite**
!
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip rip authentication mode md5**
R4(config-if)# **ip rip authentication key-chain RIP-KEYS**
!
R4(config-if)#**interface serial 1/0**
R4(config-if)#**ip rip authentication mode md5**
R4(config-if)# **ip rip authentication key-chain RIP-KEYS**

Verifications:

R1#sh ip protocols
Routing Protocol is “rip”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is 1
Incoming routes in Serial1/1 will have 5 added to metric if on list 2
Sending updates every 30 seconds, next due in 22 seconds

https://t.me/learningnets

Invalid after 180 seconds, hold down 180, flushed after 240
Redistributing: rip
Default version control: send version 2, receive version 2
Interface Send Recv Triggered RIP Key-chain
FastEthernet0/0 2 2 RIP-KEYS
Serial1/0 2 2 RIP-KEYS
Serial1/1 2 2 RIP-KEYS
Automatic network summarization is not in effect
Maximum path: 4
Routing for Networks:
10.0.0.0
Routing Information Sources:
Gateway Distance Last Update
10.0.0.2 120 00:10:43
10.0.0.6 120 00:00:08
10.0.1.4 120 00:00:06
Distance: (default is 120)

R2#sh ip protocols
Routing Protocol is “rip”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Sending updates every 30 seconds, next due in 21 seconds
Invalid after 180 seconds, hold down 180, flushed after 240
Redistributing: rip
Default version control: send version 2, receive version 2
Interface Send Recv Triggered RIP Key-chain
FastEthernet0/0 2 2 RIP-KEYS
Serial1/0 2 2 RIP-KEYS
Serial1/1 2 2 RIP-KEYS
Automatic network summarization is not in effect
Maximum path: 4
Routing for Networks:
10.0.0.0
150.2.0.0
Routing Information Sources:
Gateway Distance Last Update
10.0.0.10 120 00:06:29
10.0.0.1 120 00:12:09

https://t.me/learningnets

Distance: (default is 120)

R3#sh ip protocols
Routing Protocol is “rip”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Sending updates every 30 seconds, next due in 17 seconds
Invalid after 180 seconds, hold down 180, flushed after 240
Redistributing: rip
Default version control: send version 2, receive version 2
Interface Send Recv Triggered RIP Key-chain
FastEthernet0/0 2 2 RIP-KEYS
Serial1/0 2 2 RIP-KEYS
Serial1/1 2 2 RIP-KEYS
Serial1/2 2 2 RIP-KEYS
Automatic network summarization is not in effect
Maximum path: 4
Routing for Networks:
10.0.0.0
150.3.0.0
Routing Information Sources:
Gateway Distance Last Update
10.0.0.9 120 00:05:38
10.0.0.14 120 00:00:11
10.0.0.5 120 00:00:15
Distance: (default is 120)

R4#sh ip protocols
Routing Protocol is “rip”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Sending updates every 30 seconds, next due in 24 seconds
Invalid after 180 seconds, hold down 180, flushed after 240
Redistributing: rip
Default version control: send version 2, receive version 2
Interface Send Recv Triggered RIP Key-chain
FastEthernet0/0 2 2 RIP-KEYS
Serial1/0 2 2 RIP-KEYS
Loopback0 2 2
Loopback1 2 2

https://t.me/learningnets

Loopback2 2 2
Automatic network summarization is not in effect
Address Summarization:
150.4.0.0/16 for Serial1/0
150.4.0.0/16 for FastEthernet0/0
Maximum path: 4
Routing for Networks:
10.0.0.0
150.4.0.0
Routing Information Sources:
Gateway Distance Last Update
Gateway Distance Last Update
10.0.0.13 120 00:00:18
10.0.1.1 120 00:00:29
Distance: (default is 120)

Note:

We have not applied authentication to loopback networks as there are no neighbors on those interfaces and we don't expect any updates on those interfaces.

Show Runs

R1

hostname R1

!

boot-start-marker

boot-end-marker

!

!

no aaa new-model

memory-size iomem 5

ip cef

!

no ip domain lookup

ip domain name lab.local

!

multilink bundle-name authenticated

https://t.me/learningnets

Technet24

```
!
key chain RIP-KEYS
key 1
key-string cisco
accept-lifetime 13:11:00 Mar 4 2019 infinite
send-lifetime 13:11:00 Mar 4 2019 infinite
!
!
archive
log config
hidekeys
!
!
interface FastEthernet0/0
ip address 10.0.1.1 255.255.255.0
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
duplex auto
speed auto
!
interface FastEthernet0/1
no ip address
shutdown
duplex auto
speed auto
!
interface Serial1/0
ip address 10.0.0.1 255.255.255.252
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
serial restart-delay 0
```

https://t.me/learningnets

```
!
interface Serial1/1
ip address 10.0.0.5 255.255.255.252
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
serial restart-delay 0
!
interface Serial1/2
no ip address
shutdown
serial restart-delay 0
!
interface Serial1/3
no ip address
shutdown
serial restart-delay 0
!
router rip
version 2
offset-list 2 in 5 Serial1/1
network 10.0.0.0
distribute-list 1 in
no auto-summary
!
ip forward-protocol nd
!
!
no ip http server
no ip http secure-server
!
access-list 1 deny 150.2.2.0 0.0.0.255
```

https://t.me/learningnets

```
access-list 1 permit any
access-list 2 permit 150.3.3.0 0.0.0.255
!
line con 0
exec-timeout 0 0
privilege level 15
logging synchronous
line aux 0
exec-timeout 0 0
privilege level 15
logging synchronous
line vty 0 4
login
!
!
end
R2
hostname R2
!
boot-start-marker
boot-end-marker
!
!
no aaa new-model
memory-size iomem 5
ip cef
!
no ip domain lookup
ip domain name lab.local
!
multilink bundle-name authenticated
```

https://t.me/learningnets

```
!
key chain RIP-KEYS
key 1
key-string cisco
accept-lifetime 13:11:00 Mar 4 2019 infinite
send-lifetime 13:11:00 Mar 4 2019 infinite
!
archive
log config
hidekeys
!
interface FastEthernet0/0
ip address 150.2.2.2 255.255.255.0
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
duplex auto
speed auto
no keepalive
!
interface FastEthernet0/1
no ip address
shutdown
duplex auto
speed auto
!
interface Serial1/0
ip address 10.0.0.2 255.255.255.252
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
serial restart-delay 0
!
```

https://t.me/learningnets

Technet24

```
interface Serial1/1
ip address 10.0.0.9 255.255.255.252
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
serial restart-delay 0
!
interface Serial1/2
no ip address
shutdown
serial restart-delay 0
!
interface Serial1/3
no ip address
shutdown
serial restart-delay 0
!
router rip
version 2
network 10.0.0.0
network 150.2.0.0
no auto-summary
!
ip forward-protocol nd
!
!
no ip http server
no ip http secure-server
!
control-plane
!
line con 0
```

https://t.me/learningnets

```
exec-timeout 0 0
privilege level 15
logging synchronous
line aux 0
exec-timeout 0 0
privilege level 15
logging synchronous
line vty 0 4
login
!
!
end
R3
hostname R3
!
boot-start-marker
boot-end-marker
!
!
no aaa new-model
memory-size iomem 5
ip cef
!
no ip domain lookup
ip domain name lab.local
!
multilink bundle-name authenticated
!
key chain RIP-KEYS
key 1
key-string cisco
```

https://t.me/learningnets

```
accept-lifetime 13:11:00 Mar 4 2019 infinite
send-lifetime 13:11:00 Mar 4 2019 infinite
!
archive
log config
hidekeys
!
interface FastEthernet0/0
ip address 150.3.3.3 255.255.255.0
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
duplex auto
speed auto
no keepalive
!
interface FastEthernet0/1
no ip address
shutdown
duplex auto
speed auto
!
interface Serial1/0
ip address 10.0.0.6 255.255.255.252
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
serial restart-delay 0
!
interface Serial1/1
ip address 10.0.0.10 255.255.255.252
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
```

https://t.me/learningnets

```
serial restart-delay 0
!
interface Serial1/2
ip address 10.0.0.13 255.255.255.252
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
serial restart-delay 0
!
interface Serial1/3
no ip address
shutdown
serial restart-delay 0
!
router rip
version 2
network 10.0.0.0
network 150.3.0.0
no auto-summary
!
ip forward-protocol nd
!
!
no ip http server
no ip http secure-server
!
control-plane
!
line con 0
exec-timeout 0 0
privilege level 15
logging synchronous
```

https://t.me/learningnets

```
line aux 0
exec-timeout 0 0
privilege level 15
logging synchronous
line vty 0 4
login
!
!
end
R4
hostname R4
!
boot-start-marker
boot-end-marker
!
!
no aaa new-model
memory-size iomem 5
ip cef
!
no ip domain lookup
ip domain name lab.local
!
multilink bundle-name authenticated
!
key chain RIP-KEYS
key 1
key-string cisco
accept-lifetime 13:11:00 Mar 4 2019 infinite
send-lifetime 13:11:00 Mar 4 2019 infinite
!
```

https://t.me/learningnets

```
archive
log config
hidekeys
!
interface Loopback0
ip address 150.4.1.4 255.255.255.0
!
interface Loopback1
ip address 150.4.3.4 255.255.255.0
!
interface Loopback2
ip address 150.4.2.4 255.255.255.0
!
interface FastEthernet0/0
ip address 10.0.1.4 255.255.255.0
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
ip summary-address rip 150.4.0.0 255.255.0.0
duplex auto
speed auto
!
interface Serial0/0
no ip address
shutdown
clock rate 2000000
!
interface FastEthernet0/1
no ip address
shutdown
duplex auto
speed auto
```

https://t.me/learningnets

Technet24

```
!
interface Serial0/1
no ip address
shutdown
clock rate 2000000
!
interface Serial1/0
ip address 10.0.0.14 255.255.255.252
ip rip authentication mode md5
ip rip authentication key-chain RIP-KEYS
ip summary-address rip 150.4.0.0 255.255.0.0
serial restart-delay 0
!
interface Serial1/1
no ip address
shutdown
serial restart-delay 0
!
interface Serial1/2
no ip address
shutdown
serial restart-delay 0
!
interface Serial1/3
no ip address
shutdown
serial restart-delay 0
!
router rip
version 2
network 10.0.0.0
```

https://t.me/learningnets

```
network 150.4.0.0
no auto-summary
!
ip forward-protocol nd
!
!
no ip http server
no ip http secure-server
!
control-plane
!
line con 0
exec-timeout 0 0
privilege level 15
logging synchronous
line aux 0
exec-timeout 0 0
privilege level 15
logging synchronous
line vty 0 4
login
!
!
end
```

https://t.me/learningnets

Technet24

CCNP Lab 013: RIPv2 Redistribution into EIGRP

Lab Objective:

The focus of this lab is to understand RIPv2 redistribution into EIGRP. You will learn how to redistribute RIPv2 into EIGRP, how you can make one path prioritized over the other, and how you can filter routes while advertising into EIGRP.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Technet24

Configure EIGRP on interfaces Serial 1/0, and Serial 1/1 of R1, Serial 1/0 of R4, and all interfaces of R2 and R3 as shown in the diagram.

Configure FastEthernet 0/0 of R1 and R4 to be passive interfaces so EIGRP updates are not sent on these interfaces and no neighbor adjacencies are formed.

Task 3

Configure RIPv2 on R1 FastEthernet 0/0, and R2 FastEthernet 0/0 interface. Configure Other interfaces of R1 and R2 to be passive so no updates are sent on these interfaces.

Task 4

Redistribute RIPv2 into EIGRP and make sure R2 & R3 can reach RIP network 10.0.1.0/24 and R1, R4 are able to reach networks connected to R2 (150.2.2.0/24) and R3 (150.3.3.0/24)

Task 5

Add the following networks to R1

Loopback1: 172.16.1.1/24

Loopback2: 172.16.2.1/24

Loopback3: 172.16.3.1/24

Add the following networks to R4

Loopback1: 172.16.11.1/24

Loopback2: 172.16.12.1/24

Loopback3: 172.16.13.1/24

Advertise these networks into RIPv2 on each router.

Task 6

Redistribute RIP into EIGRP in such a way that all the traffic for new loopback subnets should traverse R4. That is, even the traffic that needs to go to subnets attached to R1 should also go via R4

Task 7

Filter the routes 172.16.1.0/24 and 172.16.11.0/24 when redistributing from RIPv2 to EIGRP

Lab configuration and Verifications:

Task 1

Router#**configure terminal**
R1(config)#**hostname R1**

https://t.me/learningnets

R1(config)#**interface serial 1/0**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**
R1(config-if)#**no shutdown**
R1(config-if)#**interface serial 1/1**
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**
R1(config-if)#**no shutdown**
R1(config-if)#**interface f0/0**
R1(config-if)#**ip address 10.0.1.1 255.255.255.0**
R1(config-if)#**no shutdown**

Router#**configure terminal**
R2(config)#**hostname R2**
R2(config)#
R2(config)#**interface serial 1/0**
R2(config-if)# **ip address 10.0.0.2 255.255.255.252**
R2(config-if)# **no shutdown**
R2(config-if)#**interface serial 1/1**
R2(config-if)# **ip address 10.0.0.9 255.255.255.252**
R2(config-if)# **no shutdown**
R2(config-if)#**interface f0/0**
R2(config-if)# **ip address 150.2.2.2 255.255.255.0**
R2(config-if)# **no shutdown**

Router#**configure terminal**
Router(config)#**hostname R3**
R3(config)#**interface serial 1/0**
R3(config-if)# **ip address 10.0.0.6 255.255.255.252**
R3(config-if)# **no shutdown**
R3(config-if)#**interface serial 1/1**
R3(config-if)# **ip address 10.0.0.10 255.255.255.252**
R3(config-if)# **no shutdown**
R3(config-if)#**interface serial 1/2**
R3(config-if)# **ip address 10.0.0.13 255.255.255.252**
R3(config-if)# **no shutdown**
R3(config-if)#**interface f0/0**
R3(config-if)# **ip address 150.3.3.3 255.255.255.0**
R3(config-if)# **no shutdown**

R4#**configure terminal**
R4(config)#i**nterface serial 1/0**
R4(config-if)# **ip address 10.0.0.14 255.255.255.252**

https://t.me/learningnets

R4(config-if)# **no shutdown**
R4(config-if)#**interface f0/0**
R4(config-if)# **ip address 10.0.1.4 255.255.255.0**
R4(config-if)# **no shutdown**

Task 2

R1(config)#**router eigrp 100**
R1(config-router)#**no auto-summary**
R1(config-router)#**network 10.0.0.0 0.0.0.3**
R1(config-router)#**network 10.0.0.4 0.0.0.3**
R1(config-router)#**passive-interface fastethernet 0/0**

R2(config)#**router eigrp 100**
R2(config-router)#**no auto-summary**
R2(config-router)#**network 10.0.0.0 0.0.0.3**
R2(config-router)#**network 10.0.0.8 0.0.0.3**
R2(config-router)#**network 150.2.2.0 0.0.0.255**

R3(config)#**router eigrp 100**
R3(config-router)#**no auto-summary**
R3(config-router)#**network 10.0.0.8 0.0.0.3**
R3(config-router)#**network 10.0.0.4 0.0.0.3**
R3(config-router)#**network 10.0.0.12 0.0.0.3**
R3(config-router)#**network 150.3.3.0 0.0.0.255**

R4(config)#**router eigrp 100**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 10.0.0.12 0.0.0.3**
R4(config-router)#**passive-interface fastethernet 0/0**

Explanation:

You can use a network statement in EIGRP with or without a wildcard mask. Usage of the wildcard mask is recommended because it allows only the intended subnets to be advertised.

Some newer versions of IOS have 'no auto-summary' enabled in EIGRP by default but older IOSs will have auto-summary enabled so it is a good idea to manually disable it just in case your IOS is trying to do an auto-summary for you.

The passive-interface command will stop the sending of 'hello's on the interface so no adjacencies are formed and secondly it will stop that subnet being advertised into EIGRP.

https://t.me/learningnets

Verification:

Check if EIGRP is enabled on an interface

R1#show ip eigrp interfaces
Xmit Queue Mean Pacing Time Multicast Pending
Interface Peers Un/Reliable SRTT Un/Reliable Flow Timer Routes
Se1/0 1 0/0 52 0/15 239 0
Se1/1 1 0/0 51 0/15 239 0

R2#show ip eigrp interfaces
IP-EIGRP interfaces for process 100

Xmit Queue Mean Pacing Time Multicast Pending
Interface Peers Un/Reliable SRTT Un/Reliable Flow Timer Routes
Se1/0 1 0/0 50 0/15 207 0
Se1/1 1 0/0 56 0/15 283 0
Fa0/0 0 0/0 0 0/1 0 0

R3#show ip eigrp interfaces
IP-EIGRP interfaces for process 100

Xmit Queue Mean Pacing Time Multicast Pending
Interface Peers Un/Reliable SRTT Un/Reliable Flow Timer Routes
Se1/1 1 0/0 45 0/15 223 0
Se1/0 1 0/0 38 0/15 187 0
Se1/2 1 0/0 42 0/15 239 0
Fa0/0 0 0/0 0 0/1 0 0

R4#show ip eigrp interfaces
IP-EIGRP interfaces for process 100

Xmit Queue Mean Pacing Time Multicast Pending
Interface Peers Un/Reliable SRTT Un/Reliable Flow Timer Routes
Se1/0 1 0/0 41 0/15 183 0

To verify EIGRP is running as expected, we should also check if the neighbor adjacencies are formed.

R1#show ip eigrp neighbors
IP-EIGRP neighbors for process 100
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.6 Se1/1 10 00:23:25 51 306 0 10
0 10.0.0.2 Se1/0 12 00:23:48 52 312 0 13

https://t.me/learningnets

Technet24

As expected R1 has 2 neighbors; R2 and R3. No neighbor adjacency is formed with R4 using EIGRP.

```
R2#show ip eigrp neighbors
IP-EIGRP neighbors for process 100
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.10 Se1/1 11 00:26:24 56 336 0 9
0 10.0.0.1 Se1/0 13 00:26:47 50 300 0 14
```

```
R3#show ip eigrp neighbors
IP-EIGRP neighbors for process 100
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
2 10.0.0.14 Se1/2 14 00:26:55 42 252 0 3
1 10.0.0.5 Se1/0 13 00:27:24 38 228 0 13
0 10.0.0.9 Se1/1 10 00:27:24 45 270 0 12
```

R3 has 3 neighbors as expected; R1, R2, and R3.

```
R4#show ip eigrp neighbors
IP-EIGRP neighbors for process 100
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.13 Se1/0 14 00:27:33 41 246 0 13
```

R4 has only 1 neighbor which is R3.

Task 3

```
R1(config)#router rip
R1(config-router)#version 2
R1(config-router)#no auto-summary
R1(config-router)#network 10.0.1.0
R1(config-router)#passive-interface serial 1/0
R1(config-router)#passive-interface serial 1/1
```

```
R4(config)#router rip
R4(config-router)#version 2
R4(config-router)#no auto-summary
R4(config-router)#network 10.0.1.0
R4(config-router)#passive-interface serial 1/0
```

RIP is configured on both routers. We can check the RIP database to see which networks are learned.

https://t.me/learningnets

R1#sh ip rip database
10.0.0.0/8 auto-summary
10.0.0.0/30 directly connected, Serial1/0
10.0.0.4/30 directly connected, Serial1/1
10.0.1.0/24 directly connected, FastEthernet0/0

R4#sh ip rip database
10.0.0.0/8 auto-summary
10.0.0.12/30 directly connected, Serial1/0
10.0.1.0/24 directly connected, FastEthernet0/0

Task 4

R1(config)#router eigrp 100
R1(config-router)#redistribute rip metric 1500 0 255 1 1500

R4(config)#router eigrp 100
R4(config-router)#redistribute rip metric 1500 0 255 1 1500

When redistributing from any protocol (other than another EIGRP process or IGRP) you will need to specify the metric, otherwise redistribution will not occur. This is due to the fact that EIGRP has a composite metric and needs values for each element to create a composite metric for the received route.

Redistribution statement in EIGRP is as follows:

router eigrp 100
redistribute rip metric bandwidth delay load reliability MTU

Verification:

The first thing to check is the RIP routes have made into the EIGRP topology table. We can see only RIP route 10.0.1.0/24 is in the EIGRP topology table as redistributed.

R1#show ip eigrp topology
IP-EIGRP Topology Table for AS(100)/ID(10.0.1.1)

Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
r - reply Status, s - sia Status

P 10.0.0.8/30, 2 successors, FD is 2681856
via 10.0.0.2 (2681856/2169856), Serial1/0
via 10.0.0.6 (2681856/2169856), Serial1/1
P 10.0.0.12/30, 1 successors, FD is 2681856
via 10.0.0.6 (2681856/2169856), Serial1/1
P 10.0.0.0/30, 1 successors, FD is 2169856
via Connected, Serial1/0

https://t.me/learningnets

Technet24

P 10.0.1.0/24, 1 successors, FD is 1706496
via Redistributed (1706496/0)
P 10.0.0.4/30, 1 successors, FD is 2169856
via Connected, Serial1/1
P 150.2.2.0/24, 1 successors, FD is 2195456
via 10.0.0.2 (2195456/281600), Serial1/0
P 150.3.3.0/24, 1 successors, FD is 2195456
via 10.0.0.6 (2195456/281600), Serial1/1

R4#show ip eigrp topology
IP-EIGRP Topology Table for AS(100)/ID(10.0.1.4)

Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
r - reply Status, s - sia Status

P 10.0.0.8/30, 1 successors, FD is 2681856
via 10.0.0.13 (2681856/2169856), Serial1/0
P 10.0.0.12/30, 1 successors, FD is 2169856
via Connected, Serial1/0
P 10.0.0.0/30, 1 successors, FD is 3193856
via 10.0.0.13 (3193856/2681856), Serial1/0
P 10.0.1.0/24, 1 successors, FD is 1706496
via Redistributed (1706496/0)
P 10.0.0.4/30, 1 successors, FD is 2681856
via 10.0.0.13 (2681856/2169856), Serial1/0
P 150.2.2.0/24, 1 successors, FD is 2707456
via 10.0.0.13 (2707456/2195456), Serial1/0
P 150.3.3.0/24, 1 successors, FD is 2195456
via 10.0.0.13 (2195456/281600), Serial1/0

We can see that EIGRP is redistributed at both routers R1 and R4 as expected. Both have the same metric as we used the same values for the composite metric of EIGRP when doing the redistribution.

Now, check routing tables of R2, and R3 to see if they have learned the RIP route.

R2#sh ip route 10.0.1.0
Routing entry for 10.0.1.0/24
Known via “eigrp 100”, **distance 170**, metric 2218496, **type external**
Redistributing via eigrp 100
Last update from 10.0.0.1 on Serial1/0, 00:17:41 ago
Routing Descriptor Blocks:
* 10.0.0.1, from 10.0.0.1, 00:17:41 ago, via Serial1/0

https://t.me/learningnets

Route metric is 2218496, traffic share count is 1
Total delay is 20000 microseconds, minimum bandwidth is 1500 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1

R2 has learned the route 10.0.1.0/24. It's an external route as it is redistributed from RIP, it has admin distance of 170 which is the default for any external EIGRP routes (redistributed from other protocols).

Total delay is the sum of the delays along the path, bandwidth is the minimum bandwidth along the path. Reliability, Loading, and MTU don't have any significance by default due to the default K values!

R3#sh ip route 10.0.1.0
Routing entry for 10.0.1.0/24
Known via "eigrp 100", **distance 170, metric 2218496, type external**
Redistributing via eigrp 100
Last update from 10.0.0.14 on Serial1/2, 00:35:45 ago
Routing Descriptor Blocks:
10.0.0.14, from 10.0.0.14, 00:35:45 ago, via Serial1/2
Route metric is 2218496, **traffic share count is 1**
Total delay is 20000 microseconds, minimum bandwidth is 1500 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1
*** 10.0.0.5, from 10.0.0.5, 00:35:45 ago, via Serial1/0**
Route metric is 2218496, **traffic share count is 1**
Total delay is 20000 microseconds, minimum bandwidth is 1500 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1

R3's routing table is a little more interesting. As we kept the metric the same when redistributing at both R1 and R2. R3's own cost to reach R1 and R4 is also the same, so now R3 has in it's routing 2 equal cost paths; one from R1 and other coming from R4.

R3 will perform equal cost load balancing for the route learned from R1 and R4.

One last thing to verify if the redistribution is working as expected. Let's try to ping R1 and R4's FastEthernet interface from both R2 and R3.

R2#ping 10.0.1.1

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.1.1, timeout is 2 seconds:
!!!!!

https://t.me/learningnets

Technet24

Success rate is 100 percent (5/5), round-trip min/avg/max = 16/25/44 ms
R2#ping 10.0.1.4

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.1.4, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 20/37/48 ms

R3#ping 10.0.1.1

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.1.1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/20/24 ms
R3#ping 10.0.1.4

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.1.4, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 20/26/32 ms

Ping is working so we know redistribution is working as expected.

Task 5

R1(config)#**interface loopback 1**
R1(config-if)#**ip address 172.16.1.1 255.255.255.0**
R1(config-if)#**interface loopback 2**
R1(config-if)#**ip address 172.16.2.1 255.255.255.0**
R1(config-if)#**interface loopback 3**
R1(config-if)#**ip address 172.16.3.1 255.255.255.0**
R1(config-if)#exit
R1(config)#**router rip**
R1(config-router)#**network 172.16.1.0**
R1(config-router)#**network 172.16.2.0**
R1(config-router)#**network 172.16.3.0**

R4(config)#**interface loopback 1**
R4(config-if)#**ip address 172.16.11.4 255.255.255.0**
R4(config-if)#**interface loopback 2**
R4(config-if)#**ip address 172.16.12.4 255.255.255.0**
R4(config-if)#**interface loopback 3**
R4(config-if)#**ip address 172.16.13.4 255.255.255.0**
R1(config-if)#exit

https://t.me/learningnets

R4(config-if)#**router rip**
R4(config-router)#**network 172.16.11.0**
R4(config-router)#**network 172.16.12.0**
R4(config-router)#**network 172.16.13.0**

To verify the networks are advertised into RIP, check the database at each router.

R1#show ip rip database
10.0.0.0/8 auto-summary
10.0.0.0/30 directly connected, Serial1/0
10.0.0.4/30 directly connected, Serial1/1
10.0.1.0/24 directly connected, FastEthernet0/0
172.16.0.0/16 auto-summary
172.16.1.0/24 directly connected, Loopback1
172.16.2.0/24 directly connected, Loopback2
172.16.3.0/24 directly connected, Loopback3
172.16.11.0/24
[1] via 10.0.1.4, 00:00:01, FastEthernet0/0
172.16.12.0/24
[1] via 10.0.1.4, 00:00:01, FastEthernet0/0
172.16.13.0/24
[1] via 10.0.1.4, 00:00:01, FastEthernet0/0

R4#show ip rip database
10.0.0.0/8 auto-summary
10.0.0.12/30 directly connected, Serial1/0
10.0.1.0/24 directly connected, FastEthernet0/0
172.16.0.0/16 auto-summary
172.16.1.0/24
[1] via 10.0.1.1, 00:00:23, FastEthernet0/0
172.16.2.0/24
[1] via 10.0.1.1, 00:00:23, FastEthernet0/0
172.16.3.0/24
[1] via 10.0.1.1, 00:00:23, FastEthernet0/0
172.16.11.0/24 directly connected, Loopback1
172.16.12.0/24 directly connected, Loopback2
172.16.13.0/24 directly connected, Loopback3

Task 6

R1(config)#router eigrp 100
R1(config-router)#redistribute rip metric 1500 **10000** 255 1 1500

https://t.me/learningnets

R4(config)#router eigrp 100
R4(config-router)#redistribute rip metric 1500 **0** 255 1 1500

As we wanted R4 to be the preferred path, we added an extra delay when redistributing from R1. The reason we didn't use bandwidth is that EIGRP takes into account the minimum bandwidth along the path not maximum so no matter what bandwidth we enter there are serial links in the path so the bandwidth of the serial link will be used for the metric calculation.

Let's examine R2's database:

R2#sh ip eigrp topology 172.16.1.0/24
IP-EIGRP (AS 100): Topology entry for 172.16.1.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 2730496
Routing Descriptor Blocks:
10.0.0.10 (Serial1/1), from 10.0.0.10, Send flag is 0x0 <<< R4
Composite metric is (2730496/2218496), Route is External
Vector metric:
Minimum bandwidth is 1500 Kbit
Total delay is 40000 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 2
External data:
Originating router is 10.0.1.4
AS number of route is 0
External protocol is RIP, external metric is 1
Administrator tag is 0 (0x00000000)
10.0.0.1 (Serial1/0), from 10.0.0.1, Send flag is 0x0 <<< via R1
Composite metric is (4778496/4266496), Route is External
Vector metric:
Minimum bandwidth is 1500 Kbit
Total delay is 120000 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1
External data:
Originating router is 10.0.1.1
AS number of route is 0

https://t.me/learningnets

External protocol is RIP, external metric is 0
Administrator tag is 0 (0x00000000)

Checking the routing table, it's preferred to go via R3 NOT via R1 even though it's closer!

R2#sh ip route 172.16.1.0
Routing entry for 172.16.1.0/24
Known via "eigrp 100", distance 170, metric 2730496, type external
Redistributing via eigrp 100
Last update from 10.0.0.10 on Serial1/1, 00:06:45 ago
Routing Descriptor Blocks:
*** 10.0.0.10, from 10.0.0.10, 00:06:45 ago, via Serial1/1**
Route metric is 2730496, traffic share count is 1
Total delay is 40000 microseconds, minimum bandwidth is 1500 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 2

Finally, the traceroute establishes which path we are taking:

R2#traceroute 172.16.1.1

Type escape sequence to abort.
Tracing the route to 172.16.1.1

1 10.0.0.10 20 msec 28 msec 20 msec << R3
2 10.0.0.14 40 msec 36 msec 28 msec << R4
3 10.0.1.1 52 msec 48 msec 32 msec << R1

Task 7

R1(config)#**access-list 14 deny 172.16.1.0 0.0.0.255**
R1(config)#**access-list 14 deny 172.16.11.0 0.0.0.255**
R1(config)#**access-list 14 permit any**
R1(config)#**route-map RIP2EIGRP**
R1(config-route-map)#**match ip add 14**
R4(config-route-map)#**exit**
R1(config)#**router eigrp 100**
R1(config)#**redistribute rip metric 1500 10000 255 1 1500 route-map RIP2EIGRP**

R4(config)#**access-list 14 deny 172.16.1.0 0.0.0.255**
R4(config)#**access-list 14 deny 172.16.11.0 0.0.0.255**
R4(config)#**access-list 14 permit any**
R4(config)#**route-map RIP2EIGRP permit 10**
R4(config-route-map)#**match ip address 14**

https://t.me/learningnets

Technet24

R4(config-route-map)#**exit**
R4(config)#**router eigrp 100**
R4(config-router#**redistribute rip metric 1500 0 255 1 1500 route-map RIP2EIGRP**

Check the filter at both points where we are redistributing into EIGRP!

Verifications:

R2#sh ip route 172.16.1.0
% Subnet not in table
R2#sh ip route 172.16.11.0
% Subnet not in table

R2#sh ip route 172.16.2.0
Routing entry for 172.16.2.0/24
Known via "eigrp 100", distance 170, metric 2730496, type external
Redistributing via eigrp 100
Last update from 10.0.0.10 on Serial1/1, 00:21:49 ago
Routing Descriptor Blocks:
* 10.0.0.10, from 10.0.0.10, 00:21:49 ago, via Serial1/1
Route metric is 2730496, traffic share count is 1
Total delay is 40000 microseconds, minimum bandwidth is 1500 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 2

R3#sh ip route 172.16.1.0
% Subnet not in table
R3#sh ip route 172.16.11.0
% Subnet not in table

R3#sh ip route 172.16.2.0
Routing entry for 172.16.2.0/24
Known via "eigrp 100", distance 170, metric 2218496, type external
Redistributing via eigrp 100
Last update from 10.0.0.14 on Serial1/2, 00:23:09 ago
Routing Descriptor Blocks:
* 10.0.0.14, from 10.0.0.14, 00:23:09 ago, via Serial1/2
Route metric is 2218496, traffic share count is 1
Total delay is 20000 microseconds, minimum bandwidth is 1500 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1

We can see we only filtered the routes we needed. The rest of the networks are still in

https://t.me/learningnets

the routing table.

https://t.me/learningnets

CCNP Lab 014: EIGRP Multi-Technology

Lab Objective:

The focus of this lab is to understand EIGRP implementation and configuration in Cisco IOS routers. Additional technologies tested include redistribution and path control. In addition, basic ODR implementation and configuration is also tested.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

https://t.me/learningnets

Technet24

Task 2

Configure EIGRP for AS 1as is illustrated in the topology; however, you should NOT advertise the 10.0.0.12/30 subnet between routers R3 and R4 or the 150.3.3.0/24 LAN subnet connected to R3 via EIGRP. Ensure that no EIGRP packets are sent or received on any interfaces for which EIGRP is enabled but which will have no EIGRP neighbors. Verify your configuration.

Task 3

Configure ODR between R3 and R4. Verify that R3 receives the 150.4.4.0/24, 160.4.4.0/24, and 170.4.4.0/24 subnets connected to R4s LAN interface via ODR.

Task 4

Configure your network so that all the other routers can reach the 150.4.4.0/24, 160.4.4.0/24 , and 170.4.4.4.0/24 subnets configured on R4. These prefixes should be assigned a route tag of 150, 160, and 170, respectively. Ensure all routers can ping each other following this configuration. Verify your configuration using the appropriate commands.

Task 5

Configure your network so R1 prefers the path via R2 to reach the 150.3.3.0/24 and 150.4.4.0/24 subnets. All other routes should follow the best path. Do NOT modify EIGRP metrics in any manner to complete this task. Verify your configuration.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**
R1(config-if)#**exit**

https://t.me/learningnets

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 150.3.3.3 255.255.255.0**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.6 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.4.4.4 255.255.255.0**
R4(config-if)#**ip address 160.4.4.4 255.255.255.0 secondary**

https://t.me/learningnets

R4(config-if)#**ip address 170.4.4.4 255.255.255.0 secondary**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**exit**

Task 2

R1(config)#**router eigrp 1**
R1(config-router)#**network 150.1.1.0 0.0.0.255**
R1(config-router)#**network 10.0.0.0 0.0.0.3**
R1(config-router)#**network 10.0.0.4 0.0.0.3**
R1(config-router)#**passive-interface fastethernet 0/0**
R1(config-router)#**no auto-summary**
R1(config-router)#**exit**

R2(config)#**router eigrp 1**
R2(config-router)#**network 150.2.2.0 0.0.0.255**
R2(config-router)#**network 10.0.0.0 0.0.0.3**
R2(config-router)#**network 10.0.0.8 0.0.0.3**
R2(config-router)#**passive-interface fastethernet 0/0**
R2(config-router)#**no auto-summary**
R2(config-router)#**exit**

R3(config)#**router eigrp 1**
R3(config-router)#**network 10.0.0.4 0.0.0.3**
R3(config-router)#**network 10.0.0.8 0.0.0.3**
R3(config-router)#**no auto-summary**
R3(config-router)#**exit**

Verify your configuration using the **show ip eigrp neighbors** command:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.6 Se0/1 13 00:00:06 14 200 0 21
0 10.0.0.2 Se0/0 12 00:00:07 5 200 0 25

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq

https://t.me/learningnets

(sec) (ms) Cnt Num
1 10.0.0.1 Se0/0 11 00:00:03 3 200 0 31
0 10.0.0.10 Se0/1 14 00:00:05 24 200 0 30

R3#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.9 Se1/1 11 00:00:03 15 1140 0 38
0 10.0.0.5 Se1/0 14 00:00:05 11 1140 0 35

You can view passive interfaces using the **show ip protocols** command:

R1#**show ip protocols**
Routing Protocol is “eigrp 1”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Default networks flagged in outgoing updates
Default networks accepted from incoming updates
EIGRP metric weight K1=1, K2=0, K3=1, K4=0, K5=0
EIGRP maximum hopcount 100
EIGRP maximum metric variance 1
Redistributing: eigrp 1
EIGRP NSF-aware route hold timer is 240s
Automatic network summarization is not in effect
Maximum path: 4
Routing for Networks:
10.0.0.0/30
10.0.0.4/30
150.1.1.0/24
Passive Interface(s):
FastEthernet0/0
Routing Information Sources:
Gateway Distance Last Update
(this router) 90 00:00:27
10.0.0.2 90 00:00:22
10.0.0.6 90 00:00:22
Distance: internal 90 external 170

Task 3

In order to run ODR, CDP must be enabled. By default, CDP is enabled on LAN and

https://t.me/learningnets
Technet24

point-to-point WAN interfaces. If CDP is disabled, it can be globally enabled using the **cdp run** command. Alternatively, CDP can be enabled on a per-interface basis using the **cdp enable** command. Use the **show cdp interface** command to see the interfaces running CDP.

R4#**show cdp interface**
FastEthernet0/0 is up, line protocol is up
Encapsulation ARPA
Sending CDP packets every 60 seconds
Holdtime is 180 seconds
Serial0/0 is up, line protocol is up
Encapsulation HDLC
Sending CDP packets every 60 seconds
Holdtime is 180 seconds
Serial0/1 is administratively down, line protocol is down
Encapsulation HDLC
Sending CDP packets every 60 seconds
Holdtime is 180 seconds

The second requirement is that ODR routing is enabled only on the hub using the **router odr** command. This command should not be enabled on the spoke router. Additionally, there should be no other routing protocols enabled on the spoke router. If a routing protocol has been enabled, ODR will not run on the spoke router. Complete the first part of this task as follows:

R3(config)#**router odr**
R3(config-router)#**exit**

Verify your configuration using the **show ip route** command:

R3#**show ip route odr**
170.4.0.0/24 is subnetted, 1 subnets
o 170.4.4.0 [160/1] via 10.0.0.14, 00:00:09, Serial1/2
160.4.0.0/24 is subnetted, 1 subnets
o 160.4.4.0 [160/1] via 10.0.0.14, 00:00:09, Serial1/2
150.4.0.0/24 is subnetted, 1 subnets
o 150.4.4.0 [160/1] via 10.0.0.14, 00:00:09, Serial1/2

By default, the hub will advertise the spoke router(s) a default route when ODR is enabled:

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area

https://t.me/learningnets

N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 10.0.0.13 to network 0.0.0.0

170.4.0.0/24 is subnetted, 1 subnets
C 170.4.4.0 is directly connected, FastEthernet0/0
160.4.0.0/24 is subnetted, 1 subnets
C 160.4.4.0 is directly connected, FastEthernet0/0
10.0.0.0/30 is subnetted, 1 subnets
C 10.0.0.12 is directly connected, Serial0/0
150.4.0.0/24 is subnetted, 1 subnets
C 150.4.4.0 is directly connected, FastEthernet0/0
o* 0.0.0.0/0 [160/1] via 10.0.0.13, 00:00:48, Serial0/0

Task 4

There are multiple ways in which this task can be completed. The first overall requirement is to complete this task are to redistribute ODR routes into EIGRP via a route map using an IP prefix list or ACL matching. Because EIGRP does not assign a default metric to ODR routes, you must specify the metric in the route map, when using the **redistribute** command, or by configuring a seed metric for EIGRP using the **default-metric** command. The second overall requirement is to complete this task is to redistribute the connected ODR subnets into EIGRP. This will allow R4 to ping all other routers and vice-versa.

R3(config)#**ip prefix-list NET-150 seq 5 permit 150.4.4.0/24**
R3(config)#**ip prefix-list NET-160 seq 5 permit 160.4.4.0/24**
R3(config)#**ip prefix-list NET-170 seq 5 permit 170.4.4.0/24**
R3(config)#**route-map ODR-2-EIGRP permit 10**
R3(config-route-map)#**match ip address prefix-list NET-150**
R3(config-route-map)#**set tag 150**
R3(config-route-map)#**exit**
R3(config)#**route-map ODR-2-EIGRP permit 20**
R3(config-route-map)#**match ip address prefix-list NET-160**
R3(config-route-map)#**set tag 160**
R3(config-route-map)#**exit**
R3(config)#**route-map ODR-2-EIGRP permit 30**
R3(config-route-map)#**match ip address prefix-list NET-170**

https://t.me/learningnets

Technet24

R3(config-route-map)#**set tag 170**
R3(config-route-map)#**exit**
R3(config)#**router eigrp 1**
R3(config-router)#**redistribute odr route-map ODR-2-EIGRP**
R3(config-router)#**redistribute connected**
R3(config-router)#**default-metric 100000 100 255 1 1500**
R3(config-router)#**exit**

Verify the EIGRP redistribution configuration using the **show ip eigrp topology** command on the local router:

R3#**show ip eigrp topology | include (tag|Redistributed)**

P 150.4.4.0/24, 1 successors, FD is 51200, tag is 150

via Redistributed (51200/0)

P 160.4.4.0/24, 1 successors, FD is 51200, tag is 160

via Redistributed (51200/0)

P 170.4.4.0/24, 1 successors, FD is 51200, tag is 170

via Redistributed (51200/0)

NOTE: When routes are redistributed into EIGRP from ODR, the routing protocol is listed as 'Unknown'. This can be verified by looking at specific route entries in the topology table:

R3#**show ip eigrp topology 150.4.4.0/24**
IP-EIGRP (AS 1): Topology entry for 150.4.4.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 51200
Routing Descriptor Blocks:
10.0.0.14, from Redistributed, Send flag is 0x0
Composite metric is (51200/0), Route is External
Vector metric:
Minimum bandwidth is 100000 Kbit
Total delay is 1000 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 0
External data:
Originating router is 150.3.3.3 (this system)
AS number of route is 0
External protocol is Unknown protocol, external metric is 1

https://t.me/learningnets

Administrator tag is 150 (0x00000096)

Complete this task by pinging between the routers as required in the task:

R1#**ping 10.0.0.14 source 150.1.1.1**

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 10.0.0.14, timeout is 2 seconds:

Packet sent with a source address of 150.1.1.1

!!!!!

Success rate is 100 percent (5/5), round-trip min/avg/max = 28/28/32 ms

R1#**ping 150.3.3.3 source 150.1.1.1**

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:

Packet sent with a source address of 150.1.1.1

!!!!!

Success rate is 100 percent (5/5), round-trip min/avg/max = 16/16/16 ms

R1#**ping 150.2.2.2 source 150.1.1.1**

Type escape sequence to abort.

Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:

Packet sent with a source address of 150.1.1.1

!!!!!

Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms

Task 5

Before completing this task, the RIB on R1 should show the following external route entries:

R1#**show ip route eigrp | include EX**
D EX 170.4.4.0 [170/2195456] via 10.0.0.6, 00:21:13, Serial0/1
D EX 160.4.4.0 [170/2195456] via 10.0.0.6, 00:21:13, Serial0/1
D EX 10.0.0.12 [170/21024000] via 10.0.0.6, 00:21:27, Serial0/1
D EX 150.3.3.0 [170/2172416] via 10.0.0.6, 00:21:27, Serial0/1
D EX 150.4.4.0 [170/2195456] via 10.0.0.6, 00:21:13, Serial0/1

Complete this task my modifying the metrics with an offset list as follows:

R1(config)#**access-list 1 permit 150.3.3.0 0.0.0.255**
R1(config)#**access-list 1 permit 150.4.4.0 0.0.0.255**

https://t.me/learningnets

Technet24

```
R1(config)#router eigrp 1
R1(config-router)#offset-list 1 in 123456789 serial 0/1
R1(config-router)#exit
```

Following this change, the RIB on R1 should show the following external route entries:

```
R1#show ip route eigrp | include EX
D EX 170.4.4.0 [170/2195456] via 10.0.0.6, 00:02:16, Serial0/1
D EX 160.4.4.0 [170/2195456] via 10.0.0.6, 00:02:16, Serial0/1
D EX 10.0.0.12 [170/21024000] via 10.0.0.6, 00:02:16, Serial0/1
D EX 150.3.3.0 [170/2684416] via 10.0.0.2, 00:01:36, Serial0/0
D EX 150.4.4.0 [170/2707456] via 10.0.0.2, 00:01:36, Serial0/0
```

https://t.me/learningnets

CCNP Lab 015: EIGRP Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand EIGRP implementation and configuration in Cisco IOS routers. Additional technologies tested include path control and stub routing.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure EIGRP for AS 1 as shown in the topology. R4 should be configured as an

https://t.me/learningnets

EIGRP stub router. R4 should NEVER advertise any routes. In addition to this, ensure that router R4 will only ever receive a default route from R1 even if external routes are redistributed into EIGRP 1.

Task 3

Configure EIGRP for AS 2 as illustrated in the topology. Verify your configuration using the appropriate commands for EIGRP.

Task 4

Configure EIGRP so that R4 can reach all other routers in the network and vice-versa. Ensure that only the 150.1.1.0/24 is allowed into the topology table for EIGRP 2. Verify your configuration and also ping to and from R4 from the 150.2.2.0/24 and 150.3.3.0/24 subnets.

Task 5

Assume that the WAN link between R1 and R3 is unreliable and should only be used when the WAN link between R1 and R2 is down. However, an EIGRP neighbor relationship should still be maintained across this link. Configure EIGRP so that neither routers R1 nor R3 use this link unless the WAN link between R1 and R2 is down. You are only allowed to configure R3. Do NOT issue any configuration commands on R1 to complete this task.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**
R1(config-if)#**exit**

Router(config)#**hostname R2**

https://t.me/learningnets

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 150.3.3.3 255.255.255.0**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.6 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.1.1.4 255.255.255.0**
R4(config-if)#**exit**

Task 2

R1(config)#**ip prefix-list DEFAULT-ONLY seq 5 permit 0.0.0.0/0**
R1(config)#**router eigrp 1**
R1(config-router)#**network 150.1.1.0 0.0.0.255**
R1(config-router)#**distribute-list prefix DEFAULT-ONLY out fastethernet 0/0**

https://t.me/learningnets

R1(config-router)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip summary-address eigrp 1 0.0.0.0 0.0.0.0**
R1(config-if)#**exit**

NOTE: You can also configure a static default route to Null0 and redistribute into EIGRP. For example, you could complete this task as follows:

R1(config)#**ip prefix-list DEFAULT-ONLY seq 5 permit 0.0.0.0/0**
R1(config)#**ip route 0.0.0.0 0.0.0.0 null 0**
R1(config)#**router eigrp 1**
R1(config-router)#**redistribute static**
R1(config-router)#**distribute-list prefix DEFAULT-ONLY out fastethernet 0/0**
R1(config-router)#**exit**

Complete the configuration on R4 as follows:

R4(config)#**router eigrp 1**
R4(config-router)#**network 150.1.1.0 0.0.0.255**
R4(config-router)#**eigrp stub receive-only**
R4(config-router)#**exit**

Verify your EIGRP configuration using the **show ip eigrp neighbors [detail]** and the **show ip route [eigrp]** commands:

R1#**show ip eigrp neighbors detail**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.1.1.4 Fa0/0 12 00:05:24 653 3918 0 6
Restart time 00:01:18
Version 12.4/1.2, Retrans: 0, Retries: 0
Receive-Only Peer Advertising (No) Routes
Suppressing queries

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

https://t.me/learningnets
Technet24

Gateway of last resort is 150.1.1.1 to network 0.0.0.0

150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
D* 0.0.0.0/0 [90/30720] via 150.1.1.1, 00:01:49, FastEthernet0/0

Task 3

R1(config)#**router eigrp 2**
R1(config-router)#**no auto-summary**
R1(config-router)#**network 10.0.0.0 0.0.0.3**
R1(config-router)#**network 10.0.0.4 0.0.0.3**
R1(config-router)#**exit**

R2(config)#**router eigrp 2**
R2(config-router)#**no auto-summary**
R2(config-router)#**network 150.2.2.2 0.0.0.0**
R2(config-router)#**network 10.0.0.2 0.0.0.0**
R2(config-router)#**network 10.0.0.9 0.0.0.0**
R2(config-router)#**exit**

R3(config)#**router eigrp 2**
R3(config-router)#**network 150.3.3.3 0.0.0.0**
R3(config-router)#**network 10.0.0.6 0.0.0.0**
R3(config-router)#**network 10.0.0.10 0.0.0.0**
R3(config-router)#**no auto-summary**
R3(config-router)#**exit**

Task 4

To complete this task, you need to redistribute between EIGRP for AS 1 and EIGRP for AS 2. It is important to remember that a seed metric is not required when redistributing between different EIGRP processes. Additionally, configure filtering when redistributing so that only the 150.1.1.0/24 subnet is allowed into EIGRP 2. Complete this task as follows:

R1(config)#**router eigrp 1**
R1(config-router)#**redistribute eigrp 2**
R1(config-router)#**exit**
R1(config)#**ip prefix-list NET-150-ONLY seq 5 permit 150.1.1.0/24**
R1(config)#**route-map EIGRP1-2-EIGRP2 permit 10**
R1(config-route-map)#**match ip address prefix-list NET-150-ONLY**
R1(config-route-map)#**exit**
R1(config)#**route-map EIGRP1-2-EIGRP2 deny 20**

https://t.me/learningnets

R1(config-route-map)#**exit**
R1(config)#**router eigrp 2**
R1(config-router)#**redistribute eigrp 1 route-map EIGRP1-2-EIGRP2**
R1(config-router)#**exit**

Following this configuration, verify that external routes exist in the topology tables for both of the autonomous systems. Use the **show ip eigrp topology** command. Next, verify the routing tables of all the other routers in the topology following the redistribution configuration:

R2#**show ip route eigrp**

10.0.0.0/30 is subnetted, 3 subnets

D 10.0.0.4 [90/2681856] via 10.0.0.1, 00:16:15, Serial0/0

150.1.0.0/24 is subnetted, 1 subnets

D EX 150.1.1.0 [170/2172416] via 10.0.0.1, 00:14:33, Serial0/0

150.3.0.0/24 is subnetted, 1 subnets

D 150.3.3.0 [90/2172416] via 10.0.0.10, 00:16:11, Serial0/1

R3#**show ip route eigrp**

10.0.0.0/30 is subnetted, 3 subnets

D 10.0.0.0 [90/21024000] via 10.0.0.9, 00:15:46, Serial1/1

[90/21024000] via 10.0.0.5, 00:15:46, Serial1/0

150.1.0.0/24 is subnetted, 1 subnets

D EX 150.1.1.0 [170/20514560] via 10.0.0.5, 00:14:04, Serial1/0

150.2.0.0/24 is subnetted, 1 subnets

D 150.2.2.0 [90/20514560] via 10.0.0.9, 00:15:46, Serial1/1

R4#**show ip route**

Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP

D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area

N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2

E1 - OSPF external type 1, E2 - OSPF external type 2

i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2

ia - IS-IS inter area, * - candidate default, U - per-user static route

o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.1.1.1 to network 0.0.0.0

https://t.me/learningnets

Technet24

150.1.0.0/24 is subnetted, 1 subnets

C 150.1.1.0 is directly connected, FastEthernet0/0

D* 0.0.0.0/0 [90/30720] via 150.1.1.1, 00:06:21, FastEthernet0/0

Finally, ping between R4 and 150.2.2.0/24 and 150.3.3.0/24 subnets:

R4#**ping 150.2.2.2 source 150.1.1.4 repeat 10**

Type escape sequence to abort.

Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:

Packet sent with a source address of 150.1.1.4

!!!!!!!!!!

Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R4#**ping 150.3.3.3 source 150.1.1.4 repeat 10**

Type escape sequence to abort.

Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:

Packet sent with a source address of 150.1.1.4

!!!!!!!!!!

Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

Task 5

To complete this task, you need to configure an inbound AND outbound offset list on R3 so that routes received or sent via the WAN link between R1 and R3 are undesirable:

R3(config)#**router eigrp 2**
R3(config-router)#**offset-list 0 in 1234567890 serial 1/0**
R3(config-router)#**offset-list 0 out 123456789 serial 1/0**
R3(config-router)#**exit**

Following this, R3 should prefer the path via R2 - even for the 150.1.1.0/24 subnet:

R3#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.0 [90/21024000] via 10.0.0.9, 00:00:04, Serial1/1
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/21026560] via 10.0.0.9, 00:00:04, Serial1/1
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/20514560] via 10.0.0.9, 00:00:04, Serial1/1

The same applies to R1, which prefers the path via R2 - even for the 150.3.3.0/24 subnet:

https://t.me/learningnets

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/2681856] via 10.0.0.2, 00:01:24, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 10.0.0.2, 00:01:24, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2684416] via 10.0.0.2, 00:01:24, Serial0/0
D* 0.0.0.0/0 is a summary, 00:29:25, Null0

In the event that the link to R2 fails, the WAN link between R1 and R2 is used:

R3#**configure terminal**
Enter configuration commands, one per line. End with CNTL/Z.
R3(config)#**interface serial 1/1**
R3(config-if)#**shutdown**
R3(config-if)#**do ping 150.1.1.4 source 150.3.3.3**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.4, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/16/16 ms
R3(config-if)#**do show ip route eigrp**
10.0.0.0/30 is subnetted, 2 subnets
D 10.0.0.0 [90/1255591890] via 10.0.0.5, 00:00:05, Serial1/0
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/1255082450] via 10.0.0.5, 00:00:05, Serial1/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/1255594450] via 10.0.0.5, 00:00:05, Serial1/0

https://t.me/learningnets

Technet24

CCNP Lab 016: EIGRP Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand EIGRP implementation and configuration in Cisco IOS routers. Additional technologies tested include summarization and authentication.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure EIGRP for AS 1 as illustrated in the topology. However, do NOT advertise

https://t.me/learningnets

Technet24

the 150.2.2.0/24 and 150.3.3.0/24 subnets connected to R2 and R3 via EIGRP. Additionally, authenticate EIGRP protocol updates using the password 'CCNP'.

Task 3

Configure routers R2 and R3 to advertise ONLY the default route to R1 and R4. Ensure that R2 and R3 can ping each others' 150.x.x.x/24 subnets. Verify that R1 and R4 can reach the 150.2.2.0/24 and 150.3.3.0/24 subnets even if their own WAN links are down or unavailable.

Task 4

Configure the following secondary subnets on the LAN segment between R1 and R4:

- Network: 192.168.0.0/24 - Assign 192.168.0.1/24 to R1 and 192.168.0.4/24 to R4
- Network: 192.168.1.0/24 - Assign 192.168.1.1/24 to R1 and 192.168.1.4/24 to R4
- Network: 192.168.2.0/24 - Assign 192.168.2.1/24 to R1 and 192.168.2.4/24 to R4
- Network: 192.168.3.0/24 - Assign 192.168.3.1/24 to R1 and 192.168.3.4/24 to R4

Next, configure R1 and R4 to advertise only a single route for these subnets to R2 and R3.

Task 5

Management has decided that packets sourced from the LAN interface of R2 (150.2.2.2) should use the R2-R3-R4 path to reach the 150.1.1.0/24 and 192.168.1.0/24 subnets. This should be completed without performing any modifications on any other router except for R2. Verify your configuration using the appropriate commands. Corporate IT policy states that NO static routes are allowed. Complete this solution while adhering to this policy.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**

https://t.me/learningnets

R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 150.3.3.3 255.255.255.0**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.1.1.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**

https://t.me/learningnets

R4(config-if)#**no shutdown**
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**exit**

Task 2

R1(config)#**key chain EIGRP-AUTH**
R1(config-keychain)#**key 1**
R1(config-keychain-key)#**key-string CCNP**
R1(config-keychain-key)#**exit**
R1(config-keychain)#**exit**
R1(config)#**router eigrp 1**
R1(config-router)#**network 150.1.1.1 0.0.0.0**
R1(config-router)#**network 10.0.0.1 0.0.0.0**
R1(config-router)#**no auto-summary**
R1(config-router)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip authentication mode eigrp 1 md5**
R1(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip authentication mode eigrp 1 md5**
R1(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R1(config-if)#**exit**

R2(config)#**key chain EIGRP-AUTH**
R2(config-keychain)#**key 1**
R2(config-keychain-key)#**key-string CCNP**
R2(config-keychain-key)#**exit**
R2(config)#**router eigrp 1**
R2(config-router)#**network 10.0.0.2 0.0.0.0**
R2(config-router)#**network 10.0.0.9 0.0.0.0**
R2(config-router)#**no auto-summary**
R2(config-router)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip authentication mode eigrp 1 md5**
R2(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip authentication mode eigrp 1 md5**

https://t.me/learningnets

R2(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R2(config-if)#**exit**

R3(config)#**key chain EIGRP-AUTH**
R3(config-keychain)#**key 1**
R3(config-keychain-key)#**key-string CCNP**
R3(config-keychain-key)#**exit**
R3(config-keychain)#**exit**
R3(config **router eigrp 1**
R3(config-router)#**no auto-summary**
R3(config-router)#**network 10.0.0.10 0.0.0.0**
R3(config-router)#**network 10.0.0.13 0.0.0.0**
R3(config-router)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip authentication mode eigrp 1 md5**
R3(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip authentication mode eigrp 1 md5**
R3(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R3(config-if)#**exit**

R4(config)#**key chain EIGRP-AUTH**
R4(config-keychain)#**key 1**
R4(config-keychain-key)#**key-string CCNP**
R4(config-keychain-key)#**exit**
R4(config-keychain)#**exit**
R4(config)#**router eigrp 1**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 150.1.1.4 0.0.0.0**
R4(config-router)#**network 10.0.0.14 0.0.0.0**
R4(config-router)#**exit**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip authentication mode eigrp 1 md5**
R4(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip authentication mode eigrp 1 md5**
R4(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R4(config-if)#**exit**

https://t.me/learningnets

Verify your configuration using the **show ip eigrp neighbors** command:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 150.1.1.4 Fa0/0 10 00:01:22 3 200 0 4
0 10.0.0.2 Se0/0 14 00:06:40 3 200 0 11

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.10 Se0/1 14 00:04:30 15 200 0 8
0 10.0.0.1 Se0/0 11 00:06:52 4 200 0 10

R3#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.14 Se1/2 10 00:01:36 21 1140 0 7
0 10.0.0.9 Se1/1 11 00:04:42 19 1140 0 10

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.13 Se0/0 14 00:01:59 21 200 0 9
0 150.1.1.1 Fa0/0 12 00:02:10 1022 5000 0 9

Verify configured key chains using the **show key chain [name]** command:

R1#**show key chain EIGRP-AUTH**
Key-chain EIGRP-AUTH:
key 1 -- text “CCNP”
accept lifetime (always valid) - (always valid) [valid now]
send lifetime (always valid) - (always valid) [valid now]

Verify authentication using the **show ip eigrp interfaces detail [name]** command:

R1#**show ip eigrp interfaces detail**
IP-EIGRP interfaces for process 1
Xmit Queue Mean Pacing Time Multicast Pending
Interface Peers Un/Reliable SRTT Un/Reliable Flow Timer Routes
Fa0/0 1 0/0 3 0/1 50 0

https://t.me/learningnets

Hello interval is 5 sec
Next xmit serial <none>
Un/reliable mcasts: 0/2 Un/reliable ucasts: 1/4
Mcast exceptions: 1 CR packets: 1 ACKs suppressed: 1
Retransmissions sent: 1 Out-of-sequence rcvd: 0
Authentication mode is md5, key-chain is "EIGRP-AUTH"
Use multicast
Se0/0 1 0/0 3 0/15 50 0
Hello interval is 5 sec
Next xmit serial <none>
Un/reliable mcasts: 0/0 Un/reliable ucasts: 2/6
Mcast exceptions: 0 CR packets: 0 ACKs suppressed: 3
Retransmissions sent: 0 Out-of-sequence rcvd: 0
Authentication mode is md5, key-chain is "EIGRP-AUTH"
Use unicast

Task 3

R2(config)#**ip prefix-list DEFAULT-ONLY seq 5 permit 0.0.0.0/0**
R2(config)#**router eigrp 1**
R2(config-router)#**redistribute connected**
R2(config-router)#**distribute-list prefix DEFAULT-ONLY out serial 0/0**
R2(config-router)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip summary-address eigrp 1 0.0.0.0 0.0.0.0**
R2(config-if)#**exit**

R3(config)#**ip prefix-list DEFAULT-ONLY seq 5 permit 0.0.0.0/0**
R3(config)#**router eigrp 1**
R3(config-router)#**redistribute connected**
R3(config-router)#**distribute-list prefix DEFAULT-ONLY out serial 1/2**
R3(config-router)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip summary-address eigrp 1 0.0.0.0 0.0.0.0**
R3(config-if)#**exit**

NOTE: You can also configure a static default route to Null0 and redistribute into EIGRP. For example, you could complete this task as follows:

R2(config)#**ip prefix-list DEFAULT-ONLY seq 5 permit 0.0.0.0/0**
R2(config)#**ip route 0.0.0.0 0.0.0.0 null 0**
R2(config)#**router eigrp 1**

https://t.me/learningnets
Technet24

R2(config-router)#**redistribute connected**
R2(config-router)#**redistribute static**
R2(config-router)#**distribute-list prefix DEFAULT-ONLY out serial 0/0**
R2(config-router)#**exit**

Verify your configurations by looking at the routing tables of all routers:

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 2 subnets
D 10.0.0.12 [90/2172416] via 150.1.1.4, 00:14:57, FastEthernet0/0
D* 0.0.0.0/0 [90/2172416] via 10.0.0.2, 00:05:17, Serial0/0

R2#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.12 [90/2684416] via 10.0.0.1, 00:15:15, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:15:05, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.10, 00:06:05, Serial0/1
D* 0.0.0.0/0 is a summary, 00:05:35, Null0

R3#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.0 [90/21024000] via 10.0.0.9, 00:15:22, Serial1/1
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/20514560] via 10.0.0.14, 00:15:22, Serial1/2
150.2.0.0/24 is subnetted, 1 subnets
D EX 150.2.2.0 [170/20514560] via 10.0.0.9, 00:08:15, Serial1/1
D* 0.0.0.0/0 is a summary, 00:05:51, Null0

R4#**show ip route eigrp**
10.0.0.0/30 is subnetted, 2 subnets
D 10.0.0.0 [90/2172416] via 150.1.1.1, 00:06:14, FastEthernet0/0
D* 0.0.0.0/0 [90/2172416] via 10.0.0.13, 00:06:07, Serial0/0

Test R1 or R4 failover by shutting down the WAN interface and pinging R2 and R3 (remember to 'no shut' it after the test):

R1(config)#**interface serial 0/0**
R1(config-if)#**shutdown**
R1(config-if)#**do ping 150.2.2.2 source 150.1.1.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:

https://t.me/learningnets

Packet sent with a source address of 150.1.1.1
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms
R1(config-if)#**do ping 150.3.3.3 source 150.1.1.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/16/16 ms
R1(config-if)#**do show ip route eigrp**
10.0.0.0/30 is subnetted, 1 subnets
D 10.0.0.12 [90/2172416] via 150.1.1.4, 00:17:20, FastEthernet0/0
D* 0.0.0.0/0 [90/2174976] via 150.1.1.4, 00:00:47, FastEthernet0/0

Task 4

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip address 192.168.0.1 255.255.255.0 secondary**
R1(config-if)#**ip address 192.168.1.1 255.255.255.0 secondary**
R1(config-if)#**ip address 192.168.2.1 255.255.255.0 secondary**
R1(config-if)#**ip address 192.168.3.1 255.255.255.0 secondary**
R1(config-if)#**exit**
R1(config)#**router eigrp 1**
R1(config-router)#**network 192.168.0.0 0.0.3.255**
R1(config-router)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip summary-address eigrp 1 192.168.0.0 255.255.252.0**
R1(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip address 192.168.0.4 255.255.255.0 secondary**
R4(config-if)#**ip address 192.168.1.4 255.255.255.0 secondary**
R4(config-if)#**ip address 192.168.2.4 255.255.255.0 secondary**
R4(config-if)#**ip address 192.168.3.4 255.255.255.0 secondary**
R4(config-if)#**exit**
R4(config)#**router eigrp 1**
R4(config-router)#**network 192.168.0.0 0.0.3.255**
R4(config-router)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip summary-address eigrp 1 192.168.0.0 255.255.252.0**

https://t.me/learningnets
Technet24

R4(config-if)#**exit**

Verify your configuration by looking at the routing tables of all routers:

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 2 subnets
D 10.0.0.12 [90/2172416] via 150.1.1.4, 00:26:41, FastEthernet0/0
D* 0.0.0.0/0 [90/2172416] via 10.0.0.2, 00:03:13, Serial0/0
D 192.168.0.0/22 is a summary, 00:02:43, Null0

R2#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.12 [90/2684416] via 10.0.0.1, 00:03:47, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:03:47, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.10, 00:18:06, Serial0/1
D* 0.0.0.0/0 is a summary, 00:03:50, Null0
D 192.168.0.0/22 [90/2172416] via 10.0.0.1, 00:01:44, Serial0/0

R3#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.0 [90/21024000] via 10.0.0.9, 00:03:57, Serial1/1
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/20514560] via 10.0.0.14, 00:03:53, Serial1/2
150.2.0.0/24 is subnetted, 1 subnets
D EX 150.2.2.0 [170/20514560] via 10.0.0.9, 00:20:06, Serial1/1
D* 0.0.0.0/0 is a summary, 00:17:42, Null0
D 192.168.0.0/22 [90/20514560] via 10.0.0.14, 00:01:51, Serial1/2

R4#**show ip route eigrp**
10.0.0.0/30 is subnetted, 2 subnets
D 10.0.0.0 [90/2172416] via 150.1.1.1, 00:04:00, FastEthernet0/0
D* 0.0.0.0/0 [90/2172416] via 10.0.0.13, 00:03:57, Serial0/0
D 192.168.0.0/22 is a summary, 00:01:54, Null0

Additionally, test connectivity to these subnets using a simple ping:

R2#**ping 192.168.0.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.0.0, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/3/4 ms

https://t.me/learningnets

R2#**ping 192.168.1.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.1.0, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/3/4 ms

R2#**ping 192.168.2.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.2.0, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms

R2#**ping 192.168.3.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.3.0, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/3/4 ms

R3#**ping 192.168.0.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.0.0, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/16/16 ms

R3#**ping 192.168.1.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.1.0, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/16/16 ms

R3#**ping 192.168.2.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.2.0, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/16/16 ms

R3#**ping 192.168.3.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.3.0, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 12/16/20 ms

https://t.me/learningnets

Technet24

Task 5

This task requires that PBR be configured on R2 as it cannot be completed with routing alone:

R2(config)#**access-list 100 permit ip host 150.2.2.2 150.1.1.0 0.0.0.255**
R2(config)#**access-list 100 permit ip host 150.2.2.2 192.168.1.0 0.0.0.255**
R2(config)#**route-map R2-FA-0/0-PBR permit 10**
R2(config-route-map)#**match ip address 100**
R2(config-route-map)#**set ip next-hop 10.0.0.10**
R2(config-route-map)#**exit**
R2(config)#**route-map R2-FA-0/0-PBR deny 20**
R2(config-route-map)#**exit**
R2(config)#**ip local policy route-map R2-FA-0/0-PBR**
R2(config)#**exit**

Verify your configuration for the 150.1.1.0/24 subnet by debugging PBR on R2:

R2#**debug ip policy**
Policy routing debugging is on
R2#**ping 150.1.1.1 source 150.2.2.2 repeat 1**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!
Success rate is 100 percent (1/1), round-trip min/avg/max = 16/18/20 ms
R2#
***May 6 00:03:23.379: IP: s=150.2.2.2 (local), d=150.1.1.1, len 100, policy match**
***May 6 00:03:23.379: IP: route map R2-FA-0/0-PBR, item 10, permit**
***May 6 00:03:23.379: IP: s=150.2.2.2 (local), d=150.1.1.1 (Serial0/1), len 100, policy routed**
***May 6 00:03:23.383: IP: local to Serial0/1 10.0.0.10**

Verify your configuration for the 192.168.1.0/24 subnet by debugging PBR on R2:

R2#**ping 192.168.1.0 source 150.2.2.2 repeat 1**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 192.168.1.0, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!
Success rate is 100 percent (1/1), round-trip min/avg/max = 32/32/32 ms
R2#

https://t.me/learningnets

***May 6 00:04:46.951: IP: s=150.2.2.2 (local), d=192.168.1.0, len 100, policy match**
***May 6 00:04:46.951: IP: route map R2-FA-0/0-PBR, item 10, permit**
***May 6 00:04:46.951: IP: s=150.2.2.2 (local), d=192.168.1.0 (Serial0/1), len 100, policy routed**
***May 6 00:04:46.951: IP: local to Serial0/1 10.0.0.10**

You can also use the **show route-map [name]** command to view matches against the configured statement(s) within the route map:

R2#**show route-map R2-FA-0/0-PBR**
route-map R2-FA-0/0-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): 100
Set clauses:
ip next-hop 10.0.0.10
Policy routing matches: 2 packets, 200 bytes
route-map R2-FA-0/0-PBR, deny, sequence 20
Match clauses:
Set clauses:
Policy routing matches: 0 packets, 0 bytes

https://t.me/learningnets

Technet24

CCNP Lab 017: EIGRP Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand EIGRP implementation and configuration in Cisco IOS routers. Additional technologies tested include stub routing, filtering, and authentication.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab. Also, if you are using the www.101labs.net racks, configure R3 as the Frame Relay switch using the following configuration commands:

hostname R3-Frame-Relay-Switch

https://t.me/learningnets

Technet24

```
!
frame-relay switching
!
interface serial 1/0
description ‘Connected To R1 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 102 interface serial 1/1 201
frame-relay route 104 interface serial 1/2 401
no shutdown
!
interface serial 1/1
description ‘Connected To R2 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 201 interface serial 1/0 102
no shutdown
!
interface serial 1/2
description ‘Connected To R4 Serial 0/0’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 401 interface serial 1/0 104
no shutdown
!
end
```

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure EIGRP for AS 1 as illustrated in the topology. However, do NOT advertise

https://t.me/learningnets

the 150.x.x.x subnets on any router via EIGRP.

Task 3

Configure routers R2 and R4 to as EIGRP stub routers. These routers should advertise their 150.x.x.x/24 subnets as Internal EIGRP routes to R1.

Task 4

Configure R1 so that it advertises ONLY a default route to both R2 and R4 as an External EIGRP route. Next, verify your configuration using the appropriate commands. Additionally, also verify that R2 and R4 can ping each others' 150.x.x.x/24 subnets from their LAN interfaces, as well as the 150.1.1.0/24 subnet on R1s LAN.

Task 5

Configure EIGRP authentication for AS 1 so that all the routers use the password CCNP-2010; however, after 15 minutes, the routers should stop using this password and begin using the password CCNP-2011. The password CCNP-2011 should be used by all routers indefinitely. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.1 255.255.255.0**
R1(config-if)#**no shutdown**
R1(config-if)#**encapsulation frame-relay**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip address 10.0.0.2 255.255.255.0**
R2(config-if)#**no shutdown**
R2(config-if)#**encapsulation frame-relay**

https://t.me/learningnets

Technet24

R2(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.4.4.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.4 255.255.255.0**
R4(config-if)#**no shutdown**
R4(config-if)#**encapsulation frame-relay**
R4(config-if)#**exit**

Task 2

R1(config)#**router eigrp 1**
R1(config-router)#**no auto-summary**
R1(config-router)#**network 10.0.0.1 0.0.0.0**
R1(config-router)#**exit**

R2(config)#**router eigrp 1**
R2(config-router)#**no auto-summary**
R2(config-router)#**network 10.0.0.2 0.0.0.0**
R2(config-router)#**exit**

R4(config)#**router eigrp 1**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 10.0.0.4 0.0.0.0**
R4(config-router)#**exit**

Use the **show ip eigrp neighbors** command to verify your configuration:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.4 Se0/1 135 00:00:46 16 200 0 3
0 10.0.0.2 Se0/1 157 00:01:20 15 200 0 3

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.1 Se0/1 166 00:01:39 1264 5000 0 3

https://t.me/learningnets

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.1 Se0/0 151 00:01:19 1219 5000 0 5

Task 3

By default, EIGRP stub routers advertise connected and summary routes. Therefore, no explicit configuration other than enabling EIGRP for the 150.x.x.x/24 subnets is required:

R2(config)#**router eigrp 1**
R2(config-router)#**network 150.2.2.2 0.0.0.0**
R2(config-router)#**eigrp stub**
R2(config-router)#**exit**

R4(config)#**router eigrp 1**
R4(config-router)#**network 150.4.4.4 0.0.0.0**
R4(config-router)#**eigrp stub**
R4(config-router)#**exit**

Verify your configuration using the **show ip eigrp neighbors detail** command on R1:

R1#**show ip eigrp neighbors detail**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.4 Se0/1 160 00:00:21 1253 5000 0 8
Version 12.4/1.2, Retrans: 0, Retries: 0, Prefixes: 1
Stub Peer Advertising (CONNECTED SUMMARY) Routes
Suppressing queries

0 10.0.0.2 Se0/1 161 00:02:15 654 3924 0 7
Version 12.4/1.2, Retrans: 0, Retries: 0, Prefixes: 1
Stub Peer Advertising (CONNECTED SUMMARY) Routes
Suppressing queries

Alternatively, you can use the **show ip protocols** command on the stub routers:

R2#**show ip protocols**
Routing Protocol is “eigrp 1”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Default networks flagged in outgoing updates

https://t.me/learningnets
Technet24

Default networks accepted from incoming updates
EIGRP metric weight K1=1, K2=0, K3=1, K4=0, K5=0
EIGRP maximum hopcount 100
EIGRP maximum metric variance 1
EIGRP stub, connected, summary
Redistributing: eigrp 1
EIGRP NSF-aware route hold timer is 240s
Automatic network summarization is not in effect
Maximum path: 4
Routing for Networks:
10.0.0.2/32
150.2.2.2/32
Routing Information Sources:
Gateway Distance Last Update
10.0.0.1 90 00:01:39
Distance: internal 90 external 170

R4#**show ip protocols**
Routing Protocol is “eigrp 1”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Default networks flagged in outgoing updates
Default networks accepted from incoming updates
EIGRP metric weight K1=1, K2=0, K3=1, K4=0, K5=0
EIGRP maximum hopcount 100
EIGRP maximum metric variance 1
EIGRP stub, connected, summary
Redistributing: eigrp 1
EIGRP NSF-aware route hold timer is 240s
Automatic network summarization is not in effect
Maximum path: 4
Routing for Networks:
10.0.0.4/32
150.4.4.4/32
Routing Information Sources:
Gateway Distance Last Update
10.0.0.1 90 00:00:48
Distance: internal 90 external 170

Verify that the routes are received on R1 using the **show ip route [eigrp]** command:

https://t.me/learningnets

R1#**show ip route eigrp**
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 10.0.0.2, 00:05:26, Serial0/1
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/2172416] via 10.0.0.4, 00:03:32, Serial0/1

Task 4

The task is to advertise an external default route to R2 and R4. Because split horizon is enabled by default, R1 will not advertise the 150.2.2.0/24 and 150.3.3.0/24 subnets out the same interface via which they were received, so no explicit filtering configuration for EIGRP is required on R1. This task is completed as follows:

R1(config)#**ip route 0.0.0.0 0.0.0.0 null 0**
R1(config)#**router eigrp 1**
R1(config-router)#**redistribute static**
R1(config-router)#**exit**

Verify your configuration by looking at the routing tables on R2 and R4:

R2#**show ip route eigrp**
D*EX 0.0.0.0/0 [170/2169856] via 10.0.0.1, 00:00:35, Serial0/1

R4#**show ip route eigrp**
D*EX 0.0.0.0/0 [170/2169856] via 10.0.0.1, 00:00:53, Serial0/0

Verify IP connectivity using simple pings:

R1#**ping 150.2.2.2 source 150.1.1.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

R1#**ping 150.4.4.4 source 150.1.1.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

R2#**ping 150.1.1.1 source 150.2.2.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:

https://t.me/learningnets
Technet24

Packet sent with a source address of 150.2.2.2
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

R2#**ping 150.4.4.4 source 150.2.2.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 56/57/60 ms

R4#**ping 150.1.1.1 source 150.4.4.4**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.2.2.2 source 150.4.4.4**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 56/57/60 ms

Task 5

There are several ways in which this task can be completed. One way would be to synchronize the router clocks by manually setting the system clock using the clock set command or using the Network Time Protocol (NTP). If this solution is used, this task is completed as follows:

R1(config)#**clock timezone CST -6**
R1(config)#**clock summer-time CST recurring**
R1(config)#**ntp master**
R1(config)#**exit**

R2(config)#**clock timezone CST -6**
R2(config)#**clock summer-time CST recurring**
R2(config)#**ntp server 10.0.0.1**
R2(config)#**exit**

R4(config)#**clock timezone CST -6**

https://t.me/learningnets

R4(config)#**clock summer-time CST recurring**
R4(config)#**ntp server 10.0.0.1**
R4(config)#**exit**

Verify Network Time Protocol and clock settings using the **show ntp status** command:

R4#**show ntp status**
Clock is synchronized, stratum 9, reference is 10.0.0.1
nominal freq is 250.0000 Hz, actual freq is 250.0000 Hz, precision is 2**18
reference time is D170B71D.82C8E0A7 (01:30:53.510 CST Sun May 8 2011)
clock offset is -0.0292 msec, root delay is 24.98 msec
root dispersion is 125.11 msec, peer dispersion is 125.05 msec
Following this configuration, you can then configure EIGRP authentication as follows:

R1(config)#**key chain EIGRP-AUTH**
R1(config-keychain)#**key 1**
R1(config-keychain-key)#**key-string CCNP-2010**
R1(config-keychain-key)#**accept local 01:45:00 May 8 2011 02:00:00 May 8 2011**
R1(config-keychain-key)#**send local 01:45:00 May 8 2011 02:00:00 May 8 2011**
R1(config-keychain-key)#**exit**
R1(config-keychain)#**key 2**
R1(config-keychain-key)#**key-string CCNP-2011**
R1(config-keychain-key)#**accept-lifetime local 02:00:00 May 8 2011 infinite**
R1(config-keychain-key)#**send-lifetime local 02:00:00 May 8 2011 infinite**
R1(config-keychain-key)#**exit**
R1(config-keychain)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip authentication mode eigrp 1 md5**
R1(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R1(config-if)#**exit**

R2(config)#**key chain EIGRP-AUTH**
R2(config-keychain)#**key 1**
R2(config-keychain-key)#**key-string CCNP-2010**
R2(config-keychain-key)#**accept local 01:45:00 May 8 2011 02:00:00 May 8 2011**
R2(config-keychain-key)#**send local 01:45:00 May 8 2011 02:00:00 May 8 2011**
R2(config-keychain-key)#**exit**
R2(config-keychain)#**key 2**
R2(config-keychain-key)#**key-string CCNP-2011**
R2(config-keychain-key)#**accept-lifetime local 02:00:00 May 8 2011 infinite**
R2(config-keychain-key)#**send-lifetime local 02:00:00 May 8 2011 infinite**

https://t.me/learningnets
Technet24

R2(config-keychain-key)#**exit**
R2(config-keychain)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip authentication mode eigrp 1 md5**
R2(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R2(config-if)#**exit**

R4(config)#**key chain EIGRP-AUTH**
R4(config-keychain)#**key 1**
R4(config-keychain-key)#**key-string CCNP-2010**
R4(config-keychain-key)#**accept local 01:45:00 May 8 2011 02:00:00 May 8 2011**
R4(config-keychain-key)#**send local 01:45:00 May 8 2011 02:00:00 May 8 2011**
R4(config-keychain-key)#**exit**
R4(config-keychain)#**key 2**
R4(config-keychain-key)#**key-string CCNP-2011**
R4(config-keychain-key)#**accept-lifetime local 02:00:00 May 8 2011 infinite**
R4(config-keychain-key)#**send-lifetime local 02:00:00 May 8 2011 infinite**
R4(config-keychain-key)#**exit**
R4(config-keychain)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip authentication mode eigrp 1 md5**
R4(config-if)#**ip authentication key-chain eigrp 1 EIGRP-AUTH**
R4(config-if)#**exit**

Following this, verify the key chain configuring using the **show key chain** command:

R1#**show clock**
01:54:36.175 CST Sun May 8 2011

R1#**show key chain EIGRP-AUTH**
Key-chain EIGRP-AUTH:
key 1 -- text "CCNP-2010"
accept lifetime (01:45:00 CST May 8 2011) - (02:00:00 CST May 8 2011) [valid now]
send lifetime (01:45:00 CST May 8 2011) - (02:00:00 CST May 8 2011) [valid now]
key 2 -- text "CCNP-2011"
accept lifetime (02:00:00 CST May 8 2011) - (infinite)
send lifetime (02:00:00 CST May 8 2011) - (infinite)

After the configured time interval has elapsed, the second key is used and the first invalidated:

R1#**show key chain EIGRP-AUTH**

https://t.me/learningnets

Key-chain EIGRP-AUTH:
key 1 -- text “CCNP-2010”
accept lifetime (01:45:00 CST May 8 2011) - (02:00:00 CST May 8 2011)
send lifetime (01:45:00 CST May 8 2011) - (02:00:00 CST May 8 2011)
key 2 -- text “CCNP-2011”
accept lifetime (02:00:00 CST May 8 2011) - (infinite) [valid now]
send lifetime (02:00:00 CST May 8 2011) - (infinite) [valid now]

The second method would simply be to specify the duration in the key chain. To do this, you will need to know the local time on each router, which is why the synchronized time, i.e. the NTP method is better - especially if you have multiple routers. This is completed as follows:

R1(config)#**key chain EIGRP-AUTH**
R1(config-keychain)#**key 1**
R1(config-keychain-key)#**key-string CCNP-2010**
R1(config-keychain-key)#**send-lifetime 01:45:00 May 8 2011 duration 900**
R1(config-keychain-key)#**accept-lifetime 01:45:00 May 8 2011 duration 900**
R1(config-keychain-key)#**exit**
R1(config-keychain)#**exit**
R1(config)#**key chain EIGRP-AUTH**
R1(config-keychain)#**key 2**
R1(config-keychain-key)#**key-string CCNP-2011**
R1(config-keychain-key)#**accept 02:00:00 May 8 2011 infinite**
R1(config-keychain-key)#**exit**

NOTE: The **duration** is specified in seconds. 15 minutes = 900 seconds.

R1#**show key chain EIGRP-AUTH**
Key-chain EIGRP-AUTH:
key 1 -- text “CCNP-2010”
accept lifetime (01:45:00 UTC May 8 2011) - (900 seconds) [valid now]
send lifetime (01:45:00 UTC May 8 2011) - (900 seconds) [valid now]
key 2 -- text “CCNP-2011”
accept lifetime (02:00:00 UTC May 8 2011) - (infinite)
send lifetime (02:00:00 UTC May 8 2011) - (infinite)

After the configured time interval has elapsed, the second key is used and the first invalidated:

R1#**show key chain EIGRP-AUTH**
Key-chain EIGRP-AUTH:
key 1 -- text “CCNP-2010”

https://t.me/learningnets
Technet24

accept lifetime (01:45:00 UTC May 8 2011) - (900 seconds)
send lifetime (01:45:00 UTC May 8 2011) - (900 seconds)
key 2 -- text “CCNP-2011”
accept lifetime (02:00:00 UTC May 8 2011) - (infinite) [valid now]
send lifetime (02:00:00 UTC May 8 2011) - (infinite) [valid now]

https://t.me/learningnets

CCNP Lab 018: EIGRP Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand EIGRP implementation and configuration in Cisco IOS routers. Additional technologies tested include authentication and default routing.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab. Also, if you are using the www.101labs.net racks, configure R3 as the Frame Relay switch using the following configuration commands:

hostname R3-Frame-Relay-Switch
!

https://t.me/learningnets

```
frame-relay switching
!
interface serial 1/0
description ‘Connected To R1 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 102 interface serial 1/1 201
frame-relay route 104 interface serial 1/2 401
no shutdown
!
interface serial 1/1
description ‘Connected To R2 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 201 interface serial 1/0 102
no shutdown
!
interface serial 1/2
description ‘Connected To R4 Serial 0/0’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 401 interface serial 1/0 104
no shutdown
!
end
```

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure EIGRP for AS 1 across the Frame Relay WAN as illustrated in the topology. Do NOT enable EIGRP for the point-to-point link between R1 and R2.

https://t.me/learningnets

Technet24

Task 3

Configure EIGRP for AS 2 over the LAN segment between R2 and R4 as illustrated in the topology. Do NOT enable EIGRP for the point-to-point link between R1 and R2.

Task 4

Advertise the 150.1.1.0/24 via EIGRP as an External EIGRP route. This route should be injected into EIGRP with a metric of 100,000 - 100 - 255 - 1 - 1500 and administrative route tag of 1111.

Additionally, advertise the 150.6.6.0/24 subnet via EIGRP 1. The route advertised by R2 should include the administrator tag 2222 and the route advertised by R4 should include the administrative tag 4444. Ensure that R1 prefers the path via R2 to reach this subnet. In the event that this path is unavailable, R1 should prefer the path via R4. In the event that the Frame Relay WAN is down, R1 should use the point-to-point link between R1 and R2. Verify your configuration using the appropriate commands.

Task 5

Configure EIGRP AS 2 so that the 150.6.6.0/24 subnet uses R2s Frame Relay connection to reach the 150.1.1.0/24 subnet. In the event that R2s Frame Relay connection is down, R4s Frame Relay connection should be used.

In the event that both R2 and R4 Frame Relay connections are down, then the point-to-point link between R1 and R2 should be used. You are NOT allowed to use offset lists or modify interface bandwidth values in your solution. Verify and test your configuration.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip address 10.0.1.1 255.255.255.252**
R1(config-if)#**no shutdown**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.1 255.255.255.0**

https://t.me/learningnets

R1(config-if)#**no shutdown**
R1(config-if)#**encapsulation frame-relay**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.6.6.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip address 10.0.1.2 255.255.255.252**
R2(config-if)#**no shutdown**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip address 10.0.0.2 255.255.255.0**
R2(config-if)#**no shutdown**
R2(config-if)#**encapsulation frame-relay**
R2(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.6.6.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.4 255.255.255.0**
R4(config-if)#**no shutdown**
R4(config-if)#**encapsulation frame-relay**
R4(config-if)#**exit**

Task 2

R1(config)#**router eigrp 1**
R1(config-router)#**no auto-summary**
R1(config-router)#**network 10.0.0.1 0.0.0.0**
R1(config-router)#**exit**

R2(config)#**router eigrp 1**
R2(config-router)#**no auto-summary**
R2(config-router)#**network 10.0.0.2 0.0.0.0**
R2(config-router)#**exit**

R4(config)#**router eigrp 1**

https://t.me/learningnets

Technet24

R4(config-router)#**no auto-summary**
R4(config-router)#**network 10.0.0.4 0.0.0.0**
R4(config-router)#**exit**

Verify your configuration using the **show ip eigrp neighbors** command:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.4 Se0/1 145 00:00:36 1561 5000 0 3
0 10.0.0.2 Se0/1 144 00:02:30 20 200 0 3

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.1 Se0/1 163 00:03:09 1240 5000 0 3

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.1 Se0/0 160 00:01:18 15 200 0 5

Task 3

R2(config)#**router eigrp 2**
R2(config-router)#**no auto-summary**
R2(config-router)#**network 150.6.6.2 0.0.0.0**
R2(config-router)#**exit**

R4(config)#**router eigrp 2**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 150.6.6.4 0.0.0.0**
R4(config-router)#**exit**

Verify your configuration using the **show ip eigrp neighbors** command:

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.1 Se0/1 152 00:06:09 1240 5000 0 3

IP-EIGRP neighbors for process 2

https://t.me/learningnets

H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.6.6.4 Fa0/0 14 00:00:48 3 200 0 3

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.1 Se0/0 171 00:03:57 15 200 0 5

IP-EIGRP neighbors for process 2
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.6.6.2 Fa0/0 14 00:00:29 5 200 0 3

Task 4

The first part of this task is completed by redistributing the 150.1.1.0/24 subnet into EIGRP using a route map to administrative tag. The metric can also be specified in the route map, or alternatively, you can specify the metric using the **redistribute** command. Either option is acceptable to complete this task:

R1(config)#**route-map CONNECTED permit 10**
R1(config-route-map)#**match interface fastethernet 0/0**
R1(config-route-map)#**set metric 100000 100 255 1 1500**
R1(config-route-map)#**set tag 1111**
R1(config-route-map)#**exit**
R1(config)#**route-map CONNECTED deny 20**
R1(config-route-map)#**exit**
R1(config)#**router eigrp 1**
R1(config-router)#**redistribute connected route-map CONNECTED**
R1(config-router)#**exit**

The second part of this task requires redistribution metric manipulation and floating static route configuration. The 150.6.6.0/24 subnet must be redistributed into EIGRP 1 with a better route metric on R2 than on R4. Next, a floating static route is required to ensure that if the Frame Relay WAN is down, R1 will send packets to the 150.6.6.0/24 subnet via the point-to-point link to R2. The floating static route is should be configured with an administrative distance greater than 170 (external EIGRP administrative distance) but less than 255 (discard route). This task is completed by specifying an administrative distance between 171 and 254:

R1(config)#**ip route 150.6.6.0 255.255.255.0 serial 0/0 200**

https://t.me/learningnets

Technet24

The redistribution section of this task is completed as follows:

R2(config)#**route-map CONNECTED permit 10**
R2(config-route-map)#**match interface fastethernet 0/0**
R2(config-route-map)#**set metric 100000 100 255 1 1500**
R2(config-route-map)#**set tag 2222**
R2(config-route-map)#**exit**
R2(config)#**route-map CONNECTED deny 20**
R2(config-route-map)#**exit**
R2(config)#**router eigrp 1**
R2(config-router)#**redistribute connected route-map CONNECTED**
R2(config-router)#**exit**

R4(config)#**route-map CONNECTED permit 10**
R4(config-route-map)#**match interface fastethernet 0/0**
R4(config-route-map)#**set metric 10000 1000 255 1 1500**
R4(config-route-map)#**set tag 4444**
R4(config-route-map)#**exit**
R4(config)#**route-map CONNECTED deny 20**
R4(config-route-map)#**exit**
R4(config)#**router eigrp 1**
R4(config-router)#**redistribute connected route-map CONNECTED**
R4(config-router)#**exit**

Verify your configuration by looking at the topology table on R1:

R1#**show ip eigrp topology 150.6.6.0 255.255.255.0**
IP-EIGRP (AS 1): Topology entry for 150.6.6.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 2195456
Routing Descriptor Blocks:
10.0.0.2 (Serial0/1), from 10.0.0.2, Send flag is 0x0
Composite metric is (2195456/51200), Route is External
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 21000 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1
External data:
Originating router is 150.6.6.2

https://t.me/learningnets

AS number of route is 0
External protocol is Connected, external metric is 0
Administrator tag is 2222 (0x000008AE)

10.0.0.4 (Serial0/1), from 10.0.0.4, Send flag is 0x0
Composite metric is (2425856/512000), Route is External
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 30000 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1
External data:
Originating router is 150.6.6.4
AS number of route is 0
External protocol is Connected, external metric is 0
Administrator tag is 4444 (0x0000115C)

Verify the floating static route configuration by shutting down the Frame Relay WAN:

R1(config)#**interface serial 0/1**
R1(config-if)#**shutdown**
R1(config-if)#**exit**
R1(config)#**do show ip route 150.6.6.0 255.255.255.0**
Routing entry for 150.6.6.0/24
Known via “static”, distance 200, metric 0 (connected)
Routing Descriptor Blocks:
* directly connected, via Serial0/0
Route metric is 0, traffic share count is 1

Task 5

The first requirement of this task is that the 150.1.1.0/24 subnet should be known within EIGRP AS 2. This requires that EIGRP 1 be redistributed into EIGRP 2 on R2 and R4:

R2(config)#**router eigrp 2**

R2(config-router)#**redistribute eigrp 1**

R2(config-router)#**exit**

R4(config)#**router eigrp 2**

R4(config-router)#**redistribute eigrp 1**

https://t.me/learningnets

Technet24

R4(config-router)#**exit**

The second requirement is completed by modifying the default interface delay values so that routes received via R4 are less preferable to those received via R2.

To influence path selection, increase the delay on R4s Frame Relay interface OR decrease the delay on R2s Frame Relay interface. Either solution is acceptable.

R2(config)#**int s 0/1**

R2(config-if)#**delay 100**

R2(config-if)#**exit**

Following this change, R2 and R4 show the following route entries for the 150.1.1.0/24 subnet:

R2#**show ip route 150.1.1.0 255.255.255.0**
Routing entry for 150.1.1.0/24
Known via "eigrp 1", distance 170, metric 1709056
Tag 1111, type external
Redistributing via eigrp 1, eigrp 2
Advertised by eigrp 2
Last update from 10.0.0.1 on Serial0/1, 00:00:42 ago
Routing Descriptor Blocks:
*** 10.0.0.1, from 10.0.0.1, 00:00:42 ago, via Serial0/1**
Route metric is 1709056, traffic share count is 1
Total delay is 2000 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1
Route tag 1111

R4#**show ip route 150.1.1.0 255.255.255.0**
Routing entry for 150.1.1.0/24
Known via "eigrp 2", distance 170, metric 1711616
Tag 1111, type external
Redistributing via eigrp 2
Last update from 150.6.6.2 on FastEthernet0/0, 00:01:04 ago
Routing Descriptor Blocks:
*** 150.6.6.2, from 150.6.6.2, 00:01:04 ago, via FastEthernet0/0**
Route metric is 1711616, traffic share count is 1
Total delay is 2100 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 2

https://t.me/learningnets

Route tag 1111

The third required requires a floating static route to be configured on R2 for the 150.1.1.0/24 subnet. This floating static will also need to be redistributed into EIGRP 2 so that R4 receives this route when the Frame Relay WAN in down. This task is completed as follows:

R2(config)#**ip route 150.1.1.0 255.255.255.0 serial 0/0 200 name R1-BACKUP**
R2(config)#**router eigrp 2**
R2(config-router)#**redistribute static metric 5000 5000 255 1 1500**
R2(config-router)#**exit**

Finally, verify that routing works as required. Shut down the Frame Relay WAN link on R2 and ensure that this router can still reach the 150.1.1.0/24 subnet and vice-versa across the Frame Relay network, i.e. via R4:

R2(config)#**int s0/1**
R2(config-if)#**shutdown**
R2(config-if)#**exit**
R2(config)#**do show ip route 150.1.1.0 255.255.255.0**
Routing entry for 150.1.1.0/24
Known via "eigrp 2", distance 170, metric 2198016
Tag 1111, type external
Redistributing via eigrp 2
Last update from 150.6.6.4 on FastEthernet0/0, 00:00:14 ago
Routing Descriptor Blocks:
*** 150.6.6.4, from 150.6.6.4, 00:00:14 ago, via FastEthernet0/0**
Route metric is 2198016, traffic share count is 1
Total delay is 21100 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 2
Route tag 1111

R2(config)#**do ping 150.1.1.1 source 150.6.6.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.6.6.2
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/31/32 ms

Next, shut down the Frame Relay WAN link on R4 and ensure that both R2 and R4 can still reach the 150.1.1.0/24 subnet and vice-versa:

https://t.me/learningnets

Technet24

R2(config)#**int s0/1**
R2(config-if)#**shutdown**
R2(config-if)#**exit**

R4(config)#**int s0/0**
R4(config-if)#**shutdown**
R4(config-if)#**exit**

R1#**show ip route 150.6.6.0 255.255.255.0**
Routing entry for 150.6.6.0/24
Known via "static", distance 200, metric 0 (connected)
Routing Descriptor Blocks:
* directly connected, via Serial0/0
Route metric is 0, traffic share count is 1

R2#**show ip route 150.1.1.0 255.255.255.0**
Routing entry for 150.1.1.0/24
Known via "static", distance 200, metric 0 (connected)
Redistributing via eigrp 2
Advertised by eigrp 2 metric 5000 5000 255 1 1500
Routing Descriptor Blocks:
* directly connected, via Serial0/0
Route metric is 0, traffic share count is 1

R4#**show ip route 150.1.1.0 255.255.255.0**
Routing entry for 150.1.1.0/24
Known via "eigrp 2", distance 170, metric 1794560, type external
Redistributing via eigrp 2
Last update from 150.6.6.2 on FastEthernet0/0, 00:00:47 ago
Routing Descriptor Blocks:
* 150.6.6.2, from 150.6.6.2, 00:00:47 ago, via FastEthernet0/0
Route metric is 1794560, traffic share count is 1
Total delay is 50100 microseconds, minimum bandwidth is 5000 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1

R1#**ping 150.6.6.0 source 150.1.1.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.6.6.0, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms

https://t.me/learningnets

R2#**ping 150.1.1.0 source 150.6.6.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.0, timeout is 2 seconds:
Packet sent with a source address of 150.6.6.2
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/3/4 ms

R4#**ping 150.1.1.0 source 150.6.6.4**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.0, timeout is 2 seconds:
Packet sent with a source address of 150.6.6.4
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/3/4 ms

https://t.me/learningnets

Technet24

CCNP Lab 019: EIGRP Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand EIGRP implementation and configuration in Cisco IOS routers. Additional technologies tested include split horizon and next-hop processing.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab. Also, if you are using the www.101labs.net racks, configure R3 as the Frame Relay switch using the following configuration commands:

hostname R3-Frame-Relay-Switch

https://t.me/learningnets

Technet24

```
!
frame-relay switching
!
interface serial 1/0
description ‘Connected To R1 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 102 interface serial 1/1 201
frame-relay route 104 interface serial 1/2 401
no shutdown
!
interface serial 1/1
description ‘Connected To R2 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 201 interface serial 1/0 102
no shutdown
!
interface serial 1/2
description ‘Connected To R4 Serial 0/0’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 401 interface serial 1/0 104
no shutdown
!
end
```

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure EIGRP for AS 1 as illustrated in the topology. Use a single ‘network’

https://t.me/learningnets

command to enable EIGRP for all interfaces. No EIGRP packets should be sent out of the LAN interfaces.

Task 3

Configure EIGRP so that routers R2 and R4 are able to ping each others' 150.x.x.x/24 subnets, as well as the 150.1.1.0/24 subnet connected to R1. Do NOT use default or static routing to do this.

Task 4

Additional spoke routers will be added to the Frame Relay network in the future. In order to easily identify which spoke router is advertising which 150.x.x.x subnet, configure EIGRP so that the next hop IP address for each 150.x.x.x is the WAN IP address of the router that advertised it instead of the IP address of the hub router (R1). For example, on R2, the next hop IP address of the 150.4.4.0/24 subnet should be 10.0.0.4.

Task 5

Configure the network so that spoke R2 and R4 routers can ping each others' 150.x.x.x/24 subnets. Test your configuration by pinging LAN-to-LAN between the spoke routers.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.1 255.255.255.0**
R1(config-if)#**no shutdown**
R1(config-if)#**encapsulation frame-relay**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**

https://t.me/learningnets

Technet24

R2(config-if)#**ip address 10.0.0.2 255.255.255.0**
R2(config-if)#**no shutdown**
R2(config-if)#**encapsulation frame-relay**
R2(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.4.4.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.4 255.255.255.0**
R4(config-if)#**no shutdown**
R4(config-if)#**encapsulation frame-relay**
R4(config-if)#**exit**

Task 2

R1(config)#**router eigrp 1**
R1(config-router)#**no auto-summary**
R1(config-router)#**passive-interface fastethernet 0/0**
R1(config-router)#**network 0.0.0.0 255.255.255.255**
R1(config-router)#**exit**

R2(config)#**router eigrp 1**
R2(config-router)#**no auto-summary**
R4(config-router)#**passive-interface fastethernet 0/0**
R2(config-router)#**network 0.0.0.0 255.255.255.255**
R2(config-router)#**exit**

R4(config)#**router eigrp 1**
R4(config-router)#**no auto-summary**
R4(config-router)#**passive-interface fastethernet 0/0**
R4(config-router)#**network 0.0.0.0 255.255.255.255**
R4(config-router)#**exit**

Verify your configuration using the **show ip eigrp neighbors** command:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
2 10.0.0.4 Se0/1 141 00:02:32 20 200 0 11

https://t.me/learningnets

0 10.0.0.2 Se0/1 159 00:03:02 23 200 0 3

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.1 Se0/1 138 00:03:06 1215 5000 0 12

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.1 Se0/0 147 00:02:26 20 200 0 12

Task 3

By default, EIGRP will not advertise routes out the same interface via which they were learned due to split horizon. Prior to any changes, the routing tables of all three routers are as follows:

R1#**show ip route eigrp**
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 10.0.0.2, 00:04:21, Serial0/1
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/2172416] via 10.0.0.4, 00:02:29, Serial0/1

R2#**show ip route eigrp**
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:04:58, Serial0/1

R4#**show ip route eigrp**
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:02:37, Serial0/0

To complete this task, split horizon should be disabled on the WAN interface on R1 (hub):

R1(config)#**interface serial 0/1**
R1(config-if)#**no ip split-horizon eigrp 1**
R1(config-if)#**exit**

Following this change, the routing tables on all three routers show the following:

R1#**show ip route eigrp**
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 10.0.0.2, 00:06:42, Serial0/1

https://t.me/learningnets

Technet24

150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/2172416] via 10.0.0.4, 00:04:50, Serial0/1

R2#**show ip route eigrp**
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:07:37, Serial0/1
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/2684416] via 10.0.0.1, 00:01:19, Serial0/1

R4#**show ip route eigrp**
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:05:38, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2684416] via 10.0.0.1, 00:01:43, Serial0/0

Verify connectivity between the LAN subnets using a simple ping:

R1#**ping 150.2.2.2 source 150.1.1.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

R1#**ping 150.4.4.4 source 150.1.1.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

R2#**ping 150.1.1.1 source 150.2.2.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/31/32 ms

R2#**ping 150.4.4.4 source 150.2.2.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!

https://t.me/learningnets

Success rate is 100 percent (5/5), round-trip min/avg/max = 56/58/60 ms

R4#**ping 150.1.1.1 source 150.4.4.4**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.2.2.2 source 150.4.4.4**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 56/70/120 ms

Task 4

EIGRP does not set the NEXT HOP field in EIGRP packets by default. Therefore, on a multi-access network, such as an NBMA or Ethernet network, a router receiving routes from an EIGRP router assumes that the next hop of these routes is the router sending the updates, even though it might actually be another router on the same subnet, as illustrated below:

R2#**show ip route 150.4.4.0 255.255.255.0**
Routing entry for 150.4.4.0/24
Known via "eigrp 1", distance 90, metric 2684416, type internal
Redistributing via eigrp 1
Last update from 10.0.0.1 on Serial0/1, 00:08:43 ago
Routing Descriptor Blocks:
*** 10.0.0.1, from 10.0.0.1, 00:08:43 ago, via Serial0/1**
Route metric is 2684416, traffic share count is 1
Total delay is 40100 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 2

R4#**show ip route 150.2.2.0 255.255.255.0**
Routing entry for 150.2.2.0/24
Known via "eigrp 1", distance 90, metric 2684416, type internal
Redistributing via eigrp 1
Last update from 10.0.0.1 on Serial0/0, 00:09:23 ago
Routing Descriptor Blocks:

https://t.me/learningnets

Technet24

*** 10.0.0.1, from 10.0.0.1, 00:09:23 ago, via Serial0/0**
Route metric is 2684416, traffic share count is 1
Total delay is 40100 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 2
The first part of this task is completed by using the **no ip next-hop-self eigrp <ASN>** command on the hub router interface. When this command is issued, R1 will begin to set the NEXT HOP field in outgoing routing updates only if the IP next hop in its EIGRP topology table belongs to the IP subnet of the outgoing interface. The NEXT HOP field is set in internal as well as external EIGRP routing updates, optimizing traffic flow in route redistribution scenarios.

R1(config)#**interface serial 0/1**
R1(config-if)#**no ip next-hop-self eigrp 1**
R1(config-if)#**exit**

Following this configuration, the routing tables for the spoke routers show the following:

R2#**show ip route 150.4.4.0 255.255.255.0**
Routing entry for 150.4.4.0/24
Known via "eigrp 1", distance 90, metric 2684416, type internal
Redistributing via eigrp 1
Last update from 10.0.0.4 on Serial0/1, 00:00:20 ago
Routing Descriptor Blocks:
*** 10.0.0.4, from 10.0.0.1, 00:00:20 ago, via Serial0/1**
Route metric is 2684416, traffic share count is 1
Total delay is 40100 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 2

R4#**show ip route 150.2.2.0 255.255.255.0**
Routing entry for 150.2.2.0/24
Known via "eigrp 1", distance 90, metric 2684416, type internal
Redistributing via eigrp 1
Last update from 10.0.0.2 on Serial0/0, 00:01:03 ago
Routing Descriptor Blocks:
*** 10.0.0.2, from 10.0.0.1, 00:01:03 ago, via Serial0/0**
Route metric is 2684416, traffic share count is 1
Total delay is 40100 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes

https://t.me/learningnets

Loading 1/255, Hops 2

Notice that the NEXT HOP has changed for each spoke LAN subnet and it reflects the interface address of the actual spoke router. However, because there is no direct Frame Relay PVC between the two spoke routers, you will not be able to ping between the LAN interfaces:

R4#**show frame-relay map**
Serial0/0 (up): ip 10.0.0.1 dlci 401(0x191,0x6410), dynamic,
broadcast,, status defined, active

R4#**ping 150.2.2.2 source 150.4.4.4**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
.....
Success rate is 0 percent (0/5)

Task 5

In the previous task, following the changing of the NEXT HOP, we observed that we were still unable to ping between the LAN routers. This task is required to allow this connectivity:

R2(config)#**interface serial 0/1**
R2(config-if)#**frame-relay map ip 10.0.0.1 201 broadcast**
R2(config-if)#**frame-relay map ip 10.0.0.4 201 broadcast**
R2(config-if)#**exit**
R2(config)#
R2(config)#**do show frame-relay map**
Serial0/1 (up): ip 10.0.0.1 dlci 201(0xC9,0x3090), static,
broadcast,
CISCO, status defined, active
Serial0/1 (up): ip 10.0.0.4 dlci 201(0xC9,0x3090), static,
broadcast,
CISCO, status defined, active

R4(config)#**interface serial 0/0**
R4(config-if)#**frame-relay map ip 10.0.0.1 401 broadcast**
R4(config-if)#**frame-relay map ip 10.0.0.2 401 broadcast**
R4(config-if)#**exit**
R4(config)#
R4(config)#**do show frame-relay map**

https://t.me/learningnets

Technet24

Serial0/0 (up): ip 10.0.0.1 dlci 401(0x191,0x6410), static,
broadcast,
CISCO, status defined, active
Serial0/0 (up): ip 10.0.0.2 dlci 401(0x191,0x6410), static,
broadcast,
CISCO, status defined, active

Following this configuration, the spokes are again able to ping LAN to LAN:

R4#**ping 150.2.2.2 source 150.4.4.4 repeat 10 size 1500 df-bit timeout 1**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.2.2.2, timeout is 1 seconds:
Packet sent with a source address of 150.4.4.4
Packet sent with the DF bit set
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 760/760/760 ms

It should be noted that simply creating the static Frame Relay map statement does not mean that an EIGRP neighbor relationship is established between the spokes. The spoke routing information will not change. In other words the NEXT HOP will still be the spoke router that originated the route, but the route will still be received from R1:

R4#**show ip route 150.2.2.0 255.255.255.0**
Routing entry for 150.2.2.0/24
Known via "eigrp 1", distance 90, metric 2684416, type internal
Redistributing via eigrp 1
Last update from 10.0.0.2 on Serial0/0, 00:24:56 ago
Routing Descriptor Blocks:
*** 10.0.0.2, from 10.0.0.1, 00:24:56 ago, via Serial0/0**
Route metric is 2684416, traffic share count is 1
Total delay is 40100 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 2

https://t.me/learningnets

CCNP Lab 020: EIGRP Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand EIGRP implementation and configuration in Cisco IOS routers. Additional technologies tested include path control and summarization.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure EIGRP AS 100 for the 150.1.1.0/24 subnet between R1 and R4. Configure

https://t.me/learningnets

EIGRP AS 200 as illustrated in the topology.

Task 3

Redistribute between EIGRP 100 and EIGRP 200. Use default metrics in your configuration. Verify that R1 has three paths to the 150.3.3.0/24 subnet.

Task 4

Without modifying interface bandwidth or delay values, configure routing and path control for EIGRP on R1 as shown below. Use the most simple configuration in your solution:

- R1 should first prefer the path via R4 (FastEthernet 0/0) to reach the 150.3.3.0/24 subnet
- If the path via R4 is down, R1 should prefer the path via R2 (Serial 0/0)
- If the path via R4 and via R2 is down, R1 should use the direct path to R3 (Serial 0/1)

Task 5

Without modifying interface bandwidth or delay values, configure routing and path control for EIGRP on R1 as shown below. Use the most simple configuration in your solution:

- R3 should first prefer the path via R4 (Serial 1/2) to reach the 150.1.1.0/24 subnet
- If the path via R4 is down, R3 should prefer the path via R2 (Serial 1/1)
- If the paths via R4 R2 are down, R3 should use the direct path to R1 (Serial 1/0)

Task 6

Configure routing on R3 so that all three paths are installed into the routing table; however, ONLY a single path - the path via R4 - should actually be used to forward packets destined to that subnet. The other two paths should not be used while this path is up. The path with the next-best route metric should then be used when the primary path is unavailable.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**

https://t.me/learningnets

Technet24

R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 150.3.3.3 255.255.255.0**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.6 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**no shutdown**

https://t.me/learningnets

R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.4.4.4 255.255.255.0**
R4(config-if)#**exit**
R3(config)#**interface serial 0/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.14 255.255.255.252**
R3(config-if)#**exit**

Task 2

R1(config)#**router eigrp 100**
R1(config-router)#**no auto-summary**
R1(config-router)#**network 150.1.1.1 0.0.0.0**
R1(config-router)#**exit**
R1(config)#**router eigrp 200**
R1(config-router)#**network 10.0.0.1 0.0.0.0**
R1(config-router)#**network 10.0.0.5 0.0.0.0**
R1(config-router)#**exit**

R2(config)#**router eigrp 200**
R2(config-router)#**no auto-summary**
R2(config-router)#**network 10.0.0.2 0.0.0.0**
R2(config-router)#**network 10.0.0.9 0.0.0.0**
R2(config-router)#**exit**

R3(config)#**router eigrp 200**
R3(config-router)#**no auto-summary**
R3(config-router)#**network 150.3.3.3 0.0.0.0**
R3(config-router)#**network 10.0.0.6 0.0.0.0**
R3(config-router)#**network 10.0.0.10 0.0.0.0**
R3(config-router)#**network 10.0.0.13 0.0.0.0**
R3(config-router)#**exit**

R4(config)#**router eigrp 100**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 150.1.1.4 0.0.0.0**
R4(config-router)#**exit**

https://t.me/learningnets

Technet24

R4(config)#**router eigrp 200**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 10.0.0.14 0.0.0.0**
R4(config-router)#**exit**

Verify your configuration using the **show ip eigrp neighbors** command:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 100
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.1.1.4 Fa0/0 11 00:09:19 5 200 0 3

IP-EIGRP neighbors for process 200
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.6 Se0/1 13 00:05:52 10 200 0 13
0 10.0.0.2 Se0/0 12 00:07:13 2 200 0 11

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 200
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.10 Se0/1 11 00:05:49 10 200 0 14
0 10.0.0.1 Se0/0 11 00:07:18 1 200 0 11

R3#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 200
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
2 10.0.0.14 Se1/2 11 00:01:46 14 1140 0 3
1 10.0.0.9 Se1/1 11 00:05:53 10 1140 0 12
0 10.0.0.5 Se1/0 11 00:06:00 9 1140 0 12

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 100
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.1.1.1 Fa0/0 14 00:09:32 4 200 0 3

IP-EIGRP neighbors for process 200
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.13 Se0/0 13 00:01:50 14 200 0 17

https://t.me/learningnets

Task 3

R1(config)#**router eigrp 100**
R1(config-router)#**redistribute eigrp 200**
R1(config-router)#**exit**
R1(config)#**router eigrp 200**
R1(config-router)#**redistribute eigrp 100**
R1(config-router)#**exit**

R4(config)#**router eigrp 100**
R4(config-router)#**redistribute eigrp 200**
R4(config-router)#**exit**
R4(config)#**router eigrp 200**
R4(config-router)#**redistribute eigrp 100**
R4(config-router)#**exit**

Verify that R1 has three routes to 150.3.3.0/24 by looking at the EIGRP topology table:

R1#**show ip eigrp topology 150.3.3.0 255.255.255.0**
IP-EIGRP (AS 100): Topology entry for 150.3.3.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 2172416
Routing Descriptor Blocks:
10.0.0.6, from Redistributed, Send flag is 0x0
Composite metric is (2172416/0), Route is External
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 20100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1
External data:
Originating router is 150.1.1.1 (this system)
AS number of route is 200
External protocol is EIGRP, external metric is 2172416
Administrator tag is 0 (0x00000000)
150.1.1.4 (FastEthernet0/0), from 150.1.1.4, Send flag is 0x0
Composite metric is (2174976/2172416), Route is External
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 20200 microseconds

https://t.me/learningnets
Technet24

Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 2
External data:
Originating router is 150.1.1.4
AS number of route is 200
External protocol is EIGRP, external metric is 2172416
Administrator tag is 0 (0x00000000)
IP-EIGRP (AS 200): Topology entry for 150.3.3.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 2172416
Routing Descriptor Blocks:
10.0.0.6 (Serial0/1), from 10.0.0.6, Send flag is 0x0
Composite metric is (2172416/28160), Route is Internal
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 20100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1
10.0.0.2 (Serial0/0), from 10.0.0.2, Send flag is 0x0
Composite metric is (2684416/2172416), Route is Internal
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 40100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 2

Task 4

This task requires a little thought. First, the path via R4 is external, which means that this route has a higher administrative distance than the paths via R2 and directly to R3 and is therefore less preferred. The first task is therefore to ‘level the playing field’ by adjusting the default administrative distance values. In this case, the better administrative distance values, i.e. those for EIGRP AS 200 should be modified so that they are numerically higher than those of EIGRP for AS 100. Before any changes are made, R1s routing table shows the following entry:

https://t.me/learningnets

R1#**show ip route 150.3.3.0 255.255.255.0**
Routing entry for 150.3.3.0/24
Known via "eigrp 200", distance 90, metric 2172416, type internal
Redistributing via eigrp 100, eigrp 200
Advertised by eigrp 100
Last update from 10.0.0.6 on Serial0/1, 00:02:33 ago
Routing Descriptor Blocks:
*** 10.0.0.6, from 10.0.0.6, 00:02:33 ago, via Serial0/1**
Route metric is 2172416, traffic share count is 1
Total delay is 20100 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1

The first part of this task is completed by increasing the administrative distance of EIGRP 200. Use any acceptable values between 171 and 254 to complete this task.

R1(config)#**router eigrp 200**
R1(config-router)#**distance eigrp 180 200**
R1(config-router)#**exit**
Following this change, verify your configuration using the **show ip route** command:

R1#**show ip route 150.3.3.0 255.255.255.0**
Routing entry for 150.3.3.0/24
Known via "eigrp 100", distance 170, metric 2174976, type external
Redistributing via eigrp 100, eigrp 200
Advertised by eigrp 200
Last update from 150.1.1.4 on FastEthernet0/0, 00:01:29 ago
Routing Descriptor Blocks:
*** 150.1.1.4, from 150.1.1.4, 00:01:29 ago, via FastEthernet0/0**
Route metric is 2174976, traffic share count is 1
Total delay is 20200 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 2

NOTE: There is no need to configure a filter for EIGRP 200 on R1 so that it doesn't re-advertise this route back to R3 because even if it does, the route will not meet the Feasibility Condition on R3 and will never be considered a feasible successor. The Feasibility Condition is met when the Reported or Advertised Distance (RD or AD) is less than the Feasible Distance (FD). This can be verified by looking at the entry for the 150.3.3.0/24 subnet in R3s topology table:

R3#**show ip eigrp 200 topology 150.3.3.0 255.255.255.0**

https://t.me/learningnets

IP-EIGRP (AS 200): Topology entry for 150.3.3.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 28160
Routing Descriptor Blocks:
0.0.0.0 (FastEthernet0/0), from Connected, Send flag is 0x0
Composite metric is (28160/0), Route is Internal
Vector metric:
Minimum bandwidth is 100000 Kbit
Total delay is 100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 0
10.0.0.5 (Serial1/0), from 10.0.0.5, Send flag is 0x0
Composite metric is (21029120/2174976), Route is External
Vector metric:
Minimum bandwidth is 128 Kbit
Total delay is 40200 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 3
External data:
Originating router is 150.1.1.1
AS number of route is 100
External protocol is EIGRP, external metric is 2174976
Administrator tag is 0 (0x00000000)

The second part of this task requires the use of an inbound offset list to ensure that the path via R2 is preferred over the path via R3. Prior to any changes the topology table on R1 shows:

R1#**show ip eigrp 200 topology 150.3.3.0 255.255.255.0**
IP-EIGRP (AS 200): Topology entry for 150.3.3.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 2174976
Routing Descriptor Blocks:
150.1.1.4, from Redistributed, Send flag is 0x0
Composite metric is (2174976/0), Route is External
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 20200 microseconds

https://t.me/learningnets

Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 2
External data:
Originating router is 150.1.1.1 (this system)
AS number of route is 100
External protocol is EIGRP, external metric is 2174976
Administrator tag is 0 (0x00000000)
10.0.0.6 (Serial0/1), from 10.0.0.6, Send flag is 0x0
Composite metric is (2172416/28160), Route is Internal
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 20100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1
10.0.0.2 (Serial0/0), from 10.0.0.2, Send flag is 0x0
Composite metric is (2684416/2172416), Route is Internal
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 40100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 2

This task is completed by modifying the metric using an offset list for Serial 0/1. Use any acceptable value to complete this task:

R1(config)#**router eigrp 200**
R1(config-router)#**offset-list 0 in 1234567890 serial 0/1**
R1(config-router)#**exit**

Following the offset list configuration, the topology table on R1 shows the following:

R1#**show ip eigrp 200 topology 150.3.3.0 255.255.255.0**
IP-EIGRP (AS 200): Topology entry for 150.3.3.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 2174976
Routing Descriptor Blocks:

https://t.me/learningnets
Technet24

150.1.1.4, from Redistributed, Send flag is 0x0
Composite metric is (2174976/0), Route is External
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 20200 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 2
External data:
Originating router is 150.1.1.1 (this system)
AS number of route is 100
External protocol is EIGRP, external metric is 2174976
Administrator tag is 0 (0x00000000)
10.0.0.2 (Serial0/0), from 10.0.0.2, Send flag is 0x0
Composite metric is (2684416/2172416), Route is Internal
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 40100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 2
10.0.0.6 (Serial0/1), from 10.0.0.6, Send flag is 0x0
Composite metric is (1236740306/1234596050), Route is Internal
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 48245408 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1

Task 5

To complete this task, you only need to configure a single offset-list. By default, the paths via R4 and R1 are equal cost. The only thing that needs to be done is that the path via R1 is assigned a worse metric than that via R2. This automatically makes it the least preferred path, completing the requirements stipulated in the task. Prior to any changes, the R3 topology table shows:

https://t.me/learningnets

R3#**show ip eigrp 200 topology 150.1.1.0 255.255.255.0**
IP-EIGRP (AS 200): Topology entry for 150.1.1.0/24
State is Passive, Query origin flag is 1, 2 Successor(s), FD is 20258560
Routing Descriptor Blocks:
10.0.0.5 (Serial1/0), from 10.0.0.5, Send flag is 0x0
Composite metric is (20514560/28160), Route is External
Vector metric:
Minimum bandwidth is 128 Kbit
Total delay is 20100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1
External data:
Originating router is 150.1.1.1
AS number of route is 100
External protocol is EIGRP, external metric is 0
Administrator tag is 0 (0x00000000)
10.0.0.14 (Serial1/2), from 10.0.0.14, Send flag is 0x0
Composite metric is (20514560/28160), Route is External
Vector metric:
Minimum bandwidth is 128 Kbit
Total delay is 20100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1
External data:
Originating router is 150.1.1.4
AS number of route is 100
External protocol is EIGRP, external metric is 0

https://t.me/learningnets
Technet24

Administrator tag is 0 (0x00000000)

10.0.0.9 (Serial1/1), from 10.0.0.9, Send flag is 0x0

Composite metric is (20770560/2172416), Route is External

Vector metric:

Minimum bandwidth is 128 Kbit

Total delay is 30100 microseconds

Reliability is 255/255

Load is 1/255

Minimum MTU is 1500

Hop count is 2

External data:

Originating router is 150.1.1.1

AS number of route is 100

External protocol is EIGRP, external metric is 0

Administrator tag is 0 (0x00000000)

This task is completed by off-setting the metric routes received via the current best path. Use any acceptable value to complete this task.

R3(config)#**router eigrp 200**

R3(config-router)# **offset-list 0 in 300000 serial 1/0**

R3(config-router)#**exit**

Following this change, the topology table on R3 shows the following:

R3#**show ip eigrp 200 topology 150.1.1.0 255.255.255.0**

IP-EIGRP (AS 200): Topology entry for 150.1.1.0/24

State is Passive, Query origin flag is 1, 1 Successor(s), FD is 20258560

Routing Descriptor Blocks:

10.0.0.14 (Serial1/2), from 10.0.0.14, Send flag is 0x0

Composite metric is (20514560/28160), Route is External

Vector metric:

Minimum bandwidth is 128 Kbit

Total delay is 20100 microseconds

Reliability is 255/255

https://t.me/learningnets

Load is 1/255
Minimum MTU is 1500
Hop count is 1
External data:
Originating router is 150.1.1.4
AS number of route is 100
External protocol is EIGRP, external metric is 0
Administrator tag is 0 (0x00000000)
10.0.0.9 (Serial1/1), from 10.0.0.9, Send flag is 0x0
Composite metric is (20770560/2172416), Route is External
Vector metric:
Minimum bandwidth is 128 Kbit
Total delay is 30100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 2
External data:
Originating router is 150.1.1.1
AS number of route is 100
External protocol is EIGRP, external metric is 0
Administrator tag is 0 (0x00000000)
10.0.0.5 (Serial1/0), from 10.0.0.5, Send flag is 0x0
Composite metric is (20814560/328160), Route is External
Vector metric:
Minimum bandwidth is 128 Kbit
Total delay is 31818 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1

https://t.me/learningnets
Technet24

External data:

Originating router is 150.1.1.1

AS number of route is 100

External protocol is EIGRP, external metric is 0

Administrator tag is 0 (0x00000000)

Task 6

The requirements for this task are two-fold. First, to install more than one path into the routing table, when multiple paths with multiple metrics exist, you need to configure unequal-cost load-sharing for EIGRP using the **variance <multiplier>** command.

To complete the second part of this task, it is important to remember that, by default, when the unequal-cost load sharing feature is enabled, all paths installed into the routing table will be used to forward packets. To prevent this default behavior, , the **traffic-share min across-interfaces** command is required under the EIGRP configuration. The requirements in this task are completed as follows:

R3(config)#**router eigrp 200**
R3(config-router)#**variance 2**
R3(config-router)#**traffic-share min across-interfaces**
R3(config-router)#**exit**

Following this configuration, the RIB on R3 shows the following for the 150.1.1.0/24 subnet:

R3#**show ip route 150.1.1.1 255.255.255.0**

Routing entry for 150.1.1.0/24

Known via “eigrp 200”, distance 170, metric 20514560, type external

Redistributing via eigrp 200

Last update from 10.0.0.5 on Serial1/0, 00:00:18 ago

Routing Descriptor Blocks:

*** 10.0.0.14, from 10.0.0.14, 00:00:18 ago, via Serial1/2**

Route metric is 20514560, traffic share count is 1

Total delay is 20100 microseconds, minimum bandwidth is 128 Kbit

Reliability 255/255, minimum MTU 1500 bytes

Loading 1/255, Hops 1

10.0.0.9, from 10.0.0.9, 00:00:18 ago, via Serial1/1

Route metric is 20770560, traffic share count is 0

https://t.me/learningnets

Total delay is 30100 microseconds, minimum bandwidth is 128 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 2
10.0.0.5, from 10.0.0.5, 00:00:18 ago, via Serial1/0
Route metric is 20814560, traffic share count is 0
Total delay is 31818 microseconds, minimum bandwidth is 128 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1

https://t.me/learningnets

CCNP Lab 021: EIGRP Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand EIGRP implementation and configuration in Cisco IOS routers. Additional technologies tested include path control, summarization and optimization.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure EIGRP for AS 100 as illustrated in the topology. Ensure that the 150.1.1.0/24 subnet is advertised as an external EIGRP route with a route tag of 111 from R1 and 444 from R4. Verify your configuration using the appropriate commands.

https://t.me/learningnets

Technet24

Ensure that neither R1 nor R4 has a duplicate entry for this subnet in the EIGRP topology table. You are NOT allowed to use IP ACLs or IP prefix lists to implement this solution. Verify your configuration using the appropriate commands.

Task 3

Configure the 10.5.0.0/24, 10.5.1.0/24, 10.5.2.0/24, and 10.5.3.0/24 secondary subnets on the LAN segment between R1 and R4. Use the .1 address for R1 and the .4 address for R4. These should be advertised via EIGRP as internal EIGRP routes.

Task 4

Configure EIGRP on routers R1 and R4 to advertise a single summary route for the 10.5.0.0/24, 10.5.1.0/24, 10.5.2.0/24, and 10.5.3.0/24 secondary subnets. Verify this on R2 and R3.

Task 5

Without removing the summary configuration on routers R1 and R4, adding any static routes, or using PBR; configure your network so that R2 and R3 prefer the path via R1 to reach the 10.5.0.0/24 subnet; and the path via R4 to reach the 10.5.3.0/24 subnet. As a hint, use an EIGRP feature to complete this task. Verify your configuration using the appropriate commands.

Task 6

Management has advised that within the next year, the EIGRP network will scale to at least 200 routers and switches. These routers will be comprised of Cisco 2900 series routers running IOS Software 15.3. The switches will be Cisco Catalyst 6500 series switches, ranging from Catalyst 6504 through Catalyst 6513 switches. These will all be Multilayer switches. The future network will run both IPv4 and IPv6. Configure the current EIGRP implementation to support the future EIGRP network. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**

https://t.me/learningnets

R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface serial 1/1**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.4.4.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**exit**

Task 2

R1(config)#**route-map CONNECTED permit 10**
R1(config-route-map)#**match interface fastethernet 0/0**
R1(config-route-map)#**set tag 111**
R1(config-route-map)#**exit**
R1(config)#**router eigrp 100**

https://t.me/learningnets

R1(config-router)#**network 10.0.0.1 0.0.0.0**
R1(config-router)#**no auto-summary**
R1(config-router)#**redistribute connected route-map CONNECTED**
R1(config-router)#**exit**

R2(config)#**router eigrp 100**
R2(config-router)#**no auto-summary**
R2(config-router)#**network 10.0.0.2 0.0.0.0**
R2(config-router)#**network 10.0.0.9 0.0.0.0**
R2(config-router)#**exit**

R3(config)#**router eigrp 100**
R3(config-router)#**no auto-summary**
R3(config-router)#**network 10.0.0.10 0.0.0.0**
R3(config-router)#**network 10.0.0.13 0.0.0.0**
R3(config-router)#**exit**

R4(config)#**route-map CONNECTED permit 10**
R4(config-route-map)#**match interface fastethernet 0/0**
R4(config-route-map)#**set tag 444**
R4(config-route-map)#**exit**
R4(config)#**route-map CONNECTED deny 20**
R4(config-route-map)#**exit**
R4(config)#**router eigrp 100**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 10.0.0.14 0.0.0.0**
R4(config-router)#**redistribute connected route-map CONNECTED**
R4(config-router)#**exit**

Verify your base EIGRP configuration by verifying EIGRP neighbor relationships:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 100
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.2 Se0/0 12 00:03:53 6 200 0 10

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 100
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.10 Se0/1 14 00:03:18 10 200 0 10
0 10.0.0.1 Se0/0 11 00:03:59 3 200 0 3

https://t.me/learningnets

R3#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 100
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.14 Se1/2 13 00:01:27 12 1140 0 5
0 10.0.0.9 Se1/1 10 00:03:21 10 1140 0 9

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 100
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.13 Se0/0 11 00:01:31 12 200 0 9

After configuring redistribution, the EIGRP topology tables on the routers show the following:

R1#**show ip eigrp topology 150.1.1.0 255.255.255.0**
IP-EIGRP (AS 100): Topology entry for 150.1.1.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 28160
Routing Descriptor Blocks:
0.0.0.0, from Rconnected, Send flag is 0x0
Composite metric is (28160/0), Route is External
Vector metric:
Minimum bandwidth is 100000 Kbit
Total delay is 100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 0
External data:
Originating router is 150.1.1.1 (this system)
AS number of route is 0
External protocol is Connected, external metric is 0
Administrator tag is 111 (0x0000006F)

R4#**show ip eigrp topology 150.1.1.0 255.255.255.0**
IP-EIGRP (AS 100): Topology entry for 150.1.1.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 28160
Routing Descriptor Blocks:
0.0.0.0, from Rconnected, Send flag is 0x0
Composite metric is (28160/0), Route is External

https://t.me/learningnets
Technet24

Vector metric:
Minimum bandwidth is 100000 Kbit
Total delay is 100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 0
External data:
Originating router is 150.1.1.4 (this system)
AS number of route is 0
External protocol is Connected, external metric is 0
Administrator tag is 444 (0x000001BC)
10.0.0.13 (Serial0/0), from 10.0.0.13, Send flag is 0x0
Composite metric is (21538560/21026560), Route is External
Vector metric:
Minimum bandwidth is 128 Kbit
Total delay is 60100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 3
External data:
Originating router is 150.1.1.1
AS number of route is 0
External protocol is Connected, external metric is 0
Administrator tag is 111 (0x0000006F)

In the output above, we can see that R4 has a duplicate entry for the 150.1.1.0/24 subnet. This is the entry received from R1 with an administrative route tag of 111. To prevent either router from receiving or accepting the other routers' advertisement, a distribute-list used with a route map is required. The route map should perform filtering based on route tags:

R1(config)#**route-map NOT-TAG-444 deny 10**
R1(config-route-map)#**match tag 444**
R1(config-route-map)#**exit**
R1(config)#**route-map NO-TAG-444 permit 20**
R1(config-route-map)#**exit**
R1(config)#**router eigrp 100**
R1(config-router)#**distribute-list route-map NO-TAG-444 in**

https://t.me/learningnets

R1(config-router)#**exit**

R4(config)#**route-map NO-TAG-111 deny 10**
R4(config-route-map)#**match tag 111**
R4(config-route-map)#**exit**
R4(config)#**route-map NO-TAG-111 permit 20**
R4(config-route-map)#**exit**
R4(config)#**router eigrp 100**
R4(config-router)#**distribute-list route-map NO-TAG-111 in**
R4(config-router)#**exit**

Following this configuration, the topology tables on R1 and R4 show the following:

R1#**show ip eigrp topology 150.1.1.0 255.255.255.0**
IP-EIGRP (AS 100): Topology entry for 150.1.1.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 28160
Routing Descriptor Blocks:
0.0.0.0, from Rconnected, Send flag is 0x0
Composite metric is (28160/0), Route is External
Vector metric:
Minimum bandwidth is 100000 Kbit
Total delay is 100 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 0
External data:
Originating router is 150.1.1.1 (this system)
AS number of route is 0
External protocol is Connected, external metric is 0
Administrator tag is 111 (0x0000006F)

R4#**show ip eigrp topology 150.1.1.0 255.255.255.0**
IP-EIGRP (AS 100): Topology entry for 150.1.1.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 28160
Routing Descriptor Blocks:
0.0.0.0, from Rconnected, Send flag is 0x0
Composite metric is (28160/0), Route is External
Vector metric:
Minimum bandwidth is 100000 Kbit
Total delay is 100 microseconds

https://t.me/learningnets

Technet24

Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 0
External data:
Originating router is 150.1.1.4 (this system)
AS number of route is 0
External protocol is Connected, external metric is 0
Administrator tag is 444 (0x000001BC)

Task 3

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip address 10.5.0.1 255.255.255.0 secondary**
R1(config-if)#**ip address 10.5.1.1 255.255.255.0 secondary**
R1(config-if)#**ip address 10.5.2.1 255.255.255.0 secondary**
R1(config-if)#**ip address 10.5.3.1 255.255.255.0 secondary**
R1(config-if)#**exit**
R1(config)#**router eigrp 100**
R1(config-router)#**network 10.5.0.0 0.0.3.255**
R1(config-router)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip address 10.5.0.4 255.255.255.0 secondary**
R4(config-if)#**ip address 10.5.1.4 255.255.255.0 secondary**
R4(config-if)#**ip address 10.5.2.4 255.255.255.0 secondary**
R4(config-if)#**ip address 10.5.3.4 255.255.255.0 secondary**
R4(config-if)#**exit**
R4(config)#**router eigrp 100**
R4(config-router)#**network 10.5.0.0 0.0.3.255**
R4(config-router)#**exit**

Verify that the prefixes are advertised to R2 and R3 using the **show ip route** command:

R2#**show ip route eigrp**
10.0.0.0/8 is variably subnetted, 7 subnets, 2 masks
D 10.0.0.12/30 [90/2684416] via 10.0.0.1, 00:02:30, Serial0/0
D 10.5.3.0/24 [90/2172416] via 10.0.0.1, 00:02:32, Serial0/0
D 10.5.2.0/24 [90/2172416] via 10.0.0.1, 00:02:32, Serial0/0
D 10.5.1.0/24 [90/2172416] via 10.0.0.1, 00:02:32, Serial0/0
D 10.5.0.0/24 [90/2172416] via 10.0.0.1, 00:02:32, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets

https://t.me/learningnets

D EX 150.1.1.0 [170/2172416] via 10.0.0.1, 00:21:51, Serial0/0

R3#**show ip route eigrp**
10.0.0.0/8 is variably subnetted, 7 subnets, 2 masks
D 10.0.0.0/30 [90/21024000] via 10.0.0.9, 00:24:19, Serial1/1
D 10.5.3.0/24 [90/20514560] via 10.0.0.14, 00:02:51, Serial1/2
D 10.5.2.0/24 [90/20514560] via 10.0.0.14, 00:02:51, Serial1/2
D 10.5.1.0/24 [90/20514560] via 10.0.0.14, 00:02:51, Serial1/2
D 10.5.0.0/24 [90/20514560] via 10.0.0.14, 00:02:51, Serial1/2
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/20514560] via 10.0.0.14, 00:22:10, Serial1/2

Task 4

R1(config)#**interface serial 0/0**
R1(config-if)#**ip summary-address eigrp 100 10.5.0.0 255.255.252.0**
R1(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**ip summary-address eigrp 100 10.5.0.0 255.255.252.0**
R4(config-if)#**exit**

Verify that the summaries are advertised to R2 and R3 using the **show ip route** command:

R2#**show ip route eigrp**
10.0.0.0/8 is variably subnetted, 4 subnets, 2 masks
D 10.0.0.12/30 [90/2684416] via 10.0.0.1, 00:05:10, Serial0/0
D 10.5.0.0/22 [90/2172416] via 10.0.0.1, 00:00:48, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/2172416] via 10.0.0.1, 00:24:31, Serial0/0

R3#**show ip route eigrp**
10.0.0.0/8 is variably subnetted, 4 subnets, 2 masks
D 10.0.0.0/30 [90/21024000] via 10.0.0.9, 00:27:12, Serial1/1
D 10.5.0.0/22 [90/20514560] via 10.0.0.14, 00:01:20, Serial1/2
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/20514560] via 10.0.0.14, 00:25:03, Serial1/2

Task 5

EIGRP supports route leaking when summarizing, which allows for greater flexibility as far as path control is concerned. When summarizing, EIGRP allows you to ‘leak’ or advertise more specific routes encompassed by that summary, ensuring that traffic destined to the leaked subnet is sent to the router that leaked the route by virtue of the

https://t.me/learningnets
Technet24

longest-match rule. This task is completed on R1 and R4 as follows:

R1(config)#**access-list 1 permit 10.5.0.0 0.0.0.255**
R1(config)#**route-map LEAK permit 10**
R1(config-route-map)#**match ip address 1**
R1(config-route-map)#**exit**
R1(config)#**route-map LEAK deny 20**
R1(config-route-map)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip summary-a eigrp 100 10.5.0.0 255.255.252.0 leak-map LEAK**
R1(config-if)#exit

R4(config)#**access-list 4 permit 10.5.3.0 0.0.0.255**

R4(config)#**route-map LEAK permit 10**

R4(config-route-map)#**match ip address 4**

R4(config-route-map)#**exit**

R4(config)#**route-map LEAK deny 20**

R4(config-route-map)#**exit**

R4(config)#**interface serial 0/0**

R4(config-if)#**ip summary- eigrp 100 10.5.0.0 255.255.252.0 leak-map LEAK**

R4(config-if)#**exit**

Following this configuration, the routing tables on R2 and R3 show the following entries:

R2#**show ip route eigrp**
10.0.0.0/8 is variably subnetted, 6 subnets, 3 masks
D 10.0.0.12/30 [90/2684416] via 10.0.0.1, 00:17:43, Serial0/0
D 10.5.3.0/24 [90/21026560] via 10.0.0.10, 00:01:12, Serial0/1
D 10.5.0.0/24 [90/2172416] via 10.0.0.1, 00:04:02, Serial0/0
D 10.5.0.0/22 [90/2172416] via 10.0.0.1, 00:13:21, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/2172416] via 10.0.0.1, 00:37:04, Serial0/0

R3#**show ip route eigrp**
10.0.0.0/8 is variably subnetted, 6 subnets, 3 masks
D 10.0.0.0/30 [90/21024000] via 10.0.0.9, 00:39:19, Serial1/1
D 10.5.3.0/24 [90/20514560] via 10.0.0.14, 00:01:18, Serial1/2
D 10.5.0.0/24 [90/21026560] via 10.0.0.9, 00:04:08, Serial1/1
D 10.5.0.0/22 [90/20514560] via 10.0.0.14, 00:13:27, Serial1/2

https://t.me/learningnets

150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/20514560] via 10.0.0.14, 00:37:10, Serial1/2

When using route leaking (leak maps) in conjunction with EIGRP manual summarization, it is important to ensure that you remember the following considerations:

If the **leak-map** keyword is configured to reference a nonexistent route map, the configuration of this keyword has no effect. In other words, the configured summary will still be advertised, based on the stipulated rules of advertisement, and the component routes remain suppressed.

However, if the **leak-map** keyword is configured, but the access list does not exist or the route map does not reference the access list, the summary address and all component routes are sent.

Task 6

This task is straightforward. If you ignore the 'fluff' and pay attention to detail you will see that the task simply calls for increasing the default EIGRP hop count limitation of 100 to 200 to accommodate devices in the new network. The default hop count is printed in the output of the **show ip protocols** command:

R1#**show ip protocols**
Routing Protocol is "eigrp 100"
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is (route-map) NO-TAG-444
Default networks flagged in outgoing updates
Default networks accepted from incoming updates
EIGRP metric weight K1=1, K2=0, K3=1, K4=0, K5=0
EIGRP maximum hopcount 100
EIGRP maximum metric variance 1
Redistributing: connected, eigrp 100
EIGRP NSF-aware route hold timer is 240s
Automatic network summarization is not in effect
Address Summarization:
10.5.0.0/22 for Serial0/0
Summarizing with metric 28160
Maximum path: 4
Routing for Networks:
10.0.0.1/32
10.5.0.0/22
Routing Information Sources:
Gateway Distance Last Update

https://t.me/learningnets
Technet24

(this router) 90 00:22:13
10.0.0.2 90 00:09:33
150.1.1.4 90 00:21:41
Distance: internal 90 external 170

This task is completed by configuring a hop count limit of 200 or greater on ALL routers:

R1(config)#**router eigrp 100**
R1(config-router)#**metric maximum-hops 200**
R1(config-router)#**exit**

R2(config)#**router eigrp 100**
R2(config-router)#**metric maximum-hops 200**
R2(config-router)#**exit**

R3(config)#**router eigrp 100**
R3(config-router)#**metric maximum-hops 200**
R3(config-router)#**exit**

R4(config)#**router eigrp 100**
R4(config-router)#**metric maximum-hops 200**
R4(config-router)#**exit**

Following this change, the **show ip protocols** command reflects the configuration:

R1#**show ip protocols**
Routing Protocol is "eigrp 100"
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is (route-map) NO-TAG-444
Default networks flagged in outgoing updates
Default networks accepted from incoming updates
EIGRP metric weight K1=1, K2=0, K3=1, K4=0, K5=0
EIGRP maximum hopcount 200
EIGRP maximum metric variance 1
Redistributing: connected, eigrp 100
EIGRP NSF-aware route hold timer is 240s
Automatic network summarization is not in effect
Address Summarization:
10.5.0.0/22 for Serial0/0
Summarizing with metric 28160
Maximum path: 4
Routing for Networks:
10.0.0.1/32

https://t.me/learningnets

10.5.0.0/22
Routing Information Sources:
Gateway Distance Last Update
(this router) 90 00:01:20
10.0.0.2 90 00:00:24
150.1.1.4 90 00:00:24
Distance: internal 90 external 170

https://t.me/learningnets

Technet24

CCNP Lab 022: EIGRP Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand EIGRP implementation and configuration in Cisco IOS routers. Additional technologies tested include authentication and default routing.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab. Also, if you are using the www.101labs.net racks, configure R3 as the Frame Relay switch using the following configuration commands:

hostname R3-Frame-Relay-Switch
!
frame-relay switching

https://t.me/learningnets

Technet24

```
!
interface serial 1/0
description ‘Connected To R1 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 102 interface serial 1/1 201
frame-relay route 104 interface serial 1/2 401
no shutdown
!
interface serial 1/1
description ‘Connected To R2 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 201 interface serial 1/0 102
no shutdown
!
interface serial 1/2
description ‘Connected To R4 Serial 0/0’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 401 interface serial 1/0 104
no shutdown
!
end
```

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

The Frame Relay Service Provider has stated that they do not support Multicast traffic across the Frame Relay network. Configure EIGRP for AS 1 to use Unicast instead of Multicast to adhere to the Frame Relay Service Provider requirements. Verify your

https://t.me/learningnets

EIGRP configuration.

Task 3

Redistribute the 150.x.x.x/24 subnets into EIGRP on all routers. These subnets should be redistributed using the following values: 100 000 - 100 - 255 - 1 - 1500.

In the future, if any other connected routes are redistributed into EIGRP, they should be injected using the following values: 50 000 - 1250 - 255 - 1 - 1500.

Finally, ensure and verify that all routers can ping each others' 150.x.x.x/24 subnets.

Task 4

Configure EIGRP so that no more than 5 % of the WAN link bandwidth may be used by EIGRP on all routers in the network.

Task 5

In order to avoid possible SIA issues, configure the routing wait time to be 10 minutes.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.1 255.255.255.0**
R1(config-if)#**no shutdown**
R1(config-if)#**encapsulation frame-relay**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip address 10.0.0.2 255.255.255.0**
R2(config-if)#**no shutdown**
R2(config-if)#**encapsulation frame-relay**
R2(config-if)#**exit**

https://t.me/learningnets

Technet24

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.4.4.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.4 255.255.255.0**
R4(config-if)#**no shutdown**
R4(config-if)#**encapsulation frame-relay**
R4(config-if)#**exit**

Task 2

By default, EIGRP uses Multicast to send packets. To configure EIGRP to use Unicast packets, you must configure static EIGRP neighbor statements. When a static neighbor is configured, EIGRP stops sending and processing received any EIGRP Multicast packets via the interface(s).

R1(config)#**router eigrp 1**
R1(config-router)#**no auto-summary**
R1(config-router)#**neighbor 10.0.0.2 serial 0/1**
R1(config-router)#**neighbor 10.0.0.4 serial 0/1**
R1(config-router)#**network 10.0.0.1 0.0.0.0**
R1(config-router)#**exit**

R2(config)#**router eigrp 1**
R2(config-router)#**no auto-summary**
R2(config-router)#**neighbor 10.0.0.1 serial 0/1**
R2(config-router)#**network 10.0.0.2 0.0.0.0**
R2(config-router)#**exit**

R4(config)#**router eigrp 1**
R4(config-router)#**no auto-summary**
R4(config-router)#**neighbor 10.0.0.1 serial 0/0**
R4(config-router)#**network 10.0.0.4 0.0.0.0**
R4(config-router)#**exit**

Verify your configuration using the **show ip eigrp neighbors [detail]** command:

R1#**show ip eigrp neighbors detail**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num

https://t.me/learningnets

1 10.0.0.4 Se0/1 131 00:01:39 20 200 0 3
Static neighbor
Version 12.4/1.2, Retrans: 0, Retries: 0
0 10.0.0.2 Se0/1 132 00:02:39 23 200 0 3
Static neighbor
Version 12.4/1.2, Retrans: 0, Retries: 0

R2#**show ip eigrp neighbors detail**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.1 Se0/1 158 00:03:07 18 200 0 3
Static neighbor
Version 12.4/1.2, Retrans: 0, Retries: 0

R4#**show ip eigrp neighbors detail**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.1 Se0/0 169 00:01:04 23 200 0 5
Static neighbor
Version 12.4/1.2, Retrans: 0, Retries: 0

Task 3

R1(config)#**route-map CONNECTED permit 10**
R1(config-route-map)#**match interface fastethernet 0/0**
R1(config-route-map)#**set metric 100000 100 255 1 1500**
R1(config-route-map)#**exit**
R1(config)#**route-map CONNECTED permit 20**
R1(config-route-map)#**set metric 50000 1250 255 1 1500**
R1(config-route-map)#**exit**
R1(config)#**router eigrp 1**
R1(config-router)#**redistribute connected route-map CONNECTED**
R1(config-router)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**no ip split-horizon eigrp 1**
R1(config-if)#**exit**

NOTE: The default split horizon rules still apply even when using static neighbor relationships. Therefore, you must disable split horizon on R1 otherwise it will not advertise the 150.2.2.0/24 and 150.4.4.0/24 subnets received from either spoke back

https://t.me/learningnets
Technet24

out the Serial 0/1 interface. The result in that the spoke routers will not be able to ping each others' 150.x.x.x/24 subnets.

```
R2(config)#route-map CONNECTED permit 10
R2(config-route-map)#match interface fastethernet 0/0
R2(config-route-map)#set metric 100000 100 255 1 1500
R2(config-route-map)#exit
R2(config)#route-map CONNECTED permit 20
R2(config-route-map)#set metric 50000 1250 255 1 1500
R2(config-route-map)#exit
R2(config)#router eigrp 1
R2(config-router)#redistribute connected route-map CONNECTED
R2(config-router)#exit
```

```
R4(config)#route-map CONNECTED permit 10
R4(config-route-map)#match interface fastethernet 0/0
R4(config-route-map)#set metric 100000 100 255 1 1500
R4(config-route-map)#exit
R4(config)#route-map CONNECTED permit 20
R4(config-route-map)#set metric 50000 1250 255 1 1500
R4(config-route-map)#exit
R4(config)#router eigrp 1
R4(config-router)#redistribute connected route-map CONNECTED
R4(config-router)#exit
```

Following this configuration, verify the routing table using the **show ip route** command:

```
R1#show ip route eigrp
150.2.0.0/24 is subnetted, 1 subnets
D EX 150.2.2.0 [170/2195456] via 10.0.0.2, 00:07:51, Serial0/1
150.4.0.0/24 is subnetted, 1 subnets
D EX 150.4.4.0 [170/2195456] via 10.0.0.4, 00:06:30, Serial0/1
```

```
R2#show ip route eigrp
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/2195456] via 10.0.0.1, 00:24:52, Serial0/1
150.4.0.0/24 is subnetted, 1 subnets
D EX 150.4.4.0 [170/2707456] via 10.0.0.1, 00:03:16, Serial0/1
```

```
R4#show ip route eigrp
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/2195456] via 10.0.0.1, 00:07:03, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
```

https://t.me/learningnets

D EX 150.2.2.0 [170/2707456] via 10.0.0.1, 00:03:32, Serial0/0

Task 4

By default, EIGRP can use up to 50% of the link bandwidth. This is not desirable when using a low bandwidth link. This task is completed as follows:

R1(config)#**interface serial 0/1**
R1(config-if)#**ip bandwidth-percent eigrp 1 5**
R1(config-if)#**exit**

R2(config)#**interface serial 0/1**
R2(config-if)#**ip bandwidth-percent eigrp 1 5**
R2(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**ip bandwidth-percent eigrp 1 5**
R4(config-if)#**exit**

Task 5

The default route-waiting timer is set to 3 minutes. The configured timer value must be similar on all routers in the network. Complete this task as follows:

R1(config)#**router eigrp 1**
R1(config-router)#**timers active-time 10**
R1(config-router)#**exit**

R2(config)#**router eigrp 1**
R2(config-router)#**timers active-time 10**
R2(config-router)#**exit**

R4(config)#**router eigrp 1**
R4(config-router)#**timers active-time 10**
R4(config-router)#**exit**

https://t.me/learningnets

Technet24

CCNP Lab 023: EIGRP Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand EIGRP implementation and configuration in Cisco IOS routers. Additional technologies tested include advanced route filtering and manipulation.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure EIGRP for AS 1024 on R1, R3, and R4 as illustrated in the topology. EIGRP should be configured to use Unicast packets instead of Multicast packets. Verify your

https://t.me/learningnets

Technet24

configuration using the appropriate commands.

Task 3

Configure EIGRP for AS 2048 on R1 and R2 as illustrated in the topology. EIGRP should be configured to use Unicast packets instead of Multicast packets. Verify your configuration using the appropriate commands.

Task 4

Configure and advertise the following subnets via EIGRP using the following metrics:

- R2: Loopback192 - 192.1.1.1/32: Redistribution Metric - 100,000 - 1,000 - 255 - 1 - 1500
- R2: Loopback193 - 193.1.1.1/32: Redistribution Metric - 10,000 - 500 - 255 - 1 - 1500

- R3: Loopback12 - 12.1.1.1/32: Redistribution Metric - 30,000 - 300 - 255 - 1 - 1500
- R3: Loopback13 - 13.1.1./32: Redistribution Metric - 40,000 - 400 - 255 - 1 - 1500

- R4: Loopback12 - 12.1.1.1/32: Redistribution Metric - Default
- R4: Loopback13 - 13.1.1.1/32: Redistribution Metric - Default

Task 5

Redistribute between EIGRP 1024 and EIGRP 2048. Ensure that the next hop IP address for the redistributed routes is the IP address of the router that originated the route and NOT the IP address of R1. Verify your configuration.

Task 6

Configure route filtering on R4 so that the router only accepts routes with a metric between 200,000 and 300,000. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**

https://t.me/learningnets

R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.1.1.2 255.255.255.0**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 150.1.1.3 255.255.255.0**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.1.1.4 255.255.255.0**
R4(config-if)#**exit**

Task 2

R1(config)#**router eirgp 1024**
R1(config-router)#**no auto-summary**
R1(config-router)#**neighbor 150.1.1.3 fastethernet 0/0**
R1(config-router)#**neighbor 150.1.1.4 fastethernet 0/0**
R1(config-router)#**network 150.1.1.1 0.0.0.0**
R1(config-router)#**exit**

R3(config)#**router eigrp 1024**
R3(config-router)#**no auto-summary**
R3(config-router)#**neighbor 150.1.1.1 fastethernet 0/0**
R3(config-router)#**neighbor 150.1.1.4 fastethernet 0/0**
R3(config-router)#**network 150.1.1.3 0.0.0.0**
R3(config-router)#**exit**

R4(config)#**router eigrp 1024**
R4(config-router)#**no auto-summary**
R4(config-router)#**neighbor 150.1.1.1 fastethernet 0/0**
R4(config-router)#**neighbor 150.1.1.3 fastethernet 0/0**
R4(config-router)#**network 150.1.1.4 0.0.0.0**
R4(config-router)#**exit**

Verify your configuration using the **show ip eigrp neighbors** command:

https://t.me/learningnets

Technet24

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1024
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 150.1.1.4 Fa0/0 14 00:01:32 5 200 0 4
0 150.1.1.3 Fa0/0 14 00:04:52 4 200 0 3

R3#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1024
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 150.1.1.4 Fa0/0 12 00:01:48 4 200 0 5
0 150.1.1.1 Fa0/0 12 00:05:08 4 200 0 3

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1024
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 150.1.1.1 Fa0/0 13 00:02:09 4 200 0 5
0 150.1.1.3 Fa0/0 14 00:02:09 8 200 0 5

Task 3

R1(config)#**router eigrp 2048**
R1(config-router)#**no auto-summary**
R1(config-router)#**neighbor 150.1.1.2 fastethernet 0/0**
R1(config-router)#**network 150.1.1.1 0.0.0.0**
R1(config-router)#**exit**

R2(config)#**router eigrp 2048**
R2(config-router)#**no auto-summary**
R2(config-router)#**neighbor 150.1.1.1 fastethernet 0/0**
R2(config-router)#**network 150.1.1.2 0.0.0.0**
R2(config-router)#**exit**

Verify your configuration using the **show ip eigrp neighbors** command:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1024
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 150.1.1.4 Fa0/0 12 00:04:42 5 200 0 4
0 150.1.1.3 Fa0/0 14 00:08:01 4 200 0 3

https://t.me/learningnets

IP-EIGRP neighbors for process 2048
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.1.1.2 Fa0/0 12 00:00:39 4 200 0 3

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 2048
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.1.1.1 Fa0/0 12 00:00:35 2 200 0 3

Task 4

R2(config)#**interface loopback 192**
R2(config-if)#**ip address 192.1.1.1 255.255.255.255**
R2(config-if)#**exit**
R2(config)#**interface loopback 193**
R2(config-if)#**ip address 193.1.1.1 255.255.255.255**
R2(config-if)#**exit**
R2(config)#**route-map LOOPBACK permit 10**
R2(config-route-map)#**match interface loopback 192**
R2(config-route-map)#**set metric 100000 1000 255 1 1500**
R2(config-route-map)#**exit**
R2(config)#**route-map LOOPBACK permit 20**
R2(config-route-map)#**set metric 10000 500 255 1 1500**
R2(config-route-map)#**exit**
R2(config)#**router eigrp 2048**
R2(config-router)#**redistribute connected route-map LOOPBACK**
R2(config-router)#**exit**

R3(config)#**interface loopback 12**
R3(config-if)#**ip address 12.1.1.1 255.255.255.255**
R3(config-if)#**exit**
R3(config)#**interface loopback 13**
R3(config-if)#**ip address 13.1.1.1 255.255.255.255**
R3(config-if)#**exit**
R3(config)#**route-map LOOPBACK permit 10**
R3(config-route-map)#**match interface loopback 12**
R3(config-route-map)#**set metric 30000 300 255 1 1500**
R3(config-route-map)#**exit**
R3(config)#**route-map LOOPBACK permit 20**

https://t.me/learningnets

Technet24

R3(config-route-map)#**match interface loopback 13**
R3(config-route-map)#**set metric 40000 400 255 1 1500**
R3(config-route-map)#**exit**
R3(config)#**router eigrp 1024**
R3(config-router)#**redistribute connected route-map LOOPBACK**
R3(config-router)#**exit**

R4(config)#**interface loopback 12**
R4(config-if)#**ip address 12.1.1.1 255.255.255.255**
R4(config-if)#**exit**
R4(config)#**interface loopback 13**
R4(config-if)#**ip address 13.1.1.1 255.255.255.255**
R4(config-if)#**exit**
R4(config)#**router eigrp 1024**
R4(config-router)#**redistribute connected**
R4(config-router)#**exit**

Verify your configuration by looking at the EIGRP topology tables of all routers using the **show ip eigrp topology all-links** command because of the different redistribution metrics:

R1#**show ip eigrp topology all-links**
IP-EIGRP Topology Table for AS(1024)/ID(150.1.1.1)
Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
r - reply Status, s - sia Status

P 13.1.1.1/32, 1 successors, FD is 156160, serno 7
via 150.1.1.4 (156160/128256), FastEthernet0/0
via 150.1.1.3 (168960/166400), FastEthernet0/0
P 12.1.1.1/32, 1 successors, FD is 156160, serno 6
via 150.1.1.4 (156160/128256), FastEthernet0/0
via 150.1.1.3 (164608/162048), FastEthernet0/0
P 150.1.1.0/24, 1 successors, FD is 28160, serno 1
via Connected, FastEthernet0/0
IP-EIGRP Topology Table for AS(2048)/ID(150.1.1.1)
Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
r - reply Status, s - sia Status

P 150.1.1.0/24, 1 successors, FD is 28160, serno 1
via Connected, FastEthernet0/0
P 193.1.1.1/32, 1 successors, FD is 386560, serno 2
via 150.1.1.2 (386560/384000), FastEthernet0/0

https://t.me/learningnets

P 192.1.1.1/32, 1 successors, FD is 284160, serno 3
via 150.1.1.2 (284160/281600), FastEthernet0/0

R2#**show ip eigrp topology all-links**
IP-EIGRP Topology Table for AS(2048)/ID(150.1.1.2)
Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
r - reply Status, s - sia Status

P 150.1.1.0/24, 1 successors, FD is 28160, serno 1
via Connected, FastEthernet0/0
P 193.1.1.1/32, 1 successors, FD is 384000, serno 2
via Rconnected (384000/0)
P 192.1.1.1/32, 1 successors, FD is 281600, serno 3
via Rconnected (281600/0)

R3#**show ip eigrp topology all-links**
IP-EIGRP Topology Table for AS(1024)/ID(150.1.1.3)
Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
r - reply Status, s - sia Status

P 13.1.1.1/32, 1 successors, FD is 166400, serno 3
via Rconnected (166400/0)
via 150.1.1.4 (156160/128256), FastEthernet0/0
P 12.1.1.1/32, 1 successors, FD is 162048, serno 2
via Rconnected (162048/0)
via 150.1.1.4 (156160/128256), FastEthernet0/0
P 150.1.1.0/24, 1 successors, FD is 28160, serno 1
via Connected, FastEthernet0/0

R4#**show ip eigrp topology all-links**
IP-EIGRP Topology Table for AS(1024)/ID(150.1.1.4)
Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
r - reply Status, s - sia Status

P 13.1.1.1/32, 1 successors, FD is 128256, serno 7
via Rconnected (128256/0)
via 150.1.1.3 (168960/166400), FastEthernet0/0
P 12.1.1.1/32, 1 successors, FD is 128256, serno 6
via Rconnected (128256/0)
via 150.1.1.3 (164608/162048), FastEthernet0/0
P 150.1.1.0/24, 1 successors, FD is 28160, serno 1
via Connected, FastEthernet0/0

https://t.me/learningnets

Technet24

Task 5

The first part of this task is straightforward. This task is completed as follows:

R1(config)#**router eigrp 1024**
R1(config-router)#**redistribute eigrp 2048**
R1(config-router)#**exit**
R1(config)#**router eigrp 2048**
R1(config-router)#**redistribute eigrp 1024**
R1(config-router)#**exit**

The second part of this task requires that default NEXT HOP behavior for EIGRP be modified. EIGRP does not set the NEXT HOP field in EIGRP packets by default. Therefore, on a multi-access network, such as an NBMA or Ethernet network, a router receiving routes from an EIGRP router assumes that the next hop of these routes is the router sending the updates, even though it might actually be another router on the same subnet. For example, R2 assumes that the NEXT HOP address for the 12.1.1.1/32 and 13.1.1.32 is R1 (150.1.1.1) as shown below:

R2#**show ip route eigrp**

12.0.0.0/32 is subnetted, 1 subnets

D EX 12.1.1.1 [170/158720] via 150.1.1.1, 00:18:59, FastEthernet0/0

13.0.0.0/32 is subnetted, 1 subnets

D EX 13.1.1.1 [170/158720] via 150.1.1.1, 00:18:59, FastEthernet0/0

To complete this task, disable the default EIGRP NEXT HOP behavior:

R1(config)#**interface fastethernet 0/0**

R1(config-if)#**no ip next-hop-self eigrp 1024**

R1(config-if)#**no ip next-hop-self eigrp 2048**

R1(config-if)#**exit**

Following this change, verify the IP routing tables using the **show ip route** command:

R2#**show ip route eigrp**

12.0.0.0/32 is subnetted, 1 subnets

D EX 12.1.1.1 [170/158720] via 150.1.1.4, 00:01:23, FastEthernet0/0

13.0.0.0/32 is subnetted, 1 subnets

D EX 13.1.1.1 [170/158720] via 150.1.1.4, 00:01:23, FastEthernet0/0

R3#**show ip route eigrp**
193.1.1.0/32 is subnetted, 1 subnets

https://t.me/learningnets

D EX 193.1.1.1 [170/389120] via 150.1.1.2, 00:01:44, FastEthernet0/0
192.1.1.0/32 is subnetted, 1 subnets
D EX 192.1.1.1 [170/286720] via 150.1.1.2, 00:01:44, FastEthernet0/0

R4#**show ip route eigrp**
193.1.1.0/32 is subnetted, 1 subnets
D EX 193.1.1.1 [170/389120] via 150.1.1.2, 00:01:58, FastEthernet0/0
192.1.1.0/32 is subnetted, 1 subnets
D EX 192.1.1.1 [170/286720] via 150.1.1.2, 00:01:58, FastEthernet0/0

Task 6

This task requires the implementation of route map filtering. Cisco IOS route maps allow you to specify a valid metric range using standard deviation via the +- keyword. When you specify a metric deviation with the + and - keywords, the router will match any metric that falls inclusively in that range. For example, if you issue the command **match metric 100 +- 10** within the route map, the router will match routes with a metric that is 10 less than 100 (90) or 10 more than 100 (110) and anything in between. Prior to any changes, R4s EIGRP routing table shows the following entries for routes received from R1:

R4#**show ip route eigrp**
193.1.1.0/32 is subnetted, 1 subnets
D EX 193.1.1.1 [170/389120] via 150.1.1.2, 00:02:35, FastEthernet0/0
192.1.1.0/32 is subnetted, 1 subnets
D EX 192.1.1.1 [170/286720] via 150.1.1.2, 00:02:35, FastEthernet0/0

Please note that your metrics will differ from ours due to the topology you are running your lab on so please adjust your settings as appropriate and don’t just copy ours.

Notice that the 192.1.1.1/32 prefix has a route metric of 286,720 and the 193.1.1.1/32 prefix has a route metric of 389,120. To complete this task, think logically. Given the required metric range, i.e. 200,000 to 300,000; simply match a metric of 250,000 and allow for a deviation of 50,000 in either direction. This task is completed as follows:

R4(config)#**route-map EIGRP-FILTER permit 10**
R4(config-route-map)#**match metric 250000 +- 50000**
R4(config-route-map)#**exit**
R4(config)#**route-map EIGRP-FILTER deny 20**
R4(config-route-map)#**exit**
R4(config)#**router eigrp 1024**
R4(config-router)#**distribute-list route-map EIGRP-FILTER in**
R4(config-router)#**exit**

https://t.me/learningnets

Following the implementation of the route map, the routing table on R1 shows the following:

R4#**show ip route eigrp**
192.1.1.0/32 is subnetted, 1 subnets
D EX 192.1.1.1 [170/286720] via 150.1.1.2, 00:05:33, FastEthernet0/0

Notice that the 193.1.1.1/32 prefix, which had a route metric of 389,120 is no longer present in the routing table because this metric falls outside the permitted range of 200,000 to 300,000.

https://t.me/learningnets

CCNP Lab 024: OSPF Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand OSPF implementation and configuration in Cisco IOS routers. Additional technologies tested include authentication and route and LSA filtering.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Using interface-based configuration, configure the OSPF backbone (area 0) on the LAN segment between R1 and R4. In the future, additional routers may be added to this segment. Ensure that no DR/BDR election is held on this segment; however, ensure that multiple routers can exist on the same segment. Do NOT modify any OSPF priority values.

Task 3

Using interface-based configuration, configure OSPF area 1 between R1, R3 and R4. Configure MD5 authentication for area 1 using the password 'CCNP'. Verify your configuration.

Task 4

Using interface-based configuration, configure OSPF area 2 between R1 and R2. R1 should not advertise any inter-area routes into area 2; however, a default route should be advertised by default. This default route should be advertised into area 2 so that it appears in the routing table of R2 with a route metric of 500. Do NOT modify interface bandwidth or cost values when completing this task. Verify the configuration.

Task 5

R2 should inject the 150.2.2.0/24 subnet into area 2 as an External N1 route with a route tag of 2222. Verify your configuration.

Task 6

Configure a secondary subnet of 150.1.1.0/29 on the LAN segment between R1 and R4. Assign the 150.1.1.1/29 address to R1 and 150.1.1.4/29 address to R4. This subnet should not be advertised into area 1; however, R2 should be able to reach it. You are NOT allowed to use any distribute-lists or other forms of filters to complete this task. In addition to this, you are NOT allowed to configure any static routes. Verify your OSPF configuration.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.1.1 255.255.255.248**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**

https://t.me/learningnets
Technet24

R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 150.3.3.3 255.255.255.0**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.6 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)# **ip add 10.0.1.4 255.255.255.248**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**exit**

https://t.me/learningnets

Task 2

This task requires that the default OSPF network type is changed from Broadcast to point-to-multipoint, which allows multiple routers on the same segment, but requires no DR/BDR election. This task is completed as follows:

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip ospf network point-to-multipoint**
R1(config-if)#**ip ospf 1 area 0**
R1(config-if)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**exit**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip ospf network point-to-multipoint**
R4(config-if)#**ip ospf 4 area 0**
R4(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:01:56 10.0.1.4 FastEthernet0/0

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:01:49 10.0.1.1 FastEthernet0/0

Task 3

R1(config)#**router ospf 1**
R1(config-router)#**area 1 authentication message-digest**
R1(config-router)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip ospf 1 area 1**
R1(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R1(config-if)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**area 1 authentication message-digest**

https://t.me/learningnets

Technet24

R4(config-router)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip ospf 4 area 1**
R4(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R4(config-if)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**area 1 authentication message-digest**
R3(config-router)#**exit**
Enter configuration commands, one per line. End with CNTL/Z.
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip ospf 3 area 1**
R3(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**ip ospf 3 area 1**
R3(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip ospf 3 area 1**
R3(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R3(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R3#show ip ospf neighbor

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:38 10.0.0.14 Serial1/2
1.1.1.1 0 FULL/ - 00:00:36 10.0.0.5 Serial1/0

You can verify area authentication using the **show ip ospf <process>** command:

R3#**show ip ospf 3 | begin Area 1**
Area 1
Number of interfaces in this area is 3
Area has message digest authentication
SPF algorithm last executed 00:00:58.140 ago
SPF algorithm executed 6 times
Area ranges are
Number of LSA 11. Checksum Sum 0x143DCC
Number of opaque link LSA 0. Checksum Sum 0x000000

https://t.me/learningnets

Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0

Use the **show ip ospf interface <name>** to view interface authentication configuration:

R3#**show ip ospf interface serial 1/0**
Serial1/0 is up, line protocol is up
Internet Address 10.0.0.6/30, Area 1
Process ID 3, Router ID 3.3.3.3, Network Type POINT_TO_POINT, Cost: 781
Enabled by interface config, including secondary ip addresses
Transmit Delay is 1 sec, State POINT_TO_POINT
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
oob-resync timeout 40
Hello due in 00:00:00
Supports Link-local Signaling (LLS)
Index 1/1, flood queue length 0
Next 0x0(0)/0x0(0)
Last flood scan length is 1, maximum is 3
Last flood scan time is 0 msec, maximum is 0 msec
Neighbor Count is 1, Adjacent neighbor count is 1
Adjacent with neighbor 1.1.1.1
Suppress hello for 0 neighbor(s)
Message digest authentication enabled
Youngest key id is 1

Task 4

To complete this task you need to configure R1 as an NSSA totally stubby ABR so that R1 will automatically advertise the default route into area 2. To complete the second part of the task, the **area <> default-cost <cost>** command is required to specify the default cost of the default route that is advertised into the stub or NSSA area.

Because OSPF cost is cumulative, you need to calculate the cost of 500 by subtracting the cost of the link between R1 and R2 from this number and specifying the remainder using the **area <> default-cost <cost>** command. Assuming the default cost of 64 for the WAN link between R1 and R2, to configure a cost of 500 perform the following: 500 - 64 = 436. This task is completed as follows:

R1(config)#**router ospf 1**
R1(config-router)#**area 2 nssa no-summary**
R1(config-router)#**area 2 default-cost 436**

https://t.me/learningnets

Technet24

R1(config-router)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip ospf 1 area 2**
R1(config-if)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**area 2 nssa**
R2(config-router)#**exi**t
R2(config)#**interface serial 0/0**
R2(config-if)#**ip ospf 2 area 2**

Verify your configuration using the **show ip ospf neighbor** command:

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:00:36 10.0.0.1 Serial0/0

Verify the cost of the default route on R2 by looking at the routing table:

R2#**show ip route ospf**
O*IA 0.0.0.0/0 [110/500] via 10.0.0.1, 00:00:15, Serial0/0
The advertised cost can also be viewed by looking at the entry in the LSDB:

R2#**show ip ospf database summary 0.0.0.0**

OSPF Router with ID (2.2.2.2) (Process ID 2)

Summary Net Link States (Area 2)

Routing Bit Set on this LSA
LS age: 64
Options: (No TOS-capability, DC, Upward)
LS Type: Summary Links(Network)
Link State ID: 0.0.0.0 (summary Network Number)
Advertising Router: 1.1.1.1
LS Seq Number: 80000003
Checksum: 0x2556
Length: 28
Network Mask: /0
TOS: 0 **Metric: 436**

Task 5

Because only a single interface exists, this can be completed using a single configuration line:

https://t.me/learningnets

R2(config)#**router ospf 2**
R2(config-router)#**redistribute connected subnets tag 2222 metric-type 1**
R2(config-router)#**exit**

Verify your configuration by looking at the entry for this prefix in the Link State Database:

R1#**show ip ospf database external 150.2.2.0**

OSPF Router with ID (1.1.1.1) (Process ID 1)

Type-5 AS External Link States

LS age: 63

Options: (No TOS-capability, DC)

LS Type: AS External Link

Link State ID: 150.2.2.0 (External Network Number)

Advertising Router: 1.1.1.1

LS Seq Number: 80000001

Checksum: 0xCDF1

Length: 36

Network Mask: /24

Metric Type: 1 (Comparable directly to link state metric)

TOS: 0

Metric: 20

Forward Address: 10.0.0.2

External Route Tag: 2222

Task 6

The requirements of this task are two-fold (you already know how to configure Loopback interfaces so please do that). To complete the first part of this task, you need to prevent the secondary subnet configured on R1 and R4 from being advertised by OSPF. By default, OSPF will advertise all secondary subnets as can be seen in the LSDB on R3:

R3#**show ip ospf database | include 150.**
150.1.1.1 1.1.1.1 142 0x80000001 0x00A4FA
150.1.1.1 4.4.4.4 153 0x80000001 0x00543E
150.1.1.4 1.1.1.1 142 0x80000001 0x00900B
150.1.1.4 4.4.4.4 153 0x80000001 0x002C64

https://t.me/learningnets

Technet24

150.2.2.0 1.1.1.1 723 0x80000001 0x00CDF1 2222

Complete this task by preventing OSPF from advertising secondary subnets as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip ospf 1 area 0 secondaries none**
R1(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip ospf 4 area 0 secondaries none**
R4(config-if)#**exit**

Following this configuration, the secondary subnet is no longer advertised by OSPF and is no longer present in the LSDB on R3:

R3#**show ip ospf database | include 150**
150.2.2.0 1.1.1.1 1188 0x80000002 0x00CBF2 2222

To complete the second part of this task, you need to configure R1 and R4 to advertise a default route to R3 using the **default-information originate always** command. This allows OSPF to advertise a default route without one existing in the RIB:

R1(config)#**router ospf 1**
R1(config-router)#**default-information originate always**
R1(config-router)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**default-information originate always**
R4(config-router)#**exit**

Following this configuration, R3s RIB contains two default routes: one from R1 and one from R4. This is verified by looking at either the RIB or LSDB on R3:

R3#**show ip route ospf**
10.0.0.0/8 is variably subnetted, 5 subnets, 2 masks
O IA 10.0.1.1/32 [110/781] via 10.0.0.5, 00:00:52, Serial1/0
O IA 10.0.0.0/30 [110/845] via 10.0.0.5, 00:00:52, Serial1/0
O IA 10.0.1.4/32 [110/781] via 10.0.0.14, 00:00:52, Serial1/2
150.2.0.0/24 is subnetted, 1 subnets
O E1 150.2.2.0 [110/865] via 10.0.0.5, 00:00:42, Serial1/0
O*E2 0.0.0.0/0 [110/1] via 10.0.0.14, 00:00:42, Serial1/2
[110/1] via 10.0.0.5, 00:00:43, Serial1/0

Finally, verify that R3 can ping the 150.1.1.1 and 150.1.1.4 addresses:

R3#**ping 150.1.1.1 repeat 10 source fastethernet 0/0**

Type escape sequence to abort.

https://t.me/learningnets

Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R3#**ping 150.1.1.4 repeat 10 source fastethernet 0/0**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.4, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

https://t.me/learningnets

Technet24

CCNP Lab 025: OSPF Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand OSPF implementation and configuration in Cisco IOS routers. Additional technologies tested include authentication and backbone connectivity.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Technet24

Using interface-based configuration, configure OSPF area 0 on the LAN segment connecting R1 and R4. To allow for faster convergence, configure OSPF to detect a neighbor failure within one second. The OSPF Dead Interval should be set to 1 second. The routers should send four Hellos every second. Verify your configuration using the appropriate commands.

Task 3

Using interface-based configuration, configure OSPF area 1 between R1 and R2. This area should be configured as a Totally Stubby area. Verify your configuration.

Task 4

Using interface-based configuration, configure OSPF area 2 between R2 and R3. Ensure that this area is able to communicate with the OSPF backbone. Verify your configuration.

Task 5

To allow for area 2 resiliency, configure your network so that the WAN link between R1 and R3 is used to allow reachability to and from R3 as well as to the 150.3.3.0/24 subnet should the WAN link between R2 and R3 fail. You are permitted to use TWO static routes to complete this task. Test your solution by shutting down the WAN link between R2 and R3.

Task 6

Configure plain text authentication for the OSPF backbone area. Ensure that all routing still works following your configuration. Use the password 'CCNP' for authentication.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**

https://t.me/learningnets

R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 150.3.3.3 255.255.255.0**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.6 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip add 10.0.1.4 255.255.255.0**
R4(config-if)#**exit**

Task 2

The requirements for this task are two-fold. The first part entails enabling OSPF using interface-based configuration. This is completed as follows:

https://t.me/learningnets

Technet24

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip ospf 1 area 0**
R1(config-if)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**exit**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip ospf 4 area 0**
R4(config-if)#**exit**

When complete, verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 1 FULL/BDR 00:00:32 10.0.1.4 FastEthernet0/0

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 1 FULL/DR 00:00:31 10.0.1.1 FastEthernet0/0

The second part of this task requires enabling OSPF Fast Hellos. The OSPF Fast Hello feature provides a way to configure the sending of hello packets in intervals less than 1 second, thus allowing for faster convergence of the OSPF network. This feature is enabled using the **ip ospf dead-interval minimal hello-multiplier <3-20>** interface configuration command. The **ip ospf dead-interval minimal** portion of this command tells OSPF to advertise a dead interval of 1 second.

The **hello-multiplier <3-20>** portion of the command specifies the number of Hellos that should be sent every second. The valid range is 3 to 20 - although this will vary depending on Cisco IOS Software version and platform. For example, to configure OSPF to send 15 Hello packets every second, you would issue the **ip ospf dead-interval minimal hello-multiplier 15** OSPF interface configuration command. This task is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip ospf dead-interval minimal hello-multiplier 4**
R1(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip ospf dead-interval minimal hello-multiplier 4**

https://t.me/learningnets

R4(config-if)#**exit**

Verify your configuration using the **show ip ospf interface <name>** command:

R4#**show ip ospf interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet Address 10.0.1.4/24, Area 0
Process ID 4, Router ID 4.4.4.4, Network Type BROADCAST, Cost: 1
Enabled by interface config, including secondary ip addresses
Transmit Delay is 1 sec, State BDR, Priority 1
Designated Router (ID) 1.1.1.1, Interface address 10.0.1.1
Backup Designated router (ID) 4.4.4.4, Interface address 10.0.1.4
Timer intervals configured, Hello 250 msec, Dead 1, Wait 1, Retransmit 5
oob-resync timeout 40
Hello due in 166 msec
Supports Link-local Signaling (LLS)
Index 1/1, flood queue length 0
Next 0x0(0)/0x0(0)
Last flood scan length is 1, maximum is 1
Last flood scan time is 0 msec, maximum is 0 msec
Neighbor Count is 1, Adjacent neighbor count is 1
Adjacent with neighbor 1.1.1.1 (Designated Router)
Suppress hello for 0 neighbor(s)

You can also determine that Fast Hellos have been enabled if the dead timer value in the output of the **show ip ospf neighbor [detail]** command is in milliseconds versus seconds:

R1#**show ip ospf neighbor detail**
Neighbor 4.4.4.4, interface address 10.0.1.4
In the area 0 via interface FastEthernet0/0
Neighbor priority is 1, State is FULL, 6 state changes
DR is 10.0.1.1 BDR is 10.0.1.4
Options is 0x12 in Hello (E-bit L-bit)
Options is 0x52 in DBD (E-bit L-bit O-bit)
LLS Options is 0x1 (LR)
Dead timer due in 848 msec
Neighbor is up for 00:14:50
Index 1/1, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0

https://t.me/learningnets

Technet24

Last retransmission scan time is 0 msec, maximum is 0 msec

Task 3

R1(config)#**router ospf 1**
R1(config-router)#**area 1 stub no-summary**
R1(config-router)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip ospf 1 area 1**
R1(config-if)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**area 1 stub**
R2(config-router)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip ospf 2 area 1**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip ospf 2 area 1**
R2(config-if)#**exit**

When complete, verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 1 FULL/BDR 824 msec 10.0.1.4 FastEthernet0/0
2.2.2.2 0 FULL/ - 00:00:37 10.0.0.2 Serial0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:00:37 10.0.0.1 Serial0/0

Additionally, use the **show ip ospf** commands to verify totally stub area configuration:

R1#**show ip ospf**
Routing Process “ospf 1” with ID 1.1.1.1

[Truncated Output]

Number of areas in this router is 2. 1 normal 1 stub 0 nssa

[Truncated Output]

Area BACKBONE(0)
Number of interfaces in this area is 1
Area has no authentication

https://t.me/learningnets

SPF algorithm last executed 00:04:03.140 ago
SPF algorithm executed 6 times

[Truncated Output]

Area 1
Number of interfaces in this area is 1
It is a stub area, no summary LSA in this area
generates stub default route with cost 1
Area has no authentication
SPF algorithm last executed 00:02:59.252 ago
SPF algorithm executed 5 times

[Truncated Output]

R2#**show ip ospf database**

OSPF Router with ID (2.2.2.2) (Process ID 2)

Router Link States (Area 1)

Link ID ADV Router Age Seq# Checksum Link count
1.1.1.1 1.1.1.1 333 0x80000002 0x004A38 2
2.2.2.2 2.2.2.2 319 0x80000002 0x00CF03 3

Summary Net Link States (Area 1)

Link ID ADV Router Age Seq# Checksum
0.0.0.0 1.1.1.1 386 0x80000001 0x0093A6

Task 4

The requirements for this task are two-fold. The first requirement is to enable OSPF for area 2. This requirement is completed as follows:

R2(config)#**interface serial 0/1**
R2(config-if)#**ip ospf 2 area 2**
R2(config-if)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip ospf 3 area 2**
R3(config-if)#**exit**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip ospf 3 area 2**
R3(config-if)#**exit**

https://t.me/learningnets

Technet24

When complete, verify your configuration using the **show ip ospf neighbor** command:

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:00:30 10.0.0.1 Serial0/0
3.3.3.3 0 FULL/ - 00:00:31 10.0.0.10 Serial0/1

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:30 10.0.0.9 Serial1/1

Following this configuration, the routes from area 2 are not advertised into the OSPF backbone because the area is not connected to the backbone. OSPF areas are typically connected to the backbone using virtual links. However, in this case, a virtual cannot be used because a virtual link cannot be configured over a stub area. The next alternative is to use a GRE tunnel.

Prior to any changes being made, there will no entries in the LSDB of the backbone routers for the area 2 networks. This can be validated by looking at the LSDB via the **show ip ospf database** command, or looking at the routing table using the **show ip route** command:

R1#**show ip route ospf**
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 10.0.0.2, 00:07:15, Serial0/0

To complete this task, configure a GRE tunnel and assign it to the OSPF backbone (area 0):

R1(config)#**interface tunnel 0**
R1(config-if)#**ip address 11.0.0.1 255.255.255.252**
R1(config-if)#**tunnel source serial 0/0**
R1(config-if)#**tunnel destination 10.0.0.2**
R1(config-if)#**ip ospf 1 area 0**
R1(config-if)#**exit**

R2(config)#**interface tunnel 0**
R2(config-if)#**ip address 11.0.0.2 255.255.255.252**
R2(config-if)#**tunnel source serial 0/0**
R2(config-if)#**tunnel destination 10.0.0.1**
R2(config-if)#**ip ospf 2 area 0**
R2(config-if)#**exit**

When complete, verify your configuration using the **show ip ospf neighbor** command:

https://t.me/learningnets

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:34 11.0.0.2 Tunnel0
4.4.4.4 1 FULL/BDR 744 msec 10.0.1.4 FastEthernet0/0
2.2.2.2 0 FULL/ - 00:00:33 10.0.0.2 Serial0/0

Next, verify that the routes exist by looking at either the LSDB or RIB on the backbone routers:

R1#**show ip route ospf**
10.0.0.0/8 is variably subnetted, 4 subnets, 2 masks
O IA 10.0.0.8/30 [110/11175] via 11.0.0.2, 00:00:41, Tunnel0
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 10.0.0.2, 00:10:58, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O IA 150.3.3.0 [110/11176] via 11.0.0.2, 00:00:41, Tunnel0

R4#**show ip route ospf**
10.0.0.0/8 is variably subnetted, 3 subnets, 2 masks
O IA 10.0.0.8/30 [110/11176] via 10.0.1.1, 00:00:10, FastEthernet0/0
O IA 10.0.0.0/30 [110/65] via 10.0.1.1, 00:00:10, FastEthernet0/0
11.0.0.0/30 is subnetted, 1 subnets
O 11.0.0.0 [110/11112] via 10.0.1.1, 00:00:10, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
O IA 150.2.2.0 [110/66] via 10.0.1.1, 00:00:10, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
O IA 150.3.3.0 [110/11177] via 10.0.1.1, 00:00:10, FastEthernet0/0

Finally, verify end-to-end connectivity using simple pings:

R4#**ping 150.2.2.2 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/17/20 ms

R4#**ping 150.3.3.3 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 208/208/212 ms

Task 5

https://t.me/learningnets

Technet24

To complete this task, you need to configure a default route on R3 that points towards R1. You do NOT need to specify a non-default administrative distance because of the longest-match rules. The default route will therefore only be used when there are no other more specific routes in the routing table, i.e. when the WAN link between R2 and R3 fails.

The second configuration requirement is that you need to a) configure a static route on R1 that points to R3 for the 150.3.3.0/24 subnet and b) redistribute the WAN link between R1 and R3 into OSPF. The static route needs to be configured with an administrative distance higher than 110 so that the route via the tunnel is preferred instead. In addition to this, the static route also needs to be redistributed into OSPF so that it is advertised to R4. Redistributing the WAN link between R1 and R3 will allow other devices to ping R4. This task is completed as follows:

R3(config)#**ip route 0.0.0.0 0.0.0.0 serial 1/0**

R1(config)#**ip route 150.3.3.0 255.255.255.0 serial 0/1 150**

R1(config)#**router ospf 1**

R1(config-router)#**redistribute connected subnets**

R1(config-router)#**redistribute static subnets**

R1(config-router)#**exit**

After this configuration, test the solution by shutting down the WAN link between R2 and R3:

R3(config)#**interface serial 1/1**

R3(config-if)#**shutdown**

R3(config-if)#**exit**

R3(config)#**do show ip route**

Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP

D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area

N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2

E1 - OSPF external type 1, E2 - OSPF external type 2

i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2

ia - IS-IS inter area, * - candidate default, U - per-user static route

o - ODR, P - periodic downloaded static route

Gateway of last resort is 0.0.0.0 to network 0.0.0.0

10.0.0.0/30 is subnetted, 1 subnets

https://t.me/learningnets

C 10.0.0.4 is directly connected, Serial1/0

150.3.0.0/24 is subnetted, 1 subnets

C 150.3.3.0 is directly connected, FastEthernet0/0

S* 0.0.0.0/0 is directly connected, Serial1/0

Following this, verify that all other routers can ping the WAN interface of R3 as well as the connected 150.3.3.0/24 subnet:

R1#**ping 150.3.3.3 repeat 10 size 1500 source fastethernet 0/0**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 10.0.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 188/191/192 ms
R1#

R1#**ping 10.0.0.6 repeat 10 size 1500 source fastethernet 0/0**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 10.0.0.6, timeout is 2 seconds:
Packet sent with a source address of 10.0.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 188/191/192 ms

R2#**ping 10.0.0.6 repeat 10 size 1500 source fastethernet 0/0**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 10.0.0.6, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 204/206/208 ms
R2#

R2#**ping 150.3.3.3 repeat 10 size 1500 source fastethernet 0/0**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 204/206/208 ms

R4#**ping 150.3.3.3 size 1500 repeat 10**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:

https://t.me/learningnets

Technet24

!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 192/193/196 ms
R4#
R4#**ping 10.0.0.6 size 1500 repeat 10**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 10.0.0.6, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 192/193/196 ms

Task 6

R1(config)#**router ospf 1**
R1(config-router)#**area 0 authentication**
R1(config-router)#**exit**
R1(config)#**interface tunnel 0**
R1(config-if)#**ip ospf authentication-key CCNP**
R1(config-if)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip ospf authentication-key CCNP**
R1(config-if)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**area 0 authentication**
R2(config-router)#**exit**
R2(config)#**interface tunnel 0**
R2(config-if)#**ip ospf authentication-key CCNP**
R2(config-if)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**area 0 authentication**
R4(config-router)#**exit**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip ospf authentication-key CCNP**
R4(config-if)#**exit**

Verify the solution using the **show ip ospf** and **show ip ospf interface** commands:

R1#show ip ospf
Routing Process “ospf 1” with ID 1.1.1.1

[Truncated Output]

Area BACKBONE(0)
Number of interfaces in this area is 2

https://t.me/learningnets

Area has simple password authentication

[Truncated Output]

Area 1
Number of interfaces in this area is 1
It is a stub area, no summary LSA in this area
generates stub default route with cost 1
Area has no authentication

[Truncated Output]

R1#**show ip ospf interface | section Tunnel|FastEthernet**
Tunnel0 is up, line protocol is up
Internet Address 11.0.0.1/30, Area 0
Process ID 1, Router ID 1.1.1.1, Network Type POINT_TO_POINT, Cost: 11111
Enabled by interface config, including secondary ip addresses
Transmit Delay is 1 sec, State POINT_TO_POINT

[Truncated Output]

Simple password authentication enabled

FastEthernet0/0 is up, line protocol is up
Internet Address 10.0.1.1/24, Area 0
Process ID 1, Router ID 1.1.1.1, Network Type BROADCAST, Cost: 1
Enabled by interface config, including secondary ip addresses
Transmit Delay is 1 sec, State BDR, Priority 1
Designated Router (ID) 4.4.4.4, Interface address 10.0.1.4
Backup Designated router (ID) 1.1.1.1, Interface address 10.0.1.1
Timer intervals configured, Hello 250 msec, Dead 1, Wait 1, Retransmit 5
oob-resync timeout 40

[Truncated Output]

Simple password authentication enabled

Finally, verify connectivity is still present by pinging end-to-end from R4 to R3 for example:

R3#**ping 10.0.1.4 size 1500 repeat 10 source fastethernet 0/0**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 10.0.1.4, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 204/206/212 ms

https://t.me/learningnets

Technet24

https://t.me/learningnets

CCNP Lab 026: OSPF Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand OSPF implementation and configuration in Cisco IOS routers. Additional technologies tested include summarization and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Using either inter-based or legacy '**network**' statement configuration, configure the OSPF backbone on the LAN segment between R1 and R4.

Task 3

Using either inter-based or legacy '**network**' statement configuration, configure OSPF area 1 between R1, R2 and R3. Do NOT advertise the 150.3.3.0/24 subnet on R3 via OSPF.

Task 4

Using either inter-based or legacy '**network**' statement configuration, configure OSPF area 2 between R1, R3 and R4. Do NOT advertise the 150.3.3.0/24 subnet on R3 via OSPF.

Task 5

Configure the following secondary subnets on the LAN interface of R3:

- 172.16.12.0/24
- 172.16.13.0/24
- 172.16.14.0/24
- 172.16.15.0/24

Next, inject the 150.3.3.0/24 subnet as a Type 2 External LSA. The 172.16.x.x/24 subnets should be injected into OSPF as Type 1 External LSAs. You can use only ONE prefix list or ACL in your solution. Verify your configuration using the appropriate commands.

Task 6

Advertise a single route for the 172.16.x.x/24 subnets connected to the LAN interface on R3. This single route should be assigned a route tag of 3333. This summary address should NOT be present in OSPF area 0; however, it should be in OSPF areas 1 and 2. Verify your configuration.

Task 7

Configure OSPF so that R3 prefers the path via R2 to reach the OSPF backbone, i.e. 10.0.1.0/24. R1 should also be configured to prefer the path via R2 to reach the 150.3.3.0/24 subnet. This should be completed without modifying interface bandwidths. Verify this configuration using the appropriate commands.

Lab Validation:

Task 1

https://t.me/learningnets

Technet24

```
Router(config)#hostname R1
R1(config)#interface fastethernet 0/0
R1(config-if)#no shutdown
R1(config-if)#ip address 10.0.1.1 255.255.255.0
R1(config-if)#exit
R1(config)#interface serial 0/0
R1(config-if)#no shutdown
R1(config-if)#ip address 10.0.0.1 255.255.255.252
R1(config-if)#clock rate 2000000
R1(config-if)#exit
R1(config)#interface serial 0/1
R1(config-if)#no shutdown
R1(config-if)#ip address 10.0.0.5 255.255.255.252
R1(config-if)#exit
Router(config)#hostname R2
R2(config)#interface fastethernet 0/0
R2(config-if)#no shutdown
R2(config-if)#ip address 150.2.2.2 255.255.255.0
R2(config-if)#exit
R2(config)#interface serial 0/0
R2(config-if)#no shutdown
R2(config-if)#ip address 10.0.0.2 255.255.255.252
R2(config-if)#exit
R2(config)#interface serial 0/1
R2(config-if)#no shutdown
R2(config-if)#ip address 10.0.0.9 255.255.255.252
R2(config-if)#exit
Router(config)#hostname R3
R3(config)#interface fastethernet 0/0
R3(config-if)#no shutdown
R3(config-if)#ip address 150.3.3.3 255.255.255.0
R3(config-if)#exit
R3(config)#interface serial 1/0
R3(config-if)#no shutdown
R3(config-if)#ip address 10.0.0.6 255.255.255.252
R3(config-if)#clock rate 128000
R3(config-if)#exit
R3(config)#interface serial 1/1
```

https://t.me/learningnets

R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**no shutdown**
R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**clock rate 128000**
R2(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 10.0.1.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**exit**

Task 2

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**network 10.0.1.1 0.0.0.0 area 0**
R1(config-router)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**network 10.0.1.4 0.0.0.0 area 0**
R4(config-router)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 1 FULL/DR 00:00:37 10.0.1.1 FastEthernet0/0

Task 3

R1(config)#**interface serial 0/0**
R1(config-if)#**ip ospf 1 area 1**
R1(config-if)#**exit**

R2(config)#**router ospf 2**

https://t.me/learningnets

Technet24

R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip ospf 2 area 1**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip ospf 2 area 1**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip ospf 2 area 1**
R2(config-if)#**exit**

R3(config-if)#**router ospf 3**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**network 10.0.0.10 0.0.0.0 area 1**
R3(config-router)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 1 FULL/BDR 00:00:36 10.0.1.4 FastEthernet0/0
2.2.2.2 0 FULL/ - 00:00:30 10.0.0.2 Serial0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:33 10.0.0.10 Serial0/1
1.1.1.1 0 FULL/ - 00:00:38 10.0.0.1 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:39 10.0.0.9 Serial1/1

Task 4

R1(config)#**interface serial 0/1**
R1(config-if)#**ip ospf 1 area 2**
R1(config-if)#**exit**

R3(config)#**interface serial 1/0**
R3(config-if)#**ip ospf 3 area 2**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**

https://t.me/learningnets

R3(config-if)#**ip ospf 3 area 2**
R3(config-if)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**network 10.0.0.14 0.0.0.0 area 2**
R4(config-router)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 1 FULL/BDR 00:00:34 10.0.1.4 FastEthernet0/0
2.2.2.2 0 FULL/ - 00:00:37 10.0.0.2 Serial0/0
3.3.3.3 0 FULL/ - 00:00:35 10.0.0.6 Serial0/1

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:38 10.0.0.10 Serial0/1
1.1.1.1 0 FULL/ - 00:00:32 10.0.0.1 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:31 10.0.0.9 Serial1/1
4.4.4.4 0 FULL/ - 00:00:32 10.0.0.14 Serial1/2
1.1.1.1 0 FULL/ - 00:00:39 10.0.0.5 Serial1/0

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 1 FULL/DR 00:00:31 10.0.1.1 FastEthernet0/0
3.3.3.3 0 FULL/ - 00:00:38 10.0.0.13 Serial0/0

Task 5

This task has two requirements. The first requirement is simple and entails configuring the LAN interface with the specified secondary subnets. This is completed as follows:

R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip address 172.16.12.3 255.255.255.0 secondary**
R3(config-if)#**ip address 172.16.13.3 255.255.255.0 secondary**
R3(config-if)#**ip address 172.16.14.3 255.255.255.0 secondary**
R3(config-if)#**ip address 172.16.15.3 255.255.255.0 secondary**
R3(config-if)#**exit**

The second part of this task requires redistribution into OSPF using a route map. This route map can match against an ACL or IP prefix list. This task is completed as follows:

https://t.me/learningnets

Technet24

R3(config)#**ip prefix-list PRIMARY seq 5 permit 150.3.3.0/24**

R3(config)#**route-map CONNECTED permit 10**

R3(config-route-map)#**match ip address prefix-list PRIMARY**

R3(config-route-map)#**exit**

R3(config)#**route-map CONNECTED permit 20**

R3(config-route-map)#**set metric-type type-1**

R3(config-route-map)#**exit**

R3(config)#**router ospf 3**

R3(config-router)#**redistribute connected subnets route-map CONNECTED**

R3(config-router)#**exit**

Verify your configuration by looking at the Link State Database or simply by looking at the IP routing tables of any other routers in the domain:

R4#**show ip route ospf | include E1|E2**

O E1 172.16.12.0 [110/84] via 10.0.0.13, 00:01:56, Serial0/0

O E1 172.16.13.0 [110/84] via 10.0.0.13, 00:01:56, Serial0/0

O E1 172.16.14.0 [110/84] via 10.0.0.13, 00:01:56, Serial0/0

O E1 172.16.15.0 [110/84] via 10.0.0.13, 00:01:56, Serial0/0

O E2 150.3.3.0 [110/20] via 10.0.0.13, 00:01:56, Serial0/0

Task 6

The first part of this task requires summarization. Because the 172.16.x.x/24 subnets have been redistributed into OSPF, the **summary-address** command must be used on the ASBR to generate the summary route for these subnets. The first part of the task is completed as follows:

R3(config)#**router ospf 3**
R3(config-router)#**summary-address 172.16.12.0 255.255.252.0 tag 3333**
R3(config-router)#**exit**

Verify your configuration using the **show ip ospf database** command:

R3#**show ip ospf database external self-originate**

OSPF Router with ID (3.3.3.3) (Process ID 3)

Type-5 AS External Link States

[Truncated Output]

LS age: 66

https://t.me/learningnets

Options: (No TOS-capability, DC)
LS Type: AS External Link
Link State ID: 172.16.12.0 (External Network Number)
Advertising Router: 3.3.3.3
LS Seq Number: 80000002
Checksum: 0x2715
Length: 36
Network Mask: /22
Metric Type: 1 (Comparable directly to link state metric)
TOS: 0
Metric: 20
Forward Address: 0.0.0.0
External Route Tag: 3333

To complete the second part of this task, you need to configure distribute-lists so that the prefix will not be present in area 0. This task is completed as follows:

R1(config)#**route-map TAG-3333 deny 10**
R1(config-route-map)#**match tag 3333**
R1(config-route-map)#**exit**
R1(config)#**route-map TAG-3333 permit 20**
R1(config-route-map)#**exit**
R1(config)#**router ospf 1**
R1(config-router)#**distribute-list route-map TAG-3333 in**
R1(config-router)#**exit**

R4(config)#**route-map TAG-3333 deny 10**
R4(config-route-map)#**match tag 3333**
R4(config-route-map)#**exit**
R4(config)#**route-map TAG-3333 permit 20**
R4(config-route-map)#**exit**
R4(config)#**router ospf 4**
R4(config-router)#**distribute-list route-map TAG-3333 in**
R4(config-router)#**exit**

Verify your configuration by looking at the routing tables on R1, R2 and R4. Only R2 should have a route for the 172.16.12.0/22 prefix. Here is R4 and R2:

R4#**show ip route ospf**
10.0.0.0/8 is variably subnetted, 5 subnets, 2 masks
O IA 10.0.0.8/30 [110/129] via 10.0.1.1, 00:00:52, FastEthernet0/0
O IA 10.0.0.0/30 [110/65] via 10.0.1.1, 00:00:52, FastEthernet0/0

https://t.me/learningnets
Technet24

O 10.0.0.4/30 [110/845] via 10.0.0.13, 00:00:52, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
O IA 150.2.2.0 [110/66] via 10.0.1.1, 00:00:52, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
O E2 150.3.3.0 [110/20] via 10.0.0.13, 00:00:52, Serial0/0

R2#show ip route ospf
172.16.0.0/22 is subnetted, 1 subnets
O E1 172.16.12.0 [110/84] via 10.0.0.10, 00:12:01, Serial0/1
10.0.0.0/8 is variably subnetted, 5 subnets, 2 masks
O IA 10.0.0.12/30 [110/909] via 10.0.0.1, 00:20:02, Serial0/0
O IA 10.0.1.0/24 [110/65] via 10.0.0.1, 00:20:02, Serial0/0
O IA 10.0.0.4/30 [110/128] via 10.0.0.1, 00:20:02, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O E2 150.3.3.0 [110/20] via 10.0.0.10, 00:19:52, Serial0/1

NOTE: As described in the ROUTE guide, filtering using distribute lists prevents the prefix from being accepted by the router and installed into the RIB; however, the Link State Advertisement (LSA) for the prefix will still be present in the Link State Database (LSDB). Consider, for example, the LSDB on R1, which still shows the LSA for the 172.16.12.0/22 prefix even though the prefix itself is filtered via the distribute-list:

R1#**show ip ospf database external**

OSPF Router with ID (1.1.1.1) (Process ID 1)

Type-5 AS External Link States

Routing Bit Set on this LSA
LS age: 1484
Options: (No TOS-capability, DC)
LS Type: AS External Link
Link State ID: 150.3.3.0 (External Network Number)
Advertising Router: 3.3.3.3
LS Seq Number: 80000001
Checksum: 0xA255
Length: 36
Network Mask: /24
Metric Type: 2 (Larger than any link state path)
TOS: 0
Metric: 20
Forward Address: 0.0.0.0
External Route Tag: 0

https://t.me/learningnets

Routing Bit Set on this LSA
LS age: 999
Options: (No TOS-capability, DC)
LS Type: AS External Link
Link State ID: 172.16.12.0 (External Network Number)
Advertising Router: 3.3.3.3
LS Seq Number: 80000002
Checksum: 0x2715
Length: 36
Network Mask: /22
Metric Type: 1 (Comparable directly to link state metric)
TOS: 0
Metric: 20
Forward Address: 0.0.0.0
External Route Tag: 3333

Task 7

This task is completed by modifying the default interface OSPF costs using the **ip ospf cost** interface configuration command. You can complete this task by increasing the cost of the R3-R1 and R3-R4 links OR lowering the cost of the R1-R2 and R2-R3 links. Either option will be ok:

R1(config)#**interface serial 0/0**
R1(config-if)#**ip ospf cost 1**
R1(config-if)#**exit**

R2(config)#**interface serial 0/0**
R2(config-if)#**ip ospf cost 1**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip ospf cost 1**
R2(config-if)#**exit**

R3(config)#**interface serial 1/1**
R3(config-if)#**ip ospf cost 1**
R3(config-if)#**exit**

Verify your configuration by looking at the routing tables of R1 and R3:

R1#**show ip route ospf**
10.0.0.0/8 is variably subnetted, 5 subnets, 2 masks
O 10.0.0.8/30 [110/2] via 10.0.0.2, 00:00:35, Serial0/0

https://t.me/learningnets
Technet24

O 10.0.0.12/30 [110/845] via 10.0.0.6, 00:15:05, Serial0/1
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/2] via 10.0.0.2, 00:00:35, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O E2 150.3.3.0 [110/20] via 10.0.0.2, 00:00:35, Serial0/0

R3#**show ip route ospf**
172.16.0.0/16 is variably subnetted, 5 subnets, 2 masks
O 172.16.12.0/22 is a summary, 00:23:36, Null0
10.0.0.0/8 is variably subnetted, 5 subnets, 2 masks
O 10.0.0.0/30 [110/2] via 10.0.0.9, 00:00:42, Serial1/1
O IA 10.0.1.0/24 [110/3] via 10.0.0.9, 00:00:42, Serial1/1
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/2] via 10.0.0.9, 00:00:42, Serial1/1

https://t.me/learningnets

CCNP Lab 027: OSPF Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand OSPF implementation and configuration in Cisco IOS routers. Additional technologies tested include Frame Relay connectivity and redistribution.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab. Also, if you are using the www.101labs.net racks, configure R3 as the Frame Relay switch using the following configuration commands:

hostname R3-Frame-Relay-Switch

https://t.me/learningnets

```
!
frame-relay switching
!
interface serial 1/0
description ‘Connected To R1 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 102 interface serial 1/1 201
frame-relay route 104 interface serial 1/2 401
no shutdown
!
interface serial 1/1
description ‘Connected To R2 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 201 interface serial 1/0 102
no shutdown
!
interface serial 1/2
description ‘Connected To R4 Serial 0/0’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 401 interface serial 1/0 104
no shutdown
!
end
```

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure the Frame Relay network so that all routers can ping each others’ WAN

https://t.me/learningnets

Technet24

interfaces. Verify your configuration by pinging the WAN interfaces of all routers from each other.

Task 3

Using interface-based configuration, configure OSPF using process ID number 1 on all routers for the Frame Relay WAN connecting routers R1, R2, and R4. Use the default network type and ensure that R1 is always elected DR even if it fails and comes back up. Verify your configuration.

Task 4

Using interface-based configuration, enable OSPF for the LAN segment connected to R1. This LAN segment should reside on OSPF area 1. No Hellos should be sent on this segment.

Task 5

Using interface-based configuration, configure OSPF using process ID number 2 on the LAN segment connected to R2 and R4. Ensure that no DR/BDR election takes place on this segment; however, ensure that multiple routers can still exist on the segment.

Task 6

Configure and perform mutual redistribution between OSPF process 1 and OSPF process 2 on routers R2 and R4. Ensure that routes from one process are not re-advertised back to the same process. You are NOT allowed to use any ACLs or IP prefix lists in your solution. Verify the configuration using the appropriate commands.

Task 7

Configure your network so that R1 prefers the path via R2 to reach the 150.5.5.0/24 subnet. In the event that R2 is down, the path via R4 should be used. Additionally, configure R4 so that it prefers the path via R2 to reach the 150.1.1.0/24 subnet. In the event that R2 is down, it should use the Frame Relay WAN connection to R1. Verify your configuration.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**

https://t.me/learningnets

R1(config-if)#**ip address 10.0.0.1 255.255.255.0**
R1(config-if)#**no shutdown**
R1(config-if)#**encapsulation frame-relay**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.5.5.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip address 10.0.0.2 255.255.255.0**
R2(config-if)#**no shutdown**
R2(config-if)#**encapsulation frame-relay**
R2(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.5.5.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.4 255.255.255.0**
R4(config-if)#**no shutdown**
R4(config-if)#**encapsulation frame-relay**
R4(config-if)#**exit**

Task 2

Although Frame Relay configuration is not a CCNP topic, per se, it is still important that you remember your Frame Relay configurations from the CCNA. The task is completed as follows:

R1(config)#**interface serial 0/1**
R1(config-if)#**frame-relay map ip 10.0.0.2 102 broadcast**
R1(config-if)#**frame-relay map ip 10.0.0.4 104 broadcast**
R1(config-if)#**exit**

On the spoke routers, because the same DLCI is being used, the **broadcast** keyword should only be specified once to avoid duplicate Broadcast packets across the Frame Relay WAN. This task is completed as follows:

R2(config)#**interface serial 0/1**

https://t.me/learningnets

Technet24

R2(config-if)#**frame-relay map ip 10.0.0.1 201 broadcast**
R2(config-if)#**frame-relay map ip 10.0.0.4 201**
R2(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**frame-relay map ip 10.0.0.1 401 broadcast**
R4(config-if)#**frame-relay map ip 10.0.0.2 401**
R4(config-if)#**exit**

Verify your Frame Relay configuration using the **show frame-relay map** command:

R1#**show frame-relay map**
Serial0/1 (up): ip 10.0.0.2 dlci 102(0x66,0x1860), static,
broadcast,
CISCO, status defined, active
Serial0/1 (up): ip 10.0.0.4 dlci 104(0x68,0x1880), static,
broadcast,
CISCO, status defined, active

R2#**show frame-relay map**
Serial0/1 (up): ip 10.0.0.1 dlci 201(0xC9,0x3090), static,
broadcast,
CISCO, status defined, active
Serial0/1 (up): ip 10.0.0.4 dlci 201(0xC9,0x3090), static,
CISCO, status defined, active

R4#**show frame-relay map**
Serial0/0 (up): ip 10.0.0.1 dlci 401(0x191,0x6410), static,
broadcast,
CISCO, status defined, active
Serial0/0 (up): ip 10.0.0.2 dlci 401(0x191,0x6410), static,
CISCO, status defined, active

Finally, verify that you can ping between all routers across the Frame Relay WAN:

R1#**ping 10.0.0.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms
R1#
R1#**ping 10.0.0.4 repeat 10**

Type escape sequence to abort.

https://t.me/learningnets

Sending 10, 100-byte ICMP Echos to 10.0.0.4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

R2#**ping 10.0.0.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.1, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms
R2#
R2#**ping 10.0.0.4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 56/59/64 ms

R4#**ping 10.0.0.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.1, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/34/52 ms
R4#
R4#**ping 10.0.0.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 56/58/60 ms

Task 3

In order to ensure that R1 is always elected DR even if it fails and comes back up, you need to disable DR/BDR election on R2 and R4 by assigning them an OSPF priority of 0. Also, when configuring OSPF on NBMA networks, you need to manually specify neighbors, even though the **broadcast** keyword has been specified for the static Frame Relay map statements:

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**neighbor 10.0.0.2**
R1(config-router)#**neighbor 10.0.0.4**
R1(config-router)#**exit**

https://t.me/learningnets

Technet24

R1(config)#**interface serial 0/1**
R1(config-if)#**ip ospf 1 area 0**
R1(config-if)#**exit**

R2(config)#**router ospf 1**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**neighbor 10.0.0.1**
R2(config-router)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip ospf 1 area 0**
R2(config-if)#**ip ospf priority 0**
R2(config-if)#**exit**

R4(config)#**router ospf 1**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**neighbor 10.0.0.1**
R4(config-router)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip ospf 1 area 0**
R4(config-if)#**ip ospf priority 0**
R4(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/DROTHER 00:01:46 10.0.0.2 Serial0/1
4.4.4.4 0 FULL/DROTHER 00:01:57 10.0.0.4 Serial0/1

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 1 FULL/DR 00:01:39 10.0.0.1 Serial0/1

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 1 FULL/DR 00:01:31 10.0.0.1 Serial0/0

Task 4

R1(config)#**router ospf 1**
R1(config-router)#**passive-interface fastethernet 0/0**
R1(config-router)#**exit**
R1(config)#**interface fastethernet 0/0**

https://t.me/learningnets

R1(config-if)#**ip ospf 1 area 1**
R1(config-if)#**exit**

Verify your configuration using the **show ip ospf <options>** commands:

R1#**show ip ospf**
Routing Process "ospf 1" with ID 1.1.1.1
Start time: 03:04:16.984, Time elapsed: 00:10:22.164

[Truncated Output]

Number of areas in this router is 2. 2 normal 0 stub 0 nssa
Number of areas transit capable is 0
External flood list length 0
Area BACKBONE(0)
Number of interfaces in this area is 1
Area has no authentication
SPF algorithm last executed 00:00:48.304 ago
SPF algorithm executed 11 times
Area ranges are
Number of LSA 6. Checksum Sum 0x033F51
Number of opaque link LSA 0. Checksum Sum 0x000000
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0
Area 1
Number of interfaces in this area is 1
Area has no authentication
SPF algorithm last executed 00:00:48.304 ago
SPF algorithm executed 2 times
Area ranges are
Number of LSA 2. Checksum Sum 0x014C32
Number of opaque link LSA 0. Checksum Sum 0x000000
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0

R1#**show ip ospf interface brief**
Interface PID Area IP Address/Mask Cost State Nbrs F/C
Se0/1 1 0 10.0.0.1/24 64 DR 2/2

https://t.me/learningnets

Technet24

Fa0/0 1 1 150.1.1.1/24 1 DR 0/0

Task 5

To prevent DR/BDR election but allow multiple routers to exist on the same multi-access segment, you need to configure a point-to-multipoint network type:

R2(config)#**router ospf 2**
R2(config-router)#**router-id 22.22.22.22**
R2(config-router)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip ospf network point-to-multipoint**
R2(config-if)#**ip ospf 2 area 0**
R2(config-if)#**exit**

R4(config)#**router ospf 2**

R4(config-router)#**router-id 44.44.44.44**

R4(config-router)#**exit**

R4(config)#**interface fastethernet 0/0**

R4(config-if)#**ip ospf network point-to-multipoint**

R4(config-if)#**ip ospf 2 area 0**

R4(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface

22.22.22.22 0 FULL/ - 00:01:48 150.5.5.2 FastEthernet0/0

1.1.1.1 1 FULL/DR 00:01:47 10.0.0.1 Serial0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
44.44.44.44 0 FULL/ - 00:01:49 150.5.5.4 FastEthernet0/0
1.1.1.1 1 FULL/DR 00:01:57 10.0.0.1 Serial0/1

Task 6

To complete this task you need to use route tags. This task is completed as follows:

R2(config)#**route-map OSPF1-INTO-OSPF2 deny 10**
R2(config-route-map)#**match tag 444**
R2(config-route-map)#**exit**
R2(config)#**route-map OSPF1-INTO-OSPF2 permit 20**

https://t.me/learningnets

```
R2(config-route-map)#set tag 222
R2(config-route-map)#exit
R2(config)#route-map OSPF2-INTO-OSPF1 deny 10
R2(config-route-map)#match tag 444
R2(config-route-map)#exit
R2(config)#route-map OSPF2-INTO-OSPF1 permit 20
R2(config-route-map)#set tag 222
R2(config-route-map)#exit
R2(config)#router ospf 1
R2(config-router)#redistribute ospf 2 subnets route-map OSPF2-INTO-OSPF1
R2(config-router)#exit
R2(config)#router ospf 2
R2(config-router)#redistribute ospf 1 subnets route-map OSPF1-INTO-OSPF2
R2(config-router)#exit
```

```
R4(config)#route-map OSPF1-INTO-OSPF2 deny 10
R4(config-route-map)#match tag 222
R4(config-route-map)#exit
R4(config)#route-map OSPF1-INTO-OSPF2 permit 20
R4(config-route-map)#set tag 444
R4(config-route-map)#exit
R4(config)#route-map OSPF2-INTO-OSPF1 deny 10
R4(config-route-map)#match tag 222
R4(config-route-map)#exit
R4(config)#route-map OSPF2-INTO-OSPF1 permit 20
R4(config-route-map)#set tag 444
R4(config-route-map)#exit
R4(config)#router ospf 1
R4(config-router)#redistribute ospf 2 subnets route-map OSPF2-INTO-OSPF1
R4(config-router)#exit
R4(config)#router ospf 2
R4(config-router)#redistribute ospf 1 subnets route-map OSPF1-INTO-OSPF2
R4(config-router)#exit
```

While this configuration seems complex, it is actually quite simple. The logic is as follows:

When OSPF process ID 1 on R2 redistributes routes from OSPF process ID 2, it denies all routes with an administrative route tag of 444. This tag is specified when OSPF process ID 2 on R4 redistributes OSPF process ID 1 routes. This prevents R2 from re-advertising these same routes back across the Frame Relay WAN. After denying these

https://t.me/learningnets

routes, OSPF process ID 1 on R2 accepts all other routes and sets an administrative tag of 222 for those routes.

When those routes are received by R4 via the Frame Relay WAN, they are denied by OSPF process ID 2 on R4, again preventing those same routes from being re-advertised across the LAN between R2 and R4. The same logic works in the reverse direction.

Verify your configuration by looking at the Link State Database on all routers in the network:

R1#**show ip ospf database**

OSPF Router with ID (1.1.1.1) (Process ID 1)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
1.1.1.1 1.1.1.1 89 0x80000004 0x00DBF5 1
2.2.2.2 2.2.2.2 900 0x80000003 0x00A226 1
4.4.4.4 4.4.4.4 191 0x80000004 0x002491 1
150.5.5.2 150.5.5.2 2459 0x80000002 0x00672F 1

Net Link States (Area 0)

Link ID ADV Router Age Seq# Checksum
10.0.0.1 1.1.1.1 341 0x80000008 0x007E85

Summary Net Link States (Area 0)

Link ID ADV Router Age Seq# Checksum
150.1.1.0 1.1.1.1 89 0x80000002 0x00B6E7

Router Link States (Area 1)

Link ID ADV Router Age Seq# Checksum Link count
1.1.1.1 1.1.1.1 89 0x80000002 0x00DEB0 1

Summary Net Link States (Area 1)

Link ID ADV Router Age Seq# Checksum
10.0.0.0 1.1.1.1 91 0x80000002 0x006984

Summary ASB Link States (Area 1)

Link ID ADV Router Age Seq# Checksum
2.2.2.2 1.1.1.1 896 0x80000001 0x00836C
4.4.4.4 1.1.1.1 299 0x80000001 0x0027C0

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.5.5.0 2.2.2.2 558 0x80000002 0x007DAD 222

https://t.me/learningnets

150.5.5.0 4.4.4.4 304 0x80000001 0x00ED57 444
150.5.5.2 4.4.4.4 304 0x80000001 0x00D969 444
150.5.5.4 2.2.2.2 558 0x80000002 0x0055D1 222

R2#**show ip ospf database**

OSPF Router with ID (22.22.22.22) (Process ID 2)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
22.22.22.22 22.22.22.22 916 0x80000003 0x00D6A2 2
44.44.44.44 44.44.44.44 336 0x80000003 0x00A17B 2

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
10.0.0.0 22.22.22.22 597 0x80000002 0x0032FF 222
10.0.0.0 44.44.44.44 336 0x80000001 0x0048B3 444
150.1.1.0 22.22.22.22 597 0x80000002 0x0002A0 222
150.1.1.0 44.44.44.44 336 0x80000001 0x001854 444

OSPF Router with ID (2.2.2.2) (Process ID 1)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
1.1.1.1 1.1.1.1 123 0x80000004 0x00DBF5 1
2.2.2.2 2.2.2.2 933 0x80000003 0x00A226 1
4.4.4.4 4.4.4.4 228 0x80000004 0x002491 1
150.5.5.2 150.5.5.2 2495 0x80000002 0x00672F 1

Net Link States (Area 0)

Link ID ADV Router Age Seq# Checksum
10.0.0.1 1.1.1.1 377 0x80000008 0x007E85

Summary Net Link States (Area 0)

Link ID ADV Router Age Seq# Checksum
150.1.1.0 1.1.1.1 125 0x80000002 0x00B6E7

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.5.5.0 2.2.2.2 590 0x80000002 0x007DAD 222
150.5.5.0 4.4.4.4 339 0x80000001 0x00ED57 444
150.5.5.2 4.4.4.4 339 0x80000001 0x00D969 444
150.5.5.4 2.2.2.2 590 0x80000002 0x0055D1 222

https://t.me/learningnets

Technet24

R4#**show ip ospf database**

OSPF Router with ID (44.44.44.44) (Process ID 2)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
22.22.22.22 22.22.22.22 942 0x80000003 0x00D6A2 2
44.44.44.44 44.44.44.44 361 0x80000003 0x00A17B 2

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
10.0.0.0 22.22.22.22 624 0x80000002 0x0032FF 222
10.0.0.0 44.44.44.44 360 0x80000001 0x0048B3 444
150.1.1.0 22.22.22.22 623 0x80000002 0x0002A0 222
150.1.1.0 44.44.44.44 360 0x80000001 0x001854 444

OSPF Router with ID (4.4.4.4) (Process ID 1)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
1.1.1.1 1.1.1.1 149 0x80000004 0x00DBF5 1
2.2.2.2 2.2.2.2 960 0x80000003 0x00A226 1
4.4.4.4 4.4.4.4 252 0x80000004 0x002491 1
150.5.5.2 150.5.5.2 2520 0x80000002 0x00672F 1

Net Link States (Area 0)

Link ID ADV Router Age Seq# Checksum
10.0.0.1 1.1.1.1 403 0x80000008 0x007E85

Summary Net Link States (Area 0)

Link ID ADV Router Age Seq# Checksum
150.1.1.0 1.1.1.1 151 0x80000002 0x00B6E7

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.5.5.0 2.2.2.2 618 0x80000002 0x007DAD 222
150.5.5.0 4.4.4.4 362 0x80000001 0x00ED57 444
150.5.5.2 4.4.4.4 362 0x80000001 0x00D969 444
150.5.5.4 2.2.2.2 618 0x80000002 0x0055D1 222

Task 7

While the first option that might come to mind might be specifying costs using the **neighbor** command, keep in mind that you cannot specify cost when using the default

https://t.me/learningnets

NBMA network type. If you do attempt to do so, you will receive the following error message:

R1(config)#**router ospf 1**
R1(config-router)#**neighbor 10.0.0.2 cost 10**
R1(config-router)#
*May 10 06:59:25.183: %OSPF-4-CFG_NBR_INVAL_NBMA_OPT: Can not use configured neighbor: cost and database-filter options are allowed only for a point-to-multipoint network

Prior to any configuration changes, the routing table on R1 shows the following entries:

R1#**show ip route ospf**
150.5.0.0/16 is variably subnetted, 3 subnets, 2 masks
O E2 150.5.5.4/32 [110/1] via 10.0.0.2, 00:24:53, Serial0/1
O E2 150.5.5.2/32 [110/1] via 10.0.0.4, 00:24:53, Serial0/1
O E2 150.5.5.0/24 [110/1] via 10.0.0.4, 00:24:53, Serial0/1
[110/1] via 10.0.0.2, 00:24:53, Serial0/1

To complete this task, you need to modify redistribution metrics. The most simple way is to increment the redistribution metric configured on R4:

R4(config)#**router ospf 1**
R4(config-router)#**redis ospf 2 su route-ma OSPF2-INTO-OSPF1 met 4**
R4(config-router)#**end**
R4#**clear ip ospf redistribution**

Following this change, the routing table on R1 now shows the following entries:

R1#**show ip route ospf**
150.5.0.0/16 is variably subnetted, 3 subnets, 2 masks
O E2 150.5.5.4/32 [110/1] via 10.0.0.2, 00:27:18, Serial0/1
O E2 150.5.5.2/32 [110/4] via 10.0.0.4, 00:00:19, Serial0/1
O E2 150.5.5.0/24 [110/1] via 10.0.0.2, 00:00:19, Serial0/1

To complete the second part of this task, you need to modify default administrative distance values. You cannot use the cost because the route via the Frame Relay WAN is internal and while the route via the LAN is external. Internal will always be preferred over external. This task is completed by modifying the OSPF process ID 2s administrative distance on R4. Prior to configuration changes, the routing table on R4 shows the following entries:

R4#**show ip route ospf**
150.1.0.0/24 is subnetted, 1 subnets
O IA 150.1.1.0 [110/65] via 10.0.0.1, 00:04:41, Serial0/0

https://t.me/learningnets

Technet24

150.5.0.0/16 is variably subnetted, 2 subnets, 2 masks
O 150.5.5.2/32 [110/1] via 150.5.5.2, 00:29:22, FastEthernet0/0

This task is completed as follows:

R4(config)#**router ospf 2**
R4(config-router)#**distance ospf external 100**
R4(config-router)#**exit**

Following this change, the routing table on R4 shows the following entries:

R4#**show ip route ospf**
150.1.0.0/24 is subnetted, 1 subnets
O E2 150.1.1.0 [100/65] via 150.5.5.2, 00:00:42, FastEthernet0/0
150.5.0.0/16 is variably subnetted, 2 subnets, 2 masks
O 150.5.5.2/32 [110/1] via 150.5.5.2, 00:00:42, FastEthernet0/0

https://t.me/learningnets

CCNP Lab 028: OSPF Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand OSPF implementation and configuration in Cisco IOS routers. Additional technologies tested include Frame Relay connectivity and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab. Also, if you are using the www.101labs.net racks, configure R3 as the Frame Relay switch using the following configuration commands:

hostname R3-Frame-Relay-Switch
!

https://t.me/learningnets

```
frame-relay switching
!
interface serial 1/0
description ‘Connected To R1 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 102 interface serial 1/1 201
frame-relay route 104 interface serial 1/2 401
no shutdown
!
interface serial 1/1
description ‘Connected To R2 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 201 interface serial 1/0 102
no shutdown
!
interface serial 1/2
description ‘Connected To R4 Serial 0/0’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 401 interface serial 1/0 104
no shutdown
!
end
```

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure the Frame Relay network so that all routers can ping each others’ WAN interfaces.

https://t.me/learningnets

Technet24

Task 3

Using interface-based configuration, configure OSPF area 0 on the Frame Relay WAN between R1, R2, and R4. Configure OSPF so that there is no DR/BDR election held over the Frame Relay WAN. Ensure that OSPF uses ONLY Unicast packets and not Multicast packets over the Frame Relay WAN. Verify your configuration using the appropriate commands.

Task 4

Advertise the 150.1.1.0/24 subnet connected to the LAN segment on R1 via OSPF. This subnet should be advertised as a Type 1 External LSA with a route tag of 111 and a metric of 111.

Task 5

Using interface-based configuration, configure OSPF area 1 on the LAN between R2 and R4. In your configuration, ensure that R2 is elected master during the DBD exchange; however, R4 should be elected as the DR for the segment. Verify your configuration using the appropriate commands and debugs.

Task 6

Configure OSPF so that R1 prefers the path via R2 to reach the 150.5.5.0/24 subnet. If this path is unavailable, the path via R4 should be used. Verify your configuration.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.1 255.255.255.0**
R1(config-if)#**no shutdown**
R1(config-if)#**encapsulation frame-relay**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.5.5.2 255.255.255.0**
R2(config-if)#**exit**

https://t.me/learningnets

R2(config)#**interface serial 0/1**
R2(config-if)#**ip address 10.0.0.2 255.255.255.0**
R2(config-if)#**no shutdown**
R2(config-if)#**encapsulation frame-relay**
R2(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**ip address 150.5.5.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.4 255.255.255.0**
R4(config-if)#**no shutdown**
R4(config-if)#**encapsulation frame-relay**
R4(config-if)#**exit**

Task 2

Although Frame Relay configuration is not a CCNP topic, per se, it is still important that you remember your Frame Relay configurations from the CCNA. The task is completed as follows:

R1(config)#**interface serial 0/1**
R1(config-if)#**frame-relay map ip 10.0.0.2 102 broadcast**
R1(config-if)#**frame-relay map ip 10.0.0.4 104 broadcast**
R1(config-if)#**exit**

On the spoke routers, because the same DLCI is being used, the **broadcast** keyword should only be specified once to avoid duplicate Broadcast packets across the Frame Relay WAN. This task is completed as follows:

R2(config)#**interface serial 0/1**
R2(config-if)#**frame-relay map ip 10.0.0.1 201 broadcast**
R2(config-if)#**frame-relay map ip 10.0.0.4 201**
R2(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**frame-relay map ip 10.0.0.1 401 broadcast**
R4(config-if)#**frame-relay map ip 10.0.0.2 401**
R4(config-if)#**exit**

Verify your Frame Relay configuration using the **show frame-relay map** command:

R1#**show frame-relay map**

https://t.me/learningnets

Technet24

Serial0/1 (up): ip 10.0.0.2 dlci 102(0x66,0x1860), static,
broadcast,
CISCO, status defined, active
Serial0/1 (up): ip 10.0.0.4 dlci 104(0x68,0x1880), static,
broadcast,
CISCO, status defined, active

R2#**show frame-relay map**
Serial0/1 (up): ip 10.0.0.1 dlci 201(0xC9,0x3090), static,
broadcast,
CISCO, status defined, active
Serial0/1 (up): ip 10.0.0.4 dlci 201(0xC9,0x3090), static,
CISCO, status defined, active

R4#**show frame-relay map**
Serial0/0 (up): ip 10.0.0.1 dlci 401(0x191,0x6410), static,
broadcast,
CISCO, status defined, active
Serial0/0 (up): ip 10.0.0.2 dlci 401(0x191,0x6410), static,
CISCO, status defined, active

Finally, verify that you can ping between all routers across the Frame Relay WAN:

R1#**ping 10.0.0.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms
R1#
R1#**ping 10.0.0.4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

R2#**ping 10.0.0.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.1, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms
R2#

https://t.me/learningnets

R2#**ping 10.0.0.4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 56/59/64 ms

R4#**ping 10.0.0.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.1, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/34/52 ms
R4#
R4#**ping 10.0.0.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 56/58/60 ms

Task 3

To ensure that there is no DR/BDR election and allow OSPF to use Unicast and not Multicast packets, you need to specify a point-to-multipoint non-broadcast network type. This network type requires the static configuration of neighbors, which exchange updates using Unicast versus Multicast. This task is completed as follows:

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**neighbor 10.0.0.2**
R1(config-router)#**neighbor 10.0.0.4**
R1(config-router)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip ospf network point-to-multipoint non-broadcast**
R1(config-if)#**ip ospf 1 area 0**
R1(config-if)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**neighbor 10.0.0.1**
R2(config-router)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip ospf network point-to-multipoint non-broadcast**

https://t.me/learningnets

Technet24

R2(config-if)#**ip ospf 2 area 0**
R2(config-if)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**neighbor 10.0.0.1**
R4(config-router)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip ospf network point-to-multipoint non-broadcast**
R4(config-if)#**ip ospf 4 area 0**
R4(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:01:59 10.0.0.4 Serial0/1
2.2.2.2 0 FULL/ - 00:01:54 10.0.0.2 Serial0/1

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:01:57 10.0.0.1 Serial0/1

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:01:54 10.0.0.1 Serial0/0

Task 4

R1(config)#**router ospf 1**
R1(config-router)#**redis connected subnets metric-type 1 metric 111 tag 111**
R1(config-router)#**exit**

Verify your configuration by looking at the external LSA for the 150.1.1.0/24 subnet:

R1#**show ip ospf database external 150.1.1.0**

OSPF Router with ID (1.1.1.1) (Process ID 1)

Type-5 AS External Link States

LS age: 37
Options: (No TOS-capability, DC)
LS Type: AS External Link
Link State ID: 150.1.1.0 (External Network Number)
Advertising Router: 1.1.1.1

https://t.me/learningnets

LS Seq Number: 80000001
Checksum: 0xF0C8
Length: 36
Network Mask: /24
Metric Type: 1 (Comparable directly to link state metric)
TOS: 0
Metric: 111
Forward Address: 0.0.0.0
External Route Tag: 111

Task 5

The OSPF master/slave election process is based solely on the IP address (the highest wins), while the DR/BDR election process is based on priority or IP address. To ensure that R2 is elected master during the database exchange process, it needs to be configured with a higher IP address. To ensure that R4 is elected DR, it needs to be configured with a higher priority. This task is completed as follows:

R2(config)#**router ospf 2**
R2(config-router)#**router-id 22.22.22.22**
Reload or use "clear ip ospf process" command, for this to take effect
R2(config-router)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip ospf 2 area 1**
R2(config-if)#**end**
R2#**clear ip ospf process**
Reset ALL OSPF processes? [no]: **yes**

R4(config)#**interface fastethernet 0/0**

R4(config-if)#**ip ospf 4 area 1**

R4(config-if)#**ip ospf priority 4**

R4(config-if)#**end**

R4#**clear ip ospf process**

Reset ALL OSPF processes? [no]: **yes**

You can verify the master/slave and DR/BDR election process using the **debug ip ospf adj** command on either R2 or R4 after resetting the adjacency:

R2#**debug ip ospf adj**

OSPF adjacency events debugging is on

R2#**clear ip ospf process**

https://t.me/learningnets

Technet24

Reset ALL OSPF processes? [no]: **yes**

R2#

R2#

R2#

R2#

[Truncated Output]

*May 10 08:24:58.678: OSPF: DR/BDR election on FastEthernet0/0

***May 10 08:24:58.678: OSPF: Elect BDR 22.22.22.22**

***May 10 08:24:58.678: OSPF: Elect DR 4.4.4.4**

***May 10 08:24:58.678: OSPF: Elect BDR 22.22.22.22**

***May 10 08:24:58.678: OSPF: Elect DR 4.4.4.4**

***May 10 08:24:58.678: DR: 4.4.4.4 (Id) BDR: 22.22.22.22 (Id)**

*May 10 08:24:58.678: OSPF: Send DBD to 4.4.4.4 on FastEthernet0/0 seq 0x7B5 opt 0x52 flag 0x7 len 32

*May 10 08:24:58.686: OSPF: Rcv DBD from 4.4.4.4 on FastEthernet0/0 seq 0x3C6 opt 0x52 flag 0x7 len 32 mtu 1500 state EXSTART

***May 10 08:24:58.686: OSPF: First DBD and we are not SLAVE**

***May 10 08:24:58.686: OSPF: Rcv DBD from 4.4.4.4 on FastEthernet0/0 seq 0x7B5 opt 0x52 flag 0x2 len 172 mtu 1500 state EXSTART**

***May 10 08:24:58.686: OSPF: NBR Negotiation Done. We are the MASTER**

[Truncated Output]

Task 6

Unlike in the previous lab, in this lab you can specify a per-neighbor cost because of the point-to-multipoint non-broadcast network type. Prior to any changes being made to the current OSPF routing configuration, the routing table on router R1 shows the following route entries:

R1#**show ip ro ospf**
10.0.0.0/8 is variably subnetted, 3 subnets, 2 masks
O 10.0.0.2/32 [110/64] via 10.0.0.2, 00:05:13, Serial0/1
O 10.0.0.4/32 [110/64] via 10.0.0.4, 00:05:13, Serial0/1
150.5.0.0/24 is subnetted, 1 subnets
O IA 150.5.5.0 [110/65] via 10.0.0.4, 00:05:13, Serial0/1
[110/65] via 10.0.0.2, 00:05:13, Serial0/1

https://t.me/learningnets

Complete this task by either decreasing the cost of neighbor R2 to a value less than 64:

R1(config)#**router ospf 1**
R1(config-router)#**neighbor 10.0.0.2 cost 1**
R1(config-router)#**exit**

Following this change, the routing table on R1 now shows the following route entries:

R1#**show ip route ospf**
10.0.0.0/8 is variably subnetted, 3 subnets, 2 masks
O 10.0.0.2/32 [110/1] via 10.0.0.2, 00:00:47, Serial0/1
O 10.0.0.4/32 [110/64] via 10.0.0.4, 00:00:47, Serial0/1
150.5.0.0/24 is subnetted, 1 subnets
O IA 150.5.5.0 [110/2] via 10.0.0.2, 00:00:47, Serial0/1

https://t.me/learningnets

Technet24

CCNP Lab 029: OSPF Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand OSPF implementation and configuration in Cisco IOS routers. Additional technologies tested include path control and backbone connectivity.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab. Also, if you are using the www.101labs.net racks, configure R3 as the Frame Relay switch using the following configuration commands:

https://t.me/learningnets

Technet24

```
hostname R3-Frame-Relay-Switch
!
frame-relay switching
!
interface serial 1/0
description ‘Connected To R1 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 102 interface serial 1/1 201
frame-relay route 104 interface serial 1/2 401
no shutdown
!
interface serial 1/1
description ‘Connected To R2 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 201 interface serial 1/0 102
no shutdown
!
interface serial 1/2
description ‘Connected To R4 Serial 0/0’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 401 interface serial 1/0 104
no shutdown
!
end
```

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Configure the Frame Relay network so that all routers can ping each others' WAN interfaces.

Task 3

Using interface-based configuration, configure OSPF over the Frame Relay WAN connectivity R1, R2, and R4, as well as on the LAN segment connected to R1. Ensure that there is no DR/BDR election on the WAN segment. Also, ensure that no Hellos or LSAs are flooded out of the LAN segment. Finally, ensure that OSPF uses Multicast packets when sending updates over the WAN. Verify your configuration using the appropriate commands.

Task 4

Configure the 192.168.0.0/24 subnet on the LAN segment between R2 and R4. In addition, also configure a secondary IP subnet of 192.168.1.0/24 on the LAN segment between R2 and R4. Using interface-based configuration, configure OSPF area 1 on the LAN segment between R1 and R2. Ensure that both the primary 192.168.0.0/24 and secondary 192.168.1.0/24 subnets are advertised as internal OSPF routes. Verify that R1 can ping both subnets.

Task 5

Without modifying any interface bandwidth or cost values, or default administrative distance values, configure OSPF so that R1 prefers the path via R2 to reach the 192.168.0.0/24 and prefers the path via R4 to reach the 192.168.1.0/24 subnet. Verify your path control configuration using the appropriate commands.

Task 6

Configure OSPF so that R1 and R2 establish an OSPF adjacency in area 5. Do NOT enable OSPF for the point-to-point link, i.e. the 10.0.1.0/30 subnet, between R1 and R2. Implement your configuration so that when the Frame Relay network is unavailable, the 192.168.0.0/24 and the 192.168.1.0/24 subnets can still communicate with the 150.1.1.0/24 subnet. Verify your OSPF configuration using the appropriate commands.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**

https://t.me/learningnets

R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.1.1 255.255.255.252**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.1 255.255.255.0**
R1(config-if)#**no shutdown**
R1(config-if)#**encapsulation frame-relay**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.5.5.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.1.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip address 10.0.0.2 255.255.255.0**
R2(config-if)#**no shutdown**
R2(config-if)#**encapsulation frame-relay**
R2(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip address 150.5.5.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.4 255.255.255.0**
R4(config-if)#**no shutdown**
R4(config-if)#**encapsulation frame-relay**
R4(config-if)#**exit**

Task 2

Although Frame Relay configuration is not a CCNP topic, per se, it is still important that you remember your Frame Relay configurations from the CCNA. The task is completed as follows:

R1(config)#**interface serial 0/1**

https://t.me/learningnets

R1(config-if)#**frame-relay map ip 10.0.0.2 102 broadcast**
R1(config-if)#**frame-relay map ip 10.0.0.4 104 broadcast**
R1(config-if)#**exit**

On the spoke routers, because the same DLCI is being used, the **broadcast** keyword should only be specified once to avoid duplicate Broadcast packets across the Frame Relay WAN. This task is completed as follows:

R2(config)#**interface serial 0/1**
R2(config-if)#**frame-relay map ip 10.0.0.1 201 broadcast**
R2(config-if)#**frame-relay map ip 10.0.0.4 201**
R2(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**frame-relay map ip 10.0.0.1 401 broadcast**
R4(config-if)#**frame-relay map ip 10.0.0.2 401**
R4(config-if)#**exit**

Verify your Frame Relay configuration using the **show frame-relay map** command:

R1#**show frame-relay map**
Serial0/1 (up): ip 10.0.0.2 dlci 102(0x66,0x1860), static,
broadcast,
CISCO, status defined, active
Serial0/1 (up): ip 10.0.0.4 dlci 104(0x68,0x1880), static,
broadcast,
CISCO, status defined, active

R2#**show frame-relay map**
Serial0/1 (up): ip 10.0.0.1 dlci 201(0xC9,0x3090), static,
broadcast,
CISCO, status defined, active
Serial0/1 (up): ip 10.0.0.4 dlci 201(0xC9,0x3090), static,
CISCO, status defined, active

R4#**show frame-relay map**
Serial0/0 (up): ip 10.0.0.1 dlci 401(0x191,0x6410), static,
broadcast,
CISCO, status defined, active
Serial0/0 (up): ip 10.0.0.2 dlci 401(0x191,0x6410), static,
CISCO, status defined, active

Finally, verify that you can ping between all routers across the Frame Relay WAN:

R1#**ping 10.0.0.2 repeat 10**

https://t.me/learningnets

Technet24

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms
R1#
R1#**ping 10.0.0.4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

R2#**ping 10.0.0.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.1, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms
R2#
R2#**ping 10.0.0.4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 56/59/64 ms

R4#**ping 10.0.0.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.1, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/34/52 ms
R4#
R4#**ping 10.0.0.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 10.0.0.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 56/58/60 ms

Task 3

To complete this task, you need to configure a point-to-multipoint network type. This will allow OSPF to use Multicast but prevent DR/BDR election. This task is completed as follows:

https://t.me/learningnets

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**passive-interface fastethernet 0/0**
R1(config-router)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip ospf 1 area 0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip ospf network point-to-multipoint**
R1(config-if)#**ip ospf 1 area 0**
R1(config-if)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip ospf network point-to-multipoint**
R2(config-if)#**ip ospf 2 area 0**
R2(config-if)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip ospf network point-to-multipoint**
R4(config-if)#**ip ospf 4 area 0**
R4(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:01:59 10.0.0.4 Serial0/1
2.2.2.2 0 FULL/ - 00:01:40 10.0.0.2 Serial0/1

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:01:33 10.0.0.1 Serial0/1

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:01:40 10.0.0.1 Serial0/0

https://t.me/learningnets

Task 4

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip address 192.168.0.2 255.255.255.0**
R2(config-if)#**ip address 192.168.1.2 255.255.255.0 secondary**
R2(config-if)#**ip ospf 2 area 1**
R2(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip address 192.168.0.4 255.255.255.0**
R4(config-if)#**ip address 192.168.1.4 255.255.255.0 secondary**
R4(config-if)#**ip ospf 4 area 1**
R4(config-if)#**exit**

Verify OSPF configuration using the **show ip ospf neighbor** command:

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:01:34 10.0.0.1 Serial0/1
4.4.4.4 1 FULL/BDR 00:00:34 192.168.0.4 FastEthernet0/0

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:01:58 10.0.0.1 Serial0/0
2.2.2.2 1 FULL/DR 00:00:38 192.168.0.2 FastEthernet0/0

Finally, verify that R1 has two routes to these subnets and can ping them both:

R1#**show ip route ospf**
10.0.0.0/8 is variably subnetted, 3 subnets, 2 masks
O 10.0.0.2/32 [110/64] via 10.0.0.2, 00:01:03, Serial0/1
O 10.0.0.4/32 [110/64] via 10.0.0.4, 00:01:03, Serial0/1
O IA 192.168.0.0/24 [110/65] via 10.0.0.4, 00:01:03, Serial0/1
[110/65] via 10.0.0.2, 00:01:03, Serial0/1
O IA 192.168.1.0/24 [110/65] via 10.0.0.4, 00:01:03, Serial0/1
[110/65] via 10.0.0.2, 00:01:03, Serial0/1

R1#**ping 192.168.0.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.0.0, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

R1#**ping 192.168.1.0**

https://t.me/learningnets

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.1.0, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

Task 5

To complete this task you need to think outside the box and use the **area <area> range** command. This command allows you to directly specify the cost of the advertised summary route. Prior to any routing changes, R1 shows the following route entries:

R1#**show ip route ospf**
10.0.0.0/8 is variably subnetted, 3 subnets, 2 masks
O 10.0.0.2/32 [110/64] via 10.0.0.2, 00:01:03, Serial0/1
O 10.0.0.4/32 [110/64] via 10.0.0.4, 00:01:03, Serial0/1
O IA 192.168.0.0/24 [110/65] via 10.0.0.4, 00:01:03, Serial0/1
[110/65] via 10.0.0.2, 00:01:03, Serial0/1
O IA 192.168.1.0/24 [110/65] via 10.0.0.4, 00:01:03, Serial0/1
[110/65] via 10.0.0.2, 00:01:03, Serial0/1

This task is completed as follows:

R2(config)#**router ospf 2**
R2(config-router)#**area 1 range 192.168.0.0 255.255.255.0 cost 1**
R2(config-router)#**area 1 range 192.168.1.0 255.255.255.0 cost 5**
R2(config-router)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**area 1 range 192.168.0.0 255.255.255.0 cost 5**
R4(config-router)#**area 1 range 192.168.1.0 255.255.255.0 cost 1**
R4(config-router)#**exit**
Following this configuration, the routing table on R1 shows the following entries:

R1#**show ip route ospf**
10.0.0.0/8 is variably subnetted, 3 subnets, 2 masks
O 10.0.0.2/32 [110/64] via 10.0.0.2, 00:01:58, Serial0/1
O 10.0.0.4/32 [110/64] via 10.0.0.4, 00:01:58, Serial0/1
O IA 192.168.0.0/24 [110/65] via 10.0.0.2, 00:01:58, Serial0/1
O IA 192.168.1.0/24 [110/65] via 10.0.0.4, 00:01:35, Serial0/1

Task 6

The requirements for this task are two-fold. First, you must enable OSPF across the WAN link between R1 and R2 without explicitly enabling it for the 10.0.1.0/30 subnet. To do so, you should configure a GRE tunnel between the two routers. This task is

https://t.me/learningnets
Technet24

completed as follows:

R1(config)#**interface tunnel 0**
R1(config-if)#**ip address 200.0.0.1 255.255.255.252**
R1(config-if)#**ip ospf 1 area 5**
R1(config-if)#**tunnel source serial 0/0**
R1(config-if)#**tunnel destination 10.0.1.2**
R1(config-if)#**exit**

R2(config)#**interface tunnel 0**
R2(config-if)#**ip address 200.0.0.2 255.255.255.252**
R2(config-if)#**ip ospf 2 area 5**
R2(config-if)#**tunnel source serial 0/0**
R2(config-if)#**tunnel destination 10.0.1.1**
R2(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:01:58 10.0.0.4 Serial0/1
2.2.2.2 0 FULL/ - 00:01:57 10.0.0.2 Serial0/1
2.2.2.2 0 FULL/ - 00:00:34 200.0.0.2 Tunnel0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:01:54 10.0.0.1 Serial0/1
4.4.4.4 1 FULL/BDR 00:00:38 192.168.0.4 FastEthernet0/0
1.1.1.1 0 FULL/ - 00:00:32 200.0.0.1 Tunnel0

The second part of this task requires that you configure a virtual link so that when the Frame Relay WAN is down, area 1 still has a logical connection to the backbone. If you do not configure a virtual link, routing will 'break' when the Frame Relay WAN fails. This task is completed as follows:

R1(config)#**router ospf 1**
R1(config-router)#**area 5 virtual-link 2.2.2.2**
R1(config-router)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**area 5 virtual-link 1.1.1.1**
R2(config-router)#**exit**

Verify your configuration using the **show ip ospf virtual-links** command:

https://t.me/learningnets

R1#**show ip ospf virtual-links**
Virtual Link OSPF_VL0 to router 2.2.2.2 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 5, via interface Tunnel0, Cost of using 11111
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:02
Adjacency State FULL (Hello suppressed)
Index 3/4, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec

Finally, test your configuration by shutting down the Frame Relay interface on R1:

R1(config)#**interface serial 0/1**
R1(config-if)#**shutdown**
R1(config-if)#**exit**
R1(config)#**do show ip route ospf**
10.0.0.0/8 is variably subnetted, 2 subnets, 2 masks
O 10.0.0.2/32 [110/11111] via 200.0.0.2, 00:00:03, Tunnel0
O IA 192.168.0.0/24 [110/11112] via 200.0.0.2, 00:00:03, Tunnel0
O IA 192.168.1.0/24 [110/11116] via 200.0.0.2, 00:00:03, Tunnel0

https://t.me/learningnets

Technet24

CCNP Lab 030: OSPF Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand OSPF implementation and configuration in Cisco IOS routers. Additional technologies tested include Stub/NSSA areas and route and LSA filtering.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no
Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

https://t.me/learningnets

Technet24

Task 2

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF as illustrated in the topology. All areas should be configured as normal OSPF areas EXCEPT for area 4, which should be configured as an NSSA. Verify your configuration using the appropriate commands.

Task 3

Configure the following static routes on R4 and redistribute them as Type 1 External routes:

192.168.1.0/24 via 150.4.4.254
192.168.2.0/24 via 150.4.4.254

Next, configure your OSPF network so that the forward address in the Type 5 LSAs indicates that traffic should be sent to R3 (ASBR Type 5 LSAs) and NOT to R4 (ASBR Type 7 LSAs). In other words, ensure that the forward address of the Type 5 LSAs is set to 0.0.0.0. Verify your configuration using the appropriate commands.

Task 4

Configure a Loopback11 interface on R1 with the IP address 11.11.11.11/32. Redistribute this interface into OSPF using default metric type and metric values. Following the route redistribution, configure OSPF so that all routers are able to ping this subnet from their LAN subnets, i.e. from their 150.x.x.x addresses. Verify your configuration.

Task 5

Configure OSPF so that the 150.3.3.0/24 subnet connected to R3s LAN segment and as well as the 150.4.4.0/24 subnet connected to R4s LAN segment are not advertised to any other area. Do NOT use any ACL or prefix-list based filtering methods when implementing this solution. However, ensure that R1 and R2 are still able to ping 150.3.3.3 as well as 150.4.4.4. Verify your configuration using the appropriate commands.

Task 6

Configure OSPF so that the 150.1.1.0/24 and 150.2.2.0/24 subnets are NOT advertised only to area 3. They should still be advertised to other areas. Do NOT use any distribute-lists when completing this task. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

https://t.me/learningnets

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**
R1(config-if)#**no shutdown**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**no shutdown**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip address 150.3.3.3 255.255.255.0**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**ip address 10.0.0.6 255.255.255.252**
R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**

https://t.me/learningnets

R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip address 150.4.4.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**no shutdown**
R4(config-if)#**exit**

Task 2

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**network 10.0.0.1 0.0.0.0 area 2**
R1(config-router)#**network 10.0.0.5 0.0.0.0 area 3**
R1(config-router)#**network 150.1.1.1 0.0.0.0 area 2**
R1(config-router)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**network 10.0.0.2 0.0.0.0 area 2**
R2(config-router)#**network 10.0.0.9 0.0.0.0 area 0**
R2(config-router)#**network 150.2.2.2 0.0.0.0 area 2**
R2(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**network 10.0.0.6 0.0.0.0 area 3**
R3(config-router)#**network 10.0.0.10 0.0.0.0 area 0**
R3(config-router)#**network 10.0.0.13 0.0.0.0 area 4**
R3(config-router)#**network 150.3.3.3 0.0.0.0 area 0**
R3(config-router)#**area 4 nssa**
R3(config-router)#**exit**

https://t.me/learningnets

R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**network 150.4.4.4 0.0.0.0 area 4**
R4(config-router)#**network 10.0.0.14 0.0.0.0 area 4**
R4(config-router)#**area 4 nssa**
R4(config-router)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:30 10.0.0.2 Serial0/0
3.3.3.3 0 FULL/ - 00:00:29 10.0.0.6 Serial0/1

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:36 10.0.0.10 Serial0/1
1.1.1.1 0 FULL/ - 00:00:37 10.0.0.1 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:38 10.0.0.9 Serial1/1
1.1.1.1 0 FULL/ - 00:00:38 10.0.0.5 Serial1/0
4.4.4.4 0 FULL/ - 00:00:33 10.0.0.14 Serial1/2

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:36 10.0.0.13 Serial0/0

Task 3

The first part of this task is straightforward and is completed as follows:

R4(config)#**ip route 192.168.1.0 255.255.255.255 150.4.4.254**
R4(config)#**ip route 192.168.2.0 255.255.255.255 150.4.4.254**
R4(config)#**router ospf 4**
R4(config-router)#**redistribute static subnets metric-type 1**
R4(config-router)#**exit**

The second part of this task requires some additional thought. By default, the forward address of the external LSAs will be set to 0.0.0.0, meaning traffic should be forwarded to the ASBR, unless the next hop IP address is included in network statement configuration, i.e. is advertised by OSPF. This can be verified by checking the Link State Database (LSDB) on R1 or R3:

https://t.me/learningnets

Technet24

R1#**show ip ospf database external**

OSPF Router with ID (1.1.1.1) (Process ID 1)

Type-5 AS External Link States

Routing Bit Set on this LSA
LS age: 839
Options: (No TOS-capability, DC)
LS Type: AS External Link
Link State ID: 192.168.1.0 (External Network Number)
Advertising Router: 3.3.3.3
LS Seq Number: 80000001
Checksum: 0x1CF0
Length: 36
Network Mask: /32
Metric Type: 1 (Comparable directly to link state metric)
TOS: 0
Metric: 20
Forward Address: 150.4.4.254
External Route Tag: 0

Routing Bit Set on this LSA
LS age: 839
Options: (No TOS-capability, DC)
LS Type: AS External Link
Link State ID: 192.168.2.0 (External Network Number)
Advertising Router: 3.3.3.3
LS Seq Number: 80000001
Checksum: 0x11FA
Length: 36
Network Mask: /32
Metric Type: 1 (Comparable directly to link state metric)
TOS: 0
Metric: 20
Forward Address: 150.4.4.254
External Route Tag: 0

To modify this default behavior, you have to configure R3, the ABR, to suppress the forward address. This task is completed as follows:

R3(config)#**router ospf 3**
R3(config-router)#**area 4 nssa translate type7 suppress-fa**

https://t.me/learningnets

R3(config-router)#**exit**

Following this configuration change, the LSDB on R1 now shows the following entries:

R1#**show ip ospf database external**

OSPF Router with ID (1.1.1.1) (Process ID 1)

Type-5 AS External Link States

Routing Bit Set on this LSA
LS age: 39
Options: (No TOS-capability, DC)
LS Type: AS External Link
Link State ID: 192.168.1.0 (External Network Number)
Advertising Router: 3.3.3.3
LS Seq Number: 80000002
Checksum: 0x4B5E
Length: 36
Network Mask: /32
Metric Type: 1 (Comparable directly to link state metric)
TOS: 0
Metric: 20
Forward Address: 0.0.0.0
External Route Tag: 0

Routing Bit Set on this LSA
LS age: 39
Options: (No TOS-capability, DC)
LS Type: AS External Link
Link State ID: 192.168.2.0 (External Network Number)
Advertising Router: 3.3.3.3
LS Seq Number: 80000002
Checksum: 0x4068
Length: 36
Network Mask: /32
Metric Type: 1 (Comparable directly to link state metric)
TOS: 0
Metric: 20
Forward Address: 0.0.0.0
External Route Tag: 0

The forward address of 0.0.0.0 indicates that the traffic should be sent to the ASBR. By default, R3 will be designated ASBR because it translates the Type 3 LSAs to Type 5

https://t.me/learningnets

Technet24

LSAs, which are then flooded throughout the OSPF domain. You can verify that the Type 4 LSA for the ASBR exists using the **show ip ospf database asbr-summary** command:

R1#**show ip ospf database asbr-summary**

OSPF Router with ID (1.1.1.1) (Process ID 1)

Summary ASB Link States (Area 2)

LS age: 67
Options: (No TOS-capability, DC, Upward)
LS Type: Summary Links(AS Boundary Router)
Link State ID: 3.3.3.3 (AS Boundary Router address)
Advertising Router: 2.2.2.2
LS Seq Number: 80000002
Checksum: 0x35B1
Length: 28
Network Mask: /0
TOS: 0 Metric: 64

Task 4

The first part of this task is straightforward and requires route redistribution configuration:

R1(config)#**interface loopback 11**

R1(config-if)#**ip address 11.11.11.11 255.255.255.255**

R1(config-if)#**exit**

R1(config)#**router ospf 1**

R1(config-router)#**redistribute connected subnets**

R1(config-router)#**exit**

To complete the second part of this task, we have to remember that by default, a Type 5 LSA has a domain-flooding scope; however, it is NOT advertised into stub or NSSA areas. As a result of this default behavior, all other routers in the network will have an LSA for this subnet, except for R4. Validate this by looking at the Link State Database on R4:

R4#**show ip ospf database**

OSPF Router with ID (4.4.4.4) (Process ID 4)

Router Link States (Area 4)

Link ID ADV Router Age Seq# Checksum Link count
3.3.3.3 3.3.3.3 1937 0x80000004 0x002284 2

https://t.me/learningnets

4.4.4.4 4.4.4.4 1788 0x80000006 0x00C8C7 3

Summary Net Link States (Area 4)

Link ID ADV Router Age Seq# Checksum
10.0.0.0 3.3.3.3 424 0x80000004 0x005A76
10.0.0.4 3.3.3.3 424 0x80000004 0x00AF5D
10.0.0.8 3.3.3.3 424 0x80000004 0x008781
150.1.1.0 3.3.3.3 424 0x80000004 0x003C02
150.2.2.0 3.3.3.3 424 0x80000004 0x00A2D9
150.3.3.0 3.3.3.3 424 0x80000003 0x00EF9B

Type-7 AS External Link States (Area 4)

Link ID ADV Router Age Seq# Checksum Tag
192.168.1.0 4.4.4.4 1788 0x80000002 0x006796 0
192.168.2.0 4.4.4.4 1788 0x80000002 0x005CA0 0

Because the Type 5 LSA will not be flooded into area 4, you need to configure the ABR (R3) to advertise a default route to R4. This is completed as follows:

R3(config)#**router ospf 3**

R3(config-router)#**area 4 nssa default-information-originate**

R3(config-router)#**exit**

Following this configuration, the LSDB on R4 shows the following entries:

R4#**show ip ospf database**

OSPF Router with ID (4.4.4.4) (Process ID 4)

Router Link States (Area 4)

Link ID ADV Router Age Seq# Checksum Link count
3.3.3.3 3.3.3.3 57 0x80000005 0x002085 2
4.4.4.4 4.4.4.4 1927 0x80000006 0x00C8C7 3

Summary Net Link States (Area 4)

Link ID ADV Router Age Seq# Checksum
10.0.0.0 3.3.3.3 564 0x80000004 0x005A76
10.0.0.4 3.3.3.3 564 0x80000004 0x00AF5D
10.0.0.8 3.3.3.3 564 0x80000004 0x008781
150.1.1.0 3.3.3.3 564 0x80000004 0x003C02
150.2.2.0 3.3.3.3 564 0x80000004 0x00A2D9
150.3.3.0 3.3.3.3 564 0x80000003 0x00EF9B

Type-7 AS External Link States (Area 4)

https://t.me/learningnets

Technet24

Link ID ADV Router Age Seq# Checksum Tag
0.0.0.0 3.3.3.3 47 0x80000001 0x00B2F2 0
192.168.1.0 4.4.4.4 1927 0x80000002 0x006796 0
192.168.2.0 4.4.4.4 1929 0x80000002 0x005CA0 0

Finally, verify that all routers can ping the 11.11.11.11/32 address from their LAN interfaces:

R2#**ping 11.11.11.11 repeat 10 source fastethernet 0/0**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 11.11.11.11, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/2/4 ms

R3#**ping 11.11.11.11 repeat 10 source fastethernet 0/0**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 11.11.11.11, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R4#**ping 11.11.11.11 repeat 10 source fastethernet 0/0**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 11.11.11.11, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

Task 5

This task requires the use of the **area <area> range** command, which can also be used for route filtering. Prior to any changes, R1 and R2s routing tables show the following entries:

R1#**show ip route ospf | include 150.**
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 10.0.0.2, 00:09:46, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O IA 150.3.3.0 [110/65] via 10.0.0.6, 00:09:46, Serial0/1
150.4.0.0/24 is subnetted, 1 subnets
O IA 150.4.4.0 [110/846] via 10.0.0.6, 00:09:46, Serial0/1

https://t.me/learningnets

R2#**show ip route ospf | include 150.**
150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/65] via 10.0.0.1, 00:09:53, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O 150.3.3.0 [110/65] via 10.0.0.10, 01:19:47, Serial0/1
150.4.0.0/24 is subnetted, 1 subnets
O IA 150.4.4.0 [110/846] via 10.0.0.10, 00:09:53, Serial0/1
Complete this task by configuring both R3 and R2 as follows:

R2(config)#**router ospf 2**
R2(config-router)#**area 0 range 150.3.3.0 255.255.255.0 not-advertise**
R2(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**area 0 range 150.3.3.0 255.255.255.0 not-advertise**
R3(config-router)#**area 4 range 150.4.4.0 255.255.255.0 not-advertise**
R3(config-router)#**exit**

Following this configuration change, the routing tables on R1 and R2 show the following:

R1#**show ip route ospf | include 150.**
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 10.0.0.2, 00:02:34, Serial0/0

R2#**show ip route ospf | include 150.**
150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/65] via 10.0.0.1, 00:01:01, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O 150.3.3.0 [110/65] via 10.0.0.10, 00:01:01, Serial0/1
NOTE: The 150.3.3.0/24 prefix will show up in R2s routing table because this router also resides in area 0 along with R3. The configuration of the **area <area> range** command on BOTH routers, i.e. R2 and R3 prevents this from being advertised outside of area 0 to any other area as required in the task.

To ensure that R1 and R2 are still able to ping both the 150.3.3.0/24 and 150.4.4.0/24 subnets, you need to advertise a default route via OSPF on R3. This is completed as follows:

R3(config)#**router ospf 3**
R3(config-router)#**default-information originate always**
R3(config-router)#**exit**

Following this change, the routing tables on R1 and R2 show the following entries:

https://t.me/learningnets

Technet24

R1#**show ip route ospf**
10.0.0.0/30 is subnetted, 4 subnets
O IA 10.0.0.8 [110/128] via 10.0.0.2, 00:11:04, Serial0/0
O IA 10.0.0.12 [110/845] via 10.0.0.6, 00:11:04, Serial0/1
192.168.1.0/32 is subnetted, 1 subnets
O E1 192.168.1.0 [110/84] via 10.0.0.6, 00:11:04, Serial0/1
192.168.2.0/32 is subnetted, 1 subnets
O E1 192.168.2.0 [110/84] via 10.0.0.6, 00:11:04, Serial0/1
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 10.0.0.2, 00:11:04, Serial0/0
O*E2 0.0.0.0/0 [110/1] via 10.0.0.6, 00:00:38, Serial0/1

R2#**show ip route ospf**
10.0.0.0/30 is subnetted, 4 subnets
O IA 10.0.0.12 [110/845] via 10.0.0.10, 00:09:42, Serial0/1
O IA 10.0.0.4 [110/845] via 10.0.0.10, 00:09:42, Serial0/1
11.0.0.0/32 is subnetted, 1 subnets
O E2 11.11.11.11 [110/20] via 10.0.0.1, 00:09:42, Serial0/0
192.168.1.0/32 is subnetted, 1 subnets
O E1 192.168.1.0 [110/84] via 10.0.0.10, 00:09:42, Serial0/1
192.168.2.0/32 is subnetted, 1 subnets
O E1 192.168.2.0 [110/84] via 10.0.0.10, 00:09:42, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/65] via 10.0.0.1, 00:09:42, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O 150.3.3.0 [110/65] via 10.0.0.10, 00:09:42, Serial0/1
O*E2 0.0.0.0/0 [110/1] via 10.0.0.10, 00:00:54, Serial0/1

Finally, verify that R1 and R2 can still ping the 150.3.3.0/24 and 150.4.4.0/24 subnets:

R1#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms
R1#

R1#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:

https://t.me/learningnets

Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

R2#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms
R2#

R2#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

Task 6

To complete this task, use the **area <area> filter-list prefix <name> in** command on R1 and R3 to prevent Type 3 LSAs for the 150.1.1.0/24 and 150.2.2.0/24 subnets from being advertised into area 3. For verification, prior to filtering changes, the LSDBs on R1 and R3 show:

R1#**show ip ospf database**

OSPF Router with ID (1.1.1.1) (Process ID 1)

[Truncated Output]

Summary Net Link States (Area 3)

Link ID ADV Router Age Seq# Checksum
10.0.0.0 3.3.3.3 403 0x80000004 0x00B422
10.0.0.8 3.3.3.3 403 0x80000004 0x00E12D
10.0.0.12 3.3.3.3 403 0x80000004 0x00B951
150.1.1.0 3.3.3.3 403 0x80000004 0x0096AD
150.2.2.0 3.3.3.3 403 0x80000004 0x00FC85

[Truncated Output]

R3#**show ip ospf database**

OSPF Router with ID (3.3.3.3) (Process ID 3)

[Truncated Output]

https://t.me/learningnets

Technet24

Summary Net Link States (Area 3)

Link ID ADV Router Age Seq# Checksum
10.0.0.0 3.3.3.3 453 0x80000004 0x00B422
10.0.0.8 3.3.3.3 453 0x80000004 0x00E12D
10.0.0.12 3.3.3.3 453 0x80000004 0x00B951
150.1.1.0 3.3.3.3 453 0x80000004 0x0096AD
150.2.2.0 3.3.3.3 453 0x80000004 0x00FC85

[Truncated Output]

Complete this task by filtering the Type 3 LSAs for the 150.1.1.0/24 and 150.2.2.0/24 from being advertised into area 3. The **area <area> filter-list prefix <name> out** command prevents Type 3 LSAs from being advertised out of the specified area(s):

R1(config)#**ip prefix-list FILTER seq 5 deny 150.1.1.0/24**
R1(config)#**ip prefix-list FILTER seq 7 deny 150.2.2.0/24**
R1(config)#**ip prefix-list FILTER seq 9 permit 0.0.0.0/0 le 32**
R1(config)#**router ospf 1**
R1(config-router)#**area 3 filter-list prefix FILTER in**
R1(config-router)#**exit**

R3(config)#**ip prefix-list FILTER seq 5 deny 150.1.1.0/24**
R3(config)#**ip prefix-list FILTER seq 7 deny 150.2.2.0/24**
R3(config)#**ip prefix-list FILTER seq 9 permit 0.0.0.0/0 le 32**
R3(config)#**router ospf 3**
R3(config-router)#**area 3 filter-list prefix FILTER in**
R3(config-router)#**exit**

Following this configuration, the LSDBs on R1 and R3 show:

R1#**show ip ospf database**

OSPF Router with ID (1.1.1.1) (Process ID 1)

Router Link States (Area 2)

[Truncated Output]

Summary Net Link States (Area 3)

Link ID ADV Router Age Seq# Checksum
10.0.0.0 3.3.3.3 859 0x80000004 0x00B422
10.0.0.8 3.3.3.3 859 0x80000004 0x00E12D
10.0.0.12 3.3.3.3 859 0x80000004 0x00B951

[Truncated Output]

R3#**show ip ospf database**

https://t.me/learningnets

OSPF Router with ID (3.3.3.3) (Process ID 3)

[Truncated Output]

Summary Net Link States (Area 3)

Link ID ADV Router Age Seq# Checksum
10.0.0.0 3.3.3.3 887 0x80000004 0x00B422
10.0.0.8 3.3.3.3 887 0x80000004 0x00E12D
10.0.0.12 3.3.3.3 887 0x80000004 0x00B951

[Truncated Output]

https://t.me/learningnets

CCNP Lab 031: OSPF Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand OSPF implementation and configuration in Cisco IOS routers. Additional technologies tested include authentication, optimization and resiliency.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Technet24

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF as illustrated in the topology. Ensure that all routers are able to reach each other. Do NOT enable OSPF over the point-to-point link between R1 and R3. Additionally, ensure that no OSPF packets are sent out of the LAN interfaces on any routers. Verify the OSPF configuration using the appropriate commands.

Task 3

Authenticate the OSPF backbone using MD5 authentication with a secret of 'CCNP'. Verify that all routing is still functional following this change.

Task 4

Management is concerned about how a large Link State Database can cause adverse issues, such as performance issues, on a router. They would like to see if the LSDB on all routers can be restricted to no more than 100 LSAs. As a test, configure your network so that OSPF will limit the size of the LSDB to 100 non-self-generated LSAs. For the time being, OSPF should only log a warning message when 80% of this number has been reached.

In addition to this, configure the network so that if any router is rebooted, it will send router LSAs with a metric of infinity for 5 minutes after it has come back up. Verify your configuration using the appropriate commands.

Task 5

Management has stated that the network will grow to a significant amount of routers in the near future. This deployment will include numerous OSPF areas. They are worried about convergence and would like you to ensure that only minimal SPF calculations are performed when changes to a router or network LSAs occur within an area. Given this, configure your network so that and full SPF calculation is NOT performed, unless these changes are local to the router in question. Verify your configuration using the appropriate commands.

Task 6

The R2-to-R3 link has had a bad history of failures and management is afraid that they might lose connectivity to parts of the network when this goes down. They have therefore decided to get a point-to-point link between R1 and R3 for backup purposes should the link between R2 and R3 fail. They request that you use EIGRP to ensure that R3 and R4 can still communicate with R1 and R2 when the R2-to-R3 link fails.

However, they have made it explicitly clear that when the R2-to-R3 link is up, only OSPF routes should exist in the network. Management is fine with both internal and external OSPF and EIGRP routes when using the backup link. Additionally, you are

https://t.me/learningnets

allowed to make basic modifications to OSPF to get this solution to work. Given this information, implement a routing solution to meet these requirements. Verify your configuration by shutting down the R2-to-R3 point-to-point link and pinging LAN-to-LAN between R4 and R2.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**
R1(config-if)#**no shutdown**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**no shutdown**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip address 150.3.3.3 255.255.255.0**
R3(config-if)#**exit**

https://t.me/learningnets

R3(config)#**interface serial 1/0**
R3(config-if)#**ip address 10.0.0.6 255.255.255.252**
R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip address 150.4.4.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**no shutdown**
R4(config-if)#**exit**

Task 2

In order to complete this task, you need to ensure that you configure a virtual link across area 1, otherwise area 2 routes will not be reachable from R1 and R2. This is completed as follows:

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**network 150.1.1.1 0.0.0.0 area 0**
R1(config-router)#**network 10.0.0.1 0.0.0.0 area 0**
R1(config-router)#**passive-interface fastethernet 0/0**
R1(config-router)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**area 1 virtual-link 3.3.3.3**
R2(config-router)#**network 150.2.2.2 0.0.0.0 area 0**

https://t.me/learningnets

R2(config-router)#**network 10.0.0.2 0.0.0.0 area 0**
R2(config-router)#**network 10.0.0.9 0.0.0.0 area 1**
R2(config-router)#**passive-interface fastethernet 0/0**
R2(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**area 1 virtual-link 2.2.2.2**
R3(config-router)#**network 150.3.3.3 0.0.0.0 area 1**
R3(config-router)#**network 10.0.0.10 0.0.0.0 area 1**
R3(config-router)#**network 10.0.0.13 0.0.0.0 area 2**
R3(config-router)#**passive-interface fastethernet 0/0**
R3(config-router)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**network 150.4.4.4 0.0.0.0 area 2**
R4(config-router)#**network 10.0.0.14 0.0.0.0 area 2**
R4(config-router)#**passive-interface fastethernet 0/0**
R4(config-router)#**exit**

Verify your OSPF configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:36 10.0.0.2 Serial0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - - 10.0.0.10 OSPF_VL0
1.1.1.1 0 FULL/ - 00:00:31 10.0.0.1 Serial0/0
3.3.3.3 0 FULL/ - 00:00:37 10.0.0.10 Serial0/1

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - - 10.0.0.9 OSPF_VL0
2.2.2.2 0 FULL/ - 00:00:39 10.0.0.9 Serial1/1
4.4.4.4 0 FULL/ - 00:00:31 10.0.0.14 Serial1/2

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:34 10.0.0.13 Serial0/0

https://t.me/learningnets

Technet24

Task 3

This task is straightforward; however, you must remember that the virtual link is a logical extension of area 0 (the backbone) and this needs authentication configuration as well. This means that area 0 authentication must also be configured on R3 even though no interfaces actually reside within the backbone area. This task is completed as follows:

R1(config)#**router ospf 1**
R1(config-router)#**area 0 authentication message-digest**
R1(config-router)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R1(config-if)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**area 0 authentication message-digest**
R2(config-router)#**area 1 virtual-link 3.3.3.3 message-digest-key 1 md5 CCNP**
R2(config-router)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R2(config-if)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**area 0 authentication message-digest**
R3(config-router)#**area 1 virtual-link 2.2.2.2 message-digest-key 1 md5 CCNP**
R3(config-router)#**exit**

Following OSPF backbone authentication configuration, verify the backbone area adjacencies:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:39 10.0.0.2 Serial0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - - 10.0.0.10 OSPF_VL0
1.1.1.1 0 FULL/ - 00:00:36 10.0.0.1 Serial0/0
3.3.3.3 0 FULL/ - 00:00:32 10.0.0.10 Serial0/1

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface

https://t.me/learningnets

2.2.2.2 0 FULL/ - - 10.0.0.9 OSPF_VL0
2.2.2.2 0 FULL/ - 00:00:39 10.0.0.9 Serial1/1
4.4.4.4 0 FULL/ - 00:00:31 10.0.0.14 Serial1/2

NOTE: Use the **show ip ospf neighbor detail** command for additional detail. To view information about the virtual links, use the **show ip ospf virtual-links** command:

R2#**show ip ospf virtual-links**
Virtual Link OSPF_VL0 to router 3.3.3.3 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 1, via interface Serial0/1, Cost of using 64
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:06
Adjacency State FULL (Hello suppressed)
Index 2/3, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec
Message digest authentication enabled
Youngest key id is 1

Task 4

The OSPF Link-State Database Overload Protection feature allows you to limit the number of non self-generated LSAs for a given OSPF process. Excessive LSAs generated by other routers in the OSPF domain can substantially drain the CPU and memory resources of the router. To complete the first part of this task, you need to enable this feature using the **max-lsa <maximum> [threshold-percentage] [warning-only] [ignore-time minutes] [ignore-count count-number] [reset-time minutes]** command.

To complete the second part of this task, you will need to enable the Stub Router Advertisement feature which allows a router to advertise infinity metric (0xFFFF) for its connected links in Router LSAs, and advertise normal interface cost if the link is a stub network. The **max-metric router-lsa on-startup <seconds>** command is used to enable this feature. Be careful when performing such activities in production networks because OSPF adjacencies will be reset.

This task is completed as follows:

R1(config)#**router ospf 1**

https://t.me/learningnets

Technet24

R1(config-router)#**max-lsa 100 80 warning-only**
R1(config-router)#**max-metric router-lsa on-startup 300**
R1(config-router)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**max-lsa 100 80 warning-only**
R2(config-router)#**max-metric router-lsa on-startup 300**
R2(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**max-lsa 100 80 warning-only**
R3(config-router)#**max-metric router-lsa on-startup 300**
R3(config-router)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**max-lsa 100 80 warning-only**
R4(config-router)#**max-metric router-lsa on-startup 300**
R4(config-router)#**exit**

Verify your configurations using the **show ip ospf** command:

R4#**show ip ospf**
Routing Process "ospf 4" with ID 4.4.4.4
Start time: 02:45:57.136, Time elapsed: 00:52:38.132
Supports only single TOS(TOS0) routes
Supports opaque LSA
Supports Link-local Signaling (LLS)
Supports area transit capability
Maximum number of non self-generated LSA allowed 100 (warning-only)
Threshold for warning message 80%
Originating router-LSAs with maximum metric
Condition: on startup for 300 seconds, State: inactive
Initial SPF schedule delay 5000 msecs
Minimum hold time between two consecutive SPFs 10000 msecs
Maximum wait time between two consecutive SPFs 10000 msecs

[Truncated Output]

Task 5

To complete this task, you need to enable the incremental SPF feature. When this feature is enabled, the router will run a partial SPF to recompute the parts of the tree that have been affected, instead of running a full or complete SPF recomputation. This feature saves router resources, such as the processor (CPU) and allows for faster OSPF

https://t.me/learningnets

convergence.

When incremental SPF is enabled, the local router will run a full or complete SPF recomputation is when the changes to the router and network LSAs occurred on the local router itself. Incremental SPF is scheduled in the same way as the full SPF. Routers enabled with incremental SPF and routers not enabled with incremental SPF can function in the same internetwork. This task is completed as follows:

R1(config)#**router ospf 1**
R1(config-router)#**ispf**
R1(config-router)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**ispf**
R2(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**ispf**
R3(config-router)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**ispf**
R4(config-router)#**exit**

Verify your configuration using the **show ip ospf** command:

R1#**show ip ospf**
Routing Process "ospf 1" with ID 1.1.1.1
Start time: 02:42:17.444, Time elapsed: 01:08:22.652

[Truncated Output]

Initial SPF schedule delay 5000 msecs
Minimum hold time between two consecutive SPFs 10000 msecs
Maximum wait time between two consecutive SPFs 10000 msecs
Incremental-SPF enabled
Minimum LSA interval 5 secs
Minimum LSA arrival 1000 msecs
LSA group pacing timer 240 secs

[Truncated Output]

Task 6

This task may initially seem daunting but after further observation, it is pretty straightforward. The solution is to enable EIGRP on the point-to-point link between R1 and R3 and then redistribute between EIGRP and OSPF on both routers. Because

https://t.me/learningnets

Technet24

external EIGRP routes have an administrative distance of 170, only OSPF routes will be installed into the routing tables.

The only caveat here is understanding multi-area OSPF behavior. By default, inter-area routes will not be advertised when there is no backbone area. This means that when the R2-to-R3 point-to-point link fails, R4 will not receive the 150.3.3.0/24 route because it resides in area 1. You cannot redistribute this into OSPF on R3 because that results in a Type 5 LSA. Again, without a backbone area, this LSA is not flooded into area 2. The only solution is to reconfigure your OSPF network so that this interface resides in area 2.This task is completed as follows:

R1(config)#**router eigrp 1**
R1(config-router)#**no auto-summary**
R1(config-router)#**network 10.0.0.5 0.0.0.0**
R1(config-router)#**redistribute ospf 1 metric 100000 100 255 1 1500**
R1(config-router)#**exit**
R1(config)#**router ospf 1**
R1(config-router)#**redistribute eigrp 1 subnets**
R1(config-router)#**exit**

R3(config)#**router eigrp 1**
R3(config-router)#**no auto-summary**
R3(config-router)#**network 10.0.0.6 0.0.0.0**
R3(config-router)#**redistribute ospf 3 metric 100000 100 255 1 1500**
R3(config-router)#**exit**
R3(config)#**router ospf 3**
R3(config-router)#**network 150.3.3.3 0.0.0.0 area 2**
R3(config-router)#**redistribute eigrp 1 subnets**
R3(config-router)#**exit**

Following your configuration, first verify EIGRP neighbor relationships:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.6 Se0/1 10 00:00:56 14 200 0 5

R3#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.5 Se1/0 10 00:01:23 18 1140 0 3

https://t.me/learningnets

Next, verify the routing tables and ensure that all routes are known via OSPF as required:

R1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 4 subnets
O IA 10.0.0.8 [110/128] via 10.0.0.2, 00:00:03, Serial0/0
O IA 10.0.0.12 [110/909] via 10.0.0.2, 00:00:03, Serial0/0
C 10.0.0.0 is directly connected, Serial0/0
C 10.0.0.4 is directly connected, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 10.0.0.2, 00:00:03, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O IA 150.3.3.0 [110/129] via 10.0.0.2, 00:00:04, Serial0/0

R2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 4 subnets
C 10.0.0.8 is directly connected, Serial0/1
O IA 10.0.0.12 [110/845] via 10.0.0.10, 00:00:09, Serial0/1
C 10.0.0.0 is directly connected, Serial0/0
O E2 10.0.0.4 [110/20] via 10.0.0.10, 00:00:09, Serial0/1
[110/20] via 10.0.0.1, 00:00:09, Serial0/0

https://t.me/learningnets

Technet24

150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/65] via 10.0.0.1, 00:00:09, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
O 150.3.3.0 [110/65] via 10.0.0.10, 00:00:11, Serial0/1

R3#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 4 subnets
C 10.0.0.8 is directly connected, Serial1/1
C 10.0.0.12 is directly connected, Serial1/2
O 10.0.0.0 [110/845] via 10.0.0.9, 00:00:20, Serial1/1
C 10.0.0.4 is directly connected, Serial1/0
150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/782] via 10.0.0.14, 00:00:30, Serial1/2
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/782] via 10.0.0.9, 00:00:20, Serial1/1
150.3.0.0/24 is subnetted, 1 subnets
C 150.3.3.0 is directly connected, FastEthernet0/0

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 4 subnets
O IA 10.0.0.8 [110/845] via 10.0.0.13, 00:00:36, Serial0/0

https://t.me/learningnets

C 10.0.0.12 is directly connected, Serial0/0
O IA 10.0.0.0 [110/909] via 10.0.0.13, 00:00:26, Serial0/0
O E2 10.0.0.4 [110/20] via 10.0.0.13, 00:00:26, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
O IA 150.2.2.0 [110/846] via 10.0.0.13, 00:00:26, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O IA 150.3.3.0 [110/65] via 10.0.0.13, 00:00:37, Serial0/0

Finally, test your solution by shutting down the link between R2 and R3:

R3(config)#**interface serial 1/1**
R3(config-if)#**shutdown**

After shutting down the R2-to-R3 link, check the routing tables on all routers again:

R1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 3 subnets
D EX 10.0.0.12 [170/2195456] via 10.0.0.6, 00:06:31, Serial0/1
C 10.0.0.0 is directly connected, Serial0/0
C 10.0.0.4 is directly connected, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 10.0.0.2, 00:06:31, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2195456] via 10.0.0.6, 00:06:31, Serial0/1
150.4.0.0/24 is subnetted, 1 subnets
D EX 150.4.4.0 [170/2195456] via 10.0.0.6, 00:06:32, Serial0/1

R2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area

https://t.me/learningnets

N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 3 subnets
O E2 10.0.0.12 [110/20] via 10.0.0.1, 00:07:39, Serial0/0
C 10.0.0.0 is directly connected, Serial0/0
O E2 10.0.0.4 [110/20] via 10.0.0.1, 00:07:39, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/65] via 10.0.0.1, 00:07:39, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
O E2 150.3.3.0 [110/20] via 10.0.0.1, 00:07:40, Serial0/0
150.4.0.0/24 is subnetted, 1 subnets
O E2 150.4.4.0 [110/20] via 10.0.0.1, 00:07:40, Serial0/0

R3#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 3 subnets
C 10.0.0.12 is directly connected, Serial1/2
D EX 10.0.0.0 [170/20537600] via 10.0.0.5, 00:08:16, Serial1/0
C 10.0.0.4 is directly connected, Serial1/0
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/20537600] via 10.0.0.5, 00:08:16, Serial1/0
150.2.0.0/24 is subnetted, 1 subnets
D EX 150.2.2.0 [170/20537600] via 10.0.0.5, 00:08:16, Serial1/0
150.3.0.0/24 is subnetted, 1 subnets
C 150.3.3.0 is directly connected, FastEthernet0/0

https://t.me/learningnets

150.4.0.0/24 is subnetted, 1 subnets
O 150.4.4.0 [110/782] via 10.0.0.14, 00:03:57, Serial1/2

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 3 subnets
C 10.0.0.12 is directly connected, Serial0/0
O E2 10.0.0.0 [110/20] via 10.0.0.13, 00:04:11, Serial0/0
O E2 10.0.0.4 [110/20] via 10.0.0.13, 00:04:11, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
O E2 150.1.1.0 [110/20] via 10.0.0.13, 00:04:11, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
O E2 150.2.2.0 [110/20] via 10.0.0.13, 00:04:11, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O 150.3.3.0 [110/65] via 10.0.0.13, 00:04:12, Serial0/0
150.4.0.0/24 is subnetted, 1 subnets
C 150.4.4.0 is directly connected, FastEthernet0/0

Finally, verify your solution by pinging LAN-to-LAN between R4 and the other routers:

R4#**ping 150.1.1.1 source fastethernet 0/0 repeat 10 size 100**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.2.2.2 source fastethernet 0/0 repeat 10 size 100**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

https://t.me/learningnets

Technet24

R4#**ping 150.3.3.3 source fastethernet 0/0 repeat 10 size 100**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

https://t.me/learningnets

CCNP Lab 032: OSPF Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand OSPF implementation and configuration in Cisco IOS routers. Additional technologies tested include authentication and metrics.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF area 0 as illustrated in the topology. Ensure that no OSPF Hellos are

https://t.me/learningnets

sent out of the LAN interfaces on R2 and R3. Verify your configuration using the appropriate commands.

Task 3

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF area 2 as illustrated in the topology. This area should not allow any inter-area LSAs (except for the default route) or any external LSAs.

Additionally, the router should not send log messages when Type 6 LSAs are received. Ensure that the default route shows up in the routing table of R4 with a route metric of 222. You are NOT allowed to modify any interface bandwidth or cost values to complete this task. Ensure that no OSPF packets are sent out of the LAN interface on R4. Verify your configuration using the appropriate commands.

Task 4

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF area 3 as illustrated in the topology. Authenticate OSPF messages between R1 and R2 using the plain text password 'CCNP'. Authentication should be performed only at the interface level. Verify your configuration using the appropriate commands.

Task 5

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF area 1 as illustrated in the topology. Configure MD5 authentication for area 1 using the password 'CCNP'. Verify your configuration.

Task 6

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF for area 5 as illustrated in the topology. In the future, an additional router will be added to this segment. This router will be redistributing external routes from business partner routers. Configure area 5 so that these routes can be imported into OSPF as Type 7 routes. No inter-area or Type 5 LSAs should be allowed into this area. Finally, ensure that all other routers in the network are able to ping R1s LAN (and any future area 5 subnets).Verify your configuration using the appropriate commands.

Task 7

Configure R1 so that the virtual link going to R2 is assigned a cost of 2 and the virtual link going to R3 is assigned a cost of 3. Verify your configuration.

Task 8

In the future, the FastEthernet link on R2 will be replaced with a GigabitEthernet link.

https://t.me/learningnets

Technet24

Configure R2 so that OSPF accurately calculates route metrics when this is performed.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**
R1(config-if)#**no shutdown**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**no shutdown**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip address 150.3.3.3 255.255.255.0**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**ip address 10.0.0.6 255.255.255.252**
R3(config-if)#**no shutdown**

https://t.me/learningnets

R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip address 150.4.4.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**no shutdown**
R4(config-if)#**exit**

Task 2

R2(config)#**router ospf 2**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**network 150.2.2.2 0.0.0.0 area 0**
R2(config-router)#**network 10.0.0.9 0.0.0.0 area 0**
R2(config-router)#**passive-interface fastethernet 0/0**
R2(config-router)#**exit**

R3(config-if)#**router ospf 3**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**network 150.3.3.3 0.0.0.0 area 0**
R3(config-router)#**network 10.0.0.10 0.0.0.0 area 0**
R3(config-router)#**passive-interface fastethernet 0/0**

Verify your configuration using the **show ip ospf neighbor** command:

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:38 10.0.0.10 Serial0/1

https://t.me/learningnets

Technet24

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:32 10.0.0.9 Serial1/1

Task 3

This task requires that a totally stubby area be configured. To ensure that the default route shows up in R4s routing table with a metric of 222, you need to specify a cost value that is derived by subtracting the default interface cost of 64 from 222. The is completed as follows:

R3(config)#**router ospf 3**
R3(config-router)#**network 10.0.0.13 0.0.0.0 area 2**
R3(config-router)#**area 2 stub no-summary**
R3(config-router)#**area 2 default-cost 158**
R3(config-router)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**network 150.4.4.4 0.0.0.0 area 2**
R4(config-router)#**network 10.0.0.14 0.0.0.0 area 2**
R4(config-router)#**passive-interface fastethernet 0/0**
R4(config-router)#**area 2 stub**
R4(config-router)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:31 10.0.0.9 Serial1/1
4.4.4.4 0 FULL/ - 00:00:39 10.0.0.14 Serial1/2

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:30 10.0.0.13 Serial0/0

Next, verify that the default route has a route metric of 222 as required in the task:

R4#**show ip route ospf**
O*IA 0.0.0.0/0 [110/**222**] via 10.0.0.13, 00:01:50, Serial0/0

You can verify the cost value specified for the default route by looking at the LSA in the LSDB:

R4#**show ip ospf database summary 0.0.0.0**

https://t.me/learningnets

OSPF Router with ID (4.4.4.4) (Process ID 4)

Summary Net Link States (Area 2)

Routing Bit Set on this LSA
LS age: 226
Options: (No TOS-capability, DC, Upward)
LS Type: Summary Links(Network)
Link State ID: 0.0.0.0 (summary Network Number)
Advertising Router: 3.3.3.3
LS Seq Number: 80000003
Checksum: 0x7B17
Length: 28
Network Mask: /0
TOS: 0 **Metric: 158**

Task 4

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**network 10.0.0.1 0.0.0.0 area 2**
R1(config-router)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip ospf authentication**
R1(config-if)#**ip ospf authentication-key CCNP**
R1(config-if)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**network 10.0.0.2 0.0.0.0 area 2**
R2(config-router)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip ospf authentication**
R2(config-if)#**ip ospf authentication-key CCNP**
R2(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:34 10.0.0.2 Serial0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:33 10.0.0.10 Serial0/1

https://t.me/learningnets

Technet24

1.1.1.1 0 FULL/ - 00:00:36 10.0.0.1 Serial0/0

Verify authentication configuration using the **show ip ospf interface** command:

R1#**show ip ospf interface serial 0/0**
Serial0/0 is up, line protocol is up
Internet Address 10.0.0.1/30, Area 2
Process ID 1, Router ID 1.1.1.1, Network Type POINT_TO_POINT, Cost: 64
Transmit Delay is 1 sec, State POINT_TO_POINT
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
oob-resync timeout 40
Hello due in 00:00:02
Supports Link-local Signaling (LLS)
Index 1/1, flood queue length 0
Next 0x0(0)/0x0(0)
Last flood scan length is 1, maximum is 1
Last flood scan time is 0 msec, maximum is 0 msec
Neighbor Count is 1, Adjacent neighbor count is 1
Adjacent with neighbor 2.2.2.2
Suppress hello for 0 neighbor(s)
Simple password authentication enabled

Task 5

R1(config)#**router ospf 1**
R1(config-router)#**network 10.0.0.5 0.0.0.0 area 1**
R1(config-router)#**area 1 authentication message-digest**
R1(config-router)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R1(config-if)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**network 10.0.0.6 0.0.0.0 area 1**
R3(config-router)#**area 1 authentication message-digest**
R3(config-router)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R3(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

https://t.me/learningnets

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:30 10.0.0.6 Serial0/1
2.2.2.2 0 FULL/ - 00:00:39 10.0.0.2 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:38 10.0.0.9 Serial1/1
1.1.1.1 0 FULL/ - 00:00:39 10.0.0.5 Serial1/0
4.4.4.4 0 FULL/ - 00:00:36 10.0.0.14 Serial1/2

Verify area authentication configuration using the **show ip ospf** command:

R3#**show ip ospf | begin Area 1**
Area 1
Number of interfaces in this area is 1
Area has message digest authentication
SPF algorithm last executed 00:03:18.600 ago
SPF algorithm executed 2 times
Area ranges are
Number of LSA 8. Checksum Sum 0x03AA2E
Number of opaque link LSA 0. Checksum Sum 0x000000
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0

Verify interface authentication using the **show ip ospf interface** command:

R3#**show ip ospf interface serial 1/0**
Serial1/0 is up, line protocol is up
Internet Address 10.0.0.6/30, Area 1
Process ID 3, Router ID 3.3.3.3, Network Type POINT_TO_POINT, Cost: 781
Transmit Delay is 1 sec, State POINT_TO_POINT
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
oob-resync timeout 40
Hello due in 00:00:08
Supports Link-local Signaling (LLS)
Index 1/4, flood queue length 0
Next 0x0(0)/0x0(0)
Last flood scan length is 1, maximum is 1
Last flood scan time is 0 msec, maximum is 0 msec
Neighbor Count is 1, Adjacent neighbor count is 1

https://t.me/learningnets

Technet24

Adjacent with neighbor 1.1.1.1
Suppress hello for 0 neighbor(s)
Message digest authentication enabled
Youngest key id is 1

Task 6

This task requires the implementation of area 5 as a totally stubby NSSA. This configuration will allow a default route to be advertised into the area. It will also allow the external routes from the business partners to be advertised to the rest of the domain. Finally, you need to configure two virtual links to connect area 5 to the OSPF backbone. One virtual link will use area 1 as the transit area and the other will use area 3. This task is completed as follows:

R1(config)#**router ospf 1**
R1(config-router)#**network 150.1.1.1 0.0.0.0 area 5**
R1(config-router)#**area 5 nssa no-summary**
R1(config-router)#**area 1 virtual-link 3.3.3.3**
R1(config-router)#**area 2 virtual-link 2.2.2.2**
R1(config-router)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**area 2 virtual-link 1.1.1.1**
R2(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**area 1 virtual-link 1.1.1.1**
R3(config-router)#**exit**

Verify OSPF virtual link states using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - - 10.0.0.2 OSPF_VL1
3.3.3.3 0 FULL/ - - 10.0.0.6 OSPF_VL0
3.3.3.3 0 FULL/ - 00:00:35 10.0.0.6 Serial0/1
2.2.2.2 0 FULL/ - 00:00:34 10.0.0.2 Serial0/0

View detailed virtual link information using the **show ip ospf virtual-links** command:

R1#**show ip ospf virtual-links**
Virtual Link OSPF_VL1 to router 2.2.2.2 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 2, via interface Serial0/0, Cost of using 64

https://t.me/learningnets

Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:02
Adjacency State FULL (Hello suppressed)
Index 1/3, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec
Virtual Link OSPF_VL0 to router 3.3.3.3 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 1, via interface Serial0/1, Cost of using 64
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:05
Adjacency State FULL (Hello suppressed)
Index 2/4, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec

Finally, verify that the 150.1.1.0/24 subnet exists in the routing table of all routers. For example, on R3, you should see the following route entry:

R3#**show ip route ospf**
10.0.0.0/30 is subnetted, 4 subnets
O IA 10.0.0.0 [110/845] via 10.0.0.9, 00:03:26, Serial1/1
[110/845] via 10.0.0.5, 00:03:26, Serial1/0
150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/782] via 10.0.0.14, 00:10:45, Serial1/2
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/782] via 10.0.0.9, 00:03:26, Serial1/1

Additionally, verify connectivity by pinging LAN-to-LAN between R1 and R4:

R4#**ping 150.1.1.1 source 150.4.4.4 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 380/381/384 ms

https://t.me/learningnets

Task 7

By default, the virtual link cost is derived from the interface cost. To modify the virtual link cost, you need to modify the cost of the interface the virtual link is established across. Before any changes are made to the network, the virtual links on R1 show the following costs:

```
R1#show ip ospf virtual-links
Virtual Link OSPF_VL1 to router 2.2.2.2 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 2, via interface Serial0/0, Cost of using 64
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:02
Adjacency State FULL (Hello suppressed)
Index 1/3, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec
Virtual Link OSPF_VL0 to router 3.3.3.3 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 1, via interface Serial0/1, Cost of using 64
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:05
Adjacency State FULL (Hello suppressed)
Index 2/4, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec
```

To complete this task, implement the following configuration:

```
R1(config)#interface serial 0/0
R1(config-if)#ip ospf cost 2
R1(config-if)#exit
R1(config)#interface serial 0/1
R1(config-if)#ip ospf cost 3
R1(config-if)#exit
```

https://t.me/learningnets

Verify the new costs using the **show ip ospf virtual-links** command:

R1#**show ip ospf virtual-links**
Virtual Link OSPF_VL1 to router 2.2.2.2 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 2, via interface Serial0/0, Cost of using 2
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:08
Adjacency State FULL (Hello suppressed)
Index 1/3, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec
Virtual Link OSPF_VL0 to router 3.3.3.3 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 1, via interface Serial0/1, Cost of using 3
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:01
Adjacency State FULL (Hello suppressed)
Index 2/4, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec

Task 8

By default, OSPF uses a reference bandwidth of 100Mbps when calculating cost values for links. If you change this value on one router - change it on every other router otherwise this could result in inconsistent routing information. Complete this task by implementing the following:

R1(config)#**router ospf 1**
R1(config-router)#**auto-cost reference-bandwidth 1000**
% OSPF: Reference bandwidth is changed.
Please ensure reference bandwidth is consistent across all routers.
R1(config-router)#**exit**

R2(config)#**router ospf 2**

https://t.me/learningnets

Technet24

R2(config-router)#**auto-cost reference-bandwidth 1000**
% OSPF: Reference bandwidth is changed.
Please ensure reference bandwidth is consistent across all routers.
R2(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**auto-cost reference-bandwidth 1000**
% OSPF: Reference bandwidth is changed.
Please ensure reference bandwidth is consistent across all routers.
R3(config-router)#**exit**

R4(config)#**router ospf 1**
R4(config-router)#**auto-cost reference-bandwidth 1000**
% OSPF: Reference bandwidth is changed.
Please ensure reference bandwidth is consistent across all routers.
R4(config-router)#**exit**

Verify the default reference bandwidth using the **show ip protocols** command:

R4#**show ip protocols**
Routing Protocol is "ospf 4"
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Router ID 4.4.4.4
Number of areas in this router is 1. 0 normal 1 stub 0 nssa
Maximum path: 4
Routing for Networks:
10.0.0.14 0.0.0.0 area 2
150.4.4.4 0.0.0.0 area 2
Reference bandwidth unit is 1000 mbps
Passive Interface(s):
FastEthernet0/0
Routing Information Sources:
Gateway Distance Last Update
3.3.3.3 110 00:02:15
Distance: (default is 110)

https://t.me/learningnets

CCNP Lab 033: OSPF Multi-Technology Lab

Lab Objective:

The focus of this lab is to understand OSPF implementation and configuration in Cisco IOS routers. Additional technologies tested include management and convergence.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF area 0 between R3 and R4. Configure MD5 area authentication using a

https://t.me/learningnets

secret password of ‘CCNP’. Verify your configuration using the appropriate commands.

Task 3

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF area 1 between R1 and R3. Area 1 should be configured as a totally stub OSPF area wherein R3 advertises a default route only to R1. Verify your configuration using the appropriate commands.

Task 4

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF area 2 between R2 and R3. Ensure that OSPF Hellos are not sent out the LAN interfaces connected to R2 or R3. Verify your configuration using the appropriate commands.

Task 5

Using legacy **network x.x.x.x y.y.y.y area <area>** OSPF configuration commands, configure OSPF area 3 between R1 and R2. No OSPF packets should be sent out the LAN interfaces on R1 and R2. Additionally, ensure that this area has connectivity to all the other OSPF areas in the event that either the R1-R2 or R1-R3 links fail. Verify your configuration using the appropriate commands.

Task 6

Users in the NOC has complained that it is difficult to identify all routers based on IP addresses when they are troubleshooting. They ask if it is possible to identify OSPF neighbors by the hostnames versus IP addresses. Configure your network to provide this capability. Test your solution using the **show ip ospf neighbor** and **show ip ospf database** commands. If you have configured OSPF in the correct manner, all RIDs should be replaced by hostnames.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ip address 10.0.0.1 255.255.255.252**
R1(config-if)#**clock rate 2000000**

https://t.me/learningnets

Technet24

R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**
R1(config-if)#**no shutdown**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**no shutdown**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip address 150.3.3.3 255.255.255.0**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**ip address 10.0.0.6 255.255.255.252**
R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**no shutdown**
R3(config-if)# **clock rate 128000**
R3(config-if)#**exit**

Router(config)#**hostname R4**

https://t.me/learningnets

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip address 150.4.4.4 255.255.255.0**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**no shutdown**
R4(config-if)#**exit**

Task 2

R3(config)#**router ospf 3**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**network 10.0.0.13 0.0.0.0 area 0**
R3(config-router)#**area 0 authentication message-digest**
R3(config-router)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R3(config-router)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**network 150.4.4.4 0.0.0.0 area 0**
R4(config-router)#**network 10.0.0.14 0.0.0.0 area 0**
R4(config-router)#**area 0 authentication message-digest**
R4(config-router)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R4(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:32 10.0.0.14 Serial1/2

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:39 10.0.0.13 Serial0/0

Verify area authentication using the **show ip ospf** command:

R3#**show ip ospf | begin Area BACKBONE**
Area BACKBONE(0)
Number of interfaces in this area is 1

https://t.me/learningnets

Area has message digest authentication
SPF algorithm last executed 00:01:23.648 ago
SPF algorithm executed 2 times
Area ranges are
Number of LSA 2. Checksum Sum 0x009D60
Number of opaque link LSA 0. Checksum Sum 0x000000
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0

Finally, verify interface configuration using the **show ip ospf interface** command:

R3#**show ip ospf interface serial 1/2**
Serial1/2 is up, line protocol is up
Internet Address 10.0.0.13/30, Area 0
Process ID 3, Router ID 3.3.3.3, Network Type POINT_TO_POINT, Cost: 781
Transmit Delay is 1 sec, State POINT_TO_POINT
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
oob-resync timeout 40
Hello due in 00:00:05
Supports Link-local Signaling (LLS)
Index 1/1, flood queue length 0
Next 0x0(0)/0x0(0)
Last flood scan length is 1, maximum is 1
Last flood scan time is 0 msec, maximum is 0 msec
Neighbor Count is 1, Adjacent neighbor count is 1
Adjacent with neighbor 4.4.4.4
Suppress hello for 0 neighbor(s)
Message digest authentication enabled
Youngest key id is 1

Task 3

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**network 10.0.0.5 0.0.0.0 area 1**
R1(config-router)#**area 1 stub**
R1(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**network 10.0.0.6 0.0.0.0 area 1**

https://t.me/learningnets

R3(config-router)#**area 1 stub no-summary**
R3(config-router)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:32 10.0.0.6 Serial0/1

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:33 10.0.0.14 Serial1/2
1.1.1.1 0 FULL/ - 00:00:31 10.0.0.5 Serial1/0

Verify stub router configuration by looking at either the LSDB or routing table on R1:

R1#**show ip ospf database**

OSPF Router with ID (1.1.1.1) (Process ID 1)

Router Link States (Area 1)

Link ID ADV Router Age Seq# Checksum Link count
1.1.1.1 1.1.1.1 117 0x80000002 0x00F97D 2
3.3.3.3 3.3.3.3 118 0x80000002 0x001FAE 2

Summary Net Link States (Area 1)

Link ID ADV Router Age Seq# Checksum
0.0.0.0 3.3.3.3 190 0x80000001 0x0057DA

Additionally, you can also verify stub configuration using the **show ip ospf** command:

R1#**show ip ospf**
Routing Process “ospf 1” with ID 1.1.1.1
Start time: 00:30:16.176, Time elapsed: 00:03:00.312
Supports only single TOS(TOS0) routes
Supports opaque LSA
Supports Link-local Signaling (LLS)
Supports area transit capability
Router is not originating router-LSAs with maximum metric
Initial SPF schedule delay 5000 msecs
Minimum hold time between two consecutive SPFs 10000 msecs
Maximum wait time between two consecutive SPFs 10000 msecs
Incremental-SPF disabled
Minimum LSA interval 5 secs
Minimum LSA arrival 1000 msecs

https://t.me/learningnets

Technet24

LSA group pacing timer 240 secs
Interface flood pacing timer 33 msecs
Retransmission pacing timer 66 msecs
Number of external LSA 0. Checksum Sum 0x000000
Number of opaque AS LSA 0. Checksum Sum 0x000000
Number of DCbitless external and opaque AS LSA 0
Number of DoNotAge external and opaque AS LSA 0
Number of areas in this router is 1. 0 normal 1 stub 0 nssa
Number of areas transit capable is 0
External flood list length 0
Area 1
Number of interfaces in this area is 1
It is a stub area
Area has no authentication
SPF algorithm last executed 00:02:40.196 ago
SPF algorithm executed 2 times
Area ranges are
Number of LSA 3. Checksum Sum 0x017105
Number of opaque link LSA 0. Checksum Sum 0x000000
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0

Task 4

R2(config)#**router ospf 2**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**network 150.2.2.2 0.0.0.0 area 2**
R2(config-router)#**network 10.0.0.9 0.0.0.0 area 2**
R2(config-router)#**passive-interface fastethernet 0/0**
R2(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**network 10.0.0.10 0.0.0.0 area 2**
R3(config-router)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:31 10.0.0.10 Serial0/1

https://t.me/learningnets

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:31 10.0.0.14 Serial1/2
1.1.1.1 0 FULL/ - 00:00:39 10.0.0.5 Serial1/0
2.2.2.2 0 FULL/ - 00:00:36 10.0.0.9 Serial1/1

Task 5

To complete this task, you need to configure a virtual link across area 2. This virtual link must also be configured for MD5 authentication, which is being used in the backbone. However, because area 1 is a stub area, you cannot configure a virtual link. Instead, you need to configure a tunnel between R1 and R3. Because this tunnel will need to be assigned to area 0, you need to configure the OSPF password on this interface as well. This task is completed as follows:

R1(config)#**router ospf 1**
R1(config-router)#**area 0 authentication message-digest**
R1(config-router)#**network 10.0.0.1 0.0.0.0 area 3**
R1(config-router)#**network 11.0.0.1 0.0.0.0 area 0**
R1(config-router)#**network 150.1.1.1 0.0.0.0 area 3**
R1(config-router)#**exit**
R1(config)#**interface tunnel 0**
R1(config-if)#**ip address 11.0.0.1 255.255.255.252**
R1(config-if)#**tunnel source serial 0/1**
R1(config-if)#**tunnel destination 10.0.0.6**
R1(config-if)#**ip ospf message-digest-key 1 md5 CCNP**
R1(config-if)#**exit**

R2(config)#**router ospf 2**

R2(config-router)#**area 0 authentication message-digest**

R2(config-router)#**network 10.0.0.2 0.0.0.0 area 3**

R2(config-router)#**area 2 virtual-link 3.3.3.3 message-digest-key 1 md5 CCNP**

R2(config-router)#**exit**

R3(config)#**router ospf 3**

R3(config-router)#**area 2 virtual-link 2.2.2.2 message-digest-key 1 md5 CCNP**

R3(config-router)#**network 11.0.0.2 0.0.0.0 area 0**

R3(config-router)#**exit**

R3(config)#**interface tunnel 0**

https://t.me/learningnets

Technet24

R3(config-if)#**ip address 11.0.0.2 255.255.255.252**

R3(config-if)#**tunnel source serial 1/0**

R3(config-if)#**tunnel destination 10.0.0.5**

R3(config-if)#**ip ospf message-digest-key 1 md5 CCNP**

R3(config-if)#**exit**

Verify your configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:32 11.0.0.2 Tunnel0
3.3.3.3 0 FULL/ - 00:00:39 10.0.0.6 Serial0/1
2.2.2.2 0 FULL/ - 00:00:36 10.0.0.2 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:00:31 11.0.0.1 Tunnel0
2.2.2.2 0 FULL/ - - 10.0.0.9 OSPF_VL0
1.1.1.1 0 FULL/ - 00:00:35 10.0.0.5 Serial1/0
2.2.2.2 0 FULL/ - 00:00:38 10.0.0.9 Serial1/1

Test your configuration by disabling the R1-to-R2 link and pinging from R4 to R1. Please also test before disabling the link (not shown). After the test please enable the interface again (not shown):

R1(config)#**interface serial 0/0**
R1(config-if)#**shutdown**

R3#**show ip route 150.1.1.0 255.255.255.0**
Routing entry for 150.1.1.0/24
Known via "ospf 3", distance 110, metric 11112, type inter area
Last update from 11.0.0.1 on Tunnel0, 00:00:00 ago
Routing Descriptor Blocks:
* 11.0.0.1, from 1.1.1.1, 00:00:00 ago, via Tunnel0
Route metric is 11112, traffic share count is 1

R4#**ping 150.1.1.1 source 150.4.4.4 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 388/388/392 ms

https://t.me/learningnets

Test failover using the tunnel by shutting down the R1-to-R3 link:

R1(config)#**interface serial 0/1**
R1(config-if)#**shutdown**

R3#**show ip route 150.1.1.0 255.255.255.0**
Routing entry for 150.1.1.0/24
Known via "ospf 3", distance 110, metric 846, type inter area
Last update from 10.0.0.9 on Serial1/1, 00:00:46 ago
Routing Descriptor Blocks:
* 10.0.0.9, from 2.2.2.2, 00:00:46 ago, via Serial1/1
Route metric is 846, traffic share count is 1

R4#**ping 150.1.1.1 source 150.4.4.4 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 388/388/392 ms

Task 6

By default, OSPF uses IP addresses to identify neighbors. To configure Open Shortest Path First (OSPF) to look up Domain Name System (DNS) names for use in all OSPF **show** EXEC command displays, you need to enable OSPF name lookup. Because there are no DNS servers in this lab, you need to statically configure host entries on all routers. Prior to any changes, the **show ip ospf neighbor** command on all routers shows the following entries:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:38 11.0.0.2 Tunnel0
3.3.3.3 0 FULL/ - 00:00:39 10.0.0.6 Serial0/1
2.2.2.2 0 FULL/ - 00:00:30 10.0.0.2 Serial0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - - 10.0.0.10 OSPF_VL0
3.3.3.3 0 FULL/ - 00:00:32 10.0.0.10 Serial0/1
1.1.1.1 0 FULL/ - 00:00:36 10.0.0.1 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface

https://t.me/learningnets

Technet24

1.1.1.1 0 FULL/ - 00:00:37 11.0.0.1 Tunnel0
4.4.4.4 0 FULL/ - 00:00:37 10.0.0.14 Serial1/2
2.2.2.2 0 FULL/ - - 10.0.0.9 OSPF_VL0
1.1.1.1 0 FULL/ - 00:00:31 10.0.0.5 Serial1/0
2.2.2.2 0 FULL/ - 00:00:30 10.0.0.9 Serial1/1

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:34 10.0.0.13 Serial0/0

This task is completed using the **ip ospf name-lookup** and **ip host** commands:

R1(config)#**ip host R1 1.1.1.1**
R1(config)#**ip host R2 2.2.2.2**
R1(config)#**ip host R3 3.3.3.3**
R1(config)#**ip host R4 4.4.4.4**
R1(config)#**ip ospf name-lookup**

R2(config)#**ip host R1 1.1.1.1**
R2(config)#**ip host R2 2.2.2.2**
R2(config)#**ip host R3 3.3.3.3**
R2(config)#**ip host R4 4.4.4.4**
R2(config)#**ip ospf name-lookup**

R3(config)#**ip host R1 1.1.1.1**
R3(config)#**ip host R2 2.2.2.2**
R3(config)#**ip host R3 3.3.3.3**
R3(config)#**ip host R4 4.4.4.4**
R3(config)#**ip ospf name-lookup**

R4(config)#**ip host R1 1.1.1.1**
R4(config)#**ip host R2 2.2.2.2**
R4(config)#**ip host R3 3.3.3.3**
R4(config)#**ip host R4 4.4.4.4**
R4(config)#**ip ospf name-lookup**

After this configuration, the **show ip ospf neighbor** command now shows hostnames:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
R3 0 FULL/ - 00:00:35 11.0.0.2 Tunnel0
R3 0 FULL/ - 00:00:35 10.0.0.6 Serial0/1
R2 0 FULL/ - 00:00:37 10.0.0.2 Serial0/0

R2#**show ip ospf neighbor**

https://t.me/learningnets

Neighbor ID Pri State Dead Time Address Interface
R3 0 FULL/ - - 10.0.0.10 OSPF_VL0
R3 0 FULL/ - 00:00:35 10.0.0.10 Serial0/1
R1 0 FULL/ - 00:00:39 10.0.0.1 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
R1 0 FULL/ - 00:00:35 11.0.0.1 Tunnel0
R4 0 FULL/ - 00:00:35 10.0.0.14 Serial1/2
R2 0 FULL/ - - 10.0.0.9 OSPF_VL0
R1 0 FULL/ - 00:00:39 10.0.0.5 Serial1/0
R2 0 FULL/ - 00:00:38 10.0.0.9 Serial1/1

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
R3 0 FULL/ - 00:00:33 10.0.0.13 Serial0/0

The same is also applicable to entries that are stored in the Link State Database. The hostname replaces the IP address in the 'ADV Router' field of the **show ip ospf database** command:

R3#**show ip ospf database**

OSPF Router with ID (3.3.3.3) (Process ID 3)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
1.1.1.1 R1 824 0x80000006 0x007D54 2
2.2.2.2 R2 1 (DNA) 0x8000000B 0x002691 1
3.3.3.3 R3 771 0x8000000F 0x00F613 5
4.4.4.4 R4 1109 0x80000009 0x00A4F0 3

Summary Net Link States (Area 0)

Link ID ADV Router Age Seq# Checksum
10.0.0.0 R1 829 0x80000001 0x005998
10.0.0.0 R2 1 (DNA) 0x80000001 0x003BB2
10.0.0.4 R1 829 0x80000001 0x0031BC
10.0.0.4 R3 829 0x80000001 0x001006
10.0.0.8 R2 10 (DNA) 0x80000001 0x00EAFA
10.0.0.8 R3 782 0x80000001 0x00E72A
150.1.1.0 R1 1729 0x80000001 0x00B8E6
150.1.1.0 R2 1 (DNA) 0x80000001 0x001D3E

https://t.me/learningnets

Technet24

150.2.2.0 R2 10 (DNA) 0x80000001 0x008316
150.2.2.0 R3 773 0x80000001 0x000382

Router Link States (Area 1)

Link ID ADV Router Age Seq# Checksum Link count
1.1.1.1 R1 831 0x80000007 0x00F27E 2
3.3.3.3 R3 836 0x80000003 0x001DAF 2

Summary Net Link States (Area 1)

Link ID ADV Router Age Seq# Checksum
0.0.0.0 R1 826 0x80000003 0x008FA8
0.0.0.0 R3 1720 0x80000001 0x0057DA
10.0.0.0 R1 832 0x80000001 0x00777C
10.0.0.8 R1 785 0x80000001 0x00D0B8
10.0.0.12 R1 817 0x80000001 0x00A8DC
11.0.0.0 R1 827 0x80000001 0x00762A
150.1.1.0 R1 826 0x80000003 0x00D2CC
150.2.2.0 R1 775 0x80000001 0x00EB11
150.4.4.0 R1 817 0x80000001 0x00BD3B

Router Link States (Area 2)

Link ID ADV Router Age Seq# Checksum Link count
2.2.2.2 R2 776 0x80000017 0x00039C 3
3.3.3.3 R3 776 0x8000000D 0x00A907 2

Summary Net Link States (Area 2)

Link ID ADV Router Age Seq# Checksum
10.0.0.0 R2 781 0x80000003 0x0037B4
10.0.0.4 R3 834 0x80000001 0x001006
10.0.0.12 R3 1718 0x80000001 0x00BF4E
11.0.0.0 R3 824 0x80000001 0x001C7A
150.1.1.0 R2 781 0x80000003 0x001940
150.4.4.0 R3 1108 0x80000001 0x00D4AC

This is also applicable when looking at specific LSAs in the Link State Database:

R1#**show ip ospf database summary 0.0.0.0**

OSPF Router with ID (1.1.1.1) (Process ID 1)

Summary Net Link States (Area 1)

LS age: 997
Options: (No TOS-capability, DC, Upward)

https://t.me/learningnets

LS Type: Summary Links(Network)
Link State ID: 0.0.0.0 (summary Network Number)
Advertising Router: R1
LS Seq Number: 80000003
Checksum: 0x8FA8
Length: 28
Network Mask: /0
TOS: 0 Metric: 1

LS age: 1892
Options: (No TOS-capability, DC, Upward)
LS Type: Summary Links(Network)
Link State ID: 0.0.0.0 (summary Network Number)
Advertising Router: R3
LS Seq Number: 80000001
Checksum: 0x57DA
Length: 28
Network Mask: /0
TOS: 0 Metric: 1

https://t.me/learningnets

Technet24

CCNP Lab 034: Border Gateway Protocol Lab

Lab Objective:

The focus of this lab is to understand BGP implementation and configuration in Cisco IOS routers. Additional technologies tested include route reflectors, route-maps, and security.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Technet24

Without using peer groups, configure internal BGP on R1, R2, R3, and R4 as follows:

- Statically configure a BGP router ID using the router number, e.g. 1.1.1.1 for R1, etc.
- All routers should peer using their physical interface addresses
- R1 should peer to R2 and R3
- R2 should peer to R1
- R3 should peer to R1 and R4
- R4 should peer to R3
- All routers should use the TCP MD5 authentication password 'CCNP'
- BGP Hellos should be sent out every 5 seconds
- All of the BGP speakers should advertise a Hold Time of 15 seconds
- The COMMUNITIES attribute (standard) should be supported

Task 3

Advertise the 150.1.1.0/24, 150.2.2.0, and 150.3.3.0/24 subnets on R1, R2, and R3 via BGP. These prefixes must be advertised with the standard community values listed below. You are NOT allowed to redistribute these prefixes into BGP. Additionally, you are NOT allowed to use outbound or inbound route-maps when completing this task. Ensure that the community values are displayed in ASN:nn (RFC 1997 - BGP Communities Attribute) format. Verify your configuration using the appropriate commands.

- The 150.1.1.0/24: community value of 254:111
- The 150.2.2.0/24: community value of 254:222
- The 150.3.3.0/24: community value of 254:333

Task 4

Configure your network so that all 150.x.x.x/24 subnets can reach each other. You are NOT allowed to use any static routes in your solution. Additionally, you are NOT allowed to advertise or redistribute the 150.4.4.0/24 subnet into BGP on R4. Instead, consider other BGP features to complete this task. You are NOT allowed to configure R2 or R4. Additionally, you are NOT allowed to configure a dynamic routing protocol to complete this task.

Next, verify your configuration using the appropriate commands as well as the extended ping function. For example, on R1 use the extended ping function to send a ping to 150.2.2.2 sourced from 150.1.1.1, etc, etc. All pings should work when the task is completed correctly.

https://t.me/learningnets

Lab Validation:

Task 1

Please refer to previous tasks for basic IP addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

The requirements of this task are straightforward and are completed as follows:

R1(config)#**router bgp 254**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**neighbor 10.0.0.2 remote-as 254**
R1(config-router)#**neighbor 10.0.0.2 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R1(config-router)#**neighbor 10.0.0.2 password CCNP**
R1(config-router)#**neighbor 10.0.0.2 send-community standard**
R1(config-router)#**neighbor 10.0.0.6 remote-as 254**
R1(config-router)#**neighbor 10.0.0.6 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R1(config-router)#**neighbor 10.0.0.6 password CCNP**
R1(config-router)#**neighbor 10.0.0.6 send-community standard**
R1(config-router)#**exit**

R2(config)#**router bgp 254**
R2(config-router)#**bgp router-id 2.2.2.2**
R2(config-router)#**neighbor 10.0.0.1 remote-as 254**
R2(config-router)#**neighbor 10.0.0.1 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R2(config-router)#**neighbor 10.0.0.1 password CCNP**
R2(config-router)#**neighbor 10.0.0.1 send-community standard**
R2(config-router)#**exit**

R3(config)#**router bgp 254**
R3(config-router)#**bgp router-id 3.3.3.3**
R3(config-router)#**neighbor 10.0.0.5 remote-as 254**
R3(config-router)#**neighbor 10.0.0.5 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping

https://t.me/learningnets

Technet24

R3(config-router)#**neighbor 10.0.0.5 password CCNP**
R3(config-router)#**neighbor 10.0.0.5 send-community standard**
R3(config-router)#**neighbor 10.0.0.14 remote-as 254**
R3(config-router)#**neighbor 10.0.0.14 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R3(config-router)#**neighbor 10.0.0.14 password CCNP**
R3(config-router)#**neighbor 10.0.0.14 send-community standard**
R3(config-router)#**exit**

R4(config)#**router bgp 254**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**neighbor 10.0.0.13 remote-as 254**
R4(config-router)#**neighbor 10.0.0.13 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R4(config-router)#**neighbor 10.0.0.13 password CCNP**
R4(config-router)#**neighbor 10.0.0.13 send-community standard**
R4(config-router)#**exit**

Verify your configuration using the **show ip bgp summary** command:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.2 4 254 32 32 1 0 0 00:02:27 0
10.0.0.6 4 254 20 21 1 0 0 00:01:25 0

R2#**show ip bgp summary**
BGP router identifier 2.2.2.2, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.1 4 254 33 33 1 0 0 00:02:31 0

R3#**show ip bgp summary**
BGP router identifier 3.3.3.3, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.5 4 254 22 21 1 0 0 00:01:33 0
10.0.0.14 4 254 8 8 1 0 0 00:00:22 0

https://t.me/learningnets

R4#**show ip bgp summary**
BGP router identifier 4.4.4.4, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.13 4 254 9 9 1 0 0 00:00:25 0

Task 3

BGP allows you to set attributes for prefixes advertised via the **network <network> mask <mask>** command by appending a route map to this command. The route map can be used to set or modify different BGP attributes for the network. This is completed as follows:

R1(config)#**route-map COMMUNITY permit 10**
R1(config-route-map)#**set community 254:111**
R1(config-route-map)#**exit**
R1(config)#**router bgp 254**
R1(config-router)#**network 150.1.1.0 mask 255.255.255.0 route-map COMMUNITY**
R1(config-router)#**exit**

R2(config)#**route-map COMMUNITY permit 10**
R2(config-route-map)#**set community 254:222**
R2(config-route-map)#**exit**
R2(config)#**router bgp 254**
R2(config-router)#**network 150.2.2.0 mask 255.255.255.0 route-map COMMUNITY**
R2(config-router)#**exit**

R3(config)#**route-map COMMUNITY permit 10**
R3(config-route-map)#**set community 254:333**
R3(config-route-map)#**exit**
R3(config)#**router bgp 254**
R3(config-router)#**network 150.3.3.0 mask 255.255.255.0 route-map COMMUNITY**
R3(config-router)#**exit**

Verify your configuration using the **show ip bgp** command on all routers:

R1#**show ip bgp 150.1.1.0 255.255.255.0**
BGP routing table entry for 150.1.1.0/24, version 2
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Flag: 0x820
Advertised to update-groups:
1
Local

https://t.me/learningnets

Technet24

0.0.0.0 from 0.0.0.0 (1.1.1.1)
Origin IGP, metric 0, localpref 100, weight 32768, valid, sourced, local, best
Community: 16646255

By default, the Cisco default community format is one 32-bit number (as seen above). To ensure that the community conforms to RFC 1997 (BGP Communities Attribute), you need to issue the **ip bgp-community new-format** command on all routers. This task is completed as follows:

R1(config)#**ip bgp-community new-format**

R2(config)#**ip bgp-community new-format**

R3(config)#**ip bgp-community new-format**

R4(config)#**ip bgp-community new-format**

Verify these changes using the **show ip bgp** command on all routers:

R1#**show ip bgp 150.1.1.0 255.255.255.0**
BGP routing table entry for 150.1.1.0/24, version 2
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Flag: 0x820
Advertised to update-groups:
1
Local
0.0.0.0 from 0.0.0.0 (1.1.1.1)
Origin IGP, metric 0, localpref 100, weight 32768, valid, sourced, local, best
Community: 254:111

R2#**show ip bgp 150.2.2.0 255.255.255.0**
BGP routing table entry for 150.2.2.0/24, version 3
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Flag: 0x820
Advertised to update-groups:
1
Local
0.0.0.0 from 0.0.0.0 (2.2.2.2)
Origin IGP, metric 0, localpref 100, weight 32768, valid, sourced, local, best
Community: 254:222

R3#**show ip bgp 150.3.3.0 255.255.255.0**
BGP routing table entry for 150.3.3.0/24, version 3
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Flag: 0x820

https://t.me/learningnets

Advertised to update-groups:
1
Local
0.0.0.0 from 0.0.0.0 (3.3.3.3)
Origin IGP, metric 0, localpref 100, weight 32768, valid, sourced, local, best
Community: 254:333

You can verify that the COMMUNITY attribute is being sent to peers using the **show ip bgp neighbors <address>** command:

R1#**show ip bgp neighbors 10.0.0.2**
BGP neighbor is 10.0.0.2, remote AS 254, internal link
BGP version 4, remote router ID 10.0.0.2
BGP state = Established, up for 00:34:11
Last read 00:00:00, last write 00:00:00, hold time is 15, keepalive interval is 5 seconds
Configured hold time is 15,keepalive interval is 5 seconds Minimum holdtime from neighbor is 0 seconds
Neighbor capabilities:
Route refresh: advertised and received(old & new)
Address family IPv4 Unicast: advertised and received
Message statistics:
InQ depth is 0
OutQ depth is 0
Sent Rcvd
Opens: 1 1
Notifications: 0 0
Updates: 5 1
Keepalives: 413 413
Route Refresh: 0 0
Total: 419 415
Default minimum time between advertisement runs is 0 seconds

For address family: IPv4 Unicast
BGP table version 6, neighbor version 6/0
Output queue size : 0
Index 1, Offset 0, Mask 0x2
1 update-group member
Community attribute sent to this neighbor

Task 4

The requirements of this final task are three-fold. Because we cannot advertise the

https://t.me/learningnets

Technet24

150.4.4.0/24 subnet connected to R4 via BGP, we need to configure this router to advertise a default route to the rest of the domain, allowing all other routers to reach this subnet.

Therefore, the first part of this task is completed by advertising a default route from R4 so that all other routers can reach the 150.4.4.0/24 subnet since this cannot be advertised or redistributed into BGP. To advertise a default route without one existing in the routing table, use the **neighbor <address> default-originate** command under BGP. This task is completed by executing this command on R4 as follows:

```
R4(config)#router bgp 254
R4(config-router)#neighbor 10.0.0.13 default-originate
R4(config-router)#exit
```

Following this, verify that there is NO default route locally on R4:

```
R4#show ip bgp 0.0.0.0 0.0.0.0
% Network not in table
```

However, based on the configuration, a BGP-originated default route is now advertised to R3:

```
R3#show ip bgp 0.0.0.0 0.0.0.0
BGP routing table entry for 0.0.0.0/0, version 4
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Flag: 0x820
Not advertised to any peer
Local
10.0.0.14 from 10.0.0.14 (4.4.4.4)
Origin IGP, metric 0, localpref 100, valid, internal, best
```

The second part of this task is to ensure that routes are advertised between all routers. Since we cannot configure R2 or R4, we need to configure R1 and R3 as route reflectors. This is because, by default, internal BGP (iBGP) speakers will NOT advertise routes received from one iBGP speaker to another iBGP speaker.

Because of this default rule, the BGP tables on all routers are incomplete and do not contain all the prefixes. Verify using the **show ip bgp** command. For example, R1 will not have the default route advertised by R4 in its BGP Table because this default route is received by R3 from another iBGP peer:

```
R1#show ip bgp
BGP table version is 4, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
```

https://t.me/learningnets

Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
*>i150.2.2.0/24 10.0.0.2 0 100 0 i
*>i150.3.3.0/24 10.0.0.6 0 100 0 i

Likewise, R2 will not show an entry for the 150.3.3.0/24 (R3) and 0.0.0.0/0 (R4) prefixes in its BGP Table because the 150.3.3.0/24 prefix is advertised to R1 from an iBGP peer. Likewise, because R1 never receives the default route from R3, this will never show up in R2s BGP Table.

R2#**show ip bgp**
BGP table version is 3, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i150.1.1.0/24 10.0.0.1 0 100 0 i
*> 150.2.2.0/24 0.0.0.0 0 32768 i

The same concept is also applicable to R3 and R4. To address this issue, you need to configure R1 and R3 as route reflectors. When doing so, you do NOT need to configure R1 and R3 as clients of each other. This is because, by default, a route reflector will advertise routes received from a client to a non-client and vice versa. This task is completed as follows:

R1(config)#**router bgp 254**
R1(config-router)#**neighbor 10.0.0.2 route-reflector-client**
R1(config-router)#**exit**

R3(config)#**router bgp 254**
R3(config-router)#**neighbor 10.0.0.14 route-reflector-client**
R3(config-router)#**exit**

However, you will still notice that the routers still cannot ping each others' 150.x.x.x/24 subnets. This is because the NEXT_HOP attribute is NOT changed when these prefixes are advertised between the iBGP peers. For example, on R1, the NEXT_HOP for the 0.0.0.0/0 prefix reflects the IP address of R1 (10.0.0.14). Because there is no route for this prefix, it is considered inaccessible and is not advertised to R2:

R1#**show ip bgp 0.0.0.0 0.0.0.0**

BGP routing table entry for 0.0.0.0/0, version 12

Paths: (1 available, no best path)

https://t.me/learningnets

Technet24

Not advertised to any peer

Local

10.0.0.14 (inaccessible) from 10.0.0.6 (3.3.3.3)

Origin IGP, metric 0, localpref 100, valid, internal

Originator: 4.4.4.4, Cluster list: 3.3.3.3

To resolve this issue, you need to either run an IGP or use static routes, which is forbidden in this task, or modify the BGP NEXT_HOP. However, because these updates are from iBGP neighbors, you cannot use the **neighbor <address> next-hop-self** command. The reason you need to modify the NEXT_HOP using a route-map is that the **neighbor <address> next-hop-self** command should not be used to modify the NEXT_HOP attribute for a route reflector when this feature is enabled for a route reflector client.

It will not work because this command will modify next hop attributes only for routes that are learned from eBGP peers and not the intended routes that are being reflected from the route reflector clients. This means that the NEXT_HOP for all routes received from the iBGP peers will be inaccessible since we are not running an IGP or using static routes in the network. For example, on R1, the NEXT_HOP for the default advertised by R4 shows the IP address of the Serial0/0 interface on R4, which is 10.0.0.14, as illustrated or shown in the previous output.

Because the **neighbor <address> next-hop-self** command will not work due to the route reflector configuration, the only other way to modify the next NEXT_HOP attribute is using an outbound route map. This task is completed as follows:

R1(config)#**route-map R2-NEXT-HOP permit 10**
R1(config-route-map)#**set ip next-hop 10.0.0.1**
% Warning: Next hop address is our address
R1(config-route-map)#**exit**
R1(config)#**route-map R3-NEXT-HOP permit 10**
R1(config-route-map)#**set ip next-hop 10.0.0.5**
% Warning: Next hop address is our address
R1(config-route-map)#**exit**
R1(config)#**router bgp 254**
R1(config-router)#**neighbor 10.0.0.2 route-map R2-NEXT-HOP out**
R1(config-router)#**neighbor 10.0.0.6 route-map R3-NEXT-HOP out**
R1(config-router)#**exit**

R3(config)#**route-map R1-NEXT-HOP permit 10**
R3(config-route-map)#**set ip next-hop 10.0.0.6**

https://t.me/learningnets

% Warning: Next hop address is our address
R3(config-route-map)#**exit**
R3(config)#**route-map R4-NEXT-HOP permit 10**
R3(config-route-map)#**set ip next-hop 10.0.0.13**
% Warning: Next hop address is our address
R3(config-route-map)#**exit**
R3(config)#**router bgp 254**
R3(config-router)#**neighbor 10.0.0.14 route-map R4-NEXT-HOP out**
R3(config-router)#**neighbor 10.0.0.5 route-map R1-NEXT-HOP out**
R3(config-router)#**exit**

Following this configuration, the BGP RIBs on all routers show the following entries:

R1#**show ip bgp**
BGP table version is 7, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
***>i0.0.0.0 10.0.0.6 0 100 0 i**
*> 150.1.1.0/24 0.0.0.0 0 32768 i
*>i150.2.2.0/24 10.0.0.2 0 100 0 i
***>i150.3.3.0/24 10.0.0.6 0 100 0 i**

R2#**show ip bgp**
BGP table version is 7, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
***>i0.0.0.0 10.0.0.1 0 100 0 i**
***>i150.1.1.0/24 10.0.0.1 0 100 0 i**
*> 150.2.2.0/24 0.0.0.0 0 32768 i
***>i150.3.3.0/24 10.0.0.1 0 100 0 i**

R3#**show ip bgp**
BGP table version is 4, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path

https://t.me/learningnets
Technet24

*>i0.0.0.0 10.0.0.14 0 100 0 i
***>i150.1.1.0/24 10.0.0.5 0 100 0 i**
***>i150.2.2.0/24 10.0.0.5 0 100 0 i**

R4#**show ip bgp**
BGP table version is 7, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
***>i150.1.1.0/24 10.0.0.13 0 100 0 i**
***>i150.2.2.0/24 10.0.0.13 0 100 0 i**
***>i150.3.3.0/24 10.0.0.13 0 100 0 i**

Finally, complete this task by issuing extended pings, LAN-to-LAN, between the routers:

R1#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R1#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R1#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R2#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2

https://t.me/learningnets

!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/2/4 ms

R2#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R2#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/31/40 ms

R3#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/14/16 ms

R3#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R3#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R4#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:

https://t.me/learningnets

Technet24

Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

https://t.me/learningnets

CCNP Lab 035: Border Gateway Protocol Lab

Lab Objective:

The focus of this lab is to understand BGP implementation and configuration in Cisco IOS routers. Additional technologies tested include route reflection and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Configure the following Loopback 0 interfaces on all routers:

R1 - Loopback 0: IP Address 1.1.1.1/32
R2 - Loopback 0: IP Address 2.2.2.2/32
R3 - Loopback 0: IP Address 3.3.3.3/32
R4 - Loopback 0: IP Address 4.4.4.4/32

Next, configure EIGRP, using AS 254, on all routers and enable EIGRP for all interfaces EXCEPT for the 150.x.x.x/24 LAN subnets connected to R1, R2, R3, and R4. Verify your configuration.

Task 3

Configure internal BGP on R1, R2, R3, and R4 shown below. Use peer-group configuration on R2 and R4 but NOT on R1 and R3:

- All routers should use their Loopback 0 interface addresses as their router IDs
- All routers should peer using their Loopback 0 interface addresses
- R1 and R3 should be configured as Route Reflectors
- R2 should peer with R1 and R3
- R4 should peer with R1 and R3
- R1 and R3 belong to the same cluster to reduce the size of the RIB
- All routers should use TCP MD5 authentication with a password of 'CCNP'
- BGP Hellos should be sent every 5 seconds and the Hold Time should be set to 15 seconds

Verify your configuration using the appropriate commands.

Task 4

Advertise the 150.x.x.x/24 subnets on all routers via BGP. These prefixes should be redistributed into BGP on every router. In the future, there will be external BGP connections to one or more ISPs. Management has decided that the 150.x.x.x/24 subnets should never be advertised to these ISPs. Ensure that these prefixes are NEVER advertised out of AS 254. You are NOT allowed to use prefix lists or any type of filters. Verify your configuration using the appropriate commands. Verify that each router can also ping every other routers' 150.x.x.x/24 LAN subnet.

Task 5

Ensure that R2 and R4 always prefer routes received from R3 to those received from R1 for each others' 150.x.x.x/24 prefixes. You are only allowed to configure ONE router. Your solution should be globally significant; however, you are NOT allowed to modify any of the BGP default administrative distance values. You can modify BGP

https://t.me/learningnets

Technet24

attributes as you see fit. Verify the configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IP addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. This will not be included in this section to avoid being redundant. Following completion, the routing tables on your routers should show the following EIGRP route entries:

R1#**show ip route eigrp**
2.0.0.0/32 is subnetted, 1 subnets
D 2.2.2.2 [90/2297856] via 10.0.0.2, 00:01:21, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
D 3.3.3.3 [90/2297856] via 10.0.0.6, 00:00:46, Serial0/1
4.0.0.0/32 is subnetted, 1 subnets
D 4.4.4.4 [90/21152000] via 10.0.0.6, 00:00:15, Serial0/1
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.12 [90/21024000] via 10.0.0.6, 00:01:01, Serial0/1

R2#**show ip route eigrp**
1.0.0.0/32 is subnetted, 1 subnets
D 1.1.1.1 [90/2297856] via 10.0.0.1, 00:01:42, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
D 3.3.3.3 [90/2809856] via 10.0.0.1, 00:01:00, Serial0/0
4.0.0.0/32 is subnetted, 1 subnets
D 4.4.4.4 [90/21664000] via 10.0.0.1, 00:00:30, Serial0/0
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.12 [90/21536000] via 10.0.0.1, 00:01:15, Serial0/0
D 10.0.0.4 [90/2681856] via 10.0.0.1, 00:01:42, Serial0/0

R3#**show ip route eigrp**
1.0.0.0/32 is subnetted, 1 subnets
D 1.1.1.1 [90/20640000] via 10.0.0.5, 00:01:34, Serial1/0
2.0.0.0/32 is subnetted, 1 subnets
D 2.2.2.2 [90/21152000] via 10.0.0.5, 00:01:34, Serial1/0
4.0.0.0/32 is subnetted, 1 subnets
D 4.4.4.4 [90/20640000] via 10.0.0.14, 00:00:44, Serial1/2
10.0.0.0/30 is subnetted, 3 subnets

https://t.me/learningnets

D 10.0.0.0 [90/21024000] via 10.0.0.5, 00:01:34, Serial1/0

R4#**show ip route eigrp**
1.0.0.0/32 is subnetted, 1 subnets
D 1.1.1.1 [90/21152000] via 10.0.0.13, 00:01:06, Serial0/0
2.0.0.0/32 is subnetted, 1 subnets
D 2.2.2.2 [90/21664000] via 10.0.0.13, 00:01:06, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
D 3.3.3.3 [90/2297856] via 10.0.0.13, 00:01:06, Serial0/0
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.0 [90/21536000] via 10.0.0.13, 00:01:06, Serial0/0
D 10.0.0.4 [90/21024000] via 10.0.0.13, 00:01:06, Serial0/0

Task 3

This task is straightforward. By default, the BGP RID will be derived from the highest address of all physical interfaces or the highest address of all Loopback interfaces. Given that the Loopback0 interfaces are configured on all routers, there is NO need to manually configure the RID using the **bgp router-id <address>** command.

Additionally, when configuring the route reflectors, it is important to understand that they do not need to be clients of each other. Instead, in environments where there are multiple route reflectors being used for redundancy, you should configure route reflectors in the same cluster, i.e. serving the same clients, using the **bgp cluster-id <cluster ID>** command. This prevents multiple entries in the BGP Table because the route reflectors recognize updates from each other based on the CLUSTER_LIST attribute. The CLUSTER_LIST attribute is an optional, non-transitive BGP attribute of Type Code 10.

It is a sequence of CLUSTER_ID values representing the route reflection path that the prefix has traversed. When the RR reflects a route, it must prepend the local CLUSTER_ID to the CLUSTER_LIST. If the UPDATE has an empty CLUSTER_LIST, the RR must create a new one. Like the ORIGINATOR_ID attribute, the CLUSTER_LIST attribute is also used to prevent loops in iBGP implementations.

Finally, remember that when you are configuring multiple BGP peers, you can also configure peer groups to minimize the number of commands that are issued. Both the long version and peer group configuration are illustrated in this example. You may use either method to complete this task. In this example, the task is completed using both of the methods as follows:

R1(config)#**router bgp 254**
R1(config-router)#**bgp cluster-id 55.55.55.55**

https://t.me/learningnets

Technet24

R1(config-router)#**neighbor 2.2.2.2 remote-as 254**
R1(config-router)#**neighbor 2.2.2.2 update-source loopback 0**
R1(config-router)#**neighbor 2.2.2.2 route-reflector-client**
R1(config-router)#**neighbor 2.2.2.2 password CCNP**
R1(config-router)#**neighbor 2.2.2.2 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R1(config-router)#**neighbor 3.3.3.3 remote-as 254**
R1(config-router)#**neighbor 3.3.3.3 update-source loopback 0**
R1(config-router)#**neighbor 3.3.3.3 password CCNP**
R1(config-router)#**neighbor 3.3.3.3 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R1(config-router)#**neighbor 4.4.4.4 remote-as 254**
R1(config-router)#**neighbor 4.4.4.4 update-source loopback 0**
R1(config-router)#**neighbor 4.4.4.4 route-reflector-client**
R1(config-router)#**neighbor 4.4.4.4 password CCNP**
R1(config-router)#**neighbor 4.4.4.4 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R1(config-router)#**exit**

R2(config)#**router bgp 254**
R2(config-router)#**neighbor INTERNAL peer-group**
R2(config-router)#**neighbor INTERNAL remote-as 254**
R2(config-router)#**neighbor INTERNAL update-source loopback 0**
R2(config-router)#**neighbor INTERNAL password CCNP**
R2(config-router)#**neighbor INTERNAL timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R2(config-router)#**neighbor 1.1.1.1 peer-group INTERNAL**
R2(config-router)#**neighbor 3.3.3.3 peer-group INTERNAL**
R2(config-router)#**exit**

R3(config)#**router bgp 254**
R3(config-router)#**bgp cluster-id 55.55.55.55**
R3(config-router)#**neighbor 1.1.1.1 remote-as 254**
R3(config-router)#**neighbor 1.1.1.1 update-source loopback 0**
R3(config-router)#**neighbor 1.1.1.1 password CCNP**
R3(config-router)#**neighbor 1.1.1.1 timers 5 15**

https://t.me/learningnets

% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R3(config-router)#**neighbor 2.2.2.2 remote-as 254**
R3(config-router)#**neighbor 2.2.2.2 update-source loopback 0**
R3(config-router)#**neighbor 2.2.2.2 password CCNP**
R3(config-router)#**neighbor 2.2.2.2 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R3(config-router)#**neighbor 2.2.2.2 route-reflector-client**
R3(config-router)#**neighbor 4.4.4.4 remote-as 254**
R3(config-router)#**neighbor 4.4.4.4 update-source loopback 0**
R3(config-router)#**neighbor 4.4.4.4 password CCNP**
R3(config-router)#**neighbor 4.4.4.4 timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R3(config-router)#**neighbor 4.4.4.4 route-reflector-client**
R3(config-router)#**exit**

R4(config)#**router bgp 254**
R4(config-router)#**neighbor INTERNAL peer-group**
R4(config-router)#**neighbor INTERNAL update-source loopback 0**
R4(config-router)#**neighbor INTERNAL remote-as 254**
R4(config-router)#**neighbor INTERNAL timers 5 15**
% Warning: A hold time of less than 20 seconds increases
the chances of peer flapping
R4(config-router)#**neighbor INTERNAL password CCNP**
R4(config-router)#**neighbor 1.1.1.1 peer-group INTERNAL**
R4(config-router)#**neighbor 3.3.3.3 peer-group INTERNAL**
R4(config-router)#**exit**

Verify your configuration using the **show ip bgp summary** command:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
2.2.2.2 4 254 70 70 1 0 0 00:05:32 0
3.3.3.3 4 254 53 53 1 0 0 00:04:09 0
4.4.4.4 4 254 12 13 1 0 0 00:00:45 0

R2#**show ip bgp summary**

https://t.me/learningnets

Technet24

BGP router identifier 2.2.2.2, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
1.1.1.1 4 254 71 71 1 0 0 00:05:37 0
3.3.3.3 4 254 40 40 1 0 0 00:03:00 0

R3#**show ip bgp summary**
BGP router identifier 3.3.3.3, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
1.1.1.1 4 254 55 55 1 0 0 00:04:17 0
2.2.2.2 4 254 40 40 1 0 0 00:03:04 0
4.4.4.4 4 254 12 12 1 0 0 00:00:41 0

R4#**show ip bgp summary**
BGP router identifier 4.4.4.4, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
1.1.1.1 4 254 15 14 1 0 0 00:00:57 0
3.3.3.3 4 254 12 12 1 0 0 00:00:44 0

Task 4

To complete this task, you need to use the COMMUNITY attribute. This attribute, Attribute Type Code 8, is an optional transitive attribute that is used to group destinations, called communities. Once the destination prefixes have been grouped, routing decisions, such as acceptance, preference, and redistribution, can be applied. Cisco IOS route maps are to set the community attribute.

Well-known communities are communities that have predefined meanings. Cisco IOS software supports four well-known communities which are NO_EXPORT, NO_ADVERTISE, INTERNET, and LOCAL_AS. The NO_EXPORT well-known community prevents BGP prefixes that are specifically assigned this predefined community attribute value from being advertised to any eBGP peers. The prefixes, however, will continue to be advertised to all other BGP speakers within the local AS. In other words, prefixes assigned this community value will remain local to the Autonomous System (AS).

The NO_ADVERTISE community prevents any prefixes that are assigned to this predefined community attribute from being advertised to any peer – internal or external. The INTERNET community allows all prefixes assigned to this community to be advertised to any and all BGP peers (assuming no filtering, etc, is in place). In Cisco

https://t.me/learningnets

IOS software, all BGP prefixes belong to the INTERNET community by default.

And finally, the LOCAL_AS community is used in a somewhat similar manner to another of the previously described communities: the NO_EXPORT community. If used in a Confederation, the LOCAL_AS community prevents all prefixes assigned this community from being advertised out of the local sub autonomous system. When Confederations are not implemented, the LOCAL_AS community is applied in the same manner as the NO_EXPORT community.

To complete this task, use either the LOCAL_AS or NO_EXPORT communities. In order to use the COMMUNITY attribute, you need to configure the **neighbor <address> send-community** command for all peers. This task is completed as follows:

R1(config)#**route-map CONNECTED permit 10**
R1(config-route-map)#**match interface fastethernet 0/0**
R1(config-route-map)#**set community local-as**
R1(config-route-map)#**exit**
R1(config)#**route-map CONNECTED deny 20**
R1(config-route-map)#**exit**
R1(config)#**router bgp 254**
R1(config-router)#**redistribute connected route-map CONNECTED**
R1(config-router)#**neighbor 2.2.2.2 send-community standard**
R1(config-router)#**neighbor 3.3.3.3 send-community standard**
R1(config-router)#**neighbor 4.4.4.4 send-community standard**

R2(config)#**route-map CONNECTED permit 10**
R2(config-route-map)#**match interface fastethernet 0/0**
R2(config-route-map)#**set community local-as**
R2(config-route-map)#**exit**
R2(config)#**route-map CONNECTED deny 20**
R2(config-route-map)#**exit**
R2(config)#**router bgp 254**
R2(config-router)#**redistribute connected route-map CONNECTED**
R2(config-router)#**neighbor INTERNAL send-community standard**
R2(config-router)#**exit**

R3(config-router)#**route-map CONNECTED permit 10**
R3(config-route-map)#**match interface fastethernet 0/0**
R3(config-route-map)#**set community local-as**
R3(config-route-map)#**exit**
R3(config)#**route-map CONNECTED deny 20**
R3(config-route-map)#**exit**

https://t.me/learningnets

Technet24

R3(config)#**router bgp 254**
R3(config-router)#**redistribute connected route-map CONNECTED**
R3(config-router)#**neighbor 1.1.1.1 send-community standard**
R3(config-router)#**neighbor 2.2.2.2 send-community standard**
R3(config-router)#**neighbor 4.4.4.4 send-community standard**

R4(config)#**route-map CONNECTED permit 10**
R4(config-route-map)#**match interface fastethernet 0/0**
R4(config-route-map)#**set community local-as**
R4(config-route-map)#**exit**
R4(config)#**route-map CONNECTED deny 20**
R4(config-route-map)#**exit**
R4(config)#**router bgp 254**
R4(config-router)#**redistribute connected route-map CONNECTED**
R4(config-router)#**neighbor INTERNAL send-community standard**
R4(config-router)#**exit**

Following this configuration, verify your configuration using the **show ip bgp** command:

R1#**show ip bgp 150.1.1.0 255.255.255.0**
BGP routing table entry for 150.1.1.0/24, version 2
Paths: (1 available, best #1, table Default-IP-Routing-Table, not advertised outside local AS)
Advertised to update-groups:
1 2
Local
0.0.0.0 from 0.0.0.0 (1.1.1.1)
Origin incomplete, metric 0, localpref 100, weight 32768, valid, sourced, best
Community: local-AS

R2#**show ip bgp 150.2.2.0 255.255.255.0**
BGP routing table entry for 150.2.2.0/24, version 3
Paths: (1 available, best #1, table Default-IP-Routing-Table, not advertised outside local AS)
Flag: 0x820
Advertised to update-groups:
1
Local
0.0.0.0 from 0.0.0.0 (2.2.2.2)
Origin incomplete, metric 0, localpref 100, weight 32768, valid, sourced, best
Community: local-AS

https://t.me/learningnets

R3#**show ip bgp 150.3.3.0 255.255.255.0**
BGP routing table entry for 150.3.3.0/24, version 4
Paths: (1 available, best #1, table Default-IP-Routing-Table, not advertised outside local AS)
Advertised to update-groups:
1 2
Local
0.0.0.0 from 0.0.0.0 (3.3.3.3)
Origin incomplete, metric 0, localpref 100, weight 32768, valid, sourced, best
Community: local-AS

R4#**show ip bgp 150.4.4.0 255.255.255.0**
BGP routing table entry for 150.4.4.0/24, version 6
Paths: (1 available, best #1, table Default-IP-Routing-Table, not advertised outside local AS)
Flag: 0x820
Advertised to update-groups:
1
Local
0.0.0.0 from 0.0.0.0 (4.4.4.4)
Origin incomplete, metric 0, localpref 100, weight 32768, valid, sourced, best
Community: local-AS

You can verify that the COMMUNITY attribute is being sent to peers using the **show ip bgp neighbors <address>** command:

R1#**show ip bgp neighbors 2.2.2.2**
BGP neighbor is 2.2.2.2, remote AS 254, internal link
BGP version 4, remote router ID 2.2.2.2
BGP state = Established, up for 00:34:11
Last read 00:00:00, last write 00:00:00, hold time is 15, keepalive interval is 5 seconds
Configured hold time is 15,keepalive interval is 5 seconds Minimum holdtime from neighbor is 0 seconds
Neighbor capabilities:
Route refresh: advertised and received(old & new)
Address family IPv4 Unicast: advertised and received
Message statistics:
InQ depth is 0
OutQ depth is 0
Sent Rcvd
Opens: 1 1

https://t.me/learningnets
Technet24

Notifications: 0 0
Updates: 5 1
Keepalives: 413 413
Route Refresh: 0 0
Total: 419 415
Default minimum time between advertisement runs is 0 seconds

For address family: IPv4 Unicast
BGP table version 6, neighbor version 6/0
Output queue size : 0
Index 1, Offset 0, Mask 0x2
Route-Reflector Client
1 update-group member
Community attribute sent to this neighbor
Sent Rcvd
Prefix activity: ---- ----
Prefixes Current: 4 1 (Consumes 52 bytes)
Prefixes Total: 5 1
Implicit Withdraw: 1 0
Explicit Withdraw: 0 0
Used as bestpath: n/a 1
Used as multipath: n/a 0

Outbound Inbound
Local Policy Denied Prefixes: -------- -------
Total: 0 0
Number of NLRIs in the update sent: max 1, min 1

Task 5

Prior to any configuration changes, the BGP tables on R2 and R4 show the following entries for each others' 150.x.x.x/24 subnets:

R2#**show ip bgp 150.4.4.0 255.255.255.0**
BGP routing table entry for 150.4.4.0/24, version 13
Paths: (2 available, best #1, table Default-IP-Routing-Table, not advertised outside local AS)
Not advertised to any peer
Local
4.4.4.4 (metric 21664000) from 1.1.1.1 (1.1.1.1)
Origin incomplete, metric 0, localpref 100, valid, internal, best
Community: local-AS

https://t.me/learningnets

Originator: 4.4.4.4, Cluster list: 55.55.55.55
Local
4.4.4.4 (metric 21664000) from 3.3.3.3 (3.3.3.3)
Origin incomplete, metric 0, localpref 100, valid, internal
Community: local-AS
Originator: 4.4.4.4, Cluster list: 55.55.55.55

R4#**show ip bgp 150.2.2.0 255.255.255.0**

BGP routing table entry for 150.2.2.0/24, version 11

Paths: (2 available, best #1, table Default-IP-Routing-Table, not advertised outside local AS)

Not advertised to any peer

Local

2.2.2.2 (metric 21664000) from 1.1.1.1 (1.1.1.1)

Origin incomplete, metric 0, localpref 100, valid, internal, best

Community: local-AS

Originator: 2.2.2.2, Cluster list: 55.55.55.55

Local

2.2.2.2 (metric 21664000) from 3.3.3.3 (3.3.3.3)

Origin incomplete, metric 0, localpref 100, valid, internal

Community: local-AS

Originator: 2.2.2.2, Cluster list: 55.55.55.55

Given that all else is equal, the route received from R1 is preferred because it comes from the lowest neighbor address. To complete this task, it is most simple to use LOCAL_PREF:

R3(config)#**route-map LOCAL-PREF permit 10**

R3(config-route-map)#**set local-preference 200**

R3(config)#**router bgp 254**

R3(config-router)#**neighbor 2.2.2.2 route-map LOCAL-PREF in**

R3(config-router)#**neighbor 4.4.4.4 route-map LOCAL-PREF in**

R3(config-router)#**exit**

Following this change, the BGP RIBs show the following for the LAN subnets:

R2#**show ip bgp 150.4.4.0 255.255.255.0**
BGP routing table entry for 150.4.4.0/24, version 20

https://t.me/learningnets

Technet24

Paths: (2 available, best #2, table Default-IP-Routing-Table, not advertised outside local AS)
Flag: 0x800
Not advertised to any peer
Local
4.4.4.4 (metric 21664000) from 1.1.1.1 (1.1.1.1)
Origin incomplete, metric 0, localpref 100, valid, internal
Community: local-AS
Originator: 4.4.4.4, Cluster list: 55.55.55.55
Local
4.4.4.4 (metric 21664000) from 3.3.3.3 (3.3.3.3)
Origin incomplete, metric 0, localpref 200, valid, internal, best
Community: local-AS
Originator: 4.4.4.4, Cluster list: 55.55.55.55

R4#**show ip bgp 150.2.2.0 255.255.255.0**
BGP routing table entry for 150.2.2.0/24, version 17
Paths: (2 available, best #2, table Default-IP-Routing-Table, not advertised outside local AS)
Flag: 0x800
Not advertised to any peer
Local
2.2.2.2 (metric 21664000) from 1.1.1.1 (1.1.1.1)
Origin incomplete, metric 0, localpref 100, valid, internal
Community: local-AS
Originator: 2.2.2.2, Cluster list: 55.55.55.55
Local
2.2.2.2 (metric 21664000) from 3.3.3.3 (3.3.3.3)
Origin incomplete, metric 0, localpref 200, valid, internal, best
Community: local-AS
Originator: 2.2.2.2, Cluster list: 55.55.55.55

NOTE: Setting the route map INBOUND allows the R3 to essentially 're-set' the LOCAL_PREF of all received prefixes to the specified value. Because LOCAL_PREF is included in updates to iBGP peers, this value is propagated to all other routers in the domain. If you sent LOCAL_PREF in the outbound direction, this is applicable only to routes originated by and advertised by R3. In other words, it would only apply to the 150.3.3.0/24 prefix. Again, it is very important to understand the direction in which attributes are applied.

https://t.me/learningnets

https://t.me/learningnets

Technet24

CCNP Lab 036: Border Gateway Protocol Lab

Lab Objective:

The focus of this lab is to understand BGP implementation and configuration in Cisco IOS routers. Additional technologies include confederations, summarization and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

https://t.me/learningnets

Technet24

Task 2

Configure the following Loopback 0 interfaces on all routers and then enable OSPF using area 0 (backbone) on all routers. OSPF should only be enabled for the Loopback and 10.x.x.x/30 WAN subnets. Do NOT enable OSPF for the 150.x.x.x/24 LAN subnets.

R1: Loopback 0: IP Address 1.1.1.1/32
R2: Loopback 0: IP Address 2.2.2.2/32
R3: Loopback 0: IP Address 3.3.3.3/32
R4: Loopback 0: IP Address 4.4.4.4/32

Task 3

Configure BGP confederations as illustrated in the network topology. Use Loopback interface IP addresses for BGP peering. To the outside world, all routers should appear to be in BGP AS 254. Verify your configuration using the appropriate commands.

Task 4

Advertise the 150.x.x.x/24 subnets on R1, R2, R3, and R4 via BGP. Ensure that all routers can ping each others' LAN subnet from their own LAN subnet. For example, from R1 ping the 150.4.4.4 address using an extended ping sourced from the routers FastEthernet0/0 interface.

Task 5

In the future, a link will be provisioned between R1 and R4. However, management has decided that R1 and R2 should ALWAYS prefer the path through sub-AS 65505 to reach each others' LAN subnets ONLY. Any other subnets that may be added to additional sub-ASes in the future should be affected by this configuration. For example, if another sub-AS is connected to R4, then R1 should prefer the path directly through R4 to reach this sub-AS since it will have a shorter AS_PATH list than going through sub-AS 65505. You are NOT allowed to use IP ACLs or prefix lists to complete this task. Verify the solution using the appropriate commands.

Task 6

Configure sub-AS 65505 to advertise a single prefix instead of the two 150.2.2.0/24 as well as the 150.3.3.0/24 prefixes connected to R2 and R3s LAN interfaces to R1 and R4.

HINT: Use the **neighbor <address> unsuppress-map <route-map-name>** command on R2 and R3 to allow these prefixes to be advertised within sub AS 65505 so that R2 and R3 still have LAN-to-LAN connectivity.

Verify your configuration and ensure that R1 and R2 can still reach the LAN that is connected to R2 and R3. Use extended pings to verify your configuration.

https://t.me/learningnets

Lab Validation:

Task 1

Please refer to previous labs for basic IP addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic OSPF configuration. This will not be included in this section to avoid being redundant. Following completion, the routing tables on your routers should show the following OSPF route entries:

R1#**show ip route ospf**
2.0.0.0/32 is subnetted, 1 subnets
O 2.2.2.2 [110/65] via 10.0.0.2, 00:00:05, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
O 3.3.3.3 [110/129] via 10.0.0.2, 00:00:05, Serial0/0
4.0.0.0/32 is subnetted, 1 subnets
O 4.4.4.4 [110/910] via 10.0.0.2, 00:00:05, Serial0/0
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.8 [110/128] via 10.0.0.2, 00:00:05, Serial0/0
O 10.0.0.12 [110/909] via 10.0.0.2, 00:00:05, Serial0/0

R2#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O 1.1.1.1 [110/65] via 10.0.0.1, 00:00:11, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
O 3.3.3.3 [110/65] via 10.0.0.10, 00:00:11, Serial0/1
4.0.0.0/32 is subnetted, 1 subnets
O 4.4.4.4 [110/846] via 10.0.0.10, 00:00:11, Serial0/1
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.12 [110/845] via 10.0.0.10, 00:00:11, Serial0/1

R3#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O 1.1.1.1 [110/846] via 10.0.0.9, 00:00:14, Serial1/1
2.0.0.0/32 is subnetted, 1 subnets
O 2.2.2.2 [110/782] via 10.0.0.9, 00:00:14, Serial1/1
4.0.0.0/32 is subnetted, 1 subnets
O 4.4.4.4 [110/782] via 10.0.0.14, 00:00:14, Serial1/2
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.0 [110/845] via 10.0.0.9, 00:00:14, Serial1/1

https://t.me/learningnets

Technet24

R4#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O 1.1.1.1 [110/910] via 10.0.0.13, 00:00:12, Serial0/0
2.0.0.0/32 is subnetted, 1 subnets
O 2.2.2.2 [110/846] via 10.0.0.13, 00:00:12, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
O 3.3.3.3 [110/65] via 10.0.0.13, 00:00:12, Serial0/0
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.8 [110/845] via 10.0.0.13, 00:00:12, Serial0/0
O 10.0.0.0 [110/909] via 10.0.0.13, 00:00:12, Serial0/0

Task 3

The configuration of confederations is a little more complex than that required to configure and implement Route Reflectors. In Cisco IOS software, the following sequence of steps is required to configure and implement BGP confederations:

- Configure the local BGP speaker with the desired private AS number using the router bgp [private AS number] global configuration command
- Configure the local BGP speaker with the public AS using the bgp confederation identifier [public AS number] router configuration command
- Specify one or more sub-AS peers that this local BGP speaker will peer to using the bgp confederation peers [sub-AS] router configuration command. If the local BGP speaker does not peer to any other sub-AS, this command must be omitted
- Configure the BGP neighbor relationships following the standard steps. However, if a local BGP speaker will peer to another BGP speaker in a different sub-AS, you must use the neighbor [address] ebgp-multihop command if you will be using Loopback interfaces for the BGP session

Following the sequence of steps illustrated above, this task is completed as follows:

R1(config)#**router bgp 65501**
R1(config-router)#**bgp confederation identifier 254**
R1(config-router)#**bgp confederation peers 65505**
R1(config-router)#**neighbor 2.2.2.2 remote-as 65505**
R1(config-router)#**neighbor 2.2.2.2 update-source loopback 0**
R1(config-router)#**neighbor 2.2.2.2 ebgp-multihop**
R1(config-router)#**exit**

R2(config)#**router bgp 65505**
R2(config-router)#**bgp confederation identifier 254**

https://t.me/learningnets

R2(config-router)#**bgp confederation peers 65501**
R2(config-router)#**neighbor 1.1.1.1 remote-as 65501**
R2(config-router)#**neighbor 1.1.1.1 update-source loopback 0**
R2(config-router)#**neighbor 1.1.1.1 ebgp-multihop**
R2(config-router)#**neighbor 3.3.3.3 remote-as 65505**
R2(config-router)#**neighbor 3.3.3.3 update-source loopback 0**
R2(config-router)#**neighbor 3.3.3.3 ebgp-multihop**
R2(config-router)#**exit**

R3(config)#**router bgp 65505**
R3(config-router)#**bgp confederation identifier 254**
R3(config-router)#**bgp confederation peers 65504**
R3(config-router)#**neighbor 2.2.2.2 remote-as 65505**
R3(config-router)#**neighbor 2.2.2.2 update-source loopback 0**
R3(config-router)#**neighbor 2.2.2.2 ebgp-multihop**
R3(config-router)#**neighbor 4.4.4.4 remote-as 65504**
R3(config-router)#**neighbor 4.4.4.4 update-source loopback 0**
R3(config-router)#**neighbor 4.4.4.4 ebgp-multihop**
R3(config-router)#**exit**

R4(config)#**router bgp 65504**
R4(config-router)#**bgp confederation identifier 254**
R4(config-router)#**bgp confederation peers 65505**
R4(config-router)#**neighbor 3.3.3.3 remote-as 65505**
R4(config-router)#**neighbor 3.3.3.3 update-source loopback 0**
R4(config-router)#**neighbor 3.3.3.3 ebgp-multihop**
R4(config-router)#**exit**

Verify your configuration using the **show ip bgp summary** command:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 65501
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
2.2.2.2 4 65505 22 22 1 0 0 00:00:04 0

R2#**show ip bgp summary**
BGP router identifier 2.2.2.2, local AS number 65505
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
1.1.1.1 4 65501 22 22 1 0 0 00:00:13 0
3.3.3.3 4 65505 6 6 1 0 0 00:03:53 0

https://t.me/learningnets

Technet24

R3#**show ip bgp summary**
BGP router identifier 3.3.3.3, local AS number 65505
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
2.2.2.2 4 65505 6 6 1 0 0 00:03:57 0
4.4.4.4 4 65504 6 6 1 0 0 00:02:22 0

R4#**show ip bgp summary**
BGP router identifier 4.4.4.4, local AS number 65504
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
3.3.3.3 4 65505 6 6 1 0 0 00:02:26 0

Task 4

This is a straightforward task that is completed using the **network** command under BGP:

R1(config)#**router bgp 65501**
R1(config-router)#**network 150.1.1.0 mask 255.255.255.0**
R1(config-router)#**exit**

R2(config)#**router bgp 65505**
R2(config-router)#**network 150.2.2.0 mask 255.255.255.0**
R2(config-router)#**exit**

R3(config)#**router bgp 65505**
R3(config-router)#**network 150.3.3.0 mask 255.255.255.0**
R3(config-router)#**exit**

R4(config)#**router bgp 65504**
R4(config-router)#**network 150.4.4.0 mask 255.255.255.0**
R4(config-router)#**exit**
Verify your configuration using the **show ip bgp** command on all routers:

R1#**show ip bgp**
BGP table version is 5, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
*> 150.2.2.0/24 2.2.2.2 0 100 0 (65505) i

https://t.me/learningnets

*> 150.3.3.0/24 3.3.3.3 0 100 0 (65505) i
*> 150.4.4.0/24 4.4.4.4 0 100 0 (65505 65504) i

R2#**show ip bgp**
BGP table version is 5, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 1.1.1.1 0 100 0 (65501) i
*> 150.2.2.0/24 0.0.0.0 0 32768 i
*>i150.3.3.0/24 3.3.3.3 0 100 0 i
*>i150.4.4.0/24 4.4.4.4 0 100 0 (65504) i

R3#**show ip bgp**
BGP table version is 5, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i150.1.1.0/24 1.1.1.1 0 100 0 (65501) i
*>i150.2.2.0/24 2.2.2.2 0 100 0 i
*> 150.3.3.0/24 0.0.0.0 0 32768 i
*> 150.4.4.0/24 4.4.4.4 0 100 0 (65504) i

R4#**show ip bgp**
BGP table version is 4, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 1.1.1.1 0 100 0 (65505 65501) i
*> 150.2.2.0/24 2.2.2.2 0 100 0 (65505) i
*> 150.4.4.0/24 0.0.0.0 0 32768 i

Finally, use the extended ping function to verify LAN-to-LAN connectivity between subnets:

R1#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:

https://t.me/learningnets

Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R1#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R1#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R2#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R2#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/15/16 ms

R2#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/32/48 ms

R3#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.

https://t.me/learningnets

Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R3#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/15/16 ms

R3#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/1/4 ms

R4#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

Task 5

https://t.me/learningnets

Technet24

To complete this task, you need to use either the WEIGHT or LOCAL_PREF attributes along with a regular expression (since using IP ACLs and prefix lists is forbidden). In Cisco IOS software, AS path filters are used to perform BGP filtering policy control based on the AS_PATH attribute. The AS path attribute pattern used in these filters is defined by a regular expression string that is configured using the **ip as-path access-list [number] [permit | deny] <regexp>** global configuration command. The configured filter list may then be applied directly on a per-neighbor basis using the **neighbor [address] filter-list <as_path_acl_number>** router configuration command or indirectly on a per-neighbor basis by referencing a route map which matches one or more AS path filters using the **match as-path <as_path_acl_number>** route map match clause.

The table below shows some basic regular expression configuration and what they match:

Regular Expression

Matches

.*

This regular expression is used to match all prefixes

^$

This regular expression matches only prefixes local to the AS

_254$

This regular expression matches only prefixes that originate in AS 254

^254_ [0-9]*$

This regular expression matches prefixes received from directly connected AS 254 and any ASes directly attached to AS 254

_254_

This regular expression matches prefixes that have traversed AS 254

^254$

This regular expression matches prefixes only originated from directly connected AS 254

This task is completed using regular expressions and the Cisco proprietary WEIGHT attribute. However, keep in mind that you may also use LOCAL_PREF. Either attribute is acceptable. Match on prefixes originated from sub-AS 65501 and sub-AS 65504 to complete this task. You can verify which prefixes will match your AS_PATH ACL Filter beforehand using the **show ip bgp regexp <regular expression>** command as follows:

https://t.me/learningnets

R1#**show ip bgp regexp _\(65505 65504\)$**
BGP table version is 5, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.4.4.0/24 4.4.4.4 0 100 0 (65505 65504) i

R4#**show ip bgp regexp _\(65505 65501\)$**
BGP table version is 5, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 1.1.1.1 0 100 0 (65505 65501) i

This task is completed as follows:

R1(config)#**ip as-path access-list 1 permit _\(65505 65504\)$**
R1(config)#**route-map WEIGHT permit 10**
R1(config-route-map)#**match as-path 1**
R1(config-route-map)#**set weight 50000**
R1(config-route-map)#**exit**
R1(config)#**route-map WEIGHT permit 20**
R1(config-route-map)#**exit**
R1(config)#**router bgp 65501**
R1(config-router)#**neighbor 2.2.2.2 route-map WEIGHT in**
R1(config-router)#**exit**

R4(config)#**ip as-path access-list 1 permit _\(65505 65501\)$**
R4(config)#**route-map WEIGHT permit 10**
R4(config-route-map)#**match as-path 1**
R4(config-route-map)#**set weight 50000**
R4(config-route-map)#**exit**
R4(config)#**route-map WEIGHT permit 20**
R4(config-route-map)#**exit**
R4(config)#**router bgp 65504**
R4(config-router)#**neighbor 3.3.3.3 route-map WEIGHT in**
R4(config-router)#**exit**

Verify your configuration using the **show ip bgp** command on routers R1 and R4 as follows:

https://t.me/learningnets

Technet24

R1#**show ip bgp**
BGP table version is 6, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
*> 150.2.2.0/24 2.2.2.2 0 100 0 (65505) i
*> 150.3.3.0/24 3.3.3.3 0 100 0 (65505) i
***> 150.4.4.0/24 4.4.4.4 0 100 50000 (65505 65504) i**

R4#**show ip bgp**
BGP table version is 10, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
***> 150.1.1.0/24 1.1.1.1 0 100 50000 (65505 65501) i**
*> 150.2.2.0/24 2.2.2.2 0 100 0 (65505) i
*> 150.3.3.0/24 3.3.3.3 0 100 0 (65505) i
*> 150.4.4.0/24 0.0.0.0 0 32768 i

NOTE: Additional information on regular expressions is available in the ROUTE guide.

Task 6

This task is completed using the **aggregate-address** command. By default, this command will advertise BOTH the aggregate (summary) and the more specific prefixes. To advertise only the summary, you need to append the **summary-only** keyword. This keyword instructs the router to advertise the aggregate only and suppress the more specific routes that are covered by the summary. This task is completed as follows:

R2(config)#**router bgp 65505**
R2(config-router)#**aggregate-address 150.2.0.0 255.254.0.0 summary-only**
R2(config-router)#**exit**

R3(config)#**router bgp 65505**
R3(config-router)#**aggregate-address 150.2.0.0 255.254.0.0 summary-only**
R3(config-router)#**exit**

Next, verify that the more specific 150.2.2.0/24 and 150.3.3.0/24 prefixes are suppressed:

https://t.me/learningnets

R2#**show ip bgp**
BGP table version is 9, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 1.1.1.1 0 100 0 (65501) i
*** i150.2.0.0/15 3.3.3.3 0 100 0 i**
*> 0.0.0.0 32768 i
s> 150.2.2.0/24 0.0.0.0 0 32768 i
*>i150.4.4.0/24 4.4.4.4 0 100 0 (65504) i

R3#**show ip bgp**
BGP table version is 9, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i150.1.1.0/24 1.1.1.1 0 100 0 (65501) i
***> 150.2.0.0/15 0.0.0.0 32768 i**
* i 2.2.2.2 0 100 0 i
s> 150.3.3.0/24 0.0.0.0 0 32768 i
*> 150.4.4.0/24 4.4.4.4 0 100 0 (65504) i

You will notice that neither R2 nor R3 has a route to the other routers' LAN subnet. Therefore, as was hinted in the task, use the **neighbor <address> unsuppress-map <route-map-name>** command to unsuppress (leak) these routes between the routers. This is similar to route leaking with EIGRP. This task is completed as follows:
R2(config)#**ip prefix-list LAN-SUBNET seq 5 permit 150.2.2.0/24**
R2(config)#**route-map UNSUPRESS permit 10**
R2(config-route-map)#**match ip addres prefix-list LAN-SUBNET**
R2(config-route-map)#**exit**
R2(config)#**router bgp 65505**
R2(config-router)#**neighbor 3.3.3.3 unsuppress-map UNSUPRESS**
R2(config-router)#**exit**

R3(config)#**ip prefix-list LAN-SUBNET seq 5 permit 150.3.3.0/24**
R3(config)#**route-map UNSUPRESS permit 10**
R3(config-route-map)#**match ip addres prefix-list LAN-SUBNET**
R3(config-route-map)#**exit**

https://t.me/learningnets
Technet24

R3(config)#**router bgp 65505**
R3(config-router)#**neighbor 2.2.2.2 unsuppress-map UNSUPRESS**
R3(config-router)#**exit**

Following this configuration, you will notice that the LAN prefixes are now present as well:

R2#**show ip bgp**
BGP table version is 11, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 1.1.1.1 0 100 0 (65501) i
*** i150.2.0.0/15 3.3.3.3 0 100 0 i**
***> 0.0.0.0 32768 i**
s> 150.2.2.0/24 0.0.0.0 0 32768 i
s>i150.3.3.0/24 3.3.3.3 0 100 0 i
*>i150.4.4.0/24 4.4.4.4 0 100 0 (65504) i

R3#**show ip bgp**
BGP table version is 11, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i150.1.1.0/24 1.1.1.1 0 100 0 (65501) i
***> 150.2.0.0/15 0.0.0.0 32768 i**
*** i 2.2.2.2 0 100 0 i**
s>i150.2.2.0/24 2.2.2.2 0 100 0 i
s> 150.3.3.0/24 0.0.0.0 0 32768 i
*> 150.4.4.0/24 4.4.4.4 0 100 0 (65504) i

Although the specific LAN subnets are advertised within sub-AS 65505, verify that only a single prefix is received by routers R1 and R4 from peers R2 and R3, respectively:

R1#**show ip bgp**
BGP table version is 9, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

https://t.me/learningnets

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
***> 150.2.0.0/15 2.2.2.2 0 100 0 (65505) i**
*> 150.4.4.0/24 4.4.4.4 0 100 50000 (65505 65504) i

R4#**show ip bgp**
BGP table version is 14, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 1.1.1.1 0 100 50000 (65505 65501) i
***> 150.2.0.0/15 3.3.3.3 0 100 0 (65505) i**
*> 150.4.4.0/24 0.0.0.0 0 32768 i

Finally, verify that R1 and R4 can still ping the R2 and R3 LAN subnets using an extended ping:

R4#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/36 ms

R4#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R1#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R1#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:

https://t.me/learningnets
Technet24

Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/17/20 ms

https://t.me/learningnets

CCNP Lab 037: Border Gateway Protocol Lab

Lab Objective:

The focus of this lab is to understand BGP implementation and configuration in Cisco IOS routers. Additional technologies include BGP and OSPF route redistribution .

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Configure EIGRP using AS 254 only for the R1-to-R2 link and for the R2-to-R3 link. Do NOT enable EIGRP for any other subnets. Verify your configuration.

Task 3

Configure BGP in AS 254 as illustrated in the topology. Use physical interfaces for peering. R1 should peer with R2 and R2 should peer with R3. Verify your configuration.

Task 4

Redistribute the 150.1.1.0/24, 150.2.2.0/24 and 150.3.3.0/24 subnets on R1, R2 and R3 into BGP. There should be no 10.x.x.x prefixes in the BGP Table. You are required to use a route map in conjunction with an EXTENDED IP ACL to complete this task. Ensure that all three routers can ping each others' 150.x.x.x/24 subnets from their own LAN subnet. Use the extended ping feature to verify your configuration.

Task 5

Configure OSPF area 0 between R3 and R4. Advertise the 150.4.4.0/24 subnet via OSPF as a Type 1 External LSA. Verify your configuration using the appropriate commands.

Task 6

Redistribute between BGP and OSPF on R3. BGP should only redistribute EXTERNAL Type 5 routes from OSPF. Do NOT redistribute anything into or out of EIGRP. Ensure that the 150.4.4.0/24 subnet is able to reach all other 150.x.x.x/24 subnets and vice-versa. Verify your configuration using extended ping.

Lab Validation:

Task 1

Please refer to previous labs for basic IP addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. This will not be included in this section to avoid being redundant. Following completion, the routing tables on your routers should show the following EIGRP route entries:

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 2 subnets
D 10.0.0.8 [90/2681856] via 10.0.0.2, 00:01:05, Serial0/0

R3#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets

https://t.me/learningnets

D 10.0.0.0 [90/21024000] via 10.0.0.9, 00:00:38, Serial1/1

NOTE: R2 will not have EIGRP routes because the two WAN subnets are directly connected.

Task 3

R1(config)#**router bgp 254**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**neighbor 10.0.0.2 remote-as 254**
R1(config-router)#**exit**

R2(config)#**router bgp 254**
R2(config-router)#**bgp router-id 2.2.2.2**
R2(config-router)#**neighbor 10.0.0.1 remote-as 254**
R2(config-router)#**neighbor 10.0.0.10 remote-as 254**
R2(config-router)#**exit**

R3(config)#**router bgp 254**
R3(config-router)#**bgp router-id 3.3.3.3**
R3(config-router)#**neighbor 10.0.0.9 remote-as 254**
R3(config-router)#**exit**

Verify your configuration using the **show ip bgp summary** command:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.2 4 254 4 4 1 0 0 00:01:11 0

R2#**show ip bgp summary**
BGP router identifier 2.2.2.2, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.1 4 254 4 4 1 0 0 00:01:15 0
10.0.0.10 4 254 4 4 1 0 0 00:00:33 0

R3#**show ip bgp summary**
BGP router identifier 3.3.3.3, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.9 4 254 4 4 1 0 0 00:00:35 0

Task 4

https://t.me/learningnets

This task requires that a route-map be used for route redistribution. The route map can be used to match the interface or address (IP ACL and prefix list). Because the task requirements stipulate that an only an extended IP ACL can be used, you can use either named or numbered extended ACLs to complete. The configuration below shows how to use both named and numbered (standard and expanded range) extended IP ACLs. This task is completed as follows:

R1(config)#**access-list 100 permit ip host 150.1.1.0 host 255.255.255.0**
R1(config)#**route-map CONNECTED permit 10**
R1(config-route-map)#**match ip address 100**
R1(config-route-map)#**exit**
R1(config)#**route-map CONNECTED deny 20**
R1(config-route-map)#**exit**
R1(config)#**router bgp 254**
R1(config-router)#**redistribute connected route-map CONNECTED**
R1(config-router)#**exit**

R2(config)#**ip access-list extended CONNECTED**
R2(config-ext-nacl)#**permit ip host 150.2.2.0 host 255.255.255.0**
R2(config-ext-nacl)#**exit**
R2(config)#**route-map CONNECTED permit 10**
R2(config-route-map)#**match ip address CONNECTED**
R2(config-route-map)#**exit**
R2(config)#**route-map CONNECTED deny 20**
R2(config-route-map)#**exit**
R2(config)#**router bgp 254**
R2(config-router)#**redistribute connected route-map CONNECTED**
R2(config-router)#**exit**

R3(config)#**access-list 2000 permit ip host 150.3.3.0 host 255.255.255.0**
R3(config)#**route-map CONNECTED permit 10**
R3(config-route-map)#**match ip address 2000**
R3(config-route-map)#**exit**
R3(config)#**route-map CONNECTED deny 20**
R3(config-route-map)#**exit**
R3(config)#**router bgp 254**
R3(config-router)#**redistribute connected route-map CONNECTED**
R3(config-router)#**exit**

Following the redistribution, we have to remember the default iBGP advertisement rules. In this topology, R2 will not advertise the R1 or R3 subnets to R3 and R1

https://t.me/learningnets

Technet24

respectively because they are received from iBGP peers. To work around this limitation, then R2 should also be configured as a route reflector. This is completed as follows:

```
R2(config)#router bgp 254
R2(config-router)#neighbor 10.0.0.1 route-reflector-client
R2(config-router)#neighbor 10.0.0.10 route-reflector-client
R2(config-router)#exit
```

Next, verify your configuration using the **show ip bgp** command on all three routers:

```
R1#show ip bgp
BGP table version is 8, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 ?
*>i150.2.2.0/24 10.0.0.2 0 100 0 ?
*>i150.3.3.0/24 10.0.0.10 0 100 0 ?

R2#show ip bgp
BGP table version is 8, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i150.1.1.0/24 10.0.0.1 0 100 0 ?
*> 150.2.2.0/24 0.0.0.0 0 32768 ?
*>i150.3.3.0/24 10.0.0.10 0 100 0 ?

R3#show ip bgp
BGP table version is 8, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i150.1.1.0/24 10.0.0.1 0 100 0 ?
*>i150.2.2.0/24 10.0.0.9 0 100 0 ?
*> 150.3.3.0/24 0.0.0.0 0 32768 ?
```

Finally, verify that all LAN subnets can ping each other using the extended ping feature:

https://t.me/learningnets

R1#**ping 150.2.2.2 source 150.1.1.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R1#**ping 150.3.3.3 source 150.1.1.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R2#**ping 150.1.1.1 source 150.2.2.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R2#**ping 150.3.3.3 source 150.2.2.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R3#**ping 150.1.1.1 source 150.3.3.3 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R3#**ping 150.2.2.2 source 150.3.3.3 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

https://t.me/learningnets

Technet24

Task 5

R3(config)#**router ospf 3**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**network 10.0.0.13 0.0.0.0 area 0**
R3(config-router)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**ip ospf 4 area 0**
R4(config-if)#**exit**
R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**redistribute connected subnet metric-type 1**
R4(config-router)#**exit**

Verify your basic OSPF configuration using the **show ip ospf neighbor** command:

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:38 10.0.0.14 Serial1/2

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:34 10.0.0.13 Serial0/0

Finally, verify your OSPF redistribution using the **show ip ospf database** command:

R4#**show ip ospf database external 150.4.4.0**

OSPF Router with ID (4.4.4.4) (Process ID 4)

Type-5 AS External Link States

LS age: 132
Options: (No TOS-capability, DC)
LS Type: AS External Link
Link State ID: 150.4.4.0 (External Network Number)
Advertising Router: 4.4.4.4
LS Seq Number: 80000001
Checksum: 0xE988
Length: 36
Network Mask: /24
Metric Type: 1 (Comparable directly to link state metric)
TOS: 0
Metric: 20

https://t.me/learningnets

Forward Address: 0.0.0.0
External Route Tag: 0

Task 6

There are four caveats to be aware of when completing this task. The first is that, by default, when BGP routes are redistributed into an IGP, only EXTERNAL routes are redistributed.

The second caveat is that when OSPF routes are redistributed into BGP, only INTERNAL routes are redistributed. Explicit configuration is required to redistribute internal BGP routes and external OSPF routes when performing OSPF-to-BGP redistribution and vice-versa.

The third caveat is that by default, an iBGP speaker does not change the NEXT_HOP attribute for an external route when advertising it to another iBGP speaker. Therefore, the NEXT_HOP attribute must be changed after redistributing OSPF into BGP. The other alternative would be to redistribute the R3-to-R4 WAN link into EIGRP; however, this is not permitted.

The fourth caveat is that while the 150.3.3.0/24 subnet is advertised by BGP, it is redistributed into BGP. Therefore, it will not automatically be redistributed into OSPF when BGP is redistributed into OSPF. Instead, a route map must be used to redistribute this subnet into OSPF as was performed earlier for BGP. This task is completed as follows:

R3(config)#**router bgp 254**
R3(config-router)#**redistribute ospf 3 match external 1 external 2**
R3(config-router)#**bgp redistribute-internal**
R3(config-router)#**neighbor 10.0.0.9 next-hop-self**
R3(config-router)#**exit**
R3(config)#**router ospf 3**
R3(config-router)#**redistribute connected subnets route-map CONNECTED**
R3(config-router)#**redistribute bgp 254 subnets**
R3(config-router)#**exit**

Following this configuration, verify the LSDB and BGP Table on R3 using the **show ip ospf database** and the **show ip bgp** commands, respectively:

R3#**show ip ospf database**

OSPF Router with ID (3.3.3.3) (Process ID 3)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count

https://t.me/learningnets

Technet24

3.3.3.3 3.3.3.3 1012 0x80000004 0x007934 2
4.4.4.4 4.4.4.4 1356 0x80000001 0x002E1D 2
150.4.4.4 150.4.4.4 1385 0x80000001 0x008F98 2

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.1.1.0 3.3.3.3 1012 0x80000001 0x0012FC 0
150.2.2.0 3.3.3.3 1012 0x80000001 0x00FA12 0
150.3.3.0 3.3.3.3 16 0x80000001 0x00A255 0
150.4.4.0 4.4.4.4 1355 0x80000001 0x00E988 0

R3#**show ip bgp**
BGP table version is 9, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i150.1.1.0/24 10.0.0.1 0 100 0 ?
*>i150.2.2.0/24 10.0.0.9 0 100 0 ?
*> 150.3.3.0/24 0.0.0.0 0 32768 ?
***> 150.4.4.0/24 10.0.0.14 801 32768 ?**

To verify the redistributed route in BGP, use the **show ip bgp** command on R1 or R2:

R1#**show ip bgp 150.4.4.0 255.255.255.0**
BGP routing table entry for 150.4.4.0/24, version 9
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Flag: 0x820
Not advertised to any peer
Local
10.0.0.10 (metric 2681856) from 10.0.0.2 (2.2.2.2)
Origin incomplete, metric 801, localpref 100, valid, internal, best
Originator: 3.3.3.3, Cluster list: 2.2.2.2

Finally, verify your configuration using the extended ping feature on R4:

R4#**ping 150.1.1.1 source 150.4.4.4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

https://t.me/learningnets

R4#**ping 150.2.2.2 source 150.4.4.4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.3.3.3 source 150.4.4.4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/14/16 ms

https://t.me/learningnets

Technet24

CCNP Lab 038: Border Gateway Protocol Lab

Lab Objective:

The focus of this lab is to understand BGP implementation and configuration in Cisco IOS routers. Additional technologies include confederations and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

https://t.me/learningnets

Technet24

Task 2

Configure BGP on R1 as illustrated in the topology. R1 will peer to R2, R3, and R4 using directly connected IP addresses. From R1s perspective, all these routers reside in AS 5. R1 should advertise the 150.1.1.0/24 prefix via BGP. Verify your configuration using relevant commands.

Task 3

Configure BGP on R2, R3, and R4 as illustrated in the topology. All routers will reside in AS 5 to the outside world. Internally, R2 will reside in AS 65502, R3 will reside in AS 65503, and R4 will reside in AS 65504. R2 will peer to R3, which in turn will peer to R4. R2 and R4 will not peer with each other. Ensure that R1, R2, and R3 routers peer with R1 is AS 254. Next, configure R2, R3, and R4 to advertise their respective 150.x.x.x/24 subnets. Ensure that all of the routers can ping the LAN IP address of every other router.

Task 4

Configure AS 5 so that R2 and R3 prefer the path via R1 to reach the 150.1.1.0/24 prefix. Ensure that this is ONLY applicable to this single prefix. Verify your configuration.

Task 5

R1 has three paths to the 150.3.3.0/24 subnet advertised by R3. Configure your network so that R1 prefers the path via R2 first, the path via R4 second and then path via R3 last. You are not allowed to make any changes on R1 to complete this task. Additionally, you are NOT allowed to modify the AS_PATH or MED attributes or administrative distance in any manner. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IP addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

R1(config)#**router bgp 254**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**neighbor 150.1.1.4 remote-as 5**
R1(config-router)#**neighbor 10.0.0.2 remote-as 5**
R1(config-router)#**neighbor 10.0.0.6 remote-as 5**
R1(config-router)#**network 150.1.1.0 mask 255.255.255.0**

https://t.me/learningnets

R1(config-router)#**exit**

Because no BGP adjacencies will be present, at this point, verify that the 150.1.1.0/24 prefix has been injected into BGP as requested in this task using the **show ip bgp** command:

R1#**show ip bgp**
BGP table version is 1, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 0.0.0.0 0 32768 i

Task 3

To complete this task, you need to configure BGP confederations. When configuring the routers, keep in mind that external confederation peers (in a way) also behave in a manner similar to external BGP peers. For example, just as you would need to use **the neighbor <address> ebgp-multihop** command when peering using Loopback interfaces; you still need to modify the NEXT_HOP attribute using the **neighbor <address> next-hop-self** command just as you would when receiving routes from an eBGP peer in an environment that is not using confederations. Alternatively, you can use static routes or advertise routes using a dynamic routing protocol to ensure that the NEXT_HOP is reachable. This task is completed as follows:

R2(config)#**router bgp 65502**
R2(config-router)#**bgp router-id 2.2.2.2**
R2(config-router)#**bgp confederation identifier 5**
R2(config-router)#**bgp confederation peers 65503**
R2(config-router)#**network 150.2.2.0 mask 255.255.255.0**
R2(config-router)#**neighbor 10.0.0.1 remote-as 254**
R2(config-router)#**neighbor 10.0.0.10 remote-as 65503**
R2(config-router)#**neighbor 10.0.0.10 next-hop-self**
R2(config-router)#**exit**

R3(config)#**router bgp 65503**
R3(config-router)#**bgp router-id 3.3.3.3**
R3(config-router)#**bgp confederation identifier 5**
R3(config-router)#**bgp confederation peers 65502 65504**
R3(config-router)#**neighbor 10.0.0.5 remote-as 254**
R3(config-router)#**neighbor 10.0.0.9 remote-as 65502**

https://t.me/learningnets

Technet24

R3(config-router)#**neighbor 10.0.0.9 next-hop-self**
R3(config-router)#**neighbor 10.0.0.14 remote-as 65504**
R3(config-router)#**neighbor 10.0.0.14 next-hop-self**
R3(config-router)#**network 150.3.3.0 mask 255.255.255.0**
R3(config-router)#**exit**

R4(config)#**router bgp 65504**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**network 150.1.1.0 mask 255.255.255.0**
R4(config-router)#**bgp confederation identifier 5**
R4(config-router)#**bgp confederation peers 65503**
R4(config-router)#**neighbor 150.1.1.1 remote-as 254**
R4(config-router)#**neighbor 10.0.0.13 remote-as 65503**
R4(config-router)#**neighbor 10.0.0.13 next-hop-self**
R4(config-router)#**exit**

Next, verify BGP peering configuration using the **show ip bgp summary** command:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 254
BGP table version is 4, main routing table version 4
3 network entries using 351 bytes of memory
8 path entries using 416 bytes of memory
4/2 BGP path/bestpath attribute entries using 496 bytes of memory
1 BGP AS-PATH entries using 24 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1287 total bytes of memory
BGP activity 3/0 prefixes, 8/0 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.2 4 5 13 14 4 0 0 00:07:52 2
10.0.0.6 4 5 10 10 4 0 0 00:03:39 3
150.1.1.4 4 5 8 8 4 0 0 00:02:02 2

R2#**show ip bgp summary**
BGP router identifier 2.2.2.2, local AS number 65502
BGP table version is 4, main routing table version 4
3 network entries using 351 bytes of memory
4 path entries using 208 bytes of memory
5/3 BGP path/bestpath attribute entries using 620 bytes of memory
3 BGP AS-PATH entries using 72 bytes of memory

https://t.me/learningnets

0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1251 total bytes of memory
BGP activity 3/0 prefixes, 4/0 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.1 4 254 14 13 4 0 0 00:07:57 1
10.0.0.10 4 65503 11 9 4 0 0 00:03:51 2

R3#**show ip bgp summary**
BGP router identifier 3.3.3.3, local AS number 65503
BGP table version is 6, main routing table version 6
3 network entries using 351 bytes of memory
5 path entries using 260 bytes of memory
6/3 BGP path/bestpath attribute entries using 744 bytes of memory
4 BGP AS-PATH entries using 96 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1451 total bytes of memory
BGP activity 3/0 prefixes, 5/0 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.5 4 254 10 10 6 0 0 00:03:48 1
10.0.0.9 4 65502 9 11 6 0 0 00:03:55 2
10.0.0.14 4 65504 8 10 6 0 0 00:02:14 1

R4#**show ip bgp summary**
BGP router identifier 4.4.4.4, local AS number 65504
BGP table version is 6, main routing table version 6
3 network entries using 351 bytes of memory
4 path entries using 208 bytes of memory
5/3 BGP path/bestpath attribute entries using 620 bytes of memory
3 BGP AS-PATH entries using 72 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1251 total bytes of memory
BGP activity 3/0 prefixes, 5/1 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.13 4 65503 10 8 6 0 0 00:02:17 2
150.1.1.1 4 254 8 8 6 0 0 00:02:14 1

Finally, verify the BGP Tables on all routers using the **show ip bgp** command:

https://t.me/learningnets

Technet24

R1#**show ip bgp**
BGP table version is 4, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 10.0.0.2 0 5 i
* 10.0.0.6 0 5 i
* 150.1.1.4 0 0 5 i
*> 0.0.0.0 0 32768 i
* 150.2.2.0/24 150.1.1.4 0 5 i
* 10.0.0.6 0 5 i
*> 10.0.0.2 0 0 5 i
* 150.3.3.0/24 150.1.1.4 0 5 i
* 10.0.0.2 0 5 i
*> 10.0.0.6 0 0 5 i

R2#**show ip bgp**
BGP table version is 7, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 10.0.0.10 0 100 0 (65503 65504) i
* 10.0.0.1 0 0 254 i
*> 150.2.2.0/24 0.0.0.0 0 32768 i
*> 150.3.3.0/24 10.0.0.10 0 100 0 (65503) i

R3#**show ip bgp**
BGP table version is 8, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 10.0.0.14 0 100 0 (65504) i
* 10.0.0.5 0 0 254 i
*> 150.2.2.0/24 10.0.0.9 0 100 0 (65502) i
*> 150.3.3.0/24 0.0.0.0 0 32768 i

R4#**show ip bgp**

https://t.me/learningnets

BGP table version is 6, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
* 150.1.1.1 0 0 254 i
*> 150.2.2.0/24 10.0.0.13 0 100 0 (65503 65502) i
*> 150.3.3.0/24 10.0.0.13 0 100 0 (65503) i

Finally, verify that all routers can ping each others' LAN subnets using an extended ping:

R1#**ping 150.2.2.2 source 150.1.1.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R1#**ping 150.3.3.3 source 150.1.1.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R2#**ping 150.1.1.1 source 150.2.2.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R2#**ping 150.1.1.4 source 150.2.2.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.4, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R2#**ping 150.3.3.3 source 150.2.2.2 repeat 10**

https://t.me/learningnets

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R3#**ping 150.1.1.1 source 150.3.3.3 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R3#**ping 150.1.1.4 source 150.3.3.3 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.4, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/15/16 ms

R3#**ping 150.2.2.2 source 150.3.3.3 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R4#**ping 150.2.2.2 source 150.1.1.4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

R4#**ping 150.3.3.3 source 150.1.1.4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

https://t.me/learningnets

Task 4

To complete this task, you need to modify either the WEIGHT or the LOCAL_PREF attributes for the 150.1.1.0/24 prefix received from R1 on routers R2 and R3. Prior to any configuration changes, both routers R2 and R3 show the following BGP RIB entries for the 150.1.1.0/24 prefix:

R2#**show ip bgp 150.1.1.0 255.255.255.0**
BGP routing table entry for 150.1.1.0/24, version 9
Paths: (2 available, best #1, table Default-IP-Routing-Table)
Advertised to update-groups:
1
(65503 65504)
10.0.0.10 from 10.0.0.10 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, confed-external, best
254
10.0.0.1 from 10.0.0.1 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, external

R3#**show ip bgp 150.1.1.0 255.255.255.0**
BGP routing table entry for 150.1.1.0/24, version 10
Paths: (2 available, best #1, table Default-IP-Routing-Table)
Advertised to update-groups:
1 3
(65504)
10.0.0.14 from 10.0.0.14 (4.4.4.4)
Origin IGP, metric 0, localpref 100, valid, confed-external, best
254
10.0.0.5 from 10.0.0.5 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, external

To complete this task, use either LOCAL_PREF or WEIGHT as follows:

R2(config)#**ip prefix-list NET-ONE seq 5 permit 150.1.1.0/24**
R2(config)#**route-map WEIGHT permit 10**
R2(config-route-map)#**match ip address prefix-list NET-ONE**
R2(config-route-map)#**set weight 50000**
R2(config-route-map)#**exit**
R2(config)#**route-map WEIGHT permit 20**
R2(config-route-map)#**exit**
R2(config)#**router bgp 65502**
R2(config-router)#**neighbor 10.0.0.1 route-map WEIGHT in**

https://t.me/learningnets
Technet24

R2(config-router)#**exit**

R3(config)#**ip prefix-list NET-ONE seq 5 permit 150.1.1.0/24**
R3(config)#**route-map WEIGHT permit 10**
R3(config-route-map)#**match ip address prefix-list NET-ONE**
R3(config-route-map)#**set weight 50000**
R3(config-route-map)#**exit**
R3(config)#**router bgp 65503**
R3(config-router)#**neighbor 10.0.0.5 route-map WEIGHT in**
R3(config-router)#**exit**
R3(config)#**route-map WEIGHT permit 20**
R3(config-route-map)#**exit**

Following this change, the BGP RIB on R2 and R3 now shows the following:

R2#**show ip bgp 150.1.1.0 255.255.255.0**
BGP routing table entry for 150.1.1.0/24, version 10
Paths: (2 available, best #2, table Default-IP-Routing-Table)
Flag: 0x820
Advertised to update-groups:
2
(65503 65504)
10.0.0.10 from 10.0.0.10 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, confed-external
254
10.0.0.1 from 10.0.0.1 (1.1.1.1)
Origin IGP, metric 0, localpref 100, weight 50000, valid, external, best

R3#**show ip bgp 150.1.1.0 255.255.255.0**
BGP routing table entry for 150.1.1.0/24, version 10
Paths: (2 available, best #1, table Default-IP-Routing-Table)
Advertised to update-groups:
1 3
(65504)
10.0.0.14 from 10.0.0.14 (4.4.4.4)
Origin IGP, metric 0, localpref 100, valid, confed-external, best
254
10.0.0.5 from 10.0.0.5 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, external

Task 5

This task requires a little thought. In addition to the AS_PATH and MED attributes, there

https://t.me/learningnets

is yet another BGP attribute that can be used to influence path selection: ORIGIN. During the BGP best path selection process, if all paths have the same AS_PATH length, then prefer the path with the lowest ORIGIN. An ORIGIN of IGP (I) is more preferred (lower) than EGP (E) , which in turn in more preferred (lower) than Incomplete (?). In mathematical terms, IGP < EGP < Incomplete. Because all routers are advertising this prefix with an ORIGIN of IGP, because it was injected into BGP on R3 using the **network** command, you only need to modify this attribute on R2 and R3. Prior to any attribute changes, the BGP RIB on R1 shows as follows:

R1#**show ip bgp 150.3.3.0 255.255.255.0**
BGP routing table entry for 150.3.3.0/24, version 4
Paths: (3 available, best #3, table Default-IP-Routing-Table)
Advertised to update-groups:
1
5
150.1.1.4 from 150.1.1.4 (4.4.4.4)
Origin IGP, localpref 100, valid, external
5
10.0.0.2 from 10.0.0.2 (2.2.2.2)
Origin IGP, localpref 100, valid, external
5
10.0.0.6 from 10.0.0.6 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, external, best

This task is completed as follows:

R4(config)#**ip prefix-list NET-THREE seq 5 permit 150.3.3.0/24**
R4(config)#**route-map ORIGIN permit 10**
R4(config-route-map)#**match ip address prefix-list NET-THREE**
R4(config-route-map)#**set origin egp 1**
R4(config-route-map)#**exit**
R4(config)#**route-map ORIGIN permit 20**
R4(config-route-map)#**exit**
R4(config)#**router bgp 65504**
R4(config-router)#**neighbor 150.1.1.1 route-map ORIGIN out**
R4(config-router)#**exit**

R3(config)#**ip prefix-list NET-THREE seq 5 permit 150.3.3.0/24**
R3(config)#**route-map ORIGIN permit 10**
R3(config-route-map)#**match ip address prefix-list NET-THREE**
R3(config-route-map)#**set origin incomplete**

https://t.me/learningnets
Technet24

R3(config-route-map)#**exit**
R3(config)#**route-map ORIGIN permit 20**
R3(config-route-map)#**exit**
R3(config)#**router bgp 65503**
R3(config-router)#**neighbor 10.0.0.5 route-map ORIGIN out**
R3(config-router)#**exit**

Following these changes, the BGP RIB on R1 shows the following for the 150.3.3.0/24 prefix:

R1#**show ip bgp 150.3.3.0 255.255.255.0**
BGP routing table entry for 150.3.3.0/24, version 5
Paths: (3 available, best #2, table Default-IP-Routing-Table)
Flag: 0x840
Advertised to update-groups:
1
5
150.1.1.4 from 150.1.1.4 (4.4.4.4)
Origin EGP, localpref 100, valid, external
5
10.0.0.2 from 10.0.0.2 (2.2.2.2)
Origin IGP, localpref 100, valid, external, best
5
10.0.0.6 from 10.0.0.6 (3.3.3.3)
Origin incomplete, metric 0, localpref 100, valid, external

https://t.me/learningnets

CCNP Lab 039: Border Gateway Protocol Lab

Lab Objective:

The focus of this lab is to understand BGP implementation and configuration in Cisco IOS routers. Additional technologies include route filtering, summarization and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure BGP as illustrated in the topology. R1 will peer with R2 and R3. R2 will peer with R1 and R3. R3 will peer with R1, R2 and R4. R4 will peer only with R3. The

https://t.me/learningnets

routers should all use their physical interface addresses for BGP peering. Verify your configuration.

Task 3

Advertise the 150.x.x.x LAN subnets on all routers via BGP. These should be injected using the **network** command on all routers. Verify that all routers' LAN subnets can ping every other routers LAN subnet. Use an extended ping to perform this verification.

Task 4

Configure R1 with the following Loopback interfaces:

Loopback 1920: IP Address 192.0.0.1/32
Loopback 1921: IP Address 192.0.1.1/32

These prefixes should be advertised only to R2. Next, configure R2 to advertise a single route for these prefixes to R3. Ensure that this aggregate route ONLY appears in the BGP Table of R4 but not in the BGP Table of R1. Adhere to the following restrictions when completing this task:

- You can NOT use an outbound route map on R1
- You can NOT use any outbound filters or route maps on R2 or R3
- You can NOT use any inbound filters or route maps on R1 or R3
- You can NOT modify administrative distance values

Verify your configuration using the appropriate commands. Verify that R2, R3, and R4 can ping these prefixes from their LAN subnets, i.e. the 150.x.x.x/24 addresses.

Task 5

To support a future Anycast solution, configure R2 and R4 with a Loopback 200 interface with the IP address 200.8.8.8/32. Next, redistribute this prefix into BGP on R2 and R4 and configure BGP path control so that R1 prefers the prefix originated by R4 over the prefix originated by R1. However, you must adhere to the following restrictions when completing this task:

- You can NOT modify the AS_PATH length for this prefix on ANY router
- You can NOT modify default administrative distance values
- You can NOT modify the WEIGHT or LOCAL_PREF attributes on R1
- You can only issue ONE single command on R1, i.e. one line of code
- You MUST use route maps when redistributing this interface on R2 and R4

Verify your configuration using the appropriate commands. Ensure that R1 can ping this

https://t.me/learningnets

Technet24

address from its LAN IP address of 150.1.1.1/24.

Lab Validation:

Task 1

Please refer to previous labs for basic IP addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

R1(config)#**router bgp 1**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**neighbor 10.0.0.2 remote-as 2**
R1(config-router)#**neighbor 10.0.0.6 remote-as 3**
R1(config-router)#**exit**

R2(config)#**router bgp 2**
R2(config-router)#**bgp router-id 2.2.2.2**
R2(config-router)#**neighbor 10.0.0.1 remote-as 1**
R2(config-router)#**neighbor 10.0.0.10 remote-as 3**
R2(config-router)#**exit**

R3(config)#**router bgp 3**
R3(config-router)#**bgp router-id 3.3.3.3**
R3(config-router)#**neighbor 10.0.0.5 remote-as 1**
R3(config-router)#**neighbor 10.0.0.9 remote-as 2**
R3(config-router)#**neighbor 10.0.0.14 remote-as 4**
R3(config-router)#**exit**

R4(config)#**router bgp 4**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**neighbor 10.0.0.13 remote-as 3**
R4(config-router)#**exit**

Verify your configuration using the **show ip bgp summary** command on all routers:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 1
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.2 4 2 5 5 1 0 0 00:02:52 0
10.0.0.6 4 3 5 6 1 0 0 00:01:16 0

R2#**show ip bgp summary**
BGP router identifier 2.2.2.2, local AS number 2

https://t.me/learningnets

BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.1 4 1 5 5 1 0 0 00:02:58 0
10.0.0.10 4 3 4 5 1 0 0 00:01:24 0

R3#**show ip bgp summary**
BGP router identifier 3.3.3.3, local AS number 3
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.5 4 1 6 5 1 0 0 00:01:25 0
10.0.0.9 4 2 5 4 1 0 0 00:01:26 0
10.0.0.14 4 4 4 4 1 0 0 00:00:21 0

R4#**show ip bgp summary**
BGP router identifier 4.4.4.4, local AS number 4
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.13 4 3 4 4 1 0 0 00:00:24 0

Task 3

R1(config)#**router bgp 1**
R1(config-router)#**network 150.1.1.0 mask 255.255.255.0**
R1(config-router)#**exit**

R2(config)#**router bgp 2**
R2(config-router)#**network 150.2.2.0 mask 255.255.255.0**
R2(config-router)#**exit**

R3(config)#**router bgp 3**
R3(config-router)#**network 150.3.3.0 mask 255.255.255.0**
R3(config-router)#**exit**

R4(config)#**router bgp 4**
R4(config-router)#**network 150.4.4.0 mask 255.255.255.0**
R4(config-router)#**exit**

Verify that all routers have the 150.x.x.x/24 subnets in their BGP Tables:

R1#**show ip bgp**
BGP table version is 5, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

https://t.me/learningnets

Technet24

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
* 150.2.2.0/24 10.0.0.6 0 3 2 i
*> 10.0.0.2 0 0 2 i
* 150.3.3.0/24 10.0.0.2 0 2 3 i
*> 10.0.0.6 0 0 3 i
* 150.4.4.0/24 10.0.0.2 0 2 3 4 i
*> 10.0.0.6 0 3 4 i

R2#**show ip bgp**
BGP table version is 5, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 10.0.0.10 0 3 1 i
*> 10.0.0.1 0 0 1 i
*> 150.2.2.0/24 0.0.0.0 0 32768 i
* 150.3.3.0/24 10.0.0.1 0 1 3 i
*> 10.0.0.10 0 0 3 i
* 150.4.4.0/24 10.0.0.1 0 1 3 4 i
*> 10.0.0.10 0 3 4 i

R3#**show ip bgp**
BGP table version is 5, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 10.0.0.9 0 2 1 i
*> 10.0.0.5 0 0 1 i
* 150.2.2.0/24 10.0.0.5 0 1 2 i
*> 10.0.0.9 0 0 2 i
*> 150.3.3.0/24 0.0.0.0 0 32768 i
*> 150.4.4.0/24 10.0.0.14 0 0 4 i

R4#**show ip bgp**
BGP table version is 5, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale

https://t.me/learningnets

Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 10.0.0.13 0 3 1 i
*> 150.2.2.0/24 10.0.0.13 0 3 2 i
*> 150.3.3.0/24 10.0.0.13 0 0 3 i
*> 150.4.4.0/24 0.0.0.0 0 32768 i

Finally, verify that each router can ping every other routers' LAN interface from its own:

R1#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R1#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/15/16 ms

R1#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R2#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R2#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:

https://t.me/learningnets

Technet24

Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R2#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

R3#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R3#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R3#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/1/4 ms

R4#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.

https://t.me/learningnets

Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/15/16 ms

Task 4

The requirements for this task are three-fold. First, configure the Loopback interfaces on R1 and then advertise them via BGP but ONLY to R2. This is done using an outbound prefix list that prevents the prefixes from being advertised to R3. The first part is completed on R1 as follows:

R1(config)#**interface loopback 1920**
R1(config-if)#**ip add 192.0.0.1 255.255.255.255**
R1(config-if)#**exit**
R1(config)#**interface loopback 1921**
R1(config-if)#**ip add 192.0.1.1 255.255.255.255**
R1(config-if)#**exit**
R1(config)#**ip prefix-list FILTER seq 1 deny 192.0.0.1/32**
R1(config)#**ip prefix-list FILTER seq 2 deny 192.0.1.1/32**
R1(config)#**ip prefix-list FILTER seq 3 permit 0.0.0.0/0 le 32**
R1(config)#**router bgp 1**
R1(config-router)#**network 192.0.0.1 mask 255.255.255.255**
R1(config-router)#**network 192.0.1.1 mask 255.255.255.255**
R1(config-router)#**neighbor 10.0.0.6 prefix-list FILTER out**
R1(config-router)#**exit**

Verify your configuration using **show ip bgp neighbor <address> advertised-**routes command on R1 to see which prefixes are advertised to R2 and R3:

R1#**show ip bgp neighbors 10.0.0.2 advertised-routes**
BGP table version is 7, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

https://t.me/learningnets
Technet24

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
*> 150.2.2.0/24 10.0.0.2 0 0 2 i
*> 150.3.3.0/24 10.0.0.6 0 0 3 i
*> 150.4.4.0/24 10.0.0.6 0 3 4 i
***> 192.0.0.1/32 0.0.0.0 0 32768 i**
***> 192.0.1.1/32 0.0.0.0 0 32768 i**

Total number of prefixes 6

R1#**show ip bgp neighbors 10.0.0.6 advertised-routes**
BGP table version is 7, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
*> 150.2.2.0/24 10.0.0.2 0 0 2 i

Total number of prefixes 2

The second part of this task requires that you summarize these prefixes and ensure that they are NOT advertised back to R1 by R3. Given the restrictions, which prevent the manipulation of attributes, administrative distance values, or using inbound or outbound filters, we need to use another solution. When summarizing with BGP, if you use the **aggregate-address** command, the router that performs the aggregation removes, by default, any other AS_PATH information (AS_SET). The summarized route is therefore originated from the AS of the router that generated the summary. This means that if the routes that are summarized were received from another AS, as is our case, the aggregate can be re-advertised back to that AS, causing all sorts of issues. For example, assume the following command was issued on R2:

R2(config)#**router bgp 2**
R2(config-router)#**aggregate-address 192.0.0.0 255.255.254.0 summary-only**
R2(config-router)#**exit**

Given this configuration, R2 suppresses the specific 192.0.0.1/32 and 192.0.1.1/32 prefixes and advertises only a single route to R3. This route appears on R3 as follows:

R3#**show ip bgp 192.0.0.0 255.255.254.0**
BGP routing table entry for 192.0.0.0/23, version 10
Paths: (2 available, best #2, table Default-IP-Routing-Table)
Flag: 0x820

https://t.me/learningnets

Advertised to update-groups:
1
1 2, (aggregated by 2 2.2.2.2)
10.0.0.5 from 10.0.0.5 (1.1.1.1)
Origin IGP, localpref 100, valid, external, atomic-aggregate
2, (aggregated by 2 2.2.2.2)
10.0.0.9 from 10.0.0.9 (2.2.2.2)
Origin IGP, metric 0, localpref 100, valid, external, atomic-aggregate, best

Notice that the AS_PATH shows that this aggregate originates in AS 2, even though it is based on prefixes originated in AS 1. Given this, R1 will accept this same prefix from both R2 an R3:

R1#**show ip bgp 192.0.0.0 255.255.254.0**
BGP routing table entry for 192.0.0.0/23, version 8
Paths: (2 available, best #2, table Default-IP-Routing-Table)
Advertised to update-groups:
2
3 2, (aggregated by 2 2.2.2.2)
10.0.0.6 from 10.0.0.6 (3.3.3.3)
Origin IGP, localpref 100, valid, external, atomic-aggregate
2, (aggregated by 2 2.2.2.2)
10.0.0.2 from 10.0.0.2 (2.2.2.2)
Origin IGP, metric 0, localpref 100, valid, external, atomic-aggregate, best

To complete this task, we need to append the **as-set** keyword to the BGP **aggregate-address** command. The **as-set** argument creates an aggregate address with a mathematical set of autonomous systems. In other words, it includes all ASes of the specific prefixes from which the aggregate is generated. This prevents the aggregate from being advertised back to those ASes; i.e. the routers receiving this UPDATE will see their own AS_PATH in the string and drop it. To complete this task, configure R2 as follows:

R2(config)#**router bgp 2**
R2(config-router)#**aggregate-add 192.0.0.0 255.255.254.0 summary-only as-set**
R2(config-router)#**exit**

Following this change, the aggregate now reflects an origin of AS 1 when seen on R3:

R3#**show ip bgp 192.0.0.0 255.255.254.0**
BGP routing table entry for 192.0.0.0/23, version 13
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Advertised to update-groups:

https://t.me/learningnets
Technet24

1
2 1, (aggregated by 2 2.2.2.2)
10.0.0.9 from 10.0.0.9 (2.2.2.2)
Origin IGP, metric 0, localpref 100, valid, external, best

Because R1 sees its own AS_PATH in the list, it does NOT accept the aggregate:

R1#**show ip bgp 192.0.0.0 255.255.254.0**
% Network not in table

However, the aggregate is still advertised to R4:

R4#**show ip bgp 192.0.0.0 255.255.254.0**
BGP routing table entry for 192.0.0.0/23, version 13
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Not advertised to any peer
3 2 1, (aggregated by 2 2.2.2.2)
10.0.0.13 from 10.0.0.13 (3.3.3.3)
Origin IGP, localpref 100, valid, external, best

The final task is to verify that R1, R2 and R3 can all ping the 192.0.0.1/32 and 192.0.1.1/32 prefixes from their LAN interfaces. This last part is completed as follows:

R2#**ping 192.0.0.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 192.0.0.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R2#**ping 192.0.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 192.0.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R3#**ping 192.0.0.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 192.0.0.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R3#**ping 192.0.1.1 source fastethernet 0/0 repeat 10**

https://t.me/learningnets

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 192.0.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R4#**ping 192.0.0.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 192.0.0.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 192.0.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 192.0.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

Task 5

While seemingly very difficult, this task is quite simple IF you have read the BGP path selection process in the ROUTE guide. Because we cannot use WEIGHT or LOCAL_PREF, those two attributes are ruled out. Because both prefixes are not originated on the local router, we can skip this step of the path selection process.

The next attribute to consider then would be the AS_PATH length. However, the task says that we cannot MODIFY the AS_PATH length; however, it says nothing about ignoring the AS_PATH. In the ROUTE guide, in the BGP path selection process section, it reads as follows:

If no route was originated, prefer the route that has the shortest AS_PATH. However, if the **bgp bestpath as-path ignore** command is issued on the router, the AS_PATH attribute is not used in BGP best path selection. Also, when comparing this attribute, an AS_SET is counted once, regardless of the number of autonomous systems in the set. And, finally, the AS_CONFED_SEQUENCE is not included in the AS_PATH length.

Therefore, we can configure R1 to IGNORE the AS_PATH attribute in best path selection and look at the next attribute in the best path selection process, which is ORIGIN, we can influence the path selection by configuring R1 to ignore the AS_PATH attribute in the path selection process and advertising the prefix from R4 with a better ORIGIN code than that on R2. This task is completed as follows:

https://t.me/learningnets

Technet24

R1(config)#**router bgp 1**
R1(config-router)#**bgp bestpath as-path ignore**
R1(config-router)#**exit**

NOTE: The **bgp bestpath as-path ignore** command is a hidden command. It will not show up when you hit the question mark (?). Simply type it in and is shows up in the config.

R1(config)#**router bgp 1**
R1(config-router)#**bgp bestpath ?**
compare-routerid Compare router-id for identical EBGP paths
cost-community cost community
med MED attribute

Complete your configuration on routers R2 and R4 as follows:

R2(config)#**interface loopback 200**
R2(config-if)#**ip address 200.8.8.8 255.255.255.255**
R2(config-if)#**exit**
R2(config)#**route-map LOOPBACK permit 10**
R2(config-route-map)#**match interface loopback 200**
R2(config-route-map)#**exit**
R2(config)#**router bgp 2**
R2(config-router)#**redistribute connected route-map LOOPBACK**
R2(config-router)#**exit**

R4(config)#**interface loopback 200**
R4(config-if)#**ip address 200.8.8.8 255.255.255.255**
R4(config-if)#**exit**
R4(config)#**route-map LOOPBACK permit 10**
R4(config-route-map)#**match interface loopback 200**
R4(config-route-map)#**set origin igp**
R4(config-route-map)#**exit**
R4(config)#**router bgp 4**
R4(config-router)#**redistribute connected route-map LOOPBACK**
R4(config-router)#**exit**

Following this change, the BGP Table on R1 reflects the following for the 200.8.8.8/32 prefix:

R1#**show ip bgp 200.8.8.8 255.255.255.255**
BGP routing table entry for 200.8.8.8/32, version 8
Paths: (2 available, best #2, table Default-IP-Routing-Table)
Flag: 0x820

https://t.me/learningnets

Advertised to update-groups:
1
2
10.0.0.2 from 10.0.0.2 (2.2.2.2)
Origin incomplete, metric 0, localpref 100, valid, external
3 4
10.0.0.6 from 10.0.0.6 (3.3.3.3)
Origin IGP, localpref 100, valid, external, best

Because the AS_PATH attribute is ignored in best path selection on R1, it is omitted in the path selection process and the next valid attribute, ORIGIN, is used instead. Given that an ORIGIN of IGP > EGP > Incomplete, the path from R4 wins and is used instead. The same logic is also applicable to R3, which prefers this same path because of the ORIGIN:

R3#**show ip bgp 200.8.8.8 255.255.255.255**
BGP routing table entry for 200.8.8.8/32, version 15
Paths: (2 available, best #1, table Default-IP-Routing-Table)
Advertised to update-groups:
1
4
10.0.0.14 from 10.0.0.14 (4.4.4.4)
Origin IGP, metric 0, localpref 100, valid, external, best
2
10.0.0.9 from 10.0.0.9 (2.2.2.2)
Origin incomplete, metric 0, localpref 100, valid, external

Finally, complete this task by pinging from R1s LAN to the 192.8.8.8/32 address:

R1#**ping 200.8.8.8 source 150.1.1.1 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 200.8.8.8, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

https://t.me/learningnets

Technet24

CCNP Lab 040: Border Gateway Protocol Lab

Lab Objective:

The focus of this lab is to understand BGP implementation and configuration in Cisco IOS routers. Additional technologies include route filtering and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure BGP as illustrated in the topology. R1 will peer with R2 and R3. R2 will

https://t.me/learningnets

Technet24

peer with R1 and R3. R3 will peer with R1, R2 and R4. R4 will peer only with R3. The routers should all use their physical interface addresses for BGP peering. Verify your configuration.

Task 3

Advertise the 150.x.x.x LAN subnets on all routers via BGP. These should be injected using the **network** command on all routers. Verify that all routers' LAN subnets can ping every other routers LAN subnet. Use an extended ping to perform this verification.

Task 4

Configure BGP so that R1 prefers the path via R2 to reach the 150.4.4.0/24 subnet. You are NOT allowed to make any changes on R1 or R2 when completing this task. Ensure that when R2 is down, R1 can still reach the 150.4.4.0/24 subnet. Verify your configuration using the appropriate commands and simulating an R2 failure.

Task 5

Configure the following Loopback interfaces on R1:

Loopback 192: IP Address 192.1.1.1/32
Loopback 193: IP Address 193.1.1.1/32

Advertise the 192.1.1.1/32 subnet only to R2. Ensure that this is NOT re-advertised to R3. Next, advertise the 193.1.1.1/32 subnet only to R3. Ensure that this is NOT re-advertised to R2 or R4.

Task 6

Configure BGP in such a way that R4 can reach the 192.1.1.1/32 and 193.1.1.1/32 from its local LAN subnet. You are allowed to configure on R1 to complete this task; however, do NOT modify the existing configuration. You are NOT allowed to configure any static routes when completing this task. Ensure that R4 can always reach these prefixes even if the R1-R3 or R2-R3 link is down. Verify your configuration by pinging from the 150.4.4.0/24 subnet to the 193.1.1.1/32 host address on R1.

Lab Validation:

Task 1

Please refer to previous labs for basic IP addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

R1(config)#**router bgp 1**
R1(config-router)#**bgp router-id 1.1.1.1**

https://t.me/learningnets

R1(config-router)#**neighbor 10.0.0.2 remote-as 2**
R1(config-router)#**neighbor 10.0.0.6 remote-as 3**
R1(config-router)#**exit**

R2(config)#**router bgp 2**
R2(config-router)#**bgp router-id 2.2.2.2**
R2(config-router)#**neighbor 10.0.0.1 remote-as 1**
R2(config-router)#**neighbor 10.0.0.10 remote-as 3**
R2(config-router)#**exit**

R3(config)#**router bgp 3**
R3(config-router)#**bgp router-id 3.3.3.3**
R3(config-router)#**neighbor 10.0.0.5 remote-as 1**
R3(config-router)#**neighbor 10.0.0.9 remote-as 2**
R3(config-router)#**neighbor 10.0.0.14 remote-as 3**
R3(config-router)#**exit**

R4(config)#**router bgp 3**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**neighbor 10.0.0.13 remote-as 3**
R4(config-router)#**exit**

Verify your configuration using the **show ip bgp summary** command:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 1
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.2 4 2 12 12 1 0 0 00:09:27 0
10.0.0.6 4 3 11 12 1 0 0 00:08:44 0

R2#**show ip bgp summary**
BGP router identifier 2.2.2.2, local AS number 2
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.1 4 1 12 12 1 0 0 00:09:31 0
10.0.0.10 4 3 11 12 1 0 0 00:08:43 0

R3#**show ip bgp summary**
BGP router identifier 3.3.3.3, local AS number 3
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.5 4 1 12 11 1 0 0 00:08:51 0

https://t.me/learningnets

Technet24

10.0.0.9 4 2 12 11 1 0 0 00:08:45 0
10.0.0.14 4 3 11 11 1 0 0 00:07:17 0

R4#**show ip bgp summary**
BGP router identifier 4.4.4.4, local AS number 3
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.13 4 3 11 11 1 0 0 00:07:06 0

Task 3

R1(config)#**router bgp 1**
R1(config-router)#**network 150.1.1.0 mask 255.255.255.0**
R1(config-router)#**exit**

R2(config)#**router bgp 2**
R2(config-router)#**network 150.2.2.0 mask 255.255.255.0**
R2(config-router)#**exit**

Because R3 will be receiving prefixes from external peers (R1 and R2) and advertising those same prefixes to an internal peer (R4), you need to change the NEXT_HOP for the prefixes, otherwise R4 will not be able to reach them. The configuration to be implemented is as follows:

R3(config)#**router bgp 3**
R3(config-router)#**network 150.3.3.0 mask 255.255.255.0**
R3(config-router)#**neighbor 10.0.0.14 next-hop-self**
R3(config-router)#**exit**

R4(config)#**router bgp 3**
R4(config-router)#**network 150.4.4.0 mask 255.255.255.0**
R4(config-router)#**exit**

Verify your configuration using the **show ip bgp** command:

R1#**show ip bgp**
BGP table version is 5, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
* 150.2.2.0/24 10.0.0.6 0 3 2 i
*> 10.0.0.2 0 0 2 i

https://t.me/learningnets

* 150.3.3.0/24 10.0.0.2 0 2 3 i
*> 10.0.0.6 0 0 3 i
* 150.4.4.0/24 10.0.0.2 0 2 3 i
*> 10.0.0.6 0 3 i

R2#**show ip bgp**
BGP table version is 5, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 10.0.0.10 0 3 1 i
*> 10.0.0.1 0 0 1 i
*> 150.2.2.0/24 0.0.0.0 0 32768 i
* 150.3.3.0/24 10.0.0.1 0 1 3 i
*> 10.0.0.10 0 0 3 i
* 150.4.4.0/24 10.0.0.1 0 1 3 i
*> 10.0.0.10 0 3 i

R3#**show ip bgp**
BGP table version is 5, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 10.0.0.9 0 2 1 i
*> 10.0.0.5 0 0 1 i
* 150.2.2.0/24 10.0.0.5 0 1 2 i
*> 10.0.0.9 0 0 2 i
*> 150.3.3.0/24 0.0.0.0 0 32768 i
*>i150.4.4.0/24 10.0.0.14 0 100 0 i

R4#**show ip bgp**
BGP table version is 5, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i150.1.1.0/24 10.0.0.13 0 100 0 1 i
*>i150.2.2.0/24 10.0.0.13 0 100 0 2 i

https://t.me/learningnets

Technet24

*>i150.3.3.0/24 10.0.0.13 0 100 0 i
*> 150.4.4.0/24 0.0.0.0 0 32768 i

Finally, verify that you have LAN-to-LAN connectivity on all routers using extended pings:

R1#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R1#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R1#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

R2#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R2#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/15/16 ms

R2#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

https://t.me/learningnets

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

R3#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R3#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R3#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R4#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

R4#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

https://t.me/learningnets

Technet24

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/15/16 ms

Task 4

Because the MED attribute is not compared when routes are received from multiple ASes, unless the **bgp always-compare-med** command is used, use AS_PATH prepending to complete this task. Prior to any changes, the BGP RIB on R1 shows the following entries:

R1#show ip bgp
BGP table version is 5, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
* 150.2.2.0/24 10.0.0.6 0 3 2 i
*> 10.0.0.2 0 0 2 i
* 150.3.3.0/24 10.0.0.2 0 2 3 i
*> 10.0.0.6 0 0 3 i
*** 150.4.4.0/24 10.0.0.2 0 2 3 i**
***> 10.0.0.6 0 3 i**

NOTE: The greater than sign (>) indicates the current best path in the BGP RIB.

The current best path for 150.4.4.0/24 is via R3 because of the shorter AS_PATH. To complete this task, prepend the AS_PATH for this prefix on R3 for the neighbor relationship to R1:

R3(config)#**ip prefix-list R4-LAN seq 5 permit 150.4.4.0/24**
R3(config)#**route-map PATH-CONTROL permit 10**
R3(config-route-map)#**match ip address prefix list R4-LAN**
R3(config-route-map)#**set as-path prepend 3 3**
R3(config-route-map)#**exit**
R3(config)#**route-map PATH-CONTROL permit 20**
R3(config-route-map)#**exit**
R3(config)#**router bgp 3**
R3(config-router)#**neighbor 10.0.0.5 route-map PATH-CONTROL out**

https://t.me/learningnets

R3(config-router)#**exit**

Following this configuration, the BGP Table on R1 shows the following for 150.4.4.0/24:

R1#**show ip bgp**
BGP table version is 7, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
* 150.2.2.0/24 10.0.0.6 0 3 3 3 2 i
*> 10.0.0.2 0 0 2 i
*> 150.3.3.0/24 10.0.0.2 0 2 3 i
* 10.0.0.6 0 0 3 3 3 i
***> 150.4.4.0/24 10.0.0.2 0 2 3 i**
*** 10.0.0.6 0 3 3 3 i**

Next, verify that R1 and R4 can still ping each other LAN-to-LAN using an extended ping:

R1#**ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/35/84 ms

Finally, test the redundancy by disabling the R1-R2 WAN link and ensuring that R1 can still ping the 150.4.4.0/24 subnet (remember to enable it after the test):

R1(config)#**interface serial 0/0**
R1(config-if)#**shutdown**
R1(config-if)#**exit**
R1(config)#**do show ip bgp 150.4.4.0 255.255.255.0**
BGP routing table entry for 150.4.4.0/24, version 10
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Advertised to update-groups:
1
3 3 3
10.0.0.6 from 10.0.0.6 (3.3.3.3)

https://t.me/learningnets

Technet24

Origin IGP, localpref 100, valid, external, best
R1(config)#
R1(config)#**do ping 150.4.4.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/29/32 ms

Task 5

This task requires some thought and is three-fold. The configuration of the Loopback interfaces on router R1 is straightforward. The second part of the task is to advertise the 192.1.1.1/32 address to R2 only and then the 193.1.1.1/32 address to R3 only. This requires the use of route maps in conjunction with IP ACLs or prefix lists. The reason route maps are used in because of the third required, which will be illustrated later. This second part is completed as follows:

R1(config)#**interface loopback 192**
R1(config-if)#**ip address 192.1.1.1 255.255.255.255**
R1(config-if)#**exit**
R1(config)#**interface loopback 193**
R1(config-if)#**ip address 193.1.1.1 255.255.255.255**
R1(config-if)#**exit**
R1(config)#**ip prefix-list LOOPBACK192 seq 5 permit 192.1.1.1/32**
R1(config)#**ip prefix-list LOOPBACK193 seq 5 permit 193.1.1.1/32**
R1(config)#**route-map R2-OUTBOUND deny 10**
R1(config-route-map)#**match ip address prefix-list LOOPBACK193**
R1(config-route-map)#**exit**
R1(config)#**route-map R2-OUTBOUND permit 20**
R1(config-route-map)#**exit**
R1(config)#**route-map R3-OUTBOUND deny 10**
R1(config-route-map)#**match ip address prefix-list LOOPBACK192**
R1(config-route-map)#**exit**
R1(config)#**route-map R3-OUTBOUND permit 20**
R1(config-route-map)#**exit**
R1(config)#**router bgp 1**
R1(config-router)#**network 192.1.1.1 mask 255.255.255.255**
R1(config-router)#**network 193.1.1.1 mask 255.255.255.255**
R1(config-router)#**neighbor 10.0.0.2 route-map R2-OUTBOUND out**

https://t.me/learningnets

R1(config-router)#**neighbor 10.0.0.6 route-map R3-OUTBOUND out**
R1(config-router)#**exit**

Verify the configuration using the **show ip bgp neighbors <address> advertised-routes** command on R1 to see the prefixes advertised to R2 and R3:

R1#**show ip bgp neighbors 10.0.0.2 advertised-routes**
BGP table version is 15, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
***> 192.1.1.1/32 0.0.0.0 0 32768 i**

Total number of prefixes 2

R1#**show ip bgp neighbor 10.0.0.6 advertised-routes**
BGP table version is 15, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 i
*> 150.2.2.0/24 10.0.0.2 0 0 2 i
*> 150.3.3.0/24 10.0.0.2 0 2 3 i
*> 150.4.4.0/24 10.0.0.2 0 2 3 i
***> 193.1.1.1/32 0.0.0.0 0 32768 i**

The third part of this task requires the use of the COMMUNITY attribute. The BGP well-known communities are communities that have predefined meanings. Cisco IOS software supports four well-known communities which are:

1. NO_EXPORT
2. NO_ADVERTISE
3. INTERNET
4. LOCAL_AS

The NO_EXPORT well-known community prevents BGP prefixes that are specifically assigned this predefined community attribute value from being advertised to any eBGP peers. The prefixes, however, will continue to be advertised to all other BGP speakers within the local AS. In other words, prefixes assigned this community value will remain

https://t.me/learningnets
Technet24

local to the AS.

The NO_ADVERTISE community prevents any prefixes that are assigned this predefined community attribute from being advertised to any peer – internal or external.

The INTERNET community allows all prefixes assigned to this community to be advertised to any and all BGP peers (assuming no filtering, etc, is in place). In Cisco IOS software, all BGP prefixes belong to the INTERNET community by default.

And finally, the LOCAL_AS community is used in a somewhat similar manner to another of the previously described communities: the NO_EXPORT community. If used in a Confederation, the LOCAL_AS community prevents all prefixes assigned this community from being advertised out of the local sub autonomous system. When Confederations are not implemented, the LOCAL_AS community is applied in the same manner as the NO_EXPORT community.

This task is therefore completed by modifying the existing configuration as follows:

```
R1(config)#route-map R2-OUTBOUND permit 20
R1(config-route-map)#match ip address prefix-list LOOPBACK192
R1(config-route-map)#set community no-advertise
R1(config-route-map)#exit
R1(config)#route-map R2-OUTBOUND permit 30
R1(config-route-map)#exit
R1(config)#route-map R3-OUTBOUND permit 20
R1(config-route-map)#match ip address prefix-list LOOPBACK193
R1(config-route-map)#set community no-advertise
R1(config-route-map)#exit
R1(config)#route-map R3-OUTBOUND permit 30
R1(config-route-map)#exit
R1(config)#router bgp 1
R1(config-router)#neighbor 10.0.0.2 send-community standard
R1(config-router)#neighbor 10.0.0.6 send-community standard
R1(config-router)#end
R1#
R1#clear ip bgp * soft out
```

Next, verify that these prefixes are received by R2 and R3 and are not re-advertised as required:

```
R2#show ip bgp
BGP table version is 11, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
```

https://t.me/learningnets

Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 10.0.0.1 0 0 1 i
* 10.0.0.10 0 3 1 i
*> 150.2.2.0/24 0.0.0.0 0 32768 i
*> 150.3.3.0/24 10.0.0.10 0 0 3 i
*> 150.4.4.0/24 10.0.0.10 0 3 i
*> 192.1.1.1/32 10.0.0.1 0 0 1 i

Use the **show ip bgp <network> <mask>** command to view all attribute information:

R2#**show ip bgp 192.1.1.1 255.255.255.255**
BGP routing table entry for 192.1.1.1/32, version 10
Paths: (1 available, best #1, table Default-IP-Routing-Table, not advertised to any peer)
Not advertised to any peer
1
10.0.0.1 from 10.0.0.1 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, external, best
Community: no-advertise

The BGP RIB on R3 shows the following entries:

R3#**show ip bgp**
BGP table version is 9, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 10.0.0.9 0 2 1 i
*> 10.0.0.5 0 0 1 i
* 150.2.2.0/24 10.0.0.5 0 1 2 i
*> 10.0.0.9 0 0 2 i
*> 150.3.3.0/24 0.0.0.0 0 32768 i
*>i150.4.4.0/24 10.0.0.14 0 100 0 i
***> 193.1.1.1/32 10.0.0.5 0 0 1 i**

Use the **show ip bgp <network> <mask>** command to view all attribute information:

R3#**show ip bgp 193.1.1.1 255.255.255.255**
BGP routing table entry for 193.1.1.1/32, version 9
Paths: (1 available, best #1, table Default-IP-Routing-Table, not advertised to any peer)
Not advertised to any peer
1

https://t.me/learningnets

Technet24

10.0.0.5 from 10.0.0.5 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, external, best
Community: no-advertise

The BGP RIB on R4 should have NO entries for the 192.1.1.1/32 or 193.1.1.1/32 prefixes:

R4#**show ip bgp**
BGP table version is 9, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i150.1.1.0/24 10.0.0.13 0 100 0 1 i
*>i150.2.2.0/24 10.0.0.13 0 100 0 2 i
*>i150.3.3.0/24 10.0.0.13 0 100 0 i
*> 150.4.4.0/24 0.0.0.0 0 32768 i

Task 6

To complete this task, configure R1 to advertise a default route to R2 and R3. This will allow R4 to always reach these two prefixes when either the R1-R3 or R2-R3 link is down:

R1(config)#**router bgp 1**
R1(config-router)#**neighbor 10.0.0.2 default-originate**
R1(config-router)#**neighbor 10.0.0.6 default-originate**
R1(config-router)#**exit**

Verify that the default route exists in R4s BGP RIB using the **show ip bgp** command:

R4#**show ip bgp 0.0.0.0 0.0.0.0**
BGP routing table entry for 0.0.0.0/0, version 11
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Flag: 0x820
Not advertised to any peer
1
10.0.0.13 from 10.0.0.13 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, internal, best

Next, ping the 192.1.1.1/32 and 193.1.1.1/32 prefixes from R4s LAN subnet address:

R4#**ping 192.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.

https://t.me/learningnets

Sending 10, 100-byte ICMP Echos to 192.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 193.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 193.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

Finally, test BGP redundancy by shutting down the R1-R3 link and performing the same test:

R4#**show ip bgp 0.0.0.0 0.0.0.0**
BGP routing table entry for 0.0.0.0/0, version 13
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Flag: 0x820
Not advertised to any peer
2 1
10.0.0.13 from 10.0.0.13 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, internal, best

R4#**ping 192.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 192.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R4#**ping 193.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 193.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/31/32 ms

https://t.me/learningnets

Technet24

CCNP Lab 041: Border Gateway Protocol Lab

Lab Objective:

The focus of this lab is to understand BGP implementation and configuration in Cisco IOS routers. Additional technologies include route filtering and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Technet24

Configure BGP as illustrated in the topology. R1 will peer with R2. R2 will peer with R1 and R3. R3 will peer with R4. Do NOT peer R1 and R4 even though they exist in the same AS. Verify the configuration using the appropriate commands.

Task 3

Advertise the 150.2.2.0/24 and 150.3.3.0/24 prefixes connected to R2 and R3, respectively, using BGP. Do NOT advertise the 150.1.1.0/24 subnet connected to R1 and R4. However, ensure that both R2 and R3 can still ping this subnet. You are NOT allowed to use static routes. Verify your configuration using an extended ping from the LAN subnets connected to R2 and R3 to the 150.1.1.0/24 subnet connected to R1 and R4.

Task 4

Configure BGP so that R3 prefers the path via R2 to reach the 150.1.1.0/24 subnet. You are only allowed to configure a device in AS 1. You are NOT allowed to advertise the 150.1.1.0/24 prefix when completing this task. Verify your configuration and ensure that R2 and R3 can still ping the 150.1.1.1/24 and 150.1.1.4/24 addresses when complete. Use an extended ping that is sourced from R3s LAN IP address.

Task 5

Configure OSPF on the LAN subnet between R1 and R4. Next, configure AS 1 so that R4 will prefer the path via R1 to reach the 150.2.2.0/24 or 150.3.3.0/24 subnets. In the event that the WAN link between R1 and R2 is down, the path via R4 should be used instead. You are NOT allowed to establish an iBGP neighbor relationship between R1 and R4 to complete this task. Additionally, you are not allowed to use the **distance** command to modify any protocol administrative distance values. Instead, use a BGP feature when completing this task. Verify your configuration using the appropriate commands. Ensure R4 can still ping the 150.2.2.0/24 and the 150.3.3.0/24 subnets when complete.

HINT: Use the BGP **network** command to complete this task.

Lab Validation:

Task 1

Please refer to previous labs for basic IP addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

R1(config)#**router bgp 1**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**neighbor 10.0.0.2 remote-as 2**

https://t.me/learningnets

R1(config-router)#**exit**

R2(config)#**router bgp 2**
R2(config-router)#**bgp router-id 2.2.2.2**
R2(config-router)#**neighbor 10.0.0.1 remote-as 1**
R2(config-router)#**neighbor 10.0.0.10 remote-as 3**
R2(config-router)#**exit**

R3(config)#**router bgp 3**
R3(config-router)#**bgp router-id 3.3.3.3**
R3(config-router)#**neighbor 10.0.0.9 remote-as 2**
R3(config-router)#**neighbor 10.0.0.14 remote-as 1**
R3(config-router)#**exit**

R4(config)#**router bgp 1**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**neighbor 10.0.0.13 remote-as 3**
R4(config-router)#**exit**

Verify your configuration using the **show ip bgp summary** command:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 1
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.2 4 2 7 7 1 0 0 00:05:00 0

R2#**show ip bgp summary**
BGP router identifier 2.2.2.2, local AS number 2
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.1 4 1 8 8 1 0 0 00:05:03 0
10.0.0.10 4 3 6 7 1 0 0 00:03:31 0

R3#**show ip bgp summary**
BGP router identifier 3.3.3.3, local AS number 3
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.9 4 2 7 6 1 0 0 00:03:35 0
10.0.0.14 4 1 6 6 1 0 0 00:02:41 0

R4#**show ip bgp summary**
BGP router identifier 4.4.4.4, local AS number 1
BGP table version is 1, main routing table version 1

https://t.me/learningnets

Technet24

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.13 4 3 6 6 1 0 0 00:02:30 0

Task 3

To complete this task, you need to configure R1 and R4 to advertise defaults to R2 and R3:

R2(config)#**router bgp 2**
R2(config-router)#**network 150.2.2.0 mask 255.255.255.0**
R2(config-router)#**exit**

R3(config)#**router bgp 3**
R3(config-router)#**network 150.3.3.0 mask 255.255.255.0**
R3(config-router)#**exit**

R1(config)#**router bgp 1**
R1(config-router)#**neighbor 10.0.0.2 default-originate**
R1(config-router)#**exit**

R4(config)#**router bgp 1**
R4(config-router)#**neighbor 10.0.0.13 default-originate**
R4(config-router)#**exit**
Next, verify your configuration using the **show ip bgp** command:

R1#**show ip bgp**
BGP table version is 3, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.2.2.0/24 10.0.0.2 0 0 2 i
*> 150.3.3.0/24 10.0.0.2 0 2 3 i

R2#**show ip bgp**
BGP table version is 4, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 0.0.0.0 10.0.0.10 0 3 1 i
*> 10.0.0.1 0 0 1 i
*> 150.2.2.0/24 0.0.0.0 0 32768 i

https://t.me/learningnets

*> 150.3.3.0/24 10.0.0.10 0 0 3 i

R3#**show ip bgp**
BGP table version is 5, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 0.0.0.0 10.0.0.14 0 0 1 i
* 10.0.0.9 0 2 1 i
*> 150.2.2.0/24 10.0.0.9 0 0 2 i
*> 150.3.3.0/24 0.0.0.0 0 32768 i

R4#**show ip bgp**
BGP table version is 3, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.2.2.0/24 10.0.0.13 0 3 2 i
*> 150.3.3.0/24 10.0.0.13 0 0 3 i

Finally, verify that R2 and R3 can ping the 150.1.1.1/24 and 150.1.1.4/24 addresses from their respective LAN addresses using an extended ping:

R2#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/2/4 ms

R2#**ping 150.1.1.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.4, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R3#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:

https://t.me/learningnets

Technet24

Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R3#**ping 150.1.1.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.4, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

Task 4

To complete this task, you need to use a route map and AS_PATH prepending to make the default route advertised by R4 longer than that advertised by R1. This route-map should be applied to the default route advertised to R3. This task is completed as follows:

R4(config)#**route-map PREPEND permit 10**
R4(config-route-map)#**set as-path prepend 1 1 1 1**
R4(config-route-map)#**exit**
R4(config)#**router bgp 1**
R4(config-router)#**neighbor 10.0.0.13 default-originate route-map PREPEND**
R4(config-router)#**exit**

Following this change, verify the BGP Table on R3 to ensure the preferred default is via R2:

R3#**show ip bgp**
BGP table version is 6, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*** 0.0.0.0 10.0.0.14 0 0 1 1 1 1 1 i**
***> 10.0.0.9 0 2 1 i**
*> 150.2.2.0/24 10.0.0.9 0 0 2 i
*> 150.3.3.0/24 0.0.0.0 0 32768 i

Finally, verify that R3 can still ping the 150.1.1.1/24 and 150.1.1.4/24 addresses after the change:

R3#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

https://t.me/learningnets

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/18/28 ms

R3#**ping 150.1.1.4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.4, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

Task 5

The requirements for this task are threefold. First, you need to enable OSPF between R1 and R4 across their directly connected LAN segment. Following this configuration, verify the OSPF adjacency between the routers using the **show ip ospf neighbor** command. You can refer to previous labs for OSPF configuration basics.

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 1 FULL/BDR 00:00:37 150.1.1.4 FastEthernet0/0

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 1 FULL/DR 00:00:39 150.1.1.1 FastEthernet0/0

The second part of this task entails redistribution between OSPF and BGP. This allows the LAN subnets connected to R2 and R4 to be advertised across the LAN link connecting R1 and R2. You do NOT need to redistribute OSPF routes into BGP, otherwise you will advertise the LAN subnet between R1 and R4, which is NOT permitted as stated in previous tasks:

R1(config)#**router ospf 1**
R1(config-router)#**redistribute bgp 1 subnets**
R1(config-router)#**exit**

R4(config)#**router ospf 4**
R4(config-router)#**redistribute bgp 1 subnets**
R4(config-router)#**exit**

Following this configuration, verify that the routing tables on both routers show all routes:

https://t.me/learningnets

Technet24

R1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 1 subnets
C 10.0.0.0 is directly connected, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
B 150.2.2.0 [20/0] via 10.0.0.2, 00:28:43
150.3.0.0/24 is subnetted, 1 subnets
B 150.3.3.0 [20/0] via 10.0.0.2, 00:29:14

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 1 subnets
C 10.0.0.12 is directly connected, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
B 150.2.2.0 [20/0] via 10.0.0.13, 00:07:07
150.3.0.0/24 is subnetted, 1 subnets
B 150.3.3.0 [20/0] via 10.0.0.13, 00:29:10

As illustrated in the output above, both routers prefer the BGP routes because of the lower administrative distance of external BGP (20) versus OSPF (110). To complete this task, use the hint provided in the lab, which states that you should use the BGP

https://t.me/learningnets

network command.

The correct command to use in this case would be **network <address> <mask> backdoor** command. The **backdoor** keyword configures the router to change the administrative distance of the specified external BGP route from 20 to 200. This allows IGP routes to be preferred instead. When the IGP routes are no longer present in the routing table, the BGP route is again used. This task is completed as follows:

R4(config)#**router bgp 1**
R4(config-router)#**network 150.2.2.0 mask 255.255.255.0 backdoor**
R4(config-router)#**network 150.3.3.0 mask 255.255.255.0 backdoor**
R4(config-router)#**exit**

Following this change, the routing table on R4 shows the following route entries:

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 1 subnets
C 10.0.0.12 is directly connected, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
O E2 150.2.2.0 [110/1] via 150.1.1.1, 00:00:43, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
O E2 150.3.3.0 [110/1] via 150.1.1.1, 00:00:35, FastEthernet0/0

Next, complete this task by ensuring that R4 can still ping the 150.2.2.0/24 and the 150.3.3.0/24 subnets when complete. Because the routes are known via the FastEthernet0/0 interface, you do NOT need to use an extended ping as the ping will be sourced from the egress interface:

R4#**ping 150.2.2.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!!!!!!

https://t.me/learningnets

Technet24

Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R4#**ping 150.3.3.3 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/17/20 ms

Finally, verify redundancy by shutting down the R1-R2 link and ensuring that R1 can still reach the 150.2.2.0/24 and 150.3.3.0/24 subnets. This is completed as follows:

R1(config)#**interface serial 0/0**
R1(config-if)#**shutdown**
R1(config-if)#**exit**
R1(config)#**do show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
O E2 150.2.2.0 [110/1] via 150.1.1.4, 00:00:08, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
O E2 150.3.3.0 [110/1] via 150.1.1.4, 00:00:08, FastEthernet0/0
R1(config)#
R1(config)#**do ping 150.2.2.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms
R1(config)#
R1(config)#**do ping 150.3.3.3 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:

https://t.me/learningnets

!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

https://t.me/learningnets

CCNP Lab 042: Border Gateway Protocol Lab

Lab Objective:

The focus of this lab is to understand BGP implementation and configuration in Cisco IOS routers. Additional technologies include route filtering and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Technet24

Configure BGP as illustrated in the topology. R1 will peer with R2. R2 will peer with R1 and R3. R3 will peer with R2. Verify the configuration using the appropriate commands.

Task 3

Configure R2 and R3 to advertise their 150.2.2.0/24 and 150.3.3.0/24 prefixes via BGP. Do NOT advertise the 150.1.1.0/24 subnet via BGP; however, ensure that both R2 and R3 can ping R1s LAN IP address. They do NOT need to be able to ping the LAN address of R4. Finally, verify your configuration using the appropriate commands and as Cisco IOS extended ping functions.

Task 4

Management has decided that they would like BGP neighbor relationship between R1 and R3. This should transit R4. Configure a BGP peer relationship between R1s Fa0/0 interface and R3s Se1/2 interface. You are NOT allowed to enable an IGP on R1, R3 or R4; you are NOT allowed to configure BGP or static routing on R4; however, you are allowed to configure a single /32 host route on both R1 and R3. Ensure that when the R1-R2 WAN link is up, R1 prefers the path via R2 to reach the 150.2.2.0/24 and 150.3.3.0/24 prefixes. You are NOT allowed to use route maps as part of your solution. Verify your configuration using the appropriate commands.

Task 5

Configure your network so that when the R1-R2 link is down, R1s LAN address can still reach the 150.2.2.0/24 and 150.3.3.0/24 subnets and vice-versa. You are NOT allowed to configure static routes or an IGP on R1, R3, or R4. Do NOT configure BGP on R4. You can NOT use PBR on any routers, or create a tunnel between R1 and R3. And finally, do NOT advertise the 150.1.1.0/24 prefix via BGP. Your solution should ensure that when the R1-R2 link is up, R3 will use the path via R2 to reach the 150.1.1.0/24 subnet.

When complete, verify your configuration by shutting down the R1-R2 WAN link. After this, verify that R1s LAN interface can ping both the 150.2.2.0/24 and 150.3.3.0/24 subnets and vice-versa. All your pings should be successful.

Lab Validation:

Task 1

Please refer to previous labs for basic IP addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

R1(config)#**router bgp 1**

https://t.me/learningnets

```
R1(config-router)#bgp router-id 1.1.1.1
R1(config-router)#neighbor 10.0.0.2 remote-as 2
R1(config-router)#exit

R2(config)#router bgp 2
R2(config-router)#bgp router-id 2.2.2.2
R2(config-router)#neighbor 10.0.0.1 remote-as 1
R2(config-router)#neighbor 10.0.0.10 remote-as 3
R2(config-router)#exit

R3(config)#router bgp 3
R3(config-router)#bgp router-id 3.3.3.3
R3(config-router)#neighbor 10.0.0.9 remote-as 2
R3(config-router)#exit
```

Verify your configuration using the **show ip bgp summary** command:

```
R1#show ip bgp summary
BGP router identifier 1.1.1.1, local AS number 1
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.2 4 2 4 5 1 0 0 00:01:55 0

R2#show ip bgp summary
BGP router identifier 2.2.2.2, local AS number 2
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.1 4 1 6 5 1 0 0 00:02:12 0
10.0.0.10 4 3 8 8 1 0 0 00:00:20 0

R3#show ip bgp summary
BGP router identifier 3.3.3.3, local AS number 3
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.9 4 2 8 8 1 0 0 00:00:46 0
```

Task 3

The requirements for this task are three-fold. First, simply advertise the LAN subnets connected to R2 and R3 using the **network** command. Second, to allow R2 and R3 to ping the LAN interface address of R1, configure R1 to advertise a default route to R2, which will then advertise it to R3. The first two steps of this task are completed on R1, R2, and R3 as follows:

https://t.me/learningnets

Technet24

R1(config)#**router bgp 1**
R1(config-router)#**neighbor 10.0.0.2 default-originate**
R1(config-router)#**exit**

R2(config)#**router bgp 2**
R2(config-router)#**network 150.2.2.0 mask 255.255.255.0**
R2(config-router)#**exit**

R3(config)#**router bgp 3**
R3(config-router)#**network 150.3.3.0 mask 255.255.255.0**
R3(config-router)#**exit**

Verify your configuration using the **show ip bgp** command on all three routers:

R1#**show ip bgp**
BGP table version is 3, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.2.2.0/24 10.0.0.2 0 0 2 i
*> 150.3.3.0/24 10.0.0.2 0 2 3 i

R2#**show ip bgp**
BGP table version is 4, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 0.0.0.0 10.0.0.1 0 0 1 i
*> 150.2.2.0/24 0.0.0.0 0 32768 i
*> 150.3.3.0/24 10.0.0.10 0 0 3 i

R3#**show ip bgp**
BGP table version is 4, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 0.0.0.0 10.0.0.9 0 2 1 i
*> 150.2.2.0/24 10.0.0.9 0 0 2 i
*> 150.3.3.0/24 0.0.0.0 0 32768 i

https://t.me/learningnets

Finally, verify your configuration using extended pings between R1, R2, and R3:

R1#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/3/4 ms

R1#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/17/20 ms

R2#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 1/2/4 ms

R2#**ping 150.3.3.3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R3#**ping 150.1.1.1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

R3#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3

https://t.me/learningnets

Technet24

!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

Task 4

The requirements for this task are two-fold. The first is that you need to enable BGP between R1 and R3. This should be done across R4 and is completed using two static routes, one on R1 and the other on R3 to establish an external BGP adjacency. This task is completed as follows:

R1(config)#**router bgp 1**
R1(config-router)#**neighbor 10.0.0.13 remote-as 3**
R1(config-router)#**neighbor 10.0.0.13 update-source fastethernet 0/0**
R1(config-router)#**neighbor 10.0.0.13 ebgp-multihop**
R1(config-router)#**exit**
R1(config)#**ip route 10.0.0.13 255.255.255.255 FastEthernet0/0 150.1.1.4**

R3(config)#**router bgp 3**
R3(config-router)#**neighbor 150.1.1.1 remote-as 1**
R3(config-router)#**neighbor 150.1.1.1 ebgp-multihop**
R3(config-router)#**neighbor 150.1.1.1 update-source serial 1/2**
R3(config-router)#**exit**
R3(config)#**ip route 150.1.1.1 255.255.255.255 Serial1/2**

Verify your configuration using the **show ip bgp summary** command on R1 and R3:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 1
BGP table version is 4, main routing table version 4
2 network entries using 234 bytes of memory
4 path entries using 208 bytes of memory
5/2 BGP path/bestpath attribute entries using 620 bytes of memory
4 BGP AS-PATH entries using 96 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1158 total bytes of memory
BGP activity 2/0 prefixes, 4/0 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.2 4 2 65 66 4 0 0 00:59:35 2
10.0.0.13 4 3 8 9 0 0 0 00:01:08 2

R3#**show ip bgp summary**
BGP router identifier 3.3.3.3, local AS number 3

https://t.me/learningnets

BGP table version is 7, main routing table version 7
3 network entries using 351 bytes of memory
4 path entries using 208 bytes of memory
6/3 BGP path/bestpath attribute entries using 744 bytes of memory
4 BGP AS-PATH entries using 96 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1399 total bytes of memory
BGP activity 3/0 prefixes, 7/3 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.9 4 2 74 74 6 0 0 01:01:23 2
150.1.1.1 4 1 20 19 6 0 0 00:00:44 1

The second requirement is that R1 should prefer the path via R2 to reach the 150.2.2.0/24 prefix as well as the 150.3.3.0/24 prefix. By default, R1 will prefer the path via R2 to reach the 150.2.2.0/24 prefix because of the shorter AS_PATH. However, now that an external BGP peer session has been established between R1 and R3, R1 will prefer the path via R3 to reach the 150.3.3.0/24 prefix. Prior to changes on R1, the BGP RIB entry for this prefix shows as follows:

R1#**show ip bgp 150.3.3.0 255.255.255.0**
BGP routing table entry for 150.3.3.0/24, version 4
Paths: (2 available, best #1, table Default-IP-Routing-Table)
Advertised to update-groups:
1
3
10.0.0.13 from 10.0.0.13 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, external, best
2 3
10.0.0.2 from 10.0.0.2 (2.2.2.2)
Origin IGP, localpref 100, valid, external

Because we cannot use route maps to set the LOCAL_PREF, we must instead use the **neighbor <address> weight <value>** command to assign all prefixes received via R1 a higher WEIGHT value. This will ensure that R1 prefers the path via R2 to reach the 150.3.3.0/24 prefix:

R1(config)#**router bgp 1**
R1(config-router)#**neighbor 10.0.0.2 weight 1**
R1(config-router)#**exit**

Following this change, R1 shows the following BGP Table entry for the 150.3.3.0/24

https://t.me/learningnets
Technet24

prefix:

R1#**show ip bgp 150.3.3.0 255.255.255.0**
BGP routing table entry for 150.3.3.0/24, version 6
Paths: (2 available, best #2, table Default-IP-Routing-Table)
Flag: 0x820
Advertised to update-groups:
2
3
10.0.0.13 from 10.0.0.13 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, external
2 3
10.0.0.2 from 10.0.0.2 (2.2.2.2)
Origin IGP, localpref 100, weight 1, valid, external, best

Task 5

This task requires a little bit of thought and has two core requirements. The first requirement is that router R2 and R3 should be able to reach the 150.1.1.0/24 when the R1-R2 link is down. This must be performed in such a manner that router R3 still prefers the path via R2 to reach the 150.1.1.0/24 subnet. Because routers will not compare MED values for prefixes received from different ASes, the AS_PATH attribute must be used instead. This part is completed as follows:

R1(config)#**route-map PREPEND permit 10**
R1(config-route-map)#**set as-path prepend 1 1**
R1(config-route-map)#**exit**
R1(config)#**router bgp 1**
R1(config-router)#**neighbor 10.0.0.13 default-originate route-map PREPEND**
R1(config-router)#**exit**

Following this change, the BGP Tables on R2 and R3 show the following for the default route:

R2#**show ip bgp 0.0.0.0 0.0.0.0**
BGP routing table entry for 0.0.0.0/0, version 6
Paths: (1 available, best #1, table Default-IP-Routing-Table)
Advertised to update-groups:
1
1
10.0.0.1 from 10.0.0.1 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, external, best

https://t.me/learningnets

R3#**show ip bgp 0.0.0.0 0.0.0.0**
BGP routing table entry for 0.0.0.0/0, version 7
Paths: (2 available, best #2, table Default-IP-Routing-Table)
Advertised to update-groups:
1
1 1 1
150.1.1.1 from 150.1.1.1 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, external
2 1
10.0.0.9 from 10.0.0.9 (2.2.2.2)
Origin IGP, localpref 100, valid, external, best

The second requirement, or part, of this task is that R1s LAN interface is able to ping the R2 and R3 LAN addresses and vice-versa. From a routing perspective, when the WAN link between R1 and R2 is shut down, the routes are received via R3. This is demonstrated below:

R1(config)#**interface serial 0/0**
R1(config-if)#**shutdown**
R1(config-if)#**exit**
R1(config)#**do show ip bgp**
BGP table version is 8, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.2.2.0/24 10.0.0.13 0 3 2 i
*> 150.3.3.0/24 10.0.0.13 0 0 3 i

The issue, however, exists on R4. This router is a transit router between R1 and R3; however, it has no routing information for the 150.2.2.0/24 or 150.3.3.0/24 prefixes. Therefore, when a ping from R1 is initiated to either of these subnets, it is dropped by R4 because this router has no routing information for the destination. This is demonstrated by initiating a ping to 150.2.2.2 from R1 while running the **debug ip packet [detail]** command on R4:

R1#**ping 150.2.2.2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
U.U.U.U.U.

https://t.me/learningnets
Technet24

Success rate is 0 percent (0/10)

The **debug ip packet detail** command output on R4 shows the following:

```
R4#debug ip pack detail
IP packet debugging is on (detailed)
R4#
R4#
R4#
*May 12 19:49:29.067: IP: s=150.1.1.1 (FastEthernet0/0), d=150.2.2.2, len 100,
unroutable
*May 12 19:49:29.067: ICMP type=8, code=0
*May 12 19:49:29.067: IP: tableid=0, s=150.1.1.4 (local), d=150.1.1.1
(FastEthernet0/0), routed via FIB
*May 12 19:49:29.067: IP: s=150.1.1.4 (local), d=150.1.1.1 (FastEthernet0/0), len 56,
sending
*May 12 19:49:29.067: ICMP type=3, code=1
*May 12 19:49:31.067: IP: s=150.1.1.1 (FastEthernet0/0), d=150.2.2.2, len 100,
unroutable
*May 12 19:49:31.067: ICMP type=8, code=0
*May 12 19:49:31.067: IP: tableid=0, s=150.1.1.4 (local), d=150.1.1.1
(FastEthernet0/0), routed via FIB
*May 12 19:49:31.071: IP: s=150.1.1.4 (local), d=150.1.1.1 (FastEthernet0/0), len 56,
sending
*May 12 19:49:31.071: ICMP type=3, code=1
*May 12 19:49:33.071: IP: s=150.1.1.1 (FastEthernet0/0), d=150.2.2.2, len 100,
unroutable
*May 12 19:49:33.071: ICMP type=8, code=0
*May 12 19:49:33.071: IP: tableid=0, s=150.1.1.4 (local), d=150.1.1.1
(FastEthernet0/0), routed via FIB
*May 12 19:49:33.075: IP: s=150.1.1.4 (local), d=150.1.1.1 (FastEthernet0/0), len 56,
sending
*May 12 19:49:33.075: ICMP type=3, code=1
```

[Truncated Output]

The difficulty level of this task is further increased because we are not allowed to configure any additional static routes or enable a dynamic routing protocol on R1, R3, and R4. Additionally, the task requirements stipulate that we cannot use PBR or a tunnel to complete this task. With such stringent requirements, we must think outside the box and consider other Cisco IOS software features. In essence, based on the debug output,

https://t.me/learningnets

we know that all we need is routing information on R4 pointing to R3 for the 150.2.2.0/24 and 150.3.3.0/24 prefixes. While we cannot use static routes or enable a dynamic routing protocol, there is NO stipulation against using ODR. This is because ODR is NOT a routing protocol, but rather a CDP extension. Therefore, to complete this task, simply configure R3 to advertise a default route via ODR to R1.

Because R1 will automatically advertise the 150.1.1.0/24 prefix, we need to filter from R3 so that this path is NOT used to forward traffic to the 150.1.1.0/24 prefix when the R1-R2 link is up. This task is completed by implementing the following configuration on R3:

R3(config)#**access-list 1 deny any**
R3(config)#**router odr**
R3(config-router)#**distribute-list 1 in**
R3(config-router)#**exit**

Following this configuration R3s routing table still shows only BGP routes:

R3#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.1.1.1 to network 0.0.0.0

10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.8 is directly connected, Serial1/1
C 10.0.0.12 is directly connected, Serial1/2
150.1.0.0/32 is subnetted, 1 subnets
S 150.1.1.1 is directly connected, Serial1/2
150.2.0.0/24 is subnetted, 1 subnets
B 150.2.2.0 [20/0] via 10.0.0.9, 00:01:17
150.3.0.0/24 is subnetted, 1 subnets
C 150.3.3.0 is directly connected, FastEthernet0/0
B* 0.0.0.0/0 [20/0] via 150.1.1.1, 00:01:17

The same is also applicable to R2s routing table which only shows BGP routes:

R2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP

https://t.me/learningnets

D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 10.0.0.10 to network 0.0.0.0

10.0.0.0/30 is subnetted, 1 subnets
C 10.0.0.8 is directly connected, Serial0/1
150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
B 150.3.3.0 [20/0] via 10.0.0.10, 04:42:47
B* 0.0.0.0/0 [20/0] via 10.0.0.10, 03:01:52

R4s routing table, however, now includes a default route received via ODR pointing to R3. This will allow R4 to forward packets sent from R1 destined to 150.2.2.0/24 and 150.3.3.0/24. There is no need to configure any static routes on R3 for R1s LAN IP address because a static route already exists and is pointing to R4. This is the static route used to establish the eBGP neighbor relationship with R1 that was configured earlier in this lab:

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 10.0.0.13 to network 0.0.0.0

10.0.0.0/30 is subnetted, 1 subnets
C 10.0.0.12 is directly connected, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
o* 0.0.0.0/0 [160/1] via 10.0.0.13, 00:00:44, Serial0/0

Following this change, R1 is now able to ping the 150.2.2.0/24 and 150.3.3.0/24 subnets:

https://t.me/learningnets

R1#**ping 150.2.2.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 28/30/32 ms

R1#**ping 150.3.3.3 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/18/20 ms

https://t.me/learningnets

Technet24

CCNP Lab 043: Border Gateway Protocol Lab

Lab Objective:

The focus of this lab is to understand BGP implementation and configuration in Cisco IOS routers. Additional technologies include summarization, route filtering and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology. Additionally, configure a Loopback 0 interface on all routers using the router number and a host mask. For example, on R1, configure Loopback 0 with the IP address 1.1.1.1/32, on R2 configure interface Loopback 0 with the IP address 2.2.2.2/32 and so

https://t.me/learningnets

Technet24

forth for R3 and also R4.

Task 2

Configure BGP as illustrated in the topology. Use the Loopback 0 addresses for peering. Do NOT configure any IGPs. Instead, use static routes only. R1 should peer with R2 and R4. R2 should peer with R1 and R3. R3 should peer with R2 and R4. R4 should peer with R1 and R3. On R3 and R4, ensure that packets are load balanced between the two WAN links. Do NOT configure PPP Multilink. Verify the configuration using the appropriate commands.

Task 3

Configure all routers to advertise their LAN subnet addresses via BGP. These should appear in the BGP RIBs of all other routers with an ORIGIN code of INCOMPLETE, by default. Verify the configuration using the appropriate commands.

Task 4

Configure BGP so that R4 prefers the path via R3 to reach any subnet. You are NOT allowed to implement any configuration on R4 itself. Verify your BGP configuration using the appropriate commands.

Task 5

Configure R4 so that it sends all updates to R3 with a MED of 4. Configure R2 so that it sends all updates to R3 with a MED of 2. Ensure that R3 prefers all routes with the better (lower) MED value. Do NOT modify any other BGP attributes or default administrative distance values when completing this task. Verify your configuration using the appropriate commands.

Task 6

Configure the following Loopback interfaces on R2:

Loopback 192: IP Address 192.1.1.1/24
Loopback 193: IP Address 193.1.1.1/24
Loopback 194: IP Address 194.1.1.1/24
Loopback 195: IP Address 195.1.1.1/24

The 192.1.1.1/24 subnet should appear to have originated in AS 192. The 193.1.1.1/24 subnet should appear to have originated in AS 193. The 194.1.1.1/24 subnet should appear to have originated in AS 194. And finally, the 195.1.1.1/24 subnet should appear to have originated in AS 195. These prefixes should be advertised using the **network** command. Verify your configuration using the appropriate commands.

Task 7

https://t.me/learningnets

Configure R1 so that it only accepts prefixes originated in AS 192, 193, 194 and 195 from R4. It should never have any entries in its BGP RIB for any prefixes originating in these ASs directly from R2. Use an AS_PATH filter. This should only have TWO lines. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IP addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

The most simple way to complete this task is to use BGP peer group configuration to minimize the number of commands that you need to specify. However, the task specifically states that peer groups should not be used. Additionally, in order to establish the BGP adjacencies using peer groups, you need to configure static routes on all routers because you are not allowed to enable an IGP of any kind. This task is completed as follows:

R1(config)#**ip route 2.2.2.2 255.255.255.255 serial 0/0**
R1(config)#**ip route 4.4.4.4 255.255.255.255 fastethernet 0/0 150.1.1.4**
R1(config)#**router bgp 1**
R1(config-router)#**neighbor 2.2.2.2 remote-as 2**
R1(config-router)#**neighbor 2.2.2.2 update-source loopback 0**
R1(config-router)#**neighbor 2.2.2.2 ebgp-multihop**
R1(config-router)#**neighbor 4.4.4.4 remote-as 4**
R1(config-router)#**neighbor 4.4.4.4 update-source loopback 0**
R1(config-router)#**neighbor 4.4.4.4 ebgp-multihop**
R1(config-router)#**exit**

R2(config)#**ip route 1.1.1.1 255.255.255.255 serial 0/0**
R2(config)#**ip route 3.3.3.3 255.255.255.255 serial 0/1**
R2(config)#**router bgp 2**
R2(config-router)#**neighbor 1.1.1.1 remote-as 1**
R2(config-router)#**neighbor 1.1.1.1 update-source loopback 0**
R2(config-router)#**neighbor 1.1.1.1 ebgp-multihop**
R2(config-router)#**neighbor 3.3.3.3 remote-as 3**
R2(config-router)#**neighbor 3.3.3.3 update-source loopback 0**
R2(config-router)#**neighbor 3.3.3.3 ebgp-multihop**
R2(config-router)#**exit**

R3(config)#**ip route 2.2.2.2 255.255.255.255 serial 1/1**

https://t.me/learningnets

Technet24

R3(config)#**ip route 4.4.4.4 255.255.255.255 serial 1/2**
R3(config)#**ip route 4.4.4.4 255.255.255.255 serial 1/3**
R3(config)#**router bgp 3**
R3(config-router)#**neighbor 2.2.2.2 remote-as 2**
R3(config-router)#**neighbor 2.2.2.2 update-source loopback 0**
R3(config-router)#**neighbor 2.2.2.2 ebgp-multihop**
R3(config-router)#**neighbor 4.4.4.4 remote-as 4**
R3(config-router)#**neighbor 4.4.4.4 update-source loopback 0**
R3(config-router)#**neighbor 4.4.4.4 ebgp-multihop**
R3(config-router)#**exit**

R4(config)#**ip route 1.1.1.1 255.255.255.255 fastethernet 0/0 150.1.1.1**
R4(config)#**ip route 3.3.3.3 255.255.255.255 serial 0/0**
R4(config)#**ip route 3.3.3.3 255.255.255.255 serial 0/1**
R4(config)#**router bgp 4**
R4(config-router)#**neighbor 1.1.1.1 remote-as 1**
R4(config-router)#**neighbor 1.1.1.1 update-source loopback 0**
R4(config-router)#**neighbor 1.1.1.1 ebgp-multihop**
R4(config-router)#**neighbor 3.3.3.3 remote-as 3**
R4(config-router)#**neighbor 3.3.3.3 update-source loopback 0**
R4(config-router)#**neighbor 3.3.3.3 ebgp-multihop**
R4(config-router)#**exit**

Verify your configuration using the **show ip bgp summary** command on all routers:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 1
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
2.2.2.2 4 2 11 12 1 0 0 00:08:30 0
4.4.4.4 4 4 5 5 1 0 0 00:01:30 0

R2#**show ip bgp summary**
BGP router identifier 2.2.2.2, local AS number 2
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
1.1.1.1 4 1 12 11 1 0 0 00:08:33 0
3.3.3.3 4 3 7 8 1 0 0 00:04:03 0

R3#**show ip bgp summary**
BGP router identifier 3.3.3.3, local AS number 3
BGP table version is 1, main routing table version 1

https://t.me/learningnets

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
2.2.2.2 4 2 8 7 1 0 0 00:04:06 0
4.4.4.4 4 4 4 4 1 0 0 00:00:57 0

R4#**show ip bgp summary**
BGP router identifier 4.4.4.4, local AS number 4
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
1.1.1.1 4 1 5 5 1 0 0 00:01:40 0
3.3.3.3 4 3 5 5 1 0 0 00:01:00 0

Task 3

In order to ensure that the ORIGIN code is INCOMPLETE, you need to redistribute the LAN subnets into BGP. However, you can also use the **network** statement in conjunction with a route map and set the ORIGIN code within the route map. Either option is acceptable when completing this task. This task is completed as follows when using the redistribution method:

R1(config)#**route-map CONNECTED permit 10**
R1(config-route-map)#**match interface fastethernet 0/0**
R1(config-route-map)#**exit**
R1(config)#**route-map CONNECTED deny 20**
R1(config-route-map)#**exit**
R1(config)#**router bgp 1**
R1(config-router)#**redistribute connected route-map CONNECTED**
R1(config-router)#**exit**

R2(config)#**route-map CONNECTED permit 10**
R2(config-route-map)#**match interface fastethernet 0/0**
R2(config-route-map)#**exit**
R2(config)#**route-map CONNECTED deny 20**
R2(config-route-map)#**exit**
R2(config)#**router bgp 2**
R2(config-router)#**redistribute connected route-map CONNECTED**
R2(config-router)#**exit**

R3(config)#**route-map CONNECTED permit 10**
R3(config-route-map)#**match interface fastethernet 0/0**
R3(config-route-map)#**exit**
R3(config)#**route-map CONNECTED deny 20**
R3(config-route-map)#**exit**

https://t.me/learningnets
Technet24

R3(config)#**router bgp 3**
R3(config-router)#**redistribute connected route-map CONNECTED**
R3(config-router)#**exit**

R4(config)#**route-map CONNECTED permit 10**
R4(config-route-map)#**match interface fastethernet 0/0**
R4(config-route-map)#**exit**
R4(config)#**route-map CONNECTED deny 20**
R4(config-route-map)#**exit**
R4(config)#**router bgp 4**
R4(config-router)#**redistribute connected route-map CONNECTED**
R4(config-router)#**exit**

You can verify the ORIGIN code by looking at the prefix entry in the BGP Tables. The ORIGIN code of INCOMPLETE is denoted by a question mark (?) in the output of the **show ip bgp** command. You can view additional detail on a per-prefix basis also when using this command.

R1#**show ip bgp**
BGP table version is 4, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 4.4.4.4 0 0 4 ?
*> 0.0.0.0 0 32768 ?
*> 150.2.2.0/24 2.2.2.2 0 0 2 ?
* 150.3.3.0/24 2.2.2.2 0 2 3 ?
*> 4.4.4.4 0 4 3 ?

R2#**show ip bgp**
BGP table version is 4, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 3.3.3.3 0 3 4 ?
*> 1.1.1.1 0 0 1 ?
*> 150.2.2.0/24 0.0.0.0 0 32768 ?
* 150.3.3.0/24 1.1.1.1 0 1 4 3 ?
*> 3.3.3.3 0 0 3 ?

https://t.me/learningnets

R3#**show ip bgp**
BGP table version is 5, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 4.4.4.4 0 0 4 ?
* 2.2.2.2 0 2 1 ?
* 150.2.2.0/24 4.4.4.4 0 4 1 2 ?
*> 2.2.2.2 0 0 2 ?
*> 150.3.3.0/24 0.0.0.0 0 32768 ?

R4#**show ip bgp**
BGP table version is 6, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 ?
* 1.1.1.1 0 0 1 ?
* 150.2.2.0/24 3.3.3.3 0 3 2 ?
*> 1.1.1.1 0 1 2 ?
*> 150.3.3.0/24 3.3.3.3 0 0 3 ?

Task 4

This task requires a little thought. Because we cannot implement any configuration on R4 itself, we have to think outside the box. The current BGP RIB on R4 shows the following entries:

R4#**show ip bgp**
BGP table version is 6, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 0.0.0.0 0 32768 ?
* 1.1.1.1 0 0 1 ?
* 150.2.2.0/24 3.3.3.3 0 3 2 ?
***> 1.1.1.1 0 1 2 ?**

https://t.me/learningnets

Technet24

***> 150.3.3.0/24 3.3.3.3 0 0 3 ?**

In the output above, the path via R3 is preferred for the 150.3.3.0/24 prefix; however, the router prefers the path via R1 for the 150.2.2.0/24 prefix because, all else being equal, it is the router with the lower IP address. To influence path selection in this case, we need to configure BGP on R1 to advertise all prefixes with a longer AS_PATH. The MED will not work because this attribute is not, by default, considered when prefixes are received from multiple ASes. This task is completed by configuring R1 as follows:

R1(config)#**route-map PREPEND permit 10**
R1(config-route-map)#**set as-path prepend 1 1 1 1**
R1(config-route-map)#**exit**
R1(config)#**router bgp 1**
R1(config-router)#**neighbor 4.4.4.4 route-map PREPEND out**
R1(config-router)#**exit**

Following this configuration, the BGP Table on R4 shows the following:

R4#**show ip bgp**
BGP table version is 14, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 1.1.1.1 0 0 1 1 1 1 1 ?
*> 0.0.0.0 0 32768 ?
***> 150.2.2.0/24 3.3.3.3 0 3 2 ?**
* 1.1.1.1 0 1 1 1 1 1 2 ?
***> 150.3.3.0/24 3.3.3.3 0 0 3 ?**
* 1.1.1.1 0 1 1 1 1 1 2 3 ?

Task 5

The requirements for this task are two-fold. The first requirement is that R4 and R2 advertise all prefixes to R3 with a MED of 4 and 2, respectively. This is completed using an outbound route map on these two routers. Before any BGP configuration changes, the BGP RIB on R3 shows the following route entries:

R3#**show ip bgp**
BGP table version is 11, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

https://t.me/learningnets

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 4.4.4.4 0 0 4 ?
* 2.2.2.2 0 2 1 ?
*> 150.2.2.0/24 2.2.2.2 0 0 2 ?
*> 150.3.3.0/24 0.0.0.0 0 32768 ?

The first part of this task is completed as follows:

R4(config)#**route-map MED permit 10**
R4(config-route-map)#**set metric 4**
R4(config-route-map)#**exit**
R4(config)#**router bgp 4**
R4(config-router)#**neighbor 3.3.3.3 route-map MED out**
R4(config-router)#**exit**

R2(config)#**route-map MED permit 10**
R2(config-route-map)#**set metric 2**
R2(config-route-map)#**exit**
R2(config)#**router bgp 2**
R2(config-router)#**neighbor 3.3.3.3 route-map MED out**
R2(config-router)#**exit**

Following these changes, the BGP RIB on R3 shows the following:

R3#**show ip bgp**
BGP table version is 13, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.1.1.0/24 4.4.4.4 4 0 4 ?
* 2.2.2.2 2 0 2 1 ?
*> 150.2.2.0/24 2.2.2.2 2 0 2 ?
*> 150.3.3.0/24 0.0.0.0 0 32768 ?

The second part of this task has two caveats. The first is that the MED attribute should be used in the path selection process. The issue here is that, by default, the MED is only compared for path received from the same AS. In order to allow BGP to compare MED values from prefixes received from multiple ASes, this default behavior needs to be modified. The second caveat is that the MED is compared AFTER the AS_PATH. This means that, for example, BGP will select the path via R4 as the best path to the 150.1.1.0/24 prefix because of the shorter AS_PATH length. Again, this default behavior has to be modified to complete this task. The second part of this task is

https://t.me/learningnets
Technet24

therefore completed as follows:

R3(config)#**router bgp 3**
R3(config-router)#**bgp bestpath as-path ignore**
R3(config-router)#**bgp always-compare-med**
R3(config-router)#**exit**

Following this configuration, the BGP Table on R3 now shows the following:

R3#**show ip bgp**
BGP table version is 14, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 4.4.4.4 4 0 4 ?
***> 2.2.2.2 2 0 2 1 ?**
***> 150.2.2.0/24 2.2.2.2 2 0 2 ?**
*> 150.3.3.0/24 0.0.0.0 0 32768 ?

A more detailed look reveals that the path with the longer AS_PATH sequence, but LOWER metric (MED) value is now preferred because of the configuration implemented on R3:

R3#**show ip bgp 150.1.1.0 255.255.255.0**
BGP routing table entry for 150.1.1.0/24, version 14
Paths: (2 available, best #2, table Default-IP-Routing-Table)
Flag: 0x820
Advertised to update-groups:
1
4
4.4.4.4 from 4.4.4.4 (4.4.4.4)
Origin incomplete, metric 4, localpref 100, valid, external
2 1
2.2.2.2 from 2.2.2.2 (2.2.2.2)
Origin incomplete, metric 2, localpref 100, valid, external, best

Task 6

While seemingly difficult, this task is very straightforward and requires the use of AS_PATH prepending when advertising these prefixes via BGP on R2. This is completed as follows:

R2(config)#**interface loopback 192**

https://t.me/learningnets

R2(config-if)#**ip address 192.1.1.1 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface loopback 193**
R2(config-if)#**ip address 193.1.1.1 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface loopback 194**
R2(config-if)#**ip address 194.1.1.1 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface loopback 195**
R2(config-if)#**ip address 195.1.1.1 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**ip prefix-list LOOPBACK192 seq 5 permit 192.1.1.0/24**
R2(config)#**ip prefix-list LOOPBACK193 seq 5 permit 193.1.1.0/24**
R2(config)#**ip prefix-list LOOPBACK194 seq 5 permit 194.1.1.0/24**
R2(config)#**ip prefix-list LOOPBACK195 seq 5 permit 195.1.1.0/24**
R2(config)#**route-map PREPEND permit 10**
R2(config-route-map)#**match ip address prefix-list LOOPBACK192**
R2(config-route-map)#**set as-path prepend 192**
R2(config-route-map)#**exit**
R2(config)#**route-map PREPEND permit 20**
R2(config-route-map)#**match ip address prefix-list LOOPBACK193**
R2(config-route-map)#**set as-path prepend 193**
R2(config-route-map)#**exit**
R2(config)#**route-map PREPEND permit 30**
R2(config-route-map)#**match ip address prefix-list LOOPBACK194**
R2(config-route-map)#**set as-path prepend 194**
R2(config-route-map)#**exit**
R2(config)#**route-map PREPEND permit 40**
R2(config-route-map)#**match ip address prefix-list LOOPBACK195**
R2(config-route-map)#**set as-path prepend 195**
R2(config-route-map)#**exit**
R2(config)#**route-map PREPEND permit 50**
R2(config-route-map)#**exit**
R2(config)#**router bgp 2**
R2(config-router)#**network 192.1.1.0**
R2(config-router)#**network 193.1.1.0**
R2(config-router)#**network 194.1.1.0**
R2(config-router)#**network 195.1.1.0**

https://t.me/learningnets

R2(config-router)#**neighbor 1.1.1.1 route-map PREPEND out**
R2(config-router)#**neighbor 3.3.3.3 route-map PREPEND out**
R2(config-router)#**exit**

Following this configuration, verify the BGP RIB entries for these prefixes are correct:

R1#**show ip bgp**
BGP table version is 29, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 4.4.4.4 0 0 4 ?
*> 0.0.0.0 0 32768 ?
* 150.2.2.0/24 4.4.4.4 0 4 3 2 ?
*> 2.2.2.2 0 0 2 ?
* 150.3.3.0/24 4.4.4.4 0 4 3 ?
*> 2.2.2.2 0 2 3 ?
*** 192.1.1.0 4.4.4.4 0 4 3 2 192 i**
***> 2.2.2.2 0 0 2 192 i**
*** 193.1.1.0 4.4.4.4 0 4 3 2 193 i**
***> 2.2.2.2 0 0 2 193 i**
*** 194.1.1.0 4.4.4.4 0 4 3 2 194 i**
***> 2.2.2.2 0 0 2 194 i**
*** 195.1.1.0 4.4.4.4 0 4 3 2 195 i**
***> 2.2.2.2 0 0 2 195 i**

R3#**show ip bgp**
BGP table version is 44, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 4.4.4.4 4 0 4 ?
*> 2.2.2.2 0 2 1 ?
*> 150.2.2.0/24 2.2.2.2 0 0 2 ?
*> 150.3.3.0/24 0.0.0.0 0 32768 ?
***> 192.1.1.0 2.2.2.2 0 0 2 192 i**
***> 193.1.1.0 2.2.2.2 0 0 2 193 i**
***> 194.1.1.0 2.2.2.2 0 0 2 194 i**

https://t.me/learningnets

***> 195.1.1.0 2.2.2.2 0 0 2 195 i**

R4#**show ip bgp**
BGP table version is 38, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 3.3.3.3 0 3 2 1 ?
* 1.1.1.1 0 0 1 1 1 1 1 ?
*> 0.0.0.0 0 32768 ?
*> 150.2.2.0/24 3.3.3.3 0 3 2 ?
* 1.1.1.1 0 1 1 1 1 1 2 ?
*> 150.3.3.0/24 3.3.3.3 0 0 3 ?
* 1.1.1.1 0 1 1 1 1 1 2 3 ?
***> 192.1.1.0 3.3.3.3 0 3 2 192 i**
*** 1.1.1.1 0 1 1 1 1 1 2 192 i**
***> 193.1.1.0 3.3.3.3 0 3 2 193 i**
*** 1.1.1.1 0 1 1 1 1 1 2 193 i**
***> 194.1.1.0 3.3.3.3 0 3 2 194 i**
*** 1.1.1.1 0 1 1 1 1 1 2 194 i**
***> 195.1.1.0 3.3.3.3 0 3 2 195 i**
*** 1.1.1.1 0 1 1 1 1 1 2 195 i**

Task 7

To complete this task, we need to use a two-line AS_PATH filter. Prior to any configuration changes, the BGP Table on R1 shows the following entries:

R1#**show ip bgp**
BGP table version is 29, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 4.4.4.4 0 0 4 ?
*> 0.0.0.0 0 32768 ?
* 150.2.2.0/24 4.4.4.4 0 4 3 2 ?
*> 2.2.2.2 0 0 2 ?
* 150.3.3.0/24 4.4.4.4 0 4 3 ?
*> 2.2.2.2 0 2 3 ?

https://t.me/learningnets

Technet24

*** 192.1.1.0 4.4.4.4 0 4 3 2 192 i**
***> 2.2.2.2 0 0 2 192 i**
*** 193.1.1.0 4.4.4.4 0 4 3 2 193 i**
***> 2.2.2.2 0 0 2 193 i**
*** 194.1.1.0 4.4.4.4 0 4 3 2 194 i**
***> 2.2.2.2 0 0 2 194 i**
*** 195.1.1.0 4.4.4.4 0 4 3 2 195 i**
***> 2.2.2.2 0 0 2 195 i**

To complete this task, you need to have a good understanding of basic regular expressions and how they are configured. A regular expression comprises four main parts. These four main parts, which are described in the following sections, are:

- A Range
- An Atom
- A Piece
- A Branch

A range is a sequence of characters within left and right square brackets. Examples of ranges are [abcd] or [1-9] or [0,4-7]. An atom is a single character. A Piece or Multiplier is a symbol that follows an Atom. Examples include the plus sign (+) and the question mark (?).branch is 0 or more concatenated pieces, i.e. 0 or more pieces used together in a regular expression, for example ^[0-9]+ [0-9]+?$. Before configuring and then applying AS_PATH filters, you should always use the **show ip bgp regexp <regular expression>** command to ensure that you are matching the desired routes. For example, prior to R1s configuration change, this command, used with the appropriate regular expression, confirms that the AS_PATH filter will match the desired prefixes:

R1#**show ip bgp regexp _19[2-5]$**
BGP table version is 29, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 192.1.1.0 4.4.4.4 0 4 3 2 192 i
*> 2.2.2.2 0 0 2 192 i
* 193.1.1.0 4.4.4.4 0 4 3 2 193 i
*> 2.2.2.2 0 0 2 193 i
* 194.1.1.0 4.4.4.4 0 4 3 2 194 i
*> 2.2.2.2 0 0 2 194 i

https://t.me/learningnets

* 195.1.1.0 4.4.4.4 0 4 3 2 195 i
*> 2.2.2.2 0 0 2 195 i

To complete this task, implement the following configuration on R1:

R1(config)#**ip as-path access-list 1 deny _19[2-5]$**
R1(config)#**ip as-path access-list 1 permit .***
R1(config)#**router bgp 1**
R1(config-router)#**neighbor 2.2.2.2 filter-list 1 in**
R1(config-router)#**exit**

Following this change, the BGP Table on R1 shows the following entries:

R1#**show ip bgp**
BGP table version is 33, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* 150.1.1.0/24 4.4.4.4 0 0 4 ?
*> 0.0.0.0 0 32768 ?
* 150.2.2.0/24 4.4.4.4 0 4 3 2 ?
*> 2.2.2.2 0 0 2 ?
* 150.3.3.0/24 4.4.4.4 0 4 3 ?
*> 2.2.2.2 0 2 3 ?
***> 192.1.1.0 4.4.4.4 0 4 3 2 192 i**
***> 193.1.1.0 4.4.4.4 0 4 3 2 193 i**
***> 194.1.1.0 4.4.4.4 0 4 3 2 194 i**
***> 195.1.1.0 4.4.4.4 0 4 3 2 195 i**

NOTE: You can also complete this task by matching the configured AS_PATH ACL in a route map and applying that inbound. Either solution is acceptable.

https://t.me/learningnets

Technet24

CCNP Lab 044: IPv6 RIPng Lab

Lab Objective:

The focus of this lab is to understand RIPng implementation and configuration in Cisco IOS routers. Additional technologies include stateless auto-configuration and summarization.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IPv6 addressing on all routers as illustrated in the network topology. Do NOT configure an IPv6 address on R4s FastEthernet 0/0 interface.

Task 2

https://t.me/learningnets

Technet24

Configure R4 so that it uses stateless auto-configuration to dynamically provision its address. Ensure that this router also has a default route in its routing table. Verify your configuration.

Task 3

Configure RIPng on R1, R2, and R3. RIPng messages should be exchanged using UDP port 520.
Do NOT enable RIPng for the LAN subnet connected to R1. Next configure your network so that R2 is able to reach R4; however, R3 should NOT be able to reach R4. You are NOT allowed to use redistribution, any types of route filters on any router in the network, or static routes. Verify your configuration using the appropriate commands.

Task 4

Configure the following Loopback interfaces on R3 and redistribute them via RIPng:

- Loopback 1: IPv6 address 2002:abcd:1234:a::4/128
- Loopback 2: IPv6 address 2002:abcd:1234:b::4/128
- Loopback 3: IPv6 address 2002:abcd:1234:c::4/128
- Loopback 4: IPv6 address 2002:abcd:1234:d::4/128
- Loopback 5: IPv6 address 2002:abcd:1234:e::4/128

Next, configure RIPng to advertise a SINGLE route for these 5 Loopback interfaces. Ensure that this single route is advertised to R1 and R2 and the specific prefixes are suppressed. Verify your configuration using the appropriate commands as well as standard or extended pings.

Task 5

Configure RIPng so that all routes that R2 receives from R3 have a route metric of 10. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**ipv6 unicast-routing**
R1(config)#**ipv6 cef**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ipv6 address 3ffe:abcd:1111:1::1/64**
R1(config-if)#**no shutdown**
R1(config-if)#**exit**

https://t.me/learningnets

```
R1(config)#interface serial 0/0
R1(config-if)#ipv6 address 2001:abcd:1111:1::1/64
R1(config-if)#clock rate 2000000
R1(config-if)#no shutdown
R1(config-if)#exit
Router(config)#hostname R2
R2(config)#ipv6 unicast-routing
R2(config)#ipv6 cef
R2(config)#interface fastethernet 0/0
R2(config-if)#ipv6 address 3ffe:abcd:1111:2::2/64
R2(config-if)#no shutdown
R2(config)#interface serial 0/0
R2(config-if)#ipv6 address 2001:abcd:1111:1::2/64
R2(config-if)#no shutdown
R2(config-if)#exit
R2(config)#interface serial 0/1
R2(config-if)#ipv6 address 2001:abcd:1111:3::2/64
R2(config-if)#no shutdown
R2(config-if)#exit
Router(config)#hostname R3
R3(config)#ipv6 unicast-routing
R3(config)#ipv6 cef
R3(config)#interface fastethernet 0/0
R3(config-if)#ipv6 address 3ffe:abcd:1111:3::3/64
R3(config-if)#no shutdown
R3(config-if)#exit
R3(config)#interface serial 1/1
R3(config-if)#ipv6 address 2001:abcd:1111:3::3/64
R3(config-if)#clock rate 128000
R3(config-if)#no shutdown
R3(config-if)#exit
Router(config)#hostname R4
R4(config)#ipv6 unicast-routing
R4(config)#ipv6 cef
```

Task 2

To complete this task, append the **default** keyword to the **ipv6 address autoconfig** interface configuration command. If the **default** keyword is omitted, a default route will

https://t.me/learningnets

Technet24

not be installed into the local routers IPv6 RIB. This task is completed as follows:

```
R4(config)#interface fastethernet 0/0
R4(config-if)#no shutdown
R4(config-if)#ipv6 address autoconfig default
R4(config-if)#exit
```

Verify stateless auto-configuration using the **show ipv6 interface** command:

```
R4#show ipv6 interface fastethernet 0/0
FastEthernet0/0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::20F:23FF:FE5E:F120
Global unicast address(es):
3FFE:ABCD:1111:1:20F:23FF:FE5E:F120, subnet is 3FFE:ABCD:1111:1::/64 [PRE]
valid lifetime 2591989 preferred lifetime 604789
Joined group address(es):
FF02::1
FF02::2
FF02::1:FF5E:F120
MTU is 1500 bytes
ICMP error messages limited to one every 100 milliseconds
ICMP redirects are enabled
ND DAD is enabled, number of DAD attempts: 1
ND reachable time is 30000 milliseconds
ND advertised reachable time is 0 milliseconds
ND advertised retransmit interval is 0 milliseconds
ND router advertisements are sent every 200 seconds
ND router advertisements live for 1800 seconds
Hosts use stateless autoconfig for addresses.
```

Verify that the default route has been installed using the **show ipv6 route** command. This will point to the Link-Local address of R1, rather than the global Unicast address:

```
R4#show ipv6 route
IPv6 Routing Table - 5 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
S ::/0 [1/0]
via FE80::20F:23FF:FE5E:EC80, FastEthernet0/0
```

https://t.me/learningnets

C 3FFE:ABCD:1111:1::/64 [0/0]
via ::, FastEthernet0/0
L 3FFE:ABCD:1111:1:20F:23FF:FE5E:F120/128 [0/0]
via ::, FastEthernet0/0
L FE80::/10 [0/0]
via ::, Null0
L FF00::/8 [0/0]
via ::, Null0

Task 3

The requirements for this task are two-fold. The first requirement is to configure RIPng as stated in the requirements. This is a straightforward task; however, because the task requires RIPng to use UDP port 520 instead of the default port 521, some additional configuration is required. The first part of this task is completed as follows:

R1(config)#**ipv6 router rip CCNP**
R1(config-rtr)#**port 520 multicast-group ff02::9**
R1(config-rtr)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ipv6 rip CCNP enable**
R1(config-if)#**exit**

R2(config)#**ipv6 router rip CCNP**
R2(config-rtr)#**port 520 multicast-group ff02::9**
R2(config-rtr)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ipv6 rip CCNP enable**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**ipv6 rip CCNP enable**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ipv6 rip CCNP enable**
R2(config-if)#**exit**

R3(config)#**ipv6 router rip CCNP**
R3(config-rtr)#**port 520 multicast-group ff02::9**
R3(config-rtr)#**exit**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ipv6 rip CCNP enable**
R3(config-if)#**exit**

https://t.me/learningnets
Technet24

R3(config)#**interface serial 1/1**
R3(config-if)#**ipv6 rip CCNP enable**
R3(config-if)#**exit**

Verify your configuration using the **show ipv6 route** command:

R1#**show ipv6 route rip**
IPv6 Routing Table - 9 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R 2001:ABCD:1111:3::/64 [120/2]
via FE80::20D:28FF:FE9E:F940, Serial0/0
R 3FFE:ABCD:1111:2::/64 [120/2]
via FE80::20D:28FF:FE9E:F940, Serial0/0
R 3FFE:ABCD:1111:3::/64 [120/3]
via FE80::20D:28FF:FE9E:F940, Serial0/0

R2#**show ipv6 route rip**
IPv6 Routing Table - 8 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R 3FFE:ABCD:1111:3::/64 [120/2]
via FE80::213:7FFF:FEAF:3E00, Serial0/1

R3#**show ipv6 route rip**
IPv6 Routing Table - 7 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R 2001:ABCD:1111:1::/64 [120/2]
via FE80::20D:28FF:FE9E:F940, Serial1/1
R 3FFE:ABCD:1111:2::/64 [120/2]
via FE80::20D:28FF:FE9E:F940, Serial1/1

https://t.me/learningnets

The second part of this task requires that R2 and R3 be able to ping R4 and vice-versa without enabling RIPng on the R1-R4 LAN segment. To do so, you need to advertise a default route from R1; however, to ensure that this is not advertised to R4, you need to set a metric of 14 for this route. This means that when R2 receives it, the metric will be 15, which is the maximum allowed metric for RIP. If advertised to R3, this route will have a metric of 16 - which is unreachable for RIP - and will therefore not be installed into the routing table. The second part of this task is completed as follows:

R1(config)#**interface serial 0/0**
R1(config-if)#**ipv6 rip CCNP default-information originate metric 14**
R1(config-if)#**exit**

Verify your configuration by looking at the routings of R2 and R3:

R2#**show ipv6 route rip**
IPv6 Routing Table - 9 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R ::/0 [120/15]
via FE80::20F:23FF:FE5E:EC80, Serial0/0
R 3FFE:ABCD:1111:3::/64 [120/2]
via FE80::213:7FFF:FEAF:3E00, Serial0/1

R3#**show ipv6 route rip**
IPv6 Routing Table - 7 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R 2001:ABCD:1111:1::/64 [120/2]
via FE80::20D:28FF:FE9E:F940, Serial1/1
R 3FFE:ABCD:1111:2::/64 [120/2]
via FE80::20D:28FF:FE9E:F940, Serial1/1

Finally, verify that R2 and R4 can reach each other using a standard or extended ping:

R2#**show ipv6 route 3FFE:ABCD:1111:1:20F:23FF:FE5E:F120**
IPv6 Routing Table - 9 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP

https://t.me/learningnets
Technet24

U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R ::/0 [120/15]
via FE80::20F:23FF:FE5E:EC80, Serial0/0

R2#**ping 3FFE:ABCD:1111:1:20F:23FF:FE5E:F120 source fastethernet 0/0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 3FFE:ABCD:1111:1:20F:23FF:FE5E:F120, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:2::2
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 0/1/4 ms

Task 4

The requirements of this task are two-fold. The first requirement is that you configure Loopback interfaces on R3 and advertise them via RIPng. This is completed as follows:

R3(config)#**interface loopback 1**
R3(config-if)#**ipv6 address 2002:abcd:1234:a::4/128**
R3(config-if)#**exit**
R3(config)#**interface loopback 2**
R3(config-if)#**ipv6 address 2002:abcd:1234:b::4/128**
R3(config-if)#**exit**
R3(config)#**interface loopback 3**
R3(config-if)#**ipv6 address 2002:abcd:1234:c::4/128**
R3(config-if)#**exit**
R3(config)#**interface loopback 4**
R3(config-if)#**ipv6 address 2002:abcd:1234:d::4/128**
R3(config-if)#**exit**
R3(config)#**interface loopback 5**
R3(config-if)#**ipv6 address 2002:abcd:1234:e::4/128**
R3(config-if)#**exit**
R3(config)#**ipv6 router rip CCNP**
R3(config-rtr)#**redistribute connected**
R3(config-rtr)#**exit**

Verify your configuration by checking the routing tables on R2 and R1:

R1#**show ipv6 route rip | include 2002**

https://t.me/learningnets

R 2002:ABCD:1234:A::4/128 [120/3]
R 2002:ABCD:1234:B::4/128 [120/3]
R 2002:ABCD:1234:C::4/128 [120/3]
R 2002:ABCD:1234:D::4/128 [120/3]
R 2002:ABCD:1234:E::4/128 [120/3]

R2#**show ipv6 route rip | include 2002**
R 2002:ABCD:1234:A::4/128 [120/2]
R 2002:ABCD:1234:B::4/128 [120/2]
R 2002:ABCD:1234:C::4/128 [120/2]
R 2002:ABCD:1234:D::4/128 [120/2]
R 2002:ABCD:1234:E::4/128 [120/2]

The second part of this task requires route summarization, i.e. summarizing the 5 Loopback interface addresses and advertise only a single route using RIPng. IPv6 summarization is not as complex as one would think. It is also performed in a manner similar to IPv4 route summarization. First, identify and locate the first different 16-bit field. In our example, it is the fourth field, which contains the values a, b, c, d, and e. Next, convert these values to binary as illustrated in the following table:

Hexadecimal Value
Binary Representation
Matching Bit Values
A
0000 0000 0000 1010
0000 0000 0000 1
B
0000 0000 0000 1011
0000 0000 0000 1
C
0000 0000 0000 1100
0000 0000 0000 1
D
0000 0000 0000 1101
0000 0000 0000 1
E
0000 0000 0000 1110
0000 0000 0000 1

Referencing the table above, the first thirteen bits match. To complete the address, we simply input zeros for the non-matching bits, resulting in the Binary address: 0000 0000

https://t.me/learningnets
Technet24

0000 1000. In Hexadecimal, the same address would be written as 8.

Next, we need to calculate the mask. This is simple and entails just counting the number of matching bits in the address, which would be 61. This task is completed as follows:

```
R3(config)#interface serial 1/1
R3(config-if)#ipv6 rip CCNP summary-address 2002:abcd:1234:8::/61
R3(config-if)#exit
```

Verify your configuration by checking the routing tables on R2 and R1:

```
R1#show ipv6 route rip | include 2002
R 2002:ABCD:1234:8::/61 [120/3]
```

```
R2#show ipv6 route rip | include 2002
R 2002:ABCD:1234:8::/61 [120/2]
```

Verify your configuration using a simple ping from R1 and R2:

```
R1#ping 2002:ABCD:1234:A::4 repeat 10

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:ABCD:1234:A::4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/22/76 ms
```

```
R1#ping 2002:ABCD:1234:B::4 repeat 10

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:ABCD:1234:B::4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms
```

```
R1#ping 2002:ABCD:1234:C::4 repeat 10

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:ABCD:1234:C::4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms
```

```
R1#ping 2002:ABCD:1234:D::4 repeat 10

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:ABCD:1234:D::4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms
```

```
R1#ping 2002:ABCD:1234:E::4 repeat 10

Type escape sequence to abort.
```

https://t.me/learningnets

Sending 10, 100-byte ICMP Echos to 2002:ABCD:1234:E::4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R2#**ping 2002:ABCD:1234:A::4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:ABCD:1234:A::4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R2#**ping 2002:ABCD:1234:B::4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:ABCD:1234:B::4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/22/76 ms

R2#**ping 2002:ABCD:1234:C::4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:ABCD:1234:C::4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/14/16 ms

R2#**ping 2002:ABCD:1234:D::4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:ABCD:1234:D::4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/16 ms

R2#**ping 2002:ABCD:1234:E::4 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:ABCD:1234:E::4, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/14/16 ms

Task 5

This last task requires RIPng metric offsetting. With RIPng, this functionality is performed on a per-interface basis and can be performed in the inbound direction only. Prior to any changes, R2s routing table shows the following entries:

R2#**show ipv6 route rip**
IPv6 Routing Table - 10 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP

https://t.me/learningnets

Technet24

U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R ::/0 [120/15]
via FE80::20F:23FF:FE5E:EC80, Serial0/0
R 2002:ABCD:1234:8::/61 [120/2]
via FE80::213:7FFF:FEAF:3E00, Serial0/1
R 3FFE:ABCD:1111:3::/64 [120/2]
via FE80::213:7FFF:FEAF:3E00, Serial0/1

To ensure that the routes are received on R2 with a route-metric of 10, you have to offset the metric on R2s Serial 0/1 interface by a value of 9. This task is completed as follows:

R2(config)#**interface serial 0/1**
R2(config-if)#**ipv6 rip CCNP metric-offset 9**
R2(config-if)#**exit**

Following this configuration, the same prefixes on R2 now show a route metric of 10:

R2#**show ipv6 route rip**
IPv6 Routing Table - 11 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R ::/0 [120/15]
via FE80::20F:23FF:FE5E:EC80, Serial0/0
R 2002:ABCD:1234:8::/61 [120/10]
via FE80::213:7FFF:FEAF:3E00, Serial0/1
R 3FFE:ABCD:1111:3::/64 [120/10]
via FE80::213:7FFF:FEAF:3E00, Serial0/1

https://t.me/learningnets

CCNP Lab 045: IPv6 RIPng and OSPFv3 Lab

Lab Objective:

The focus of this lab is to understand OSPFv3 and RIPng implementation and configuration in Cisco IOS routers. Additional technologies include redistribution, path control, and security.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IPv6 addressing on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Configure RIPng on the LAN segment between R1 and R4.

Task 3

Configure OSPFv3 as illustrated in the topology. Area 1 should be configured as a totally stub OSPF area, wherein R2 generates and advertises a default route to R3. Ensure that OSPF area 2 is still connected to the backbone. Ensure that no Hellos are sent out the LAN interfaces. Verify your configuration using the appropriate commands.

Task 4

Configure redistribution on routers R1 and R4.Use the most simple solution that negates the need to filter routes when redistributing. Verify your configuration using the appropriate commands.

Task 5

Configure R4 so that it prefers the path via R1 to reach all other subnets. In the event that this path is unavailable, the path via R3 should be used instead. Verify the configuration using the appropriate commands on R4.

Task 6

For security, configure area authentication for the OSPF backbone. Use the following parameters when you are configuring the authentication parameters:

- Use a Security Parameters Index (SPI) of 678
- Use Message Digest 5 (MD5) authentication
- Use a key of 1234567890abcdef1234567890abcdef

Verify your configuration using the appropriate commands.

Task 7

For security, configure interface authentication on the OSPF interfaces residing in area 2. Use the following parameters when you are configuring the

- Use a Security Parameters Index (SPI) of 500
- Use Message Digest 5 (MD5) authentication
- Use a key of 1234567890abcdef1234567890abcdef

Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

https://t.me/learningnets

Technet24

Router(config)#**hostname R1**
R1(config)#**ipv6 unicast-routing**
R1(config)#**ipv6 cef**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ipv6 address 3ffe:abcd:1111:1::1/64**
R1(config-if)#**no shutdown**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ipv6 address 2001:abcd:1111:1::1/64**
R1(config-if)#**clock rate 2000000**
R1(config-if)#**no shutdown**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**ipv6 unicast-routing**
R2(config)#**ipv6 cef**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ipv6 address 3ffe:abcd:1111:2::2/64**
R2(config-if)#**no shutdown**
R2(config)#**interface serial 0/0**
R2(config-if)#**ipv6 address 2001:abcd:1111:1::2/64**
R2(config-if)#**no shutdown**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ipv6 address 2001:abcd:1111:3::2/64**
R2(config-if)#**no shutdown**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**ipv6 unicast-routing**
R3(config)#**ipv6 cef**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ipv6 address 3ffe:abcd:1111:3::3/64**
R3(config-if)#**no shutdown**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ipv6 address 2001:abcd:1111:3::3/64**
R3(config-if)#**clock rate 128000**
R3(config-if)#**no shutdown**
R3(config-if)#**exit**

https://t.me/learningnets

R3(config)#**interface serial 1/2**
R3(config-if)#**ipv6 address 2001:abcd:1111:4::3/64**
R3(config-if)#**clock rate 128000**
R3(config-if)#**no shutdown**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**ipv6 unicast-routing**
R4(config)#**ipv6 cef**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ipv6 address 3ffe:abcd:1111:1::4/64**
R4(config-if)#**no shutdown**
R4(config)#**interface serial 0/0**
R4(config-if)#**ipv6 address 2001:abcd:1111:4::4/64**
R4(config-if)#**no shutdown**
R4(config-if)#**exit**

Task 2

R1(config)#**ipv6 router rip CCNP**
R1(config-rtr)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ipv6 rip CCNP enable**
R1(config-if)#**exit**

R4(config)#**ipv6 router rip CCNP**
R4(config-rtr)#**exit**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ipv6 rip CCNP enable**
R4(config-if)#**exit**

Verify your configuration using the **show ipv6 rip <tag> database** command:

R1#**show ipv6 rip CCNP database**
RIP process "CCNP", local RIB
3FFE:ABCD:1111:1::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:F120, expires in 157 secs

R4#**show ipv6 rip CCNP database**
RIP process "CCNP", local RIB
3FFE:ABCD:1111:1::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:EC80, expires in 167 secs

Task 3

https://t.me/learningnets

Technet24

The basic OSPF requirements are simple. However, to ensure that area 2 is connected to area 0 we need to configure a GRE Tunnel, since a virtual link cannot be established across a stub area. The encapsulation for this tunnel should be **gre ipv6** because IPv6 will be the transport protocol. If you specify **gre**, the configuration will not work, because IPv4 is not the transport protocol. This task is completed as follows:

R1(config)#**ipv6 router ospf 1**
R1(config-rtr)#**router-id 1.1.1.1**
R1(config-rtr)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ipv6 ospf 1 area 0**
R1(config-if)#**exit**

R2(config)#**ipv6 router ospf 2**
R2(config-rtr)#**router-id 2.2.2.2**
R2(config-rtr)#**passive-interface fastethernet 0/0**
R2(config-rtr)#**area 1 stub no-summary**
R2(config-rtr)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ipv6 ospf 2 area 0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**ipv6 ospf 2 area 0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ipv6 ospf 2 area 1**
R2(config-if)#**exit**
R2(config)#**interface tunnel 0**
R2(config-if)#**tunnel source serial 0/1**
R2(config-if)#**tunnel destination 2001:abcd:1111:3::3**
R2(config-if)#**tunnel mode gre ipv6**
R2(config-if)#**ipv6 address 2001:abcd:1111:8::2/64**
R2(config-if)#**ipv6 ospf 2 area 0**
R2(config-if)#**exit**

R3(config)#**ipv6 router ospf 3**
R3(config-rtr)#**router-id 3.3.3.3**
R3(config-rtr)#**area 1 stub**
R3(config-rtr)#**passive-interface fastethernet 0/0**
R3(config-rtr)#**exit**
R3(config)#**interface serial 1/1**

https://t.me/learningnets

R3(config-if)#**ipv6 ospf 3 area 1**
R3(config-if)#**exit**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ipv6 ospf 3 area 2**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ipv6 ospf 3 area 2**
R3(config-if)#**exit**
R3(config)#**interface tunnel 0**
R3(config-if)#**tunnel source serial 1/1**
R3(config-if)#**tunnel destination 2001:abcd:1111:3::2**
R3(config-if)#**tunnel mode gre ipv6**
R3(config-if)#**ipv6 address 2001:abcd:1111:8::3/64**
R3(config-if)#**ipv6 ospf 3 area 0**
R3(config-if)#**exit**

R4(config)#**ipv6 router ospf 4**
R4(config-rtr)#**router-id 4.4.4.4**
R4(config-rtr)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ipv6 ospf 4 area 2**
R4(config-if)#**exit**

Verify your OSPF configuration using the **show ipv6 ospf neighbor** command:

R1#**show ipv6 ospf neighbor**

Neighbor ID Pri State Dead Time Interface ID Interface
2.2.2.2 1 FULL/ - 00:00:37 5 Serial0/0

R2#**show ipv6 ospf neighbor**

Neighbor ID Pri State Dead Time Interface ID Interface
3.3.3.3 1 FULL/ - 00:00:32 23 Tunnel0
1.1.1.1 1 FULL/ - 00:00:39 5 Serial0/0
3.3.3.3 1 FULL/ - 00:00:38 6 Serial0/1

R3#**show ipv6 ospf neighbor**

Neighbor ID Pri State Dead Time Interface ID Interface
2.2.2.2 1 FULL/ - 00:00:33 9 Tunnel0
2.2.2.2 1 FULL/ - 00:00:39 6 Serial1/1
4.4.4.4 1 FULL/ - 00:00:35 5 Serial1/2

R4#**show ipv6 ospf neighbor**

https://t.me/learningnets

Technet24

Neighbor ID Pri State Dead Time Interface ID Interface
3.3.3.3 1 FULL/ - 00:00:37 7 Serial0/0

Next, verify routing information using the **show ipv6 route** command:

R1#**show ipv6 route ospf**
IPv6 Routing Table - 11 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
OI 2001:ABCD:1111:3::/64 [110/128]
via FE80::20D:28FF:FE9E:F940, Serial0/0
OI 2001:ABCD:1111:4::/64 [110/11956]
via FE80::20D:28FF:FE9E:F940, Serial0/0
O 2001:ABCD:1111:8::/64 [110/11175]
via FE80::20D:28FF:FE9E:F940, Serial0/0
O 3FFE:ABCD:1111:2::/64 [110/65]
via FE80::20D:28FF:FE9E:F940, Serial0/0
OI 3FFE:ABCD:1111:3::/64 [110/11176]
via FE80::20D:28FF:FE9E:F940, Serial0/0

R2#**show ipv6 route ospf**
IPv6 Routing Table - 12 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
OI 2001:ABCD:1111:4::/64 [110/11892]
via FE80::213:7FFF:FEAF:3E00, Tunnel0
OI 3FFE:ABCD:1111:3::/64 [110/11112]
via FE80::213:7FFF:FEAF:3E00, Tunnel0

R3#**show ipv6 route ospf**
IPv6 Routing Table - 12 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2

https://t.me/learningnets

ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
O 2001:ABCD:1111:1::/64 [110/11175]
via FE80::20D:28FF:FE9E:F940, Tunnel0
O 3FFE:ABCD:1111:2::/64 [110/11112]
via FE80::20D:28FF:FE9E:F940, Tunnel0

R4#**show ipv6 route ospf**
IPv6 Routing Table - 11 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
OI 2001:ABCD:1111:1::/64 [110/11239]
via FE80::213:7FFF:FEAF:3E00, Serial0/0
OI 2001:ABCD:1111:3::/64 [110/845]
via FE80::213:7FFF:FEAF:3E00, Serial0/0
OI 2001:ABCD:1111:8::/64 [110/11175]
via FE80::213:7FFF:FEAF:3E00, Serial0/0
OI 3FFE:ABCD:1111:2::/64 [110/11176]
via FE80::213:7FFF:FEAF:3E00, Serial0/0
O 3FFE:ABCD:1111:3::/64 [110/65]
via FE80::213:7FFF:FEAF:3E00, Serial0/0

Task 4

The most simple solution that can be used to complete this task is to redistribute the connected RIPng subnet into OSPFv3 and then redistribute OSPFv3 into RIP. This negates the need to implement any filters preventing routes from being re-advertised back to into the same protocol and potentially causing a routing information loop. This task is completed as follows:

R1(config)#**ipv6 router rip CCNP**
R1(config-rtr)#**redistribute connected metric 1**
R1(config-rtr)#**redistribute ospf 1 metric 1**
R1(config-rtr)#**exit**
R1(config)#**ipv6 router ospf 1**
R1(config-rtr)#**redistribute rip CCNP**
R1(config-rtr)#**redistribute connected**
R1(config-rtr)#**exit**

R4(config)#**ipv6 router rip CCNP**

https://t.me/learningnets
Technet24

R4(config-rtr)#**redistribute connected metric 1**
R4(config-rtr)#**redistribute ospf 4 metric 1**
R4(config-rtr)#**exit**
R4(config)#**ipv6 router ospf 4**
R4(config-rtr)#**redistribute connected**
R4(config-rtr)#**redistribute rip CCNP**
R4(config-rtr)#**exit**

Verify RIPng redistributed routes by verifying the entries in the RIPng database:

R1#**show ipv6 rip CCNP database**
RIP process "CCNP", local RIB
2001:ABCD:1111:1::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:F120, expires in 178 secs
2001:ABCD:1111:3::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:F120, expires in 178 secs
2001:ABCD:1111:4::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:F120, expires in 178 secs
2001:ABCD:1111:8::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:F120, expires in 178 secs
3FFE:ABCD:1111:1::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:F120, expires in 178 secs
3FFE:ABCD:1111:2::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:F120, expires in 178 secs
3FFE:ABCD:1111:3::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:F120, expires in 178 secs

R4#**show ipv6 rip CCNP database**
RIP process "CCNP", local RIB
2001:ABCD:1111:1::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:EC80, expires in 162 secs
2001:ABCD:1111:3::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:EC80, expires in 162 secs
2001:ABCD:1111:4::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:EC80, expires in 162 secs
2001:ABCD:1111:8::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:EC80, expires in 162 secs
3FFE:ABCD:1111:1::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:EC80, expires in 162 secs
3FFE:ABCD:1111:2::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:EC80, expires in 162 secs

https://t.me/learningnets

3FFE:ABCD:1111:3::/64, metric 2
FastEthernet0/0/FE80::20F:23FF:FE5E:EC80, expires in 162 secs

Verify OSPFv3 redistributed routes by verifying Type 5 LSAs in the LSDB:

R1#**show ipv6 ospf database external**

OSPFv3 Router with ID (1.1.1.1) (Process ID 1)

Type-5 AS External Link States

LS age: 158
LS Type: AS External Link
Link State ID: 0
Advertising Router: 1.1.1.1
LS Seq Number: 80000001
Checksum: 0xA934
Length: 36
Prefix Address: 3FFE:ABCD:1111:1::
Prefix Length: 64, Options: None
Metric Type: 2 (Larger than any link state path)
Metric: 20

Routing Bit Set on this LSA
LS age: 79
LS Type: AS External Link
Link State ID: 0
Advertising Router: 4.4.4.4
LS Seq Number: 80000001
Checksum: 0x4F82
Length: 36
Prefix Address: 3FFE:ABCD:1111:1::
Prefix Length: 64, Options: None
Metric Type: 2 (Larger than any link state path)
Metric: 20

R4#**show ipv6 ospf database external**

OSPFv3 Router with ID (4.4.4.4) (Process ID 4)

Type-5 AS External Link States

Routing Bit Set on this LSA
LS age: 168
LS Type: AS External Link
Link State ID: 0

https://t.me/learningnets

Technet24

Advertising Router: 1.1.1.1
LS Seq Number: 80000001
Checksum: 0xA934
Length: 36
Prefix Address: 3FFE:ABCD:1111:1::
Prefix Length: 64, Options: None
Metric Type: 2 (Larger than any link state path)
Metric: 20

LS age: 83
LS Type: AS External Link
Link State ID: 0
Advertising Router: 4.4.4.4
LS Seq Number: 80000001
Checksum: 0x4F82
Length: 36
Prefix Address: 3FFE:ABCD:1111:1::
Prefix Length: 64, Options: None
Metric Type: 2 (Larger than any link state path)
Metric: 20

Task 5

To complete this task, simply raise the default administrative distance for OSPF internal routes, since there are no external OSPF routes, to a value higher than 120, which is the RIPng default administrative distance. Any value between 1 and 254 can be used to complete this task. This task is completed as follows:

R4(config)#**ipv6 router ospf 4**
R4(config-rtr)#**distance ospf intra-area 150 inter-area 150**
R4(config-rtr)#**exit**

Following this configuration, verify the contents of the routing table on R4:

R4#show ipv6 route

IPv6 Routing Table - 11 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R 2001:ABCD:1111:1::/64 [120/2]

https://t.me/learningnets

via FE80::20F:23FF:FE5E:EC80, FastEthernet0/0
R 2001:ABCD:1111:3::/64 [120/2]
via FE80::20F:23FF:FE5E:EC80, FastEthernet0/0
C 2001:ABCD:1111:4::/64 [0/0]
via ::, Serial0/0
L 2001:ABCD:1111:4::4/128 [0/0]
via ::, Serial0/0
R 2001:ABCD:1111:8::/64 [120/2]
via FE80::20F:23FF:FE5E:EC80, FastEthernet0/0
C 3FFE:ABCD:1111:1::/64 [0/0]
via ::, FastEthernet0/0
L 3FFE:ABCD:1111:1::4/128 [0/0]
via ::, FastEthernet0/0
R 3FFE:ABCD:1111:2::/64 [120/2]
via FE80::20F:23FF:FE5E:EC80, FastEthernet0/0
R 3FFE:ABCD:1111:3::/64 [120/2]
via FE80::20F:23FF:FE5E:EC80, FastEthernet0/0
L FE80::/10 [0/0]
via ::, Null0
L FF00::/8 [0/0]
via ::, Null0

Task 6

OSPFv3 supports both authentication and encryption for security. To configure OSPFv3 area authentication, you need to use the **area <area> authentication ipsec spi <size> [md5|sha1] <key>** OSPFv3 configuration command. This task is completed as follows:

R1(config)#**ipv6 router ospf 1**
R1(config-rtr)#**area 0 authentication ipsec spi 678 md5 1234567890abcdef1234567890abcdef**
R2(config-rtr)#**exit**

R2(config)#**ipv6 router ospf 2**
R2(config-rtr)#**area 0 authentication ipsec spi 678 md5 1234567890abcdef1234567890abcdef**
R2(config-rtr)#**exit**

R3(config)#**ipv6 router ospf 3**
R3(config-rtr)#**area 0 authentication ipsec spi 678 md5 1234567890abcdef1234567890abcdef**
R3(config-rtr)#**exit**

https://t.me/learningnets

Verify OSPFv3 area authentication using the **show ipv6 ospf** command:

```
R2#show ipv6 ospf
Routing Process "ospfv3 2" with ID 2.2.2.2
It is an area border router
SPF schedule delay 5 secs, Hold time between two SPFs 10 secs
Minimum LSA interval 5 secs. Minimum LSA arrival 1 secs
LSA group pacing timer 240 secs
Interface flood pacing timer 33 msecs
Retransmission pacing timer 66 msecs
Number of external LSA 7. Checksum Sum 0x020EF4
Number of areas in this router is 2. 1 normal 1 stub 0 nssa
Reference bandwidth unit is 100 mbps
Area BACKBONE(0)
Number of interfaces in this area is 3
MD5 Authentication, SPI 678
SPF algorithm executed 17 times
Number of LSA 16. Checksum Sum 0x07AE65
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0
Area 1
Number of interfaces in this area is 1
It is a stub area, no summary LSA in this area
generates stub default route with cost 1
SPF algorithm executed 15 times
Number of LSA 13. Checksum Sum 0x04EB52
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0
```

By default, because IPv6 uses built-in IPsec functions, Cisco IOS software automatically creates IPsec policies for the configured authentication. The policy can be viewed using the **show crypto ipsec sa [interface <name>]** command on the router(s). Authentication Header (AH) is used. If you configure encryption, then Encapsulating Security Payload (ESP) will be used instead. Check the relevant SA states based on your configuration:

```
R2#show crypto ipsec sa interface serial 0/0
```

https://t.me/learningnets

interface: Serial0/0
Crypto map tag: (none), local addr FE80::20D:28FF:FE9E:F940

IPsecv6 policy name: OSPFv3-2-678
IPsecv6-created ACL name: Serial0/0-ipsecv6-ACL

protected vrf: (none)
local ident (addr/mask/prot/port): (FE80::/10/89/0)
remote ident (addr/mask/prot/port): (::/0/89/0)
current_peer :: port 500
PERMIT, flags={origin_is_acl,}
#pkts encaps: 20, #pkts encrypt: 0, #pkts digest: 20
#pkts decaps: 23, #pkts decrypt: 0, #pkts verify: 23
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts compr. failed: 0
#pkts not decompressed: 0, #pkts decompress failed: 0
#send errors 0, #recv errors 0

local crypto endpt.: FE80::20D:28FF:FE9E:F940, remote crypto endpt.: ::
path mtu 1500, ip mtu 1500, ip mtu idb Serial0/0
current outbound spi: 0x2A6(678)

inbound esp sas:

inbound ah sas:
spi: 0x2A6(678)
transform: ah-md5-hmac ,
in use settings ={Transport, }
conn id: 2005, flow_id: SW:5, crypto map: (none)
no sa timing
replay detection support: N
Status: ACTIVE

inbound pcp sas:

outbound esp sas:

outbound ah sas:
spi: 0x2A6(678)
transform: ah-md5-hmac ,
in use settings ={Transport, }
conn id: 2006, flow_id: SW:6, crypto map: (none)
no sa timing
replay detection support: N

https://t.me/learningnets

Technet24

Status: ACTIVE

outbound pcp sas:

Additionally, you can also view the configuration parameters for the applied policy using the **show crypto ipsec policy** command on the router. The policy name, by default, will be OSPFv3-<process ID>-<SPI>. For example, on R1, the applied policy name will be OSPFv3-R1-678. This is validated and illustrated in the following output:

R1#**show crypto ipsec policy**
Crypto IPsec client security policy data

Policy name: OSPFv3-1-678
Policy refcount: 1
Inbound AH SPI: 678 (0x2A6)
Outbound AH SPI: 678 (0x2A6)
Inbound AH Key: 1234567890ABCDEF1234567890ABCDEF
Outbound AH Key: 1234567890ABCDEF1234567890ABCDEF
Transform set: ah-md5-hmac

Task 7

Interface authentication is applied at the interface using the **ipv6 ospf authentication ipsec spi <spi> [md5|sha1] <key>** interface configuration command. This task is completed by applying the specified configuration parameters on all interfaces within area 2:

R3(config)#**interface serial 1/2**
R3(config-if)#**ipv6 ospf authentication ipsec spi 500 md5 1234567890abcdef1234567890abcdef**
R3(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**ipv6 ospf authentication ipsec spi 500 md5 1234567890abcdef1234567890abcdef**
R4(config-if)#**exit**

Verify OSPFv3 interface authentication using the **show ipv6 ospf interface** command:

R4#**show ipv6 ospf interface serial 0/0**
Serial0/0 is up, line protocol is up
Link Local Address FE80::20F:23FF:FE5E:F120, Interface ID 5
Area 2, Process ID 4, Instance ID 0, Router ID 4.4.4.4
Network Type POINT_TO_POINT, Cost: 64
MD5 Authentication SPI 500, secure socket state UP (errors: 0)
Transmit Delay is 1 sec, State POINT_TO_POINT,

https://t.me/learningnets

Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:02
Index 1/1/1, flood queue length 0
Next 0x0(0)/0x0(0)/0x0(0)
Last flood scan length is 1, maximum is 5
Last flood scan time is 0 msec, maximum is 0 msec
Neighbor Count is 1, Adjacent neighbor count is 1
Adjacent with neighbor 3.3.3.3
Suppress hello for 0 neighbor(s)

NOTE: You should have NO errors (as illustrated above). If you do, check the configuration.

As is the case with area authentication, a policy is dynamically created and applied by the Cisco IOS software. This can be viewed using the **show crypto ipsec sa [interface <name>]** command on the router on which interface authentication has been implemented. The policy name, by default, will be OSPFv3-<process ID>-<SPI> as illustrated below:

R4#**show crypto ipsec sa interface serial 0/0**

interface: Serial0/0
Crypto map tag: (none), local addr FE80::20F:23FF:FE5E:F120

IPsecv6 policy name: OSPFv3-4-500
IPsecv6-created ACL name: Serial0/0-ipsecv6-ACL

protected vrf: (none)
local ident (addr/mask/prot/port): (FE80::/10/89/0)
remote ident (addr/mask/prot/port): (::/0/89/0)
current_peer :: port 500
PERMIT, flags={origin_is_acl,}
#pkts encaps: 29, #pkts encrypt: 0, #pkts digest: 29
#pkts decaps: 31, #pkts decrypt: 0, #pkts verify: 31
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts compr. failed: 0
#pkts not decompressed: 0, #pkts decompress failed: 0
#send errors 0, #recv errors 0

local crypto endpt.: FE80::20F:23FF:FE5E:F120, remote crypto endpt.: ::
path mtu 1500, ip mtu 1500, ip mtu idb Serial0/0
current outbound spi: 0x1F4(500)

inbound esp sas:

https://t.me/learningnets

Technet24

inbound ah sas:
spi: 0x1F4(500)
transform: ah-md5-hmac ,
in use settings ={Transport, }
conn id: 2001, flow_id: SW:1, crypto map: (none)
no sa timing
replay detection support: N
Status: ACTIVE

inbound pcp sas:

outbound esp sas:

outbound ah sas:
spi: 0x1F4(500)
transform: ah-md5-hmac ,
in use settings ={Transport, }
conn id: 2002, flow_id: SW:2, crypto map: (none)
no sa timing
replay detection support: N
Status: ACTIVE

outbound pcp sas:

https://t.me/learningnets

CCNP Lab 046: IPv6 OSPFv3 Lab

Lab Objective:

The focus of this lab is to understand OSPFv3 implementation and configuration in Cisco IOS routers. Additional technologies include Frame Relay, summarization and path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab. Also, if you are using the www.101labs.net racks, configure R3 as the Frame Relay switch using the following configuration commands:

hostname R3-Frame-Relay-Switch
!

https://t.me/learningnets

```
frame-relay switching
!
interface serial 1/0
description ‘Connected To R1 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 102 interface serial 1/1 201
frame-relay route 104 interface serial 1/2 401
no shutdown
!
interface serial 1/1
description ‘Connected To R2 Serial 0/1’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 201 interface serial 1/0 102
no shutdown
!
interface serial 1/2
description ‘Connected To R4 Serial 0/0’
encapsulation frame-relay
no ip address
clock rate 128000
frame-relay intf-type dce
frame-relay route 401 interface serial 1/0 104
no shutdown
!
end
```

Task 1

Configure hostnames and IP addresses on all routers as illustrated in the network topology.

Task 2

Configure the Frame Relay network so that all routers can ping each others’ WAN interfaces. This connectivity should be for Link-Local addresses only. Verify the

https://t.me/learningnets

Technet24

configuration.

Task 3

Configure OSPF over the Frame Relay WAN connectivity R1, R2, and R4. Ensure that there is no DR/BDR election held on the WAN segment. Additionally, OSPFv3 should use Unicast packets to send protocol messages. Verify your configuration using the appropriate commands.

Task 4

Redistribute the LAN subnets connected to R1 into OSPF. Configure R1 so that only a single route is advertised to R2 and R4. Verify that these routers can ping the three LAN subnets connected to R1 although they have only a single route for the subnets in their routing tables.

Task 5

Advertise the subnet connected to R2 and R4s LAN interfaces via OSPF. Do NOT redistribute this subnet into OSPF. These routes should be received as inter-area routes on R1. Ensure that no OSPFv3 messages are sent out these interfaces. Verify your configuration.

Task 6

Configure OSPF so that R1 prefers the path via R2 to reach the 3ffe:abcd:1111:5/64 IPv6 subnet connected to R2 and R4. You are NOT allowed to implement any configurations on R1 to complete this task. Additionally, you are NOT allowed to modify interface bandwidth or cost values, or default administrative distance values. Finally, you can NOT use any static routes or redistribution to complete this task. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**ipv6 unicast-routing**
R1(config)#**ipv6 cef**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no shutdown**
R1(config-if)#**ipv6 address 3ffe:abcd:1111:1000::1/64**
R1(config-if)#**ipv6 address 3ffe:abcd:1111:2000::1/64**
R1(config-if)#**ipv6 address 3ffe:abcd:1111:3000::1/64**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**

https://t.me/learningnets

R1(config-if)#**ipv6 address 2001:abcd:1111:1::1/64**
R1(config-if)#**no shutdown**
R1(config-if)#**encapsulation frame-relay**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**ipv6 unicast-routing**
R2(config)#**ipv6 cef**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#**ipv6 address 3ffe:abcd:1111:5::2/64**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)# **ipv6 address 2001:abcd:1111:1::2/64**
R2(config-if)#**no shutdown**
R2(config-if)#**encapsulation frame-relay**
R2(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**ipv6 unicast-routing**
R4(config)#**ipv6 cef**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ipv6 address 3ffe:abcd:1111:5::4/64**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ipv6 address 2001:abcd:1111:1::4/64**
R4(config-if)#**no shutdown**
R4(config-if)#**encapsulation frame-relay**
R4(config-if)#**exit**

Task 2

To complete this task, you need to use the **frame-relay map ipv6 [address] [dlci] [broadcast]** command on all routers. This task is completed as follows:

R1(config)#**interface serial 0/1**
R1(config-if)#**frame-relay map ipv6 FE80::20D:28FF:FE9E:F940 102 broadcast**
R1(config-if)#**frame-relay map ipv6 FE80::20F:23FF:FE5E:F120 104 broadcast**
R1(config-if)#**exit**

R2(config)#**interface serial 0/1**
R2(config-if)#**frame-relay map ipv6 FE80::20F:23FF:FE5E:EC80 201 broadcast**
R2(config-if)#**frame-relay map ipv6 FE80::20F:23FF:FE5E:F120 201**

https://t.me/learningnets

Technet24

R2(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**frame-relay map ipv6 FE80::20F:23FF:FE5E:EC80 401 broadcast**
R4(config-if)#**frame-relay map ipv6 FE80::20D:28FF:FE9E:F940 401**
R4(config-if)#**exit**

Verify your configuration using the **show frame-relay map** command on all routers:

R1#**show frame-relay map**
Serial0/1 (up): ipv6 FE80::20D:28FF:FE9E:F940 dlci 102(0x66,0x1860), static,
broadcast,
CISCO, status defined, active
Serial0/1 (up): ipv6 FE80::20F:23FF:FE5E:F120 dlci 104(0x68,0x1880), static,
broadcast,
CISCO, status defined, active

R2#**show frame-relay map**
Serial0/1 (up): ipv6 FE80::20F:23FF:FE5E:F120 dlci 201(0xC9,0x3090), static,
CISCO, status defined, active
Serial0/1 (up): ipv6 FE80::20F:23FF:FE5E:EC80 dlci 201(0xC9,0x3090), static,
broadcast,
CISCO, status defined, active

R4#**show frame-relay map**
Serial0/0 (up): ipv6 FE80::20D:28FF:FE9E:F940 dlci 401(0x191,0x6410), static,
CISCO, status defined, active
Serial0/0 (up): ipv6 FE80::20F:23FF:FE5E:EC80 dlci 401(0x191,0x6410), static,
broadcast,
CISCO, status defined, active

Finally, complete the task by pinging between all three routers across the Frame Relay WAN:

R1#**ping FE80::20D:28FF:FE9E:F940**
Output Interface: **serial0/1**
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to FE80::20D:28FF:FE9E:F940, timeout is 2
seconds:
Packet sent with a source address of FE80::20F:23FF:FE5E:EC80
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

R1#**ping FE80::20F:23FF:FE5E:F120**

https://t.me/learningnets

Output Interface: **serial0/1**
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to FE80::20F:23FF:FE5E:F120, timeout is 2 seconds:
Packet sent with a source address of FE80::20F:23FF:FE5E:EC80
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

R2#**ping FE80::20F:23FF:FE5E:F120**
Output Interface: **serial0/1**
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to FE80::20F:23FF:FE5E:F120, timeout is 2 seconds:
Packet sent with a source address of FE80::20D:28FF:FE9E:F940
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 84/84/88 ms

R2#**ping FE80::20F:23FF:FE5E:EC80**
Output Interface: **serial0/1**
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to FE80::20F:23FF:FE5E:EC80, timeout is 2 seconds:
Packet sent with a source address of FE80::20D:28FF:FE9E:F940
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

R4#**ping FE80::20D:28FF:FE9E:F940**
Output Interface: **serial0/0**
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to FE80::20D:28FF:FE9E:F940, timeout is 2 seconds:
Packet sent with a source address of FE80::20F:23FF:FE5E:F120
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 84/84/88 ms

R4#**ping FE80::20F:23FF:FE5E:EC80**
Output Interface: **serial0/0**
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to FE80::20F:23FF:FE5E:EC80, timeout is 2 seconds:
Packet sent with a source address of FE80::20F:23FF:FE5E:F120
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

https://t.me/learningnets
Technet24

Task 3

To prevent DR/BDR election on the Frame Relay WAN and allow OSPF to use Unicast packets to send protocol messages, you must configure a point-to-multipoint non-broadcast network type, which requires static neighbor configuration. Unlike OSPFv2, OSPFv3 neighbors are configured using the Link-Local address and under the interface. Complete this task as follows:

R1(config)#**ipv6 router ospf 1**
R1(config-rtr)#**router-id 1.1.1.1**
R1(config-rtr)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ipv6 ospf network point-to-multipoint non-broadcast**
R1(config-if)#**ipv6 ospf 1 area 0**
R1(config-if)#**ipv6 ospf neighbor FE80::20D:28FF:FE9E:F940**
R1(config-if)#**ipv6 ospf neighbor FE80::20F:23FF:FE5E:F120**
R1(config-if)#**exit**

R2(config)#**ipv6 router ospf 2**
R2(config-rtr)#**router-id 2.2.2.2**
R2(config-rtr)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ipv6 ospf network point-to-multipoint non-broadcast**
R2(config-if)#**ipv6 ospf 2 area 0**
R2(config-if)#**ipv6 ospf neighbor FE80::20F:23FF:FE5E:EC80**
R2(config-if)#**exit**

R4(config)#**ipv6 router ospf 4**
R4(config-rtr)#**router-id 4.4.4.4**
R4(config-rtr)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ipv6 ospf network point-to-multipoint non-broadcast**
R4(config-if)#**ipv6 ospf 4 area 0**
R4(config-if)#**ipv6 ospf neighbor FE80::20F:23FF:FE5E:EC80**
R4(config-if)#**exit**

Verify your configuration using the **show ipv6 ospf neighbor** command on all routers:

R1#**show ipv6 ospf neighbor**

Neighbor ID Pri State Dead Time Interface ID Interface
2.2.2.2 1 FULL/ - 00:01:58 6 Serial0/1
4.4.4.4 1 FULL/ - 00:01:30 5 Serial0/1

https://t.me/learningnets

R2#**show ipv6 ospf neighbor**

Neighbor ID Pri State Dead Time Interface ID Interface
1.1.1.1 1 FULL/ - 00:01:44 6 Serial0/1

R4#**show ipv6 ospf neighbor**

Neighbor ID Pri State Dead Time Interface ID Interface
1.1.1.1 1 FULL/ - 00:01:41 6 Serial0/0

Task 4

The first part of this task simply requires that you redistribute the connected prefixes into OSPF. This first part is completed as follows:

R1(config)#**ipv6 router ospf 1**
R1(config-rtr)#**redistribute connected**
R1(config-rtr)#**exit**

Verify your configuration by looking at the Link State Database entries on R1:

R1#**show ipv6 ospf database external**

OSPFv3 Router with ID (1.1.1.1) (Process ID 1)

Type-5 AS External Link States

LS age: 101
LS Type: AS External Link
Link State ID: 0
Advertising Router: 1.1.1.1
LS Seq Number: 80000001
Checksum: 0xA826
Length: 36
Prefix Address: 3FFE:ABCD:1111:1000::
Prefix Length: 64, Options: None
Metric Type: 2 (Larger than any link state path)
Metric: 20

LS age: 101
LS Type: AS External Link
Link State ID: 1
Advertising Router: 1.1.1.1
LS Seq Number: 80000001
Checksum: 0xAF0E
Length: 36
Prefix Address: 3FFE:ABCD:1111:2000::

https://t.me/learningnets

Technet24

Prefix Length: 64, Options: None
Metric Type: 2 (Larger than any link state path)
Metric: 20

LS age: 103
LS Type: AS External Link
Link State ID: 2
Advertising Router: 1.1.1.1
LS Seq Number: 80000001
Checksum: 0xB6F5
Length: 36
Prefix Address: 3FFE:ABCD:1111:3000::
Prefix Length: 64, Options: None
Metric Type: 2 (Larger than any link state path)
Metric: 20

Additionally, you can also verify the configuration by looking at R2 and R4s routing tables:

R2#**show ipv6 route ospf | include OE2**
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
OE2 3FFE:ABCD:1111:1000::/64 [110/20]
OE2 3FFE:ABCD:1111:2000::/64 [110/20]
OE2 3FFE:ABCD:1111:3000::/64 [110/20]

R4#**show ipv6 route ospf | include OE2**
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
OE2 3FFE:ABCD:1111:1000::/64 [110/20]
OE2 3FFE:ABCD:1111:2000::/64 [110/20]
OE2 3FFE:ABCD:1111:3000::/64 [110/20]

The second part of this task requires route summarization, i.e. summarizing the 3 FastEthernet interface addresses and advertise only a single route using OSPFv3. IPv6 summarization is not as complex as one would think. It is also performed in a manner similar to IPv4 route summarization. First, identify and locate the first different 16-bit field. In our example, it is the fourth field, which contains the values 1000, 2000 and 3000. Next, convert these values to binary as illustrated in the following table:

Hexadecimal Value
Binary Representation
Matching Bit Values
1000
0001 0000 0000 0000

https://t.me/learningnets

00
2000
0010 0000 0000 0000
00
3000
0011 0000 0000 0000
00

Referencing the table above, the first two bits match. To complete the address, we simply input zeros for the non-matching bits, resulting in the Binary address: 0000 0000 0000 0000. In Hexadecimal, the same address would be written as 0.

Next, we need to calculate the mask. This is simple and entails just counting the number of matching bits in the address, which would be 50. This task is completed as follows:

R1(config)#**ipv6 router ospf 1**
R1(config-rtr)#**summary-prefix 3ffe:abcd:1111::/50**
R1(config-rtr)#**exit**

Following your configuration, verify the summary prefix in the LSDB on R1:

R1#**show ipv6 ospf database external 3ffe:abcd:1111::/50**

OSPFv3 Router with ID (1.1.1.1) (Process ID 1)

Type-5 AS External Link States

LS age: 67
LS Type: AS External Link
Link State ID: 3
Advertising Router: 1.1.1.1
LS Seq Number: 80000001
Checksum: 0x17D2
Length: 36
Prefix Address: 3FFE:ABCD:1111::
Prefix Length: 50, Options: None
Metric Type: 2 (Larger than any link state path)
Metric: 20

The same can also be verified by looking at the LSDBs on R2 and R4. Additionally, you can also just simply check the IPv6 routing tables on these routers. Only a single external prefix should exist following the implemented route summarization on R1:

R2#**show ipv6 route ospf | include OE2**
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
OE2 3FFE:ABCD:1111::/50 [110/20]

https://t.me/learningnets

Technet24

R4#**show ipv6 route ospf | include OE2**
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
OE2 3FFE:ABCD:1111::/50 [110/20]

Finally, complete the task by verifying that R2 and R4 can ping all three R1 LAN prefixes:

R2#**ping 3FFE:ABCD:1111:1000::1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 3FFE:ABCD:1111:1000::1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/28/32 ms

R2#**ping 3FFE:ABCD:1111:2000::1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 3FFE:ABCD:1111:2000::1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/28/32 ms

R2#**ping 3FFE:ABCD:1111:3000::1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 3FFE:ABCD:1111:3000::1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

R4#**ping 3FFE:ABCD:1111:1000::1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 3FFE:ABCD:1111:1000::1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

R4#**ping 3FFE:ABCD:1111:2000::1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 3FFE:ABCD:1111:2000::1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

R4#**ping 3FFE:ABCD:1111:3000::1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 3FFE:ABCD:1111:3000::1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

https://t.me/learningnets

Task 5

Inter-area routes are routes received from another area. To complete this task, simply assign the LAN subnets connected to R2 and R4 to a different OSPF area. This is completed as follows:

R2(config)#**ipv6 router ospf 2**
R2(config-rtr)#**passive-interface fastethernet 0/0**
R2(config-rtr)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ipv6 ospf 2 area 2**
R2(config-if)#**exit**

R4(config)#**ipv6 router ospf 4**
R4(config-rtr)#**passive-interface fastethernet 0/0**
R4(config-rtr)#**exit**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ipv6 ospf 4 area 4**
R4(config-if)#**exit**

Verify your configuration by looking at the IPv6 routing table entries on R1:

R1#**show ipv6 route 3FFE:ABCD:1111:5::/64**
IPv6 Routing Table - 17 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2

OI 3FFE:ABCD:1111:5::/64 [110/65]
via FE80::20D:28FF:FE9E:F940, Serial0/1
via FE80::20F:23FF:FE5E:F120, Serial0/1

Task 6

This task requires a little thought based on the imposed restrictions. By default, R1 will load-balance between R2 and R4 for the LAN prefix these routers are connected to as follows:

R1#**show ipv6 route 3FFE:ABCD:1111:5::/64**
IPv6 Routing Table - 17 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary

https://t.me/learningnets
Technet24

O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2

OI 3FFE:ABCD:1111:5::/64 [110/65]
via FE80::20D:28FF:FE9E:F940, Serial0/1
via FE80::20F:23FF:FE5E:F120, Serial0/1

The most simple method of ensuring that R1 prefers the path via R2 would be to use the **ipv6 ospf neighbor <address> cost <cost>** interface configuration command under the Serial0/1 interface; however, we are NOT allowed to make any modifications to R1. Therefore, consideration must be given to another OSPF feature. The only other feature that allows us to assign costs directly to OSPF prefixes is the **area <are> range <prefix> cost <cost>** cost command. The task is completed by implementing different summary costs on R2 and R4:

R2(config)#**ipv6 router ospf 2**
R2(config-rtr)#**area 2 range 3FFE:ABCD:1111:5::/64 cost 2**
R2(config-rtr)#**exit**

R4(config)#**ipv6 router ospf 4**
R4(config-rtr)#**area 4 range 3FFE:ABCD:1111:5::/64 cost 4**
R4(config-rtr)#**exit**

NOTE: You could simply increment the cost on R4 to achieve the same result. As long as that value is higher than 1, the path via R2 will be preferred by R1.

Following this configuration, R1 prefers the path via R2 because of the lower cost value.

R1#**show ipv6 route 3FFE:ABCD:1111:5::/64**
IPv6 Routing Table - 17 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
OI 3FFE:ABCD:1111:5::/64 [110/66]
via FE80::20D:28FF:FE9E:F940, Serial0/1

Finally, verify that R1 can ping both R2 and R4s LAN addresses when complete:

R1#**ping 3FFE:ABCD:1111:5::2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 3FFE:ABCD:1111:5::2, timeout is 2 seconds:
!!!!!

https://t.me/learningnets

Success rate is 100 percent (5/5), round-trip min/avg/max = 28/29/32 ms

R1#**ping 3FFE:ABCD:1111:5::4**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 3FFE:ABCD:1111:5::4, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

https://t.me/learningnets

Technet24

CCNP Lab 047: IPv6 MP-BGP Lab

Lab Objective:

The focus of this lab is to understand MP-BGP implementation and configuration in Cisco IOS routers. Additional technologies include path control, attribute manipulation and filtering.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IPv6 addressing on all routers as illustrated in the network topology.

Task 2

Configure MP-BGP on R1. This router will reside in AS 123 and will peer with R2 and

https://t.me/learningnets

Technet24

R3. Use the global Unicast IPv6 addresses for peering.

Task 3

Configure MP-BGP on R2, R3, and R4. R2 and R3 will peer with R1. R2 will peer with R1 and R3. R3 will peer with R1, R2, and R4. R4 will peer only with R3. Use the global Unicast IPv6 addresses for peering. Verify your configuration.

Task 4

Advertise the 3ffe:abcd:1111:1/64 prefix connected to R1 using MP-BGP. This prefix should have an ORIGIN code of IGP and should be assigned the community 123:1. Verify your configuration using the appropriate commands.

Task 5

Advertise the 3ffe:abcd:1111:2/64 prefix as well as the 3ffe:abcd:1111:4/64 prefix connected to the LAN interfaces of R2 and R4, respectively, via MP-BGP. Ensure that R2 and R4 can ping each other LAN to LAN following this configuration. You are NOT allowed to configure R3 as a route-reflector, or use confederations. Instead, use BGP default routing. However, ensure that a default route is NEVER advertised to AS 123. Do NOT use any type of filters to complete this task. Verify your configuration.

Task 6

In the future, AS 123 will be advertising thousands of prefixes to AS 456. Configure AS 456 so that R2 prefers the path via R3 to reach all prefixes originated in AS 123 only.

The direct path to AS 123 via R2 should only be used in the event that the R2-R3 link is down. As 123 should therefore also prefer the R1-R3 for all traffic destined to AS 456.

This configuration should have no impact on any other router in the network and should be implemented on R3 and R1. Verify your configuration using the appropriate commands.

If you have completed all previous requirements correctly, R1, R2 and R4 will be able to ping each other LAN-to-LAN. Verify this using extended pings.

Lab Validation:

Task 1

Router(config)#**hostname R1**
R1(config)#**ipv6 unicast-routing**
R1(config)#**ipv6 cef**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ipv6 address 3ffe:abcd:1111:1::1/64**
R1(config-if)#**no shutdown**

https://t.me/learningnets

```
R1(config-if)#exit
R1(config)#interface serial 0/0
R1(config-if)#ipv6 address 2001:abcd:1111:1::1/64
R1(config-if)#clock rate 2000000
R1(config-if)#no shutdown
R1(config-if)#exit
R1(config)#interface serial 0/1
R1(config-if)#ipv6 address 2001:abcd:1111:2::1/64
R1(config-if)#no shutdown
R1(config-if)#exit
Router(config)#hostname R2
R2(config)#ipv6 unicast-routing
R2(config)#ipv6 cef
R2(config)#interface fastethernet 0/0
R2(config-if)#ipv6 address 3ffe:abcd:1111:2::2/64
R2(config-if)#no shutdown
R2(config)#interface serial 0/0
R2(config-if)#ipv6 address 2001:abcd:1111:1::2/64
R2(config-if)#no shutdown
R2(config-if)#exit
R2(config)#interface serial 0/1
R2(config-if)#ipv6 address 2001:abcd:1111:3::2/64
R2(config-if)#no shutdown
R2(config-if)#exit
Router(config)#hostname R3
R3(config)#ipv6 unicast-routing
R3(config)#ipv6 cef
R3(config)#interface serial 1/0
R3(config-if)#ipv6 address 2001:abcd:1111:2::3/64
R3(config-if)#clock rate 128000
R3(config-if)#no shutdown
R3(config-if)#exit
R3(config)#interface serial 1/1
R3(config-if)#ipv6 address 2001:abcd:1111:3::3/64
R3(config-if)#clock rate 128000
R3(config-if)#no shutdown
R3(config-if)#exit
R3(config)#interface serial 1/2
```

https://t.me/learningnets

Technet24

R3(config-if)#**ipv6 address 2001:abcd:1111:4::3/64**
R3(config-if)#**clock rate 128000**
R3(config-if)#**no shutdown**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**ipv6 unicast-routing**
R4(config)#**ipv6 cef**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ipv6 address 3ffe:abcd:1111:4::4/64**
R3(config-if)#**no shutdown**
R3(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ipv6 address 2001:abcd:1111:4::4/64**
R4(config-if)#**clock rate 128000**
R4(config-if)#**no shutdown**
R4(config-if)#**exit**

Task 2

R1(config)#**router bgp 123**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**address-family ipv6 unicast**
R1(config-router-af)#**neighbor 2001:abcd:1111:1::2 remote-as 456**
R1(config-router-af)#**neighbor 2001:abcd:1111:2::3 remote-as 456**
R1(config-router-af)#**exit**
R1(config-router)#**exit**

Task 3

R2(config)#**router bgp 456**
R2(config-router)#**bgp router-id 2.2.2.2**
R2(config-router)#**address-family ipv6 unicast**
R2(config-router-af)#**neighbor 2001:abcd:1111:1::1 remote-as 123**
R2(config-router-af)#**neighbor 2001:abcd:1111:3::3 remote-as 456**
R2(config-router-af)#**exit**
R2(config-router)#**exit**

R3(config)#**router bgp 456**
R3(config-router)#**bgp router-id 3.3.3.3**
R3(config-router)#**address-family ipv6 unicast**
R3(config-router-af)#**neighbor 2001:abcd:1111:2::1 remote-as 123**
R3(config-router-af)#**neighbor 2001:abcd:1111:3::2 remote-as 456**

https://t.me/learningnets

R3(config-router-af)#**neighbor 2001:abcd:1111:4::4 remote-as 456**
R3(config-router-af)#**exit**
R3(config-router)#**exit**

R4(config)#**router bgp 456**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**address-family ipv6 unicast**
R4(config-router-af)#**neighbor 2001:abcd:1111:4::3 remote-as 456**
R4(config-router-af)#**exit**
R4(config-router)#exit

Verify your configuration using the **show bgp ipv6 unicast summary** command on all MP-BGP speakers.

R1#**show bgp ipv6 unicast summary**
BGP router identifier 1.1.1.1, local AS number 123
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
2001:ABCD:1111:1::2
4 456 12 12 1 0 0 00:03:02 0
2001:ABCD:1111:2::3
4 456 13 13 1 0 0 00:01:26 0

R2#**show bgp ipv6 unicast summary**
BGP router identifier 2.2.2.2, local AS number 456
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
2001:ABCD:1111:1::1
4 123 6 6 1 0 0 00:03:06 0
2001:ABCD:1111:3::3
4 456 7 7 1 0 0 00:01:52 0

R3#**show bgp ipv6 unicast summary**
BGP router identifier 3.3.3.3, local AS number 456
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
2001:ABCD:1111:2::1
4 123 5 5 1 0 0 00:01:33 0
2001:ABCD:1111:3::2
4 456 5 5 1 0 0 00:01:55 0
2001:ABCD:1111:4::4

https://t.me/learningnets

Technet24

4 456 5 5 1 0 0 00:00:50 0

R4#**show bgp ipv6 unicast summary**
BGP router identifier 4.4.4.4, local AS number 456
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
2001:ABCD:1111:4::3
4 456 4 4 1 0 0 00:00:53 0

Task 4

By default, all prefixes injected into MP-BGP using the **network** statement will be assigned an ORIGIN code of IGP. To complete the second requirement of this task, we need to use a route-map to assign this prefix the specified COMMUNITY attribute. In addition to this, we need to configure MP-BGP so that this attribute is included in updates to peers:

R1(config)#**route-map COMMUNITY permit 10**
R1(config-route-map)#**set community 123:1**
R1(config-route-map)#**exit**
R1(config)#**ip bgp-community new-format**
R1(config)#**router bgp 123**
R1(config-router)#**address-family ipv6 unicast**
R1(config-router-af)#**network 3FFE:abcd:1111:1::/64 route-map COMMUNITY**
R1(config-router-af)#**neighbor 2001:ABCD:1111:1::2 send-community standard**
R1(config-router-af)#**neighbor 2001:ABCD:1111:2::3 send-community standard**
R1(config-router-af)#**exit**
R1(config-router)#**exit**

NOTE: The **ip bgp-community new-format** command is required to display a configured COMMUNITY value in ASN:nn notation. The Cisco default community format is one 32-bit number. The **ip bgp-community new-format** command changes the community format to AA:NN to conform to RFC 1997.

If this command is issued, the configured COMMUNITY would be displayed as follows:

R1#**show bgp ipv6 unicast 3FFE:abcd:1111:1::/64**
BGP routing table entry for 3FFE:ABCD:1111:1::/64, version 3
Paths: (1 available, best #1, table Global-IPv6-Table)
Advertised to update-groups:
1
Local

https://t.me/learningnets

:: from 0.0.0.0 (1.1.1.1)
Origin IGP, metric 0, localpref 100, weight 32768, valid, sourced, local, best
Community: 8060929
However, with this command enabled, the COMMUNITY is displayed in RFC 1997 format:

R1#**show bgp ipv6 unicast 3FFE:abcd:1111:1::/64**
BGP routing table entry for 3FFE:ABCD:1111:1::/64, version 3
Paths: (1 available, best #1, table Global-IPv6-Table)
Advertised to update-groups:
1
Local
:: from 0.0.0.0 (1.1.1.1)
Origin IGP, metric 0, localpref 100, weight 32768, valid, sourced, local, best
Community: 123:1

To complete this task, we also therefore need to issue this command on R2, R3, and R4. Also, we need to ensure that the COMMUNITY attribute is sent to all internal MP-BGP peers. In other words, this attribute should be included in updates from R2 to R3, and in updates from R3 to R2 and R4. Since R4 is not receiving and advertising any prefixes with this attribute, it does not need to include it in updates sent to R3. This part of the task is completed as follows:

R2(config)#**router bgp 456**
R2(config-router)#**address-family ipv6 unicast**
R2(config-router-af)#**neighbor 2001:abcd:1111:3::3 send-community standard**
R2(config-router-af)#**exit**
R2(config-router)#**exit**
R2(config)#**ip bgp-community new-format**
R2(config)#**exit**

R3(config)#**router bgp 456**
R3(config-router)#**address-family ipv6 unicast**
R3(config-router-af)#**neighbor 2001:abcd:1111:3::2 send-community standard**
R3(config-router-af)#**neighbor 2001:abcd:1111:4::4 send-community standard**
R3(config-router-af)#**exit**
R3(config-router)#**exit**
R3(config)#**ip bgp-community new-format**
R3(config)#**exit**

R4(config)#**ip bgp-community new-format**

Finally, verify that the prefix is received by R2 and R4 with the assigned

https://t.me/learningnets
Technet24

COMMUNITY:

R2#**show bgp ipv6 unicast 3FFE:abcd:1111:1::/64**
BGP routing table entry for 3FFE:ABCD:1111:1::/64, version 4
Paths: (2 available, best #2, table Global-IPv6-Table)
Advertised to update-groups:
2
123
2001:ABCD:1111:2::1 (inaccessible) from 2001:ABCD:1111:3::3 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, internal
Community: 123:1
123
2001:ABCD:1111:1::1 (FE80::20F:23FF:FE5E:EC80) from 2001:ABCD:1111:1::1 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, external, best
Community: 123:1

R3#**show bgp ipv6 unicast 3FFE:abcd:1111:1::/64**
BGP routing table entry for 3FFE:ABCD:1111:1::/64, version 4
Paths: (2 available, best #2, table Global-IPv6-Table)
Advertised to update-groups:
2
123
2001:ABCD:1111:1::1 (inaccessible) from 2001:ABCD:1111:3::2 (2.2.2.2)
Origin IGP, metric 0, localpref 100, valid, internal
Community: 123:1
123
2001:ABCD:1111:2::1 (FE80::20F:23FF:FE5E:EC80) from 2001:ABCD:1111:2::1 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, external, best
Community: 123:1

R4#**show bgp ipv6 unicast 3FFE:abcd:1111:1::/64**
BGP routing table entry for 3FFE:ABCD:1111:1::/64, version 0
Paths: (1 available, no best path)
Not advertised to any peer
123
2001:ABCD:1111:2::1 (inaccessible) from 2001:ABCD:1111:4::3 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, internal
Community: 123:1

https://t.me/learningnets

Task 5

The requirements for this task are two-fold. First, we need to advertise the LAN subnets that are connected to R2 and R4 via MP-BGP. This first part is completed as follows:

R2(config)#**router bgp 456**
R2(config-router)#**address-family ipv6 unicast**
R2(config-router-af)#**network 3ffe:abcd:1111:2::/64**
R2(config-router-af)#**exit**
R2(config-router)#**exit**

R4(config)#**router bgp 456**
R4(config-router)#**address-family ipv6 unicast**
R4(config-router-af)#**network 3ffe:abcd:1111:4::/64**
R4(config-router-af)#**exit**
R4(config-router)#**exit**

Verify your configuration using the **show bgp ipv6 unicast** command on R2 and R4:

R2#**show bgp ipv6 unicast 3ffe:abcd:1111:2::/64**
BGP routing table entry for 3FFE:ABCD:1111:2::/64, version 5
Paths: (1 available, best #1, table Global-IPv6-Table)
Advertised to update-groups:
1 2
Local
:: from 0.0.0.0 (2.2.2.2)
Origin IGP, metric 0, localpref 100, weight 32768, valid, sourced, local, best

R4#**show bgp ipv6 unicast 3ffe:abcd:1111:4::/64**
BGP routing table entry for 3FFE:ABCD:1111:4::/64, version 2
Paths: (1 available, best #1, table Global-IPv6-Table)
Advertised to update-groups:
1
Local
:: from 0.0.0.0 (4.4.4.4)
Origin IGP, metric 0, localpref 100, weight 32768, valid, sourced, local, best

The second part of this task requires some thought. In a typical BGP implementation, router R3 would be configured as a route reflector, allowing these prefixes to be advertised to its clients R2 and R4; however the task states that this is forbidden. To complete this task, we need to use BGP default routing as stated. However, to ensure that the default route is not advertised to AS 123, we need to use the COMMUNITY attribute (LOCAL_AS or NO_EXPORT) since we are forbidden from using any types of

https://t.me/learningnets
Technet24

filters. The second part of this task is completed as follows:

R3(config)#**route-map LOCAL permit 10**
R3(config-route-map)#**set community local-AS**
R3(config-route-map)#**exit**
R3(config)#**router bgp 456**
R3(config-router)#**address-family ipv6 unicast**
R3(config-router-af)#**neighbor 2001:ABCD:1111:3::2 default-originate route-map LOCAL**
R3(config-router-af)#**neighbor 2001:abcd:1111:4::4 default-originate**
R3(config-router-af)#**exit**

Following this configuration, verify the default routes received by R2 and R4:

R2#**show bgp ipv6 unicast ::/0**
BGP routing table entry for ::/0, version 7
Paths: (1 available, best #1, table Global-IPv6-Table, not advertised outside local AS)
Flag: 0x880
Not advertised to any peer
Local
2001:ABCD:1111:3::3 from 2001:ABCD:1111:3::3 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, internal, best
Community: local-AS

NOTE: You do NOT have to specify the NO_EXPORT or LOCAL_AS for the default route that is advertised to R4 because this BGP speaker is not peered with AS 123.

R4#**show bgp ipv6 unicast ::/0**
BGP routing table entry for ::/0, version 6
Paths: (1 available, best #1, table Global-IPv6-Table)
Not advertised to any peer
Local
2001:ABCD:1111:4::3 from 2001:ABCD:1111:4::3 (3.3.3.3)
Origin IGP, metric 0, localpref 100, valid, internal, best

Finally, complete this task by ensuring that R2 and R4 can ping each other LAN to LAN:

R2#**ping 3FFE:ABCD:1111:4::4 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:4::4, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:2::2
!!!!!!!!!!

https://t.me/learningnets

Success rate is 100 percent (10/10), round-trip min/avg/max = 384/384/384 ms

R4#**ping 3FFE:ABCD:1111:2::2 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:2::2, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:4::4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 388/388/388 ms

Task 6

To complete this task, you can use the LOCAL_PREF attributes on R3 so that it sends updates for prefixes originated in AS 123 with a higher value than the default LOCAL_PREF value. Because there will be a lot of prefixes from AS 123, use an AS_PATH filter on R3. This task is completed by implementing the following configuration on R3:

R3(config)#**ip as-path access-list 1 permit ^123$**
R3(config)#**route-map PREF permit 10**
R3(config-route-map)#**match as-path 1**
R3(config-route-map)#**set local-preference 200**
R3(config-route-map)#**exit**
R3(config-router)#**route-map PREF permit 20**
R3(config-route-map)#**exit**
R3(config)#**router bgp 456**
R3(config-router)#**address-family ipv6**
R3(config-router-af)#**neighbor 2001:abcd:1111:3::2 route-map PREF out**
R3(config-router-af)#**exit**
R3(config-router)#**exit**

Following this configuration, the MP-BGP RIB shows the following entry for the R1 prefix:

R2#**show bgp ipv6 unicast 3FFE:ABCD:1111:1::/64**
BGP routing table entry for 3FFE:ABCD:1111:1::/64, version 8
Paths: (2 available, best #1, table Global-IPv6-Table)
Advertised to update-groups:
1
123
2001:ABCD:1111:2::1 from 2001:ABCD:1111:3::3 (3.3.3.3)
Origin IGP, metric 0, localpref 200, valid, internal, best
Community: 123:1

https://t.me/learningnets

Technet24

123
2001:ABCD:1111:1::1 (FE80::20F:23FF:FE5E:EC80) from 2001:ABCD:1111:1::1 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, external
Community: 123:1

To complete the second part of this task, you can use either LOCAL_PREF or WEIGHT to ensure that R1 prefers the path via R3 for all prefixes originated in AS 456:

R1(config)#**ip as-path access-list 1 permit ^456$**
R1(config)#**route-map WEIGHT permit 10**
R1(config-route-map)#**match as-path 1**
R1(config-route-map)#**set weight 1**
R1(config-route-map)#**exit**
R1(config)#**route-map WEIGHT permit 20**
R1(config-route-map)#**exit**
R1(config)#**router bgp 123**
R1(config-router)#**address-family ipv6**
R1(config-router-af)#**neighbor 2001:ABCD:1111:2::3 route-map WEIGHT in**
R1(config-router-af)#**exit**
R1(config-router)#**exit**

Following this configuration, the MP-BGP RIB shows the following entry for the R2 prefix:

R1#**show bgp ipv6 unicast 3FFE:ABCD:1111:2::/64**
BGP routing table entry for 3FFE:ABCD:1111:2::/64, version 10
Paths: (2 available, best #1, table Global-IPv6-Table)
Flag: 0x840
Advertised to update-groups:
1
456
2001:ABCD:1111:2::3 (FE80::213:7FFF:FEAF:3E00) from 2001:ABCD:1111:2::3 (3.3.3.3)
Origin IGP, localpref 100, weight 1, valid, external, best
456
2001:ABCD:1111:1::2 (FE80::20D:28FF:FE9E:F940) from 2001:ABCD:1111:1::2 (2.2.2.2)
Origin IGP, metric 0, localpref 100, valid, external

Finally, verify your configurations using extended pings LAN-to-LAN between R1, R2, and R4:

https://t.me/learningnets

R1#**ping 3FFE:ABCD:1111:2::2 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:2::2, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 384/384/384 ms

R1#**ping 3FFE:ABCD:1111:4::4 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:4::4, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 384/384/384 ms

R2#**ping 3FFE:ABCD:1111:1::1 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:1::1, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:2::2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 384/384/384 ms

R4#**ping 3FFE:ABCD:1111:1::1 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:1::1, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:4::4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 384/384/384 ms

https://t.me/learningnets

Technet24

CCNP Lab 048: LLDP and DHCPv6

Lab Objective:

In this lab we will learn IPv6 address auto-configuration, DHCPv6, IPv6 traffic filtering, and LLDP. Both Autoconfig and DHCPv6 are part of the IPv6 Neighbor Discovery protocol. LLDP is an open standard counterpart of CDP and is used to discover neighbors on Ethernet interfaces.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure R1 FastEthernet 0/0 with IPv6 address of 2001:43:123:14::1/64

Configure R1 to provide IPv6 address to R4 on FastEthernet 0/0 link in the range of 2001:43:123:14::/64 . R4 should also be receiving a default route from R1.

Task 2

https://t.me/learningnets

Technet24

Configure R1 to provide an additional subnet 2001:43:123:100::/80 to R4 which it can further use on its other interfaces.

R1 should also provide domain name of google.com and DNS Server of 2001:43:123:14::1 to R4 over FastEthernet 0/0 link.

Task 3

Assign prefix 2001:43:123:100::/80 (DHCP-FROM-R1) to serial 1/0 interface on R4 with ::4/80 as the host address.

Assign 2001:43:123:100::3/80 on serial 1/0 of R3 and configure a default route on R3 to go via 2001:43:123:100::4.

R1 should be able to ping 2001:43:123:100::3.

Task 4

Statically assign IPv6 address to rest of the interfaces in the topology as per diagram.

R1:

Link Local for All interfaces: FE80::1

Serial 1/0: 2001:43:123:12::1/64

Serial 1/1: 2001:43:123:13::1/64

R2:

Link Local for All interfaces: FE80::2

Serial 1/0: 2001:43:123:12::2/64

Serial 1/1: 2001:43:123:23::2/64

FastEthernet 0/0: 2001:43:123:2::2/64

R3:

Link Local for All interfaces: FE80::3

Serial 1/0: 2001:43:123:13::3/64

Serial 1/1: 2001:43:123:23::3/64

FastEthernet 0/0: 2001:43:123:3::3/64

Task 5

Configure OSPFv3 for area 0 on all the interfaces in the topology.

Task 6

Configure IPv6 traffic filter, R2's LAN on FastEthernet 0/0 (2001:43:123:2::/64) should not be able to reach R3's LAN on FastEthernet 0/0 (2001:43:123:3::/64)

https://t.me/learningnets

Task 7

Configure LLDP on all the serial interfaces and make sure R1 can see R2 via LLDP

Lab configuration and Verifications:

Task 1

R1(config)#**ipv6 unicast-routing**
!
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ipv6 address 2001:43:123:14::1/64**
R1(config-if)#**no shutdown**
R1(config-if)#**ipv6 nd prefix 2001:43:123:14::/64 7200 7200**
!
R4(config)#**ipv6 unicast-routing**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ipv6 address autoconfig default**

IPv6 unicast routing will need to be enabled on both routers for IPv6 communication to work. IPv6 autoconfiguration relies on Neighbor Discovery protocol.

R1 is sending prefix 2001:43:123:14::/64 through neighbor discovery protocol with a lease time of 7200 seconds (2 hours).

R4 is configured to get IPv6 address and default route through autoconfig, it will get the prefix from R1 and add its MAC address to the prefix and make a unique IPv6 address for the interface. Note that your MAC address will differ from ours and produce a different address but the prefix should be the same.

Verifications:

R4#show ipv6 interface fastethernet 0/0
FastEthernet0/0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::**C004:7FF:FEE7:0**
No Virtual link-local address(es):
Global unicast address(es):
2001:43:123:14:C004:7FF:FEE7:0, subnet is 2001:43:123:14::/64 [EUI/CAL/PRE]
valid lifetime 7137 preferred lifetime 7137
Joined group address(es):
FF02::1
FF02::2
FF02::1:FFE7:0
MTU is 1500 bytes

https://t.me/learningnets

Technet24

ICMP error messages limited to one every 100 milliseconds
ICMP redirects are enabled
ICMP unreachables are sent
ND DAD is enabled, number of DAD attempts: 1
ND reachable time is 30000 milliseconds
ND advertised reachable time is 0 milliseconds
ND advertised retransmit interval is 0 milliseconds
ND router advertisements are sent every 200 seconds
ND router advertisements live for 1800 seconds
ND advertised default router preference is Medium
Hosts use stateless autoconfig for addresses.

R4#show ipv6 route
IPv6 Routing Table - 4 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route, M - MIPv6
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
D - EIGRP, EX - EIGRP external
S ::/0 [1/0]
via FE80::1, FastEthernet0/0
C 2001:43:123:14::/64 [0/0]
via ::, FastEthernet0/0
L 2001:43:123:14:C004:7FF:FEE7:0/128 [0/0]
via ::, FastEthernet0/0
L FF00::/8 [0/0]
via ::, Null0

R4 is using auto config to pick up an IP address as we specified on R1. R4 has also received a default route to go via FE80::1 which is link local address of R1. Keep in mind next hop values are always link-local addresses in IPv6.

We must be able to ping R1's FastEthernet interface address from R4

R4#ping 2001:43:123:14::1

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 2001:43:123:14::1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 4/12/32 ms

Task 2

https://t.me/learningnets

R1(config)#**ipv6 local pool DHCP6-POOL-LOCAL 2001:43:123:100::/64 80**
!
R1(config)#**ipv6 dhcp pool DHCP6-POOL**
R1(config-dhcp)# **prefix-delegation pool DHCP6-POOL-LOCAL lifetime 7200 7200**
!
R1(config-dhcp)#**domain-name google.com**
R1(config-dhcp)#**dns 2001:43:123:14::1**
!
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ipv6 dhcp server DHCP6-POOL**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ipv6 dhcp client pd DHCP-FROM-R1**

R1 is configured with a local pool of 2001:43:123:100::/64 which it will use to give away /80's out of it. Within DHCP pool R1 will also have a configuration for a domain name and DNS as required.

R4 is requesting dhcp information from R1 by configuring itself as a dhcp client. pd stands for prefix delegation and "**DHCP-FROM-R1"** is locally significant.

As an effect of above configurations R4 will get a prefix of 2001:43:123:100::/80 and will have a route to that prefix automatically installed pointing to Null0 that means I own this prefix.

R1 will get a static route to 2001:43:123:100::/80 automatically installed in its routing table pointing to R4's FastEthernet interface.

Verifications:

R4#show ipv6 dhcp interface fastethernet 0/0
FastEthernet0/0 is in client mode
State is OPEN
Renew will be sent in 00:50:36
List of known servers:
Reachable via address: FE80::1
DUID: 00030001C20107BA0000
Preference: 0
Configuration parameters:
IA PD: IA ID 0x00040001, T1 3600, T2 5760
Prefix: 2001:43:123:100::/80
preferred lifetime 7200, valid lifetime 7200

https://t.me/learningnets

Technet24

expires at Mar 01 2002 03:12 AM (6636 seconds)
DNS server: 2001:43:123:14::1
Domain name: google.com
Information refresh time: 0
Prefix name: DHCP-FROM-R1
Rapid-Commit: disabled

Prefix name in the output can be further used to assign the prefixes to downstream interfaces.

R4#show ipv6 route
IPv6 Routing Table - 5 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route, M - MIPv6
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
D - EIGRP, EX - EIGRP external
S ::/0 [1/0]
via FE80::1, FastEthernet0/0
C 2001:43:123:14::/64 [0/0]
via ::, FastEthernet0/0
L 2001:43:123:14:C004:7FF:FEE7:0/128 [0/0]
via ::, FastEthernet0/0
S 2001:43:123:100::/80 [1/0]
via ::, Null0
L FF00::/8 [0/0]
via ::, Null0

R1#show ipv6 route
IPv6 Routing Table - 6 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route, M - MIPv6
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
D - EIGRP, EX - EIGRP external
C 2001:43:123:12::/64 [0/0]
via ::, Serial1/0
L 2001:43:123:12::1/128 [0/0]
via ::, Serial1/0

https://t.me/learningnets

C 2001:43:123:14::/64 [0/0]
via ::, FastEthernet0/0
L 2001:43:123:14::1/128 [0/0]
via ::, FastEthernet0/0
S 2001:43:123:100::/80 [1/0]
via FE80::C004:7FF:FEE7:0, FastEthernet0/0
L FF00::/8 [0/0]
via ::, Null0

Task 3

R4(config)#**interface serial 1/0**
R4(config-if)#**ipv6 address DHCP-FROM-R1 ::4/80**
R4(config-if)#**no shut**
!
R3(config)#**ipv6 uni**
R3(config)#**interface s1/2**
R3(config-if)#**ipv6 address 2001:43:123:100::3/80**
R3(config-if)#**no shut**
R3(config-if)#**exit**
!
R3(config)#**ipv6 route ::/0 2001:43:123:100::4**

We configured 2001:43:123:100::3 on R3's serial 1/2 and configured a default route going via R4. Next hop for default (static) route we configure manually can be link-local address of the remote network or it can be just next hop global address. If using link local address of the remote router, we will need to configure the next hop interface as well.

R3#sh ipv6 route
IPv6 Routing Table - 4 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route, M - MIPv6
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
D - EIGRP, EX - EIGRP external
S ::/0 [1/0]
via 2001:43:123:100::4
C 2001:43:123:100::/80 [0/0]
via ::, Serial1/2

https://t.me/learningnets
Technet24

L 2001:43:123:100::3/128 [0/0]
via ::, Serial1/2
L FF00::/8 [0/0]
via ::, Null0

R1#ping 2001:43:123:100::3

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 2001:43:123:100::3, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 20/27/32 ms

Task 4

R1(config)#**interface serial 1/0**
R1(config-if)#**ipv6 address 2001:43:123:12::1/64**
R1(config-if)#**ipv6 address fe80::1 link-local**
R1(config-if)#**no shutdown**

R1(config-if)#**interface serial 1/1**
R1(config-if)#**ipv6 address 2001:43:123:13::1/64**
R1(config-if)#**ipv6 address fe80::1 link-local**
R1(config-if)#**no shutdown**

R2(config)#**ipv6 uni**
R2(config)#**interface serial 1/0**
R2(config-if)#**ipv6 address 2001:43:123:12::2/64**
R2(config-if)#**ipv6 address fe80::2 link-local**
R2(config-if)#**no shutdown**
!
R2(config-if)#**interface serial 1/1**
R2(config-if)#**ipv6 address 2001:43:123:23::2/64**
R2(config-if)#**ipv6 address fe80::2 link-local**
R2(config-if)#**no shutdown**
!
R2(config-if)#**interface fastethernet 0/0**
R2(config-if)#**ipv6 address 2001:43:123:2::2/64**
R2(config-if)#**ipv6 address fe80::2 link-local**
R2(config-if)#**no shutdown**

R3(config-if)#**interface serial 1/0**
R3(config-if)#**ipv6 address 2001:43:123:13::3/64**
R3(config-if)#**ipv6 address fe80::3 link-local**

https://t.me/learningnets

R3(config-if)#**no shutdown**

R3(config-if)#**interface serial 1/1**
R3(config-if)#**ipv6 address 2001:43:123:23::3/64**
R3(config-if)#**ipv6 address fe80::3 link-local**
R3(config-if)#**no shutdown**

R3(config-if)#**interface fastethernet 0/0**
R3(config-if)#**ipv6 address 2001:43:123:3::3/64**
R3(config-if)#**ipv6 address fe80::3 link-local**
R3(config-if)#**no shutdown**

Verifications:

R1#show ipv6 interface brief | exclude down|unassigned
FastEthernet0/0 [up/up]
FE80::C001:7FF:FEBA:0
2001:43:123:14::1
Serial1/0 [up/up]
FE80::1
2001:43:123:12::1
Serial1/1 [up/up]
FE80::1
2001:43:123:13::1

R2#show ipv6 interface brief | exclude down|unassigned
FastEthernet0/0 [up/up]
FE80::2
2001:43:123:2::2
Serial1/0 [up/up]
FE80::2
2001:43:123:12::2
Serial1/1 [up/up]
FE80::2
2001:43:123:23::2

R3#show ipv6 interface brief | exclude down|unassigned
FastEthernet0/0 [up/up]
FE80::3
2001:43:123:3::3
Serial1/0 [up/up]
FE80::3

https://t.me/learningnets

Technet24

2001:43:123:13::3
Serial1/1 [up/up]
FE80::3
2001:43:123:23::3
Serial1/2 [up/up]
FE80::C003:7FF:FED8:0
2001:43:123:100::3

R4#show ipv6 interface brief | exclude down|unassigned
FastEthernet0/0 [up/up]
FE80::C004:7FF:FEE7:0
2001:43:123:14:C004:7FF:FEE7:0
Serial1/0 [up/up]
FE80::C004:7FF:FEE7:0
2001:43:123:100::4

Task 5

R1(config)#**ipv6 router ospf 1**
R1(config-rtr)#**router-id 1.1.1.1**
!
R1(config)#**int fastethernet0/0**
R1(config-if)#**ipv6 ospf 1 area 0**
R1(config-if)#**int serial1/0**
R1(config-if)#**ipv6 ospf 1 area 0**
R1(config-if)#**int serial 1/1**
R1(config-if)#**ipv6 ospf 1 area 0**

R2(config)#**ipv6 router ospf 1**
R2(config-rtr)#**router-id 2.2.2.2**
R2(config-rtr)#**exit**
!
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ipv6 ospf 1 area 0**
R2(config-if)#**interface serial 1/0**
R2(config-if)#**ipv6 ospf 1 area 0**
R2(config-if)#**interface serial 1/1**
R2(config-if)#**ipv6 ospf 1 area 0**

R3(config)#**ipv6 router ospf 1**
R3(config-rtr)#**router-id 3.3.3.3**
R3(config-rtr)#**exit**

https://t.me/learningnets

!
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ipv6 ospf 1 area 0**
R3(config-if)#**interface serial 1/0**
R3(config-if)#**ipv6 ospf 1 area 0**
R3(config-if)#**interface serial 1/1**
R3(config-if)#**ipv6 ospf 1 area 0**
R3(config-if)#**interface serial 1/2**
R3(config-if)#**ipv6 ospf 1 area 0**

R4(config)#**ipv6 router ospf 1**
R4(config-rtr)#**router-id 4.4.4.4**
R4(config-rtr)#**exit**
!
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ipv6 ospf 1 area 0**
R4(config-if)#**interface serial 1/0**
R4(config-if)#**ipv6 ospf 1 area 0**

Verifications:

R1#sh ipv6 route ospf
IPv6 Routing Table - 11 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route, M - MIPv6
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
D - EIGRP, EX - EIGRP external
O 2001:43:123:2::/64 [110/74]
via FE80::2, Serial1/0
O 2001:43:123:3::/64 [110/74]
via FE80::3, Serial1/1
O 2001:43:123:23::/64 [110/128]
via FE80::2, Serial1/0
via FE80::3, Serial1/1

R2#sh ipv6 route ospf
IPv6 Routing Table - 11 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route, M - MIPv6

https://t.me/learningnets
Technet24

I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
D - EIGRP, EX - EIGRP external
O 2001:43:123:3::/64 [110/74]
via FE80::3, Serial1/1
O 2001:43:123:13::/64 [110/128]
via FE80::1, Serial1/0
via FE80::3, Serial1/1
O 2001:43:123:14::/64 [110/74]
via FE80::1, Serial1/0
O 2001:43:123:100::/80 [110/128]
via FE80::3, Serial1/1
R3#sh ipv6 route ospf
IPv6 Routing Table - 13 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route, M - MIPv6
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
D - EIGRP, EX - EIGRP external
O 2001:43:123:2::/64 [110/74]
via FE80::2, Serial1/1
O 2001:43:123:12::/64 [110/128]
via FE80::1, Serial1/0
via FE80::2, Serial1/1
O 2001:43:123:14::/64 [110/74]
via FE80::1, Serial1/0
via FE80::C004:7FF:FEE7:0, Serial1/2
R4#sh ipv6 route ospf
IPv6 Routing Table - 11 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route, M - MIPv6
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
D - EIGRP, EX - EIGRP external
O 2001:43:123:2::/64 [110/84]

https://t.me/learningnets

via FE80::C001:7FF:FEBA:0, FastEthernet0/0
O 2001:43:123:3::/64 [110/74]
via FE80::C003:7FF:FED8:0, Serial1/0
O 2001:43:123:12::/64 [110/74]
via FE80::C001:7FF:FEBA:0, FastEthernet0/0
O 2001:43:123:13::/64 [110/74]
via FE80::C001:7FF:FEBA:0, FastEthernet0/0
O 2001:43:123:23::/64 [110/128]
via FE80::C003:7FF:FED8:0, Serial1/0

R1#ping 2001:43:123:2::2

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 2001:43:123:2::2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/19/20 ms
R1#ping 2001:43:123:3::3

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 2001:43:123:3::3, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 4/7/12 ms

Task 6

Ping before applying traffic filter R2 should be able to ping 2001:43:123:3::3 coming from it's LAN

R2#ping 2001:43:123:3::3 source 2001:43:123:2::2

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 2001:43:123:3::3, timeout is 2 seconds:
Packet sent with a source address of 2001:43:123:2::2
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 4/6/8 ms

Now we will configure a traffic filter on R3 to block any traffic coming from R2's LAN and going to R3's LAN

R3(config)#**ipv6 access-list FITLER-R2-LAN**
R3(config-ipv6-acl)#**deny 2001:43:123:2::/64 2001:43:123:3::/64**
R3(config-ipv6-acl)#**permit any any**

R3(config)#**interface serial 1/0**
R3(config-if)#**ipv6 traffic-filter FITLER-R2-LAN in**
R3(config-if)#**exit**

https://t.me/learningnets

Technet24

!
R3(config)#**interface serial 1/1**
R3(config-if)#**ipv6 traffic-filter FITLER-R2-LAN in**
R3(config-if)#**exit**
!
R3(config)#**interface serial 1/2**
R3(config-if)#**ipv6 traffic-filter FITLER-R2-LAN in**
R3(config-if)#**exit**

Verifications:

R2#ping 2001:43:123:3::3 source 2001:43:123:2::2

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 2001:43:123:3::3, timeout is 2 seconds:
Packet sent with a source address of 2001:43:123:2::2
AAAAA
Success rate is 0 percent (0/5)

We can't ping, let's check the traffic filter counters on R3

R3#sh access-list
IPv6 access list FITLER-R2-LAN
deny ipv6 2001:43:123:2::/64 2001:43:123:3::/64 (5 matches) sequence 10
permit ipv6 any any (3 matches) sequence 20

Task 7

LLDP is a standard equivalent of CDP for IEEE 802 (Principally Ethernet) networks. It is useful when connecting Cisco devices to other vendor devices or to Non-Cisco IP phones.

R1(config)#lldp run
R1(config)#interface ethernet 0/0
R1(config-if)#lldp receive
R1(config-if)#lldp transmit

R2(config)#lldp run
R2(config)#interface ethernet0/0
R2(config-if)#lldp receive
R2(config-if)#lldp transmit

R3(config)#interface ethernet 0/0
R3(config-if)#lldp receive
R3(config-if)#lldp transmit

https://t.me/learningnets

R4(config)#lldp run
R4(config)#interface ethernet 0/0
R4(config-if)#lldp receive
R4(config-if)#lldp transmit

LLDP is configured similarly as CDP with minor differences. LLDP need to be run in global configuration mode. Then we need to enable sending and receiving of lldp packets on each interface we want to run it. Once enabled by default it runs on all interfaces

Note:

LLDP only works on 802.1 (Ethernet) interfaces not on serial interfaces.

Verifications:

R1#sh lldp interface

Ethernet0/0:
Tx: enabled
Rx: enabled
Tx state: IDLE
Rx state: WAIT FOR FRAME

Ethernet0/1:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

Ethernet0/2:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

Ethernet0/3:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

R2#show lldp interface

Ethernet0/0:
Tx: enabled

https://t.me/learningnets

Rx: enabled
Tx state: IDLE
Rx state: WAIT FOR FRAME

Ethernet0/1:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

Ethernet0/2:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

Ethernet0/3:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

R3#show lldp interface

Ethernet0/0:
Tx: enabled
Rx: enabled
Tx state: IDLE
Rx state: WAIT FOR FRAME

Ethernet0/1:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

Ethernet0/2:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

Ethernet0/3:
Tx: enabled

https://t.me/learningnets

Rx: enabled
Tx state: INIT

Rx state: WAIT PORT OPER

R4#show lldp interface

Ethernet0/0:
Tx: enabled
Rx: enabled
Tx state: IDLE
Rx state: WAIT FOR FRAME

Ethernet0/1:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

Ethernet0/2:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

Ethernet0/3:
Tx: enabled
Rx: enabled
Tx state: INIT
Rx state: WAIT PORT OPER

LLDP is enabled on all interfaces by default, but looking at the output we are no only seeing Rx & Tx on the ports where there is something on the other end. On interfaces that are down, LLDP Tx is at INIT and Rx is at WAIT PORT OPER state.

R1#show lldp neighbor
Capability codes:
(R) Router, (B) Bridge, (T) Telephone, (C) DOCSIS Cable Device
(W) WLAN Access Point, (P) Repeater, (S) Station, (O) Other

Device ID Local Intf Hold-time Capability Port ID
R4 Et0/0 120 R Et0/0

Total entries displayed: 1

R2#show lldp neighbor
Capability codes:

https://t.me/learningnets

(R) Router, (B) Bridge, (T) Telephone, (C) DOCSIS Cable Device
(W) WLAN Access Point, (P) Repeater, (S) Station, (O) Other

Device ID Local Intf Hold-time Capability Port ID

Total entries displayed: 0

R3#show lldp neighbor
Capability codes:
(R) Router, (B) Bridge, (T) Telephone, (C) DOCSIS Cable Device
(W) WLAN Access Point, (P) Repeater, (S) Station, (O) Other

Device ID Local Intf Hold-time Capability Port ID

Total entries displayed: 0

R4#show lldp neighbor
Capability codes:
(R) Router, (B) Bridge, (T) Telephone, (C) DOCSIS Cable Device
(W) WLAN Access Point, (P) Repeater, (S) Station, (O) Other

Device ID Local Intf Hold-time Capability Port ID
R1 Et0/0 120 R Et0/0

Total entries displayed: 1

Notice, only R1 and R4 are discovered as neighbors as these are only 2 routers connected through Ethernet links.

https://t.me/learningnets

CCNP Lab 049: IPv6 Tunnels and OSPFv3 Lab

Lab Objective:

The focus of this lab is to understand tunneling implementation and configuration in Cisco IOS routers. Additional technologies include OSPFv3 authentication and security.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Enable EIGRP on all routers as illustrated in the topology. Verify your EIGRP

https://t.me/learningnets

configuration.

Task 3

Configure a static IPv6 tunnel between R1 and R4. Ensure that you can ping across the tunnel. Verify your configuration using the appropriate commands.

Task 4

Configure OSPFv3 across the R1-R4 tunnel. Use OSPF area 0. Advertise the LAN subnets on R1 and R4 as inter-area OSPF routes. Verify that R1 and R4 can ping each other LAN-to-LAN.

Task 5

For security, configure area authentication for the OSPF backbone. Use the following parameters when you are configuring the authentication parameters:

- Use a Security Parameters Index (SPI) of 256
- Use the Secure Hash Algorithm (SHA) authentication
- Use a key of 1234567890abcdef1234567890abcdef12345678

Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

R1(config)#**router eigrp 254**
R1(config-router)#**no auto-summary**
R1(config-router)#**network 10.0.0.0**
R1(config-router)#**exit**

R2(config)#**router eigrp 254**
R2(config-router)#**no auto-summary**
R2(config-router)#**network 10.0.0.0**
R2(config-router)#**exit**

R3(config)#**router eigrp 254**
R3(config-router)#**no auto-summary**
R3(config-router)#**network 10.0.0.0**
R3(config-router)#**exit**

https://t.me/learningnets

Technet24

R4(config)#**router eigrp 254**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 10.0.0.0**
R4(config-router)#**exit**

Verify your EIGRP configuration using the **show ip eigrp neighbors** command:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.2 Se0/0 12 00:01:31 5 200 0 8

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.10 Se0/1 10 00:01:28 9 300 0 3
0 10.0.0.1 Se0/0 12 00:01:34 2 200 0 3

R3#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.14 Se1/2 13 00:01:26 12 1140 0 3
0 10.0.0.9 Se1/1 12 00:01:31 12 1140 0 7

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.13 Se0/0 14 00:01:29 14 200 0 7

Task 3

When you are configuring static (manual) IPv6 tunnels, you must specify IPv6 as the passenger protocol and IPv4 as both the encapsulation and transport protocol for the manual IPv6 tunnel using the **tunnel mode ipv6ip** interface configuration command. The requirements of this task are straightforward and are completed as follows:

R1(config)#**interface tunnel 0**
R1(config-if)#**ipv6 address 2001:abcd:1111:a::1/64**
R1(config-if)#**tunnel source serial 0/0**
R1(config-if)#**tunnel destination 10.0.0.14**

https://t.me/learningnets

R1(config-if)#**tunnel mode ipv6ip**
R1(config-if)#**exit**

R4(config)#**interface tunnel 0**
R4(config-if)#**ipv6 address 2001:abcd:1111:a::4/64**
R4(config-if)#**tunnel source serial 0/0**
R4(config-if)#**tunnel destination 10.0.0.1**
R4(config-if)#**tunnel mode ipv6ip**
R4(config-if)#**exit**

Verify your tunnel configuration using the **show interfaces** command:

R4#**show interfaces tunnel 0**
Tunnel0 is up, line protocol is up
Hardware is Tunnel
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 10.0.0.14 (Serial0/0), destination 10.0.0.1
Tunnel protocol/transport IPv6/IP
Tunnel TTL 255
Fast tunneling enabled
Tunnel transmit bandwidth 8000 (kbps)
Tunnel receive bandwidth 8000 (kbps)
Last input never, output 00:00:41, output hang never
Last clearing of "show interface" counters never
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: fifo
Output queue: 0/0 (size/max)
5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec
0 packets input, 0 bytes, 0 no buffer
Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
30 packets output, 2860 bytes, 0 underruns
0 output errors, 0 collisions, 0 interface resets
0 unknown protocol drops
0 output buffer failures, 0 output buffers swapped out

Finally, verify that you can ping across the tunnel using a simple ping:

https://t.me/learningnets

Technet24

R4#**ping 2001:abcd:1111:a::1 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 2001:ABCD:1111:A::1, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 404/407/408 ms

Task 4

The task OSPFv3 configuration requirements are straightforward. To advertise the LAN subnets that are connected as inter-area OSPF routes, you need to assign them to different areas. This task is completed as follows:

R1(config)#**ipv6 router ospf 1**
R1(config-rtr)#**router-id 1.1.1.1**
R1(config-rtr)#**exit**
R1(config)#**interface tunnel 0**
R1(config-if)#**ipv6 ospf 1 area 0**
R1(config-if)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ipv6 ospf 1 area 1**
R1(config-if)#**exit**

R4(config)#**ipv6 router ospf 4**
R4(config-rtr)#**router-id 4.4.4.4**
R4(config-rtr)#**exit**
R4(config)#**interface tunnel 0**
R4(config-if)#**ipv6 ospf 4 area 0**
R4(config-if)#**exit**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ipv6 ospf 4 area 4**
R4(config-if)#**exit**

Verify your configuration using the **show ipv6 ospf neighbor** command on R1 and R4:

R1#**show ipv6 ospf neighbor**

Neighbor ID Pri State Dead Time Interface ID Interface
4.4.4.4 1 FULL/ - 00:00:34 9 Tunnel0

R4#**show ipv6 ospf neighbor**

Neighbor ID Pri State Dead Time Interface ID Interface
1.1.1.1 1 FULL/ - 00:00:38 9 Tunnel0

Following this, verify that the prefixes are advertised and received as required:

https://t.me/learningnets

R1#**show ipv6 route ospf**
IPv6 Routing Table - 7 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
OI 3FFE:ABCD:1111:4::/64 [110/11112]
via FE80::A00:E, Tunnel0

R4#**show ipv6 route ospf**
IPv6 Routing Table - 7 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
OI 3FFE:ABCD:1111:1::/64 [110/11112]
via FE80::A00:1, Tunnel0

Finally, verify that R1 and R4 can ping each other LAN-to-LAN:

R1#**ping 3FFE:ABCD:1111:4::4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 3FFE:ABCD:1111:4::4, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 36/36/40 ms

R4#**ping 3FFE:ABCD:1111:1::1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 3FFE:ABCD:1111:1::1, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:4::4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 36/37/40 ms

Task 5

OSPFv3 supports both authentication and encryption for security. To configure OSPFv3 area authentication, you need to use the **area <area> authentication ipsec spi <size> [md5|sha1] <key>** OSPFv3 configuration command. This task is completed as follows:

R1(config)#**ipv6 router ospf 1**

https://t.me/learningnets

R1(config-rtr)#**area 0 authentication ipsec spi 256 sha1 1234567890ABCDEF1234567890ABCDEF12345678**
R1(config-rtr)#**exit**

R4(config)#**ipv6 router ospf 4**
R4(config-rtr)#**area 0 authentication ipsec spi 256 sha1 1234567890ABCDEF1234567890ABCDEF12345678**
R4(config-rtr)#**exit**

Verify OSPFv3 area authentication using the **show ipv6 ospf** command

R4#**show ipv6 ospf**
Routing Process "ospfv3 4" with ID 4.4.4.4
It is an area border router
SPF schedule delay 5 secs, Hold time between two SPFs 10 secs
Minimum LSA interval 5 secs. Minimum LSA arrival 1 secs
LSA group pacing timer 240 secs
Interface flood pacing timer 33 msecs
Retransmission pacing timer 66 msecs
Number of external LSA 0. Checksum Sum 0x000000
Number of areas in this router is 2. 2 normal 0 stub 0 nssa
Reference bandwidth unit is 100 mbps
Area BACKBONE(0)
Number of interfaces in this area is 1
SHA-1 Authentication, SPI 256
SPF algorithm executed 3 times
Number of LSA 8. Checksum Sum 0x0462B5
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0
Area 4
Number of interfaces in this area is 1
SPF algorithm executed 2 times
Number of LSA 5. Checksum Sum 0x016A26
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0

By default, because IPv6 uses built-in IPsec functions, Cisco IOS software

https://t.me/learningnets

automatically creates IPsec policies for the configured authentication. The policy can be viewed using the **show crypto ipsec sa [interface <name>]** command on the router(s). Authentication Header (AH) is used. If you configure encryption, then Encapsulating Security Payload (ESP) will be used instead. Check the relevant SA states based on your configuration:

R4#**show crypto ipsec sa interface tunnel 0**

interface: Tunnel0
Crypto map tag: (none), local addr FE80::A00:E

IPsecv6 policy name: OSPFv3-4-256
IPsecv6-created ACL name: Tunnel0-ipsecv6-ACL

protected vrf: (none)
local ident (addr/mask/prot/port): (FE80::/10/89/0)
remote ident (addr/mask/prot/port): (::/0/89/0)
current_peer :: port 500
PERMIT, flags={origin_is_acl,}
#pkts encaps: 18, #pkts encrypt: 0, #pkts digest: 18
#pkts decaps: 18, #pkts decrypt: 0, #pkts verify: 18
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts compr. failed: 0
#pkts not decompressed: 0, #pkts decompress failed: 0
#send errors 0, #recv errors 0

local crypto endpt.: FE80::A00:E, remote crypto endpt.: ::
path mtu 1514, ip mtu 1514, ip mtu idb Tunnel0
current outbound spi: 0x100(256)

inbound esp sas:

inbound ah sas:
spi: 0x100(256)
transform: ah-sha-hmac ,
in use settings ={Transport, }
conn id: 2001, flow_id: SW:1, crypto map: (none)
no sa timing
replay detection support: N
Status: ACTIVE

inbound pcp sas:

outbound esp sas:

outbound ah sas:

https://t.me/learningnets

spi: 0x100(256)
transform: ah-sha-hmac ,
in use settings ={Transport, }
conn id: 2002, flow_id: SW:2, crypto map: (none)
no sa timing
replay detection support: N
Status: ACTIVE

outbound pcp sas:

Additionally, you can also view the configuration parameters for the applied policy using the **show crypto ipsec policy** command on the router. The policy name, by default, will be OSPFv3-<process ID>-<SPI>. For example, on R1, the applied policy name will be OSPFv3-4-256. This is validated and illustrated in the following output:

R4#**show crypto ipsec policy**
Crypto IPsec client security policy data

Policy name: OSPFv3-4-256
Policy refcount: 1
Inbound AH SPI: 256 (0x100)
Outbound AH SPI: 256 (0x100)
Inbound AH Key: 1234567890ABCDEF1234567890ABCDEF12345678
Outbound AH Key: 1234567890ABCDEF1234567890ABCDEF12345678
Transform set: ah-sha-hmac

https://t.me/learningnets

CCNP Lab 050: IPv6 Tunnels and Security Lab

Lab Objective:

The focus of this lab is to understand tunneling implementation and configuration in Cisco IOS routers. Additional technologies include tunnel security.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on the all routers as illustrated in the network topology.

Task 2

In preparation for 6to4 tunnel, configure the following Loopback 0 interfaces on all routers:

https://t.me/learningnets

R1: Loopback 0 - IP Address 1.1.1.1/32
R2: Loopback 0 - IP Address 2.2.2.2/32
R3: Loopback 0 - IP Address 3.3.3.3/32
R4: Loopback 0 - IP Address 4.4.4.4/32

Task 3

Enable OSPF on all router WAN and Loopback interfaces. Verify your OSPF configuration using the appropriate commands.

Task 4

Configure 6to4 prefixes on the LAN interfaces of all routers. Use the Loopback 0 IP address to complete the 48-bit global prefix. The router number should complete the next 16-bits, for a complete 64-bit site prefix. Verify your IPv6 configuration using the appropriate commands.

Task 5

Configure 6to4 tunnels on all routers. Ensure that all routers can ping each other LAN-to-LAN.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic IPv4 and Loopback interface configuration. This will not be included in this section to avoid being redundant.

Task 3

R1(config)#**router ospf 1**
R1(config-router)#**network 0.0.0.0 255.255.255.255 area 0**
R1(config-router)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**network 0.0.0.0 255.255.255.255 area 0**
R2(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**network 0.0.0.0 255.255.255.255 area 0**
R3(config-router)#**exit**

R4(config)#**router ospf 4**

https://t.me/learningnets

R4(config-router)#**network 0.0.0.0 255.255.255.255 area 0**
R4(config-router)#**exit**

Verify basic OSPF configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:34 10.0.0.6 Serial0/1
2.2.2.2 0 FULL/ - 00:00:39 10.0.0.2 Serial0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:00:31 10.0.0.1 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:31 10.0.0.14 Serial1/2
1.1.1.1 0 FULL/ - 00:00:38 10.0.0.5 Serial1/0

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:38 10.0.0.13 Serial0/0

Finally, verify that all routing information is correct using the **show ip route** command:

R1#**show ip route ospf**
2.0.0.0/32 is subnetted, 1 subnets
O 2.2.2.2 [110/65] via 10.0.0.2, 00:02:19, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
O 3.3.3.3 [110/65] via 10.0.0.6, 00:02:19, Serial0/1
4.0.0.0/32 is subnetted, 1 subnets
O 4.4.4.4 [110/846] via 10.0.0.6, 00:02:19, Serial0/1
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.12 [110/845] via 10.0.0.6, 00:02:19, Serial0/1

R2#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O 1.1.1.1 [110/65] via 10.0.0.1, 00:02:21, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
O 3.3.3.3 [110/129] via 10.0.0.1, 00:02:21, Serial0/0
4.0.0.0/32 is subnetted, 1 subnets
O 4.4.4.4 [110/910] via 10.0.0.1, 00:02:21, Serial0/0
10.0.0.0/30 is subnetted, 3 subnets

https://t.me/learningnets

O 10.0.0.12 [110/909] via 10.0.0.1, 00:02:21, Serial0/0
O 10.0.0.4 [110/128] via 10.0.0.1, 00:02:21, Serial0/0

R3#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O 1.1.1.1 [110/782] via 10.0.0.5, 00:02:24, Serial1/0
2.0.0.0/32 is subnetted, 1 subnets
O 2.2.2.2 [110/846] via 10.0.0.5, 00:02:24, Serial1/0
4.0.0.0/32 is subnetted, 1 subnets
O 4.4.4.4 [110/782] via 10.0.0.14, 00:02:24, Serial1/2
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.0 [110/845] via 10.0.0.5, 00:02:24, Serial1/0

R4#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O 1.1.1.1 [110/846] via 10.0.0.13, 00:02:16, Serial0/0
2.0.0.0/32 is subnetted, 1 subnets
O 2.2.2.2 [110/910] via 10.0.0.13, 00:02:16, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
O 3.3.3.3 [110/65] via 10.0.0.13, 00:02:16, Serial0/0
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.0 [110/909] via 10.0.0.13, 00:02:16, Serial0/0
O 10.0.0.4 [110/845] via 10.0.0.13, 00:02:16, Serial0/0

Task 4

Unlike static tunnel configuration, 6to4 tunneling has three main characteristics, which make it unique from static tunnel implementation. These characteristics are:

- Automatic or Dynamic Tunneling
- Automatic Prefix Assignment
- There is no IPv6 Route Propagation

6to4 automatic tunneling provides a dynamic method to deploy tunnels between IPv6 sites over IPv4 networks. Unlike with manually configured tunnels, there is no need to manually configure tunnel source and destination addresses to establish the tunnels. Instead, the tunneling of IPv6 packets between 6to4 sites is performed dynamically based on the destination IPv6 address of the packets originated by IPv6 hosts. These packets are then encapsulated in IPv4 and IPv4 routing protocols are used to transport the packets between the source and destination hosts.

Automatic prefix assignment provides a global aggregate IPv6 prefix to each 6to4 site

https://t.me/learningnets

Technet24

which is based on the 2002::/16 prefix assigned by IANA for 6to4 sites. As stated earlier in this section, the tunnel endpoint, or destination is determined by the globally unique IPv4 address embedded in a 6to4 address. This address must be an address that is globally routable. In other words, RFC 1918 (private IP addresses) cannot be used for 6to4 tunnels because they are not unique. This 32-bit IPv4 address is converted to Hexadecimal and the final representation is a 48-bit prefix. For example, if the IP address 1.1.1.1 was embedded into the IPv6 6to4 prefix, the final representation would be 2002:0101:0101::/48.

And finally, 6to4 tunneling uses special addresses which are a combination of the unique IPv6 routing prefix 2002::/16 and a globally unique 32-bit IPv4 address. With 6to4 tunneling, the tunnel endpoint (destination) is determined by the globally unique IPv4 address embedded in the 6to4 address. Because 6to4 prefixes are based on unique IPv4 address, the 48-bit IPv6 routes do not need to be propagated between 6to4 sites.

Given this understanding, this task is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ipv6 address 2002:101:101:1::1/64**
R1(config-if)#**exit**

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ipv6 address 2002:202:202:2::2/64**
R2(config-if)#**exit**

R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ipv6 address 2002:303:303:3::3/64**
R3(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ipv6 address 2002:404:404:4::4/64**
R4(config-if)#**exit**

Verify your configuration using the **show ipv6 interface** command on all routers:

R1#**show ipv6 interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::20F:23FF:FE5E:EC80
Global unicast address(es):
2002:101:101:1::1, subnet is 2002:101:101:1::/64
Joined group address(es):
FF02::1
FF02::2
FF02::1:FF00:1

https://t.me/learningnets

FF02::1:FF5E:EC80
MTU is 1500 bytes

[Truncated Output]

R2#**show ipv6 interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::20D:28FF:FE9E:F940
Global unicast address(es):
2002:202:202:2::2, subnet is 2002:202:202:2::/64
Joined group address(es):
FF02::1
FF02::2
FF02::1:FF00:2
FF02::1:FF9E:F940
MTU is 1500 bytes

[Truncated Output]

R3#**show ipv6 interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::213:7FFF:FEAF:3E00
Global unicast address(es):
2002:303:303:3::3, subnet is 2002:303:303:3::/64
Joined group address(es):
FF02::1
FF02::2
FF02::1:FF00:3
FF02::1:FFAF:3E00
MTU is 1500 bytes

[Truncated Output]

R4#**show ipv6 interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::20F:23FF:FE5E:F120
Global unicast address(es):
2002:404:404:4::4, subnet is 2002:404:404:4::/64
3FFE:ABCD:1111:4::4, subnet is 3FFE:ABCD:1111:4::/64
Joined group address(es):
FF02::1
FF02::2
FF02::1:FF00:4

https://t.me/learningnets

Technet24

FF02::1:FF5E:F120
MTU is 1500 bytes

Task 5

The configuration of 6to4 tunneling in Cisco IOS software is somewhat similar to that of static tunnels with the exception that no static tunnel destinations are configured. The following sequence of configuration steps is required to implement 6to4 tunneling in Cisco IOS software:

- Configure an IPv6 address on the internal (inside) 6to4 site interface. This is typically the LAN interface to which IPv6 hosts are connected. This is configured using the ipv6 address [address/prefix-length] interface configuration command. When you configure the site prefix, it must come from the 2002::/16 range
- Configure a static tunnel interface using the interface tunnel [number] global configuration command. The number range will vary depending on the version of Cisco IOS software that the router on which the tunnel is being configured is running
- Configure a tunnel source for the static tunnel using the tunnel source [IPv4 address | interface] interface configuration command. This is used as the tunnel source address. All packets sent across this tunnel will have this IPv4 address as the source address included in the IPv4 packet header. This is typically a Loopback interface but can be any interface with a globally routable IPv4 address
- Configure the tunnel interface as an unnumbered interface that will use the IPv6 address of the inside (internal) 6to4 site interface using the ipv6 unnumbered [interface name] interface configuration command
- Specify IPv6 as the passenger protocol and IPv4 as both the encapsulation and transport protocol for the dynamic IPv6 tunnel and specify 6to4 operation using the tunnel mode ipv6ip 6to4 interface configuration command
- Configure a static route to remote 6to4 IPv6 subnets across the tunnel interface using the ipv6 route <prefix/length> tunnel <number> global configuration command

Following these guidelines, this task is completed as follows:

R1(config)#**interface tunnel 0**
R1(config-if)#**ipv6 unnumbered fastethernet 0/0**
R1(config-if)#**tunnel source loopback 0**
R1(config-if)#**tunnel mode ipv6ip 6to4**

https://t.me/learningnets

R1(config-if)#**exit**
R1(config)#**ipv6 route 2002::/16 tunnel 0**
R1(config)#**exit**

R2(config)#**interface tunnel 0**
R2(config-if)#**ipv6 unnumbered fastethernet 0/0**
R2(config-if)#**tunnel source loopback 0**
R2(config-if)#**tunnel mode ipv6ip 6to4**
R2(config-if)#**exit**
R2(config)#**ipv6 route 2002::/16 tunnel 0**
R2(config)#**exit**

R3(config)#**interface tunnel 0**
R3(config-if)#**ipv6 unnumbered fastethernet 0/0**
R3(config-if)#**tunnel source loopback 0**
R3(config-if)#**tunnel mode ipv6ip 6to4**
R3(config-if)#**exit**
R3(config)#**ipv6 route 2002::/16 tunnel 0**
R3(config)#**exit**

R4(config)#**interface tunnel 0**
R4(config-if)#**ipv6 unnumbered fastethernet 0/0**
R4(config-if)#**tunnel source loopback 0**
R4(config-if)#**tunnel mode ipv6ip 6to4**
R4(config-if)#**exit**
R4(config)#**ipv6 route 2002::/16 tunnel 0**
R4(config)#**exit**

Following this, verify 6to4 tunnel configuration using the **show interfaces** command:

R1#**show interfaces tunnel 0**
Tunnel0 is up, line protocol is up
Hardware is Tunnel
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 1.1.1.1 (Loopback0), destination UNKNOWN
Tunnel protocol/transport IPv6 6to4

Fast tunneling enabled
Tunnel transmit bandwidth 8000 (kbps)
Tunnel receive bandwidth 8000 (kbps)

https://t.me/learningnets

Technet24

Last input never, output 00:03:39, output hang never
Last clearing of "show interface" counters never
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: fifo
Output queue: 0/0 (size/max)

[Truncated Output]

Finally, complete this task by pinging LAN-to-LAN between all routers:

R1#**ping 2002:202:202:2::2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:202:202:2::2, timeout is 2 seconds:
Packet sent with a source address of 2002:101:101:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 4/4/4 ms

R1#**ping 2002:303:303:3::3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:303:303:3::3, timeout is 2 seconds:
Packet sent with a source address of 2002:101:101:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/19/20 ms

R1#**ping 2002:404:404:4::4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:404:404:4::4, timeout is 2 seconds:
Packet sent with a source address of 2002:101:101:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 32/35/36 ms

R2#**ping 2002:101:101:1::1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:101:101:1::1, timeout is 2 seconds:
Packet sent with a source address of 2002:202:202:2::2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 0/3/4 ms

R2#**ping 2002:303:303:3::3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:303:303:3::3, timeout is 2 seconds:
Packet sent with a source address of 2002:202:202:2::2

https://t.me/learningnets

!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 20/20/20 ms

R2#**ping 2002:404:404:4::4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:404:404:4::4, timeout is 2 seconds:
Packet sent with a source address of 2002:202:202:2::2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 36/36/36 ms

R3#**ping 2002:101:101:1::1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:101:101:1::1, timeout is 2 seconds:
Packet sent with a source address of 2002:303:303:3::3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/18/20 ms

R3#**ping 2002:202:202:2::2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:202:202:2::2, timeout is 2 seconds:
Packet sent with a source address of 2002:303:303:3::3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 20/20/20 ms

R3#**ping 2002:404:404:4::4 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:404:404:4::4, timeout is 2 seconds:
Packet sent with a source address of 2002:303:303:3::3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/18/20 ms

R4#**ping 2002:101:101:1::1 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:101:101:1::1, timeout is 2 seconds:
Packet sent with a source address of 2002:404:404:4::4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 32/35/36 ms

R4#**ping 2002:202:202:2::2 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:202:202:2::2, timeout is 2 seconds:

https://t.me/learningnets

Technet24

Packet sent with a source address of 2002:404:404:4::4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 36/39/56 ms

R4#**ping 2002:303:303:3::3 source fastethernet 0/0 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 2002:303:303:3::3, timeout is 2 seconds:
Packet sent with a source address of 2002:404:404:4::4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 20/20/20 ms

https://t.me/learningnets

CCNP Lab 051: IPv6 Tunnels and MP-BGP Lab

Lab Objective:

The focus of this lab is to understand tunneling implementation and configuration in Cisco IOS routers. Additional technologies include Multi-Protocol Border Gateway Protocol (MP-BGP).

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Enable EIGRP on all routers as illustrated in the topology. Verify your EIGRP

https://t.me/learningnets

configuration.

Task 3

Configure automatic IPv4-compatible tunnels on R1 and R4. The tunnel source interface should be configured as the WAN interface. Verify the configuration using the appropriate commands.

Task 4

Enable MP-BGP between R1 and R4 using AS 254 and advertise the LAN subnets connected to R1 and R4. Use the WAN interface addresses to complete the 128-bit IPv6 addresses that will be used for peering. Verify that you can ping LAN-to-LAN between R1 and R4.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

R1(config)#**router eigrp 254**
R1(config-router)#**no auto-summary**
R1(config-router)#**network 10.0.0.0**
R1(config-router)#**exit**

R2(config)#**router eigrp 254**
R2(config-router)#**no auto-summary**
R2(config-router)#**network 10.0.0.0**
R2(config-router)#**exit**

R3(config)#**router eigrp 254**
R3(config-router)#**no auto-summary**
R3(config-router)#**network 10.0.0.0**
R3(config-router)#**exit**

R4(config)#**router eigrp 254**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 10.0.0.0**
R4(config-router)#**exit**

Verify your EIGRP configuration using the **show ip eigrp neighbors** command:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254

https://t.me/learningnets

Technet24

H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.2 Se0/0 12 00:01:31 5 200 0 8

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.10 Se0/1 10 00:01:28 9 300 0 3
0 10.0.0.1 Se0/0 12 00:01:34 2 200 0 3

R3#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 10.0.0.14 Se1/2 13 00:01:26 12 1140 0 3
0 10.0.0.9 Se1/1 12 00:01:31 12 1140 0 7

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.13 Se0/0 14 00:01:29 14 200 0 7

Task 3

Automatic IPv4-compatible tunnels use a tunnel mode of **ipv6ip auto-tunnel.** The tunnels are configured using only a source interface. The destination is automatically determined based on configured static routes or received MP-BGP updates. This task is completed as follows:

R1(config)#**interface tunnel 0**
R1(config-if)#**tunnel source serial 0/0**
R1(config-if)#**tunnel mode ipv6ip auto-tunnel**
R1(config-if)#**exit**

R4(config)#**interface tunnel 0**
R4(config-if)#**tunnel source serial 0/0**
R4(config-if)#**tunnel mode ipv6ip auto-tunnel**
R4(config-if)#**exit**

Verify your Tunnel status using the **show interfaces** command:

R1#**show interfaces tunnel 0**
Tunnel0 is up, line protocol is up

https://t.me/learningnets

Hardware is Tunnel
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 10.0.0.1 (Serial0/0), destination UNKNOWN
Tunnel protocol/transport IPv6 auto-tunnel

Fast tunneling enabled
Tunnel transmit bandwidth 8000 (kbps)
Tunnel receive bandwidth 8000 (kbps)
Last input 00:00:41, output 00:00:42, output hang never
Last clearing of "show interface" counters never
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: fifo
Output queue: 0/0 (size/max)
5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec
8 packets input, 983 bytes, 0 no buffer
Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
14 packets output, 1375 bytes, 0 underruns
0 output errors, 0 collisions, 0 interface resets
0 unknown protocol drops
0 output buffer failures, 0 output buffers swapped out

Task 4

Automatic IPv4-compatible tunnels enable IPv6 hosts to automatically enable tunnels to other IPv6 hosts across an IPv4 network infrastructure. Unlike 6to4 tunneling, automatic IPv4-compatible tunneling does use the IPv4-compatible IPv6 addresses. Automatic IPv4-compatible tunnels use the IPv6 prefix ::/96. To complete the 128-bit IPv6 address, the low order 32-bits are derived from the IPv4 address. These low-order 32-bits of the source and destination IPv6 addresses represent the source and destination IPv4 addresses of the tunnel endpoints. This task is completed as follows:

R1(config)#**router bgp 254**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**no bgp default ipv4-unicast**
R1(config-router)#**neighbor ::10.0.0.14 remote-as 254**
R1(config-router)#**address-family ipv6 unicast**

https://t.me/learningnets
Technet24

R1(config-router-af)#**neighbor ::10.0.0.14 activate**
R1(config-router-af)#**neighbor ::10.0.0.14 next-hop-self**
R1(config-router-af)#**network 3ffe:abcd:1111:1::/64**
R1(config-router-af)#**exit**
R1(config-router)#**exit**

R4(config)#**router bgp 254**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**no bgp default ipv4-unicast**
R4(config-router)#**neighbor ::10.0.0.1 remote-as 254**
R4(config-router)#**address-family ipv6 unicast**
R4(config-router-af)#**neighbor ::10.0.0.1 activate**
R4(config-router-af)#**neighbor ::10.0.0.1 next-hop-self**
R4(config-router-af)#**network 3ffe:abcd:1111:4::/64**
R4(config-router-af)#**exit**
R4(config-router)#**exit**

Verify MP-BGP configuration using the **show bgp ipv6 unicast summary** command:

R1#**show bgp ipv6 unicast summary**
BGP router identifier 1.1.1.1, local AS number 254
BGP table version is 3, main routing table version 3
2 network entries using 298 bytes of memory
2 path entries using 152 bytes of memory
3/2 BGP path/bestpath attribute entries using 372 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 822 total bytes of memory
BGP activity 3/1 prefixes, 3/1 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
::10.0.0.14 4 254 4 4 3 0 0 00:00:36 1

R4#**show bgp ipv6 unicast summary**
BGP router identifier 4.4.4.4, local AS number 254
BGP table version is 3, main routing table version 3
2 network entries using 298 bytes of memory
2 path entries using 152 bytes of memory
3/2 BGP path/bestpath attribute entries using 372 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 822 total bytes of memory

https://t.me/learningnets

BGP activity 3/1 prefixes, 3/1 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
::10.0.0.1 4 254 5 5 3 0 0 00:01:24 1

Next, verify the BGP RIB entries using the **show bgp ipv6 unicast** command:

R1#**show bgp ipv6 unicast**
BGP table version is 3, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 3FFE:ABCD:1111:1::/64
:: 0 32768 i
*>i3FFE:ABCD:1111:4::/64
::10.0.0.14 0 100 0 i

R4#**show bgp ipv6 unicast**
BGP table version is 3, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i3FFE:ABCD:1111:1::/64
::10.0.0.1 0 100 0 i
*> 3FFE:ABCD:1111:4::/64
:: 0 32768 i

Finally, complete the task by pinging LAN-to-LAN between R1 and R4:

R1#**ping 3FFE:ABCD:1111:4::4 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:4::4, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 404/407/408 ms

R4#**ping 3FFE:ABCD:1111:1::1 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:1::1, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:4::4
!!!!!!!!!!

https://t.me/learningnets

Technet24

Success rate is 100 percent (10/10), round-trip min/avg/max = 404/407/412 ms

https://t.me/learningnets

CCNP Lab 052: IPv6 Tunnels and MP-BGP Lab

Lab Objective:

The focus of this lab is to understand tunneling implementation and configuration in Cisco IOS routers. Additional technologies include Multi-Protocol Border Gateway Protocol (MP-BGP).

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology. Next, configure the following Loopback 0 interfaces on all routers:

R1: Loopback 0 - IP Address 1.1.1.1/32
R2: Loopback 0 - IP Address 2.2.2.2/32
R3: Loopback 0 - IP Address 3.3.3.3/32

https://t.me/learningnets

R4: Loopback 0 - IP Address 4.4.4.4/32

Task 2

Enable OSPF on all routers as illustrated in the topology. Advertise the Loopback 0 interfaces via OSPF as Type 2 External LSAs. Verify your OSPF configuration.

Task 3

Configure ISATAP tunnels on all routers. Use the Loopback 0 interface as the tunnel source. The tunnels should be configured using the fec0:abcd:1234:1::/64 subnet. Verify your configuration using the appropriate commands.

Task 4

Configure MP-BGP on all routers. All routers should use their ISATAP tunnel addresses for peering. Ensure that all routers advertise their LAN subnet via MP-BGP. MP-BGP peering should be configured on all routers as follows:
R1 - Autonomous System 1: This router will peer with R2
R2 - Autonomous System 2: This router will peer with R1 and R2
R3 - Autonomous System 3: This router will peer with R2 and R4
R4 - Autonomous System 4: This router will peer with R3

Verify your MP-BGP configuration using the appropriate commands.

Task 5

Ensure that all routers can ping each other LAN-to-LAN. Use the extended ping function for verification. Every router should be able to ping every other routers' LAN subnet without additional configuration. If not, check the configuration implemented in the previous lab tasks.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic OSPF configuration. Following this, verify your OSPF configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:39 10.0.0.2 Serial0/0

R2#**show ip ospf neighbor**

https://t.me/learningnets

Technet24

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:35 10.0.0.10 Serial0/1
1.1.1.1 0 FULL/ - 00:00:35 10.0.0.1 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:31 10.0.0.14 Serial1/2
2.2.2.2 0 FULL/ - 00:00:33 10.0.0.9 Serial1/1

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:38 10.0.0.13 Serial0/0

Next, verify that all routing information is correct using the **show ip route** command:

R1#**show ip route ospf**
2.0.0.0/32 is subnetted, 1 subnets
O E2 2.2.2.2 [110/20] via 10.0.0.2, 00:01:32, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
O E2 3.3.3.3 [110/20] via 10.0.0.2, 00:01:32, Serial0/0
4.0.0.0/32 is subnetted, 1 subnets
O E2 4.4.4.4 [110/20] via 10.0.0.2, 00:01:32, Serial0/0
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.8 [110/128] via 10.0.0.2, 00:01:32, Serial0/0
O 10.0.0.12 [110/909] via 10.0.0.2, 00:01:32, Serial0/0

R2#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O E2 1.1.1.1 [110/20] via 10.0.0.1, 00:01:35, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
O E2 3.3.3.3 [110/20] via 10.0.0.10, 00:01:35, Serial0/1
4.0.0.0/32 is subnetted, 1 subnets
O E2 4.4.4.4 [110/20] via 10.0.0.10, 00:01:35, Serial0/1
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.12 [110/845] via 10.0.0.10, 00:01:36, Serial0/1

R3#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O E2 1.1.1.1 [110/20] via 10.0.0.9, 00:01:39, Serial1/1
2.0.0.0/32 is subnetted, 1 subnets
O E2 2.2.2.2 [110/20] via 10.0.0.9, 00:01:39, Serial1/1
4.0.0.0/32 is subnetted, 1 subnets

https://t.me/learningnets

O E2 4.4.4.4 [110/20] via 10.0.0.14, 00:01:39, Serial1/2
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.0 [110/845] via 10.0.0.9, 00:01:39, Serial1/1

R4#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O E2 1.1.1.1 [110/20] via 10.0.0.13, 00:01:42, Serial0/0
2.0.0.0/32 is subnetted, 1 subnets
O E2 2.2.2.2 [110/20] via 10.0.0.13, 00:01:42, Serial0/0
3.0.0.0/32 is subnetted, 1 subnets
O E2 3.3.3.3 [110/20] via 10.0.0.13, 00:01:42, Serial0/0
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.8 [110/845] via 10.0.0.13, 00:01:42, Serial0/0
O 10.0.0.0 [110/909] via 10.0.0.13, 00:01:42, Serial0/0

Task 3

R1(config)#**interface tunnel 0**
R1(config-if)#**tunnel source loopback 0**
R1(config-if)#**ipv6 address fec0:abcd:1234:1::/64 eui-64**
R1(config-if)#**tunnel mode ipv6ip isatap**
R1(config-if)#**no ipv6 nd ra suppress**
R1(config-if)#**exit**

R2(config)#**interface tunnel 0**
R2(config-if)#**tunnel source loopback 0**
R2(config-if)#**ipv6 address fec0:abcd:1234:1::/64 eui-64**
R2(config-if)#**tunnel mode ipv6ip isatap**
R2(config-if)#**no ipv6 nd ra suppress**
R2(config-if)#**exit**

R3(config)#**interface tunnel 0**
R3(config-if)#**tunnel source loopback 0**
R3(config-if)#**ipv6 address fec0:abcd:1234:1::/64 eui-64**
R3(config-if)#**tunnel mode ipv6ip isatap**
R3(config-if)#**no ipv6 nd ra suppress**
R3(config-if)#**exit**

R4(config)#**interface tunnel 0**
R4(config-if)#**tunnel source loopback 0**
R4(config-if)#**ipv6 address fec0:abcd:1234:1::/64 eui-64**
R4(config-if)#**tunnel mode ipv6ip isatap**
R4(config-if)#**no ipv6 nd ra suppress**

https://t.me/learningnets

R4(config-if)#**exit**

Verify ISATAP tunnel status and configuration using the **show interfaces** command:

R1#**show interfaces tunnel 0**
Tunnel0 is up, line protocol is up
Hardware is Tunnel
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 1.1.1.1 (Loopback0), destination UNKNOWN
Tunnel protocol/transport IPv6 ISATAP
Fast tunneling enabled
Tunnel transmit bandwidth 8000 (kbps)
Tunnel receive bandwidth 8000 (kbps)
Last input never, output 00:05:21, output hang never
Last clearing of "show interface" counters never
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: fifo
Output queue: 0/0 (size/max)
5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec
0 packets input, 0 bytes, 0 no buffer
Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
4 packets output, 384 bytes, 0 underruns
0 output errors, 0 collisions, 0 interface resets
0 unknown protocol drops
0 output buffer failures, 0 output buffers swapped out

Verify ISATAP IPv6 addressing using the **show ipv6 interface** command:

R1#**show ipv6 interface tunnel 0**
Tunnel0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::5EFE:101:101
Global unicast address(es):
FEC0:ABCD:1234:1:0:5EFE:101:101, subnet is FEC0:ABCD:1234:1::/64 [EUI]
Joined group address(es):
FF02::1
FF02::2

https://t.me/learningnets

FF02::1:FF01:101
MTU is 1480 bytes
ICMP error messages limited to one every 100 milliseconds
ICMP redirects are enabled
ND DAD is not supported
ND reachable time is 30000 milliseconds
ND advertised reachable time is 0 milliseconds
ND advertised retransmit interval is 0 milliseconds
ND router advertisements live for 1800 seconds
Hosts use stateless autoconfig for addresses.

Task 4

R1(config)#**router bgp 1**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**address-family ipv6**
R1(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:202:202 remote-as 2**
R1(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:202:202 activate**
R1(config-router-af)#**network 3FFE:ABCD:1111:1::/64**
R1(config-router-af)#**exit-address-family**
R1(config-router)#**exit**

R2(config)#**router bgp 2**
R2(config-router)#**bgp router-id 2.2.2.2**
R2(config-router)#**address-family ipv6**
R2(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:101:101 remote-as 1**
R2(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:101:101 activate**
R2(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:303:303 remote-as 3**
R2(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:303:303 activate**
R2(config-router-af)#**network 3FFE:ABCD:1111:2::/64**
R2(config-router-af)#**exit-address-family**
R2(config-router)#**exit**

R3(config)#**router bgp 3**
R3(config-router)#**bgp router-id 3.3.3.3**
R3(config-router)#**address-family ipv6**
R3(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:202:202 remote-as 2**
R3(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:202:202 activate**
R3(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:404:404 remote-as 4**
R3(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:404:404 activate**
R3(config-router-af)#**network 3FFE:ABCD:1111:3::/64**

https://t.me/learningnets
Technet24

R3(config-router-af)#**exit-address-family**
R3(config-router)#**exit**

R4(config)#**router bgp 4**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**address-family ipv6**
R4(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:303:303 remote-as 3**
R4(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:303:303 activate**
R4(config-router-af)#**network 3FFE:ABCD:1111:4::/64**
R4(config-router-af)#**exit-address-family**
R4(config-router)#**exit**

Verify MP-BGP configuration using the **show bgp ipv6 unicast summary** command:

R1#**show bgp ipv6 unicast summary**
BGP router identifier 1.1.1.1, local AS number 1
BGP table version is 5, main routing table version 5
4 network entries using 596 bytes of memory
4 path entries using 304 bytes of memory
5/4 BGP path/bestpath attribute entries using 620 bytes of memory
3 BGP AS-PATH entries using 72 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1592 total bytes of memory
BGP activity 4/0 prefixes, 4/0 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
FEC0:ABCD:1234:1:0:5EFE:202:202
4 2 16 14 5 0 0 00:10:15 3

R2#**show bgp ipv6 unicast summary**
BGP router identifier 2.2.2.2, local AS number 2
BGP table version is 6, main routing table version 6
4 network entries using 596 bytes of memory
4 path entries using 304 bytes of memory
5/4 BGP path/bestpath attribute entries using 620 bytes of memory
3 BGP AS-PATH entries using 72 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1592 total bytes of memory
BGP activity 4/0 prefixes, 4/0 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd

https://t.me/learningnets

FEC0:ABCD:1234:1:0:5EFE:101:101
4 1 14 16 6 0 0 00:10:19 1
FEC0:ABCD:1234:1:0:5EFE:303:303
4 3 10 10 6 0 0 00:02:32 2

R3#**show bgp ipv6 unicast summary**
BGP router identifier 3.3.3.3, local AS number 3
BGP table version is 6, main routing table version 6
4 network entries using 596 bytes of memory
4 path entries using 304 bytes of memory
5/4 BGP path/bestpath attribute entries using 620 bytes of memory
3 BGP AS-PATH entries using 72 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1592 total bytes of memory
BGP activity 4/0 prefixes, 4/0 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
FEC0:ABCD:1234:1:0:5EFE:202:202
4 2 10 10 6 0 0 00:02:37 2
FEC0:ABCD:1234:1:0:5EFE:404:404
4 4 5 8 6 0 0 00:00:58 1

R4#**show bgp ipv6 unicast summary**
BGP router identifier 4.4.4.4, local AS number 4
BGP table version is 5, main routing table version 5
4 network entries using 596 bytes of memory
4 path entries using 304 bytes of memory
5/4 BGP path/bestpath attribute entries using 620 bytes of memory
3 BGP AS-PATH entries using 72 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1592 total bytes of memory
BGP activity 4/0 prefixes, 4/0 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
FEC0:ABCD:1234:1:0:5EFE:303:303
4 3 9 6 5 0 0 00:01:02 3

Finally, verify that all routers have the LAN subnets in their MP-BGP RIB Tables:

R1#**show bgp ipv6 unicast**
BGP table version is 5, local router ID is 1.1.1.1

https://t.me/learningnets

Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 3FFE:ABCD:1111:1::/64
:: 0 32768 i
***> 3FFE:ABCD:1111:2::/64**
FEC0:ABCD:1234:1:0:5EFE:202:202
0 0 2 i
***> 3FFE:ABCD:1111:3::/64**
FEC0:ABCD:1234:1:0:5EFE:303:303
0 2 3 i
***> 3FFE:ABCD:1111:4::/64**
FEC0:ABCD:1234:1:0:5EFE:404:404
0 2 3 4 i

R2#**show bgp ipv6 unicast**
BGP table version is 6, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
***> 3FFE:ABCD:1111:1::/64**
FEC0:ABCD:1234:1:0:5EFE:101:101
0 0 1 i
*> 3FFE:ABCD:1111:2::/64
:: 0 32768 i
***> 3FFE:ABCD:1111:3::/64**
FEC0:ABCD:1234:1:0:5EFE:303:303
0 0 3 i
***> 3FFE:ABCD:1111:4::/64**
FEC0:ABCD:1234:1:0:5EFE:404:404
0 3 4 i

R3#**show bgp ipv6 unicast**
BGP table version is 6, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

https://t.me/learningnets

Network Next Hop Metric LocPrf Weight Path
***> 3FFE:ABCD:1111:1::/64**
FEC0:ABCD:1234:1:0:5EFE:101:101
0 2 1 i
***> 3FFE:ABCD:1111:2::/64**
FEC0:ABCD:1234:1:0:5EFE:202:202
0 0 2 i
*> 3FFE:ABCD:1111:3::/64
:: 0 32768 i
***> 3FFE:ABCD:1111:4::/64**
FEC0:ABCD:1234:1:0:5EFE:404:404
0 0 4 i

R4#**show bgp ipv6 unicast**
BGP table version is 5, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
***> 3FFE:ABCD:1111:1::/64**
FEC0:ABCD:1234:1:0:5EFE:101:101
0 3 2 1 i
***> 3FFE:ABCD:1111:2::/64**
FEC0:ABCD:1234:1:0:5EFE:202:202
0 3 2 i
***> 3FFE:ABCD:1111:3::/64**
FEC0:ABCD:1234:1:0:5EFE:303:303
0 0 3 i
*> 3FFE:ABCD:1111:4::/64
:: 0 32768 i

Task 5

If you have completed all of the tasks as required, this step will be completed with no issues. Use the extended ping function to ping LAN-to-LAN between routers. With the implemented configuration, all prefixes are advertised and received via BGP, as illustrated in the output of the IPv6 routing table on any one of the routers; the example below showing R1s IPv6 RIB:

R1#**show ipv6 route 3FFE:ABCD:1111:2::/64**
IPv6 Routing Table - 9 entries

https://t.me/learningnets
Technet24

Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
B 3FFE:ABCD:1111:2::/64 [20/0]
via FEC0:ABCD:1234:1:0:5EFE:202:202

However, notice that the NEXT_HOP addresses are the ISATAP tunnel interfaces, which means that the packets are forwarded out of these tunnels across the IPv4 infrastructure:

R1#**show ipv6 route FEC0:ABCD:1234:1:0:5EFE:202:202**
IPv6 Routing Table - 9 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
C FEC0:ABCD:1234:1::/64 [0/0]
via ::, Tunnel0

Complete this last task by using the extended ping function on all routers as follows:

R1#**ping 3FFE:ABCD:1111:2::2 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:2::2, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/17/20 ms

R1#**ping 3FFE:ABCD:1111:3::3 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:3::3, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 212/215/216 ms

R1#**ping 3FFE:ABCD:1111:4::4 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:4::4, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1

https://t.me/learningnets

!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 404/407/408 ms

R2#**ping 3FFE:ABCD:1111:1::1 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:1::1, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:2::2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/18/20 ms

R2#**ping 3FFE:ABCD:1111:3::3 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:3::3, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:2::2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 208/208/212 ms

R2#**ping 3FFE:ABCD:1111:4::4 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:4::4, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:2::2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 400/400/400 ms

R3#**ping 3FFE:ABCD:1111:1::1 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:1::1, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:3::3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 212/215/220 ms

R3#**ping 3FFE:ABCD:1111:2::2 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:2::2, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:3::3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 208/208/208 ms

R3#**ping 3FFE:ABCD:1111:4::4 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:4::4, timeout is 2 seconds:

https://t.me/learningnets

Technet24

Packet sent with a source address of 3FFE:ABCD:1111:3::3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 208/208/208 ms

R4#**ping 3FFE:ABCD:1111:1::1 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:1::1, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:4::4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 404/407/408 ms

R4#**ping 3FFE:ABCD:1111:2::2 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:2::2, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:4::4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 400/400/404 ms

R4#**ping 3FFE:ABCD:1111:3::3 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:3::3, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:4::4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 208/208/208 ms

https://t.me/learningnets

CCNP Lab 053: IPv6 GRE Tunnels and RIPng Lab

Lab Objective:

The focus of this lab is to understand tunneling implementation and configuration in Cisco IOS routers. Additional technologies include RIPng convergence and tunnel operation parameters.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology. Next, configure the following Loopback 0 interfaces on R1 and R4:

R1: Loopback 0 - IP Address 1.1.1.1/32
R4: Loopback 0 - IP Address 4.4.4.4/32

Task 2

https://t.me/learningnets

Enable OSPF on all routers as illustrated in the topology. Advertise the two Loopback 0 interfaces via OSPF as Type 1 External LSAs. Verify your OSPF configuration.

Task 3

Configure GRE tunnels on R1 and R4. Use the Loopback 0 interfaces as the tunnel source and destination addresses. Use an IPv6 subnet of your choosing for the GRE tunnel addressing. Verify your configuration using the appropriate commands and pinging across the GRE tunnel.

Task 4

Configure RIPng across the tunnel interfaces between R1 and R4. Advertise the LAN subnets connected to these routers via RIPng. These prefixes should be received with a metric of 10. You are NOT allowed to use offset lists when completing this task. Verify your configuration using the appropriate commands.

Task 5

To prevent incorrect configuration or injection of packets from a foreign source, secure the GRE tunnel between R1 and R4 using the password '1234'. Additionally, ensure that datagrams received out of sequence are dropped and that checksumming is enabled for both of the tunnel interfaces. Verify your configuration using the appropriate commands.

Task 6

To improve RIPng convergence, configure protocol timers so that updates are sent out every 5 seconds. The updates should expire after 10 seconds and the RIPng garbage collection period should happen after 15 seconds. There should be no hold down interval. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic OSPF configuration. Following this, verify your OSPF configuration using the **show ip ospf neighbor** command:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:39 10.0.0.2 Serial0/0

https://t.me/learningnets

Technet24

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:35 10.0.0.10 Serial0/1
1.1.1.1 0 FULL/ - 00:00:35 10.0.0.1 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:31 10.0.0.14 Serial1/2
2.2.2.2 0 FULL/ - 00:00:33 10.0.0.9 Serial1/1

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:38 10.0.0.13 Serial0/0

Next, verify that all routing information is correct using the **show ip route** command:

R1#**show ip route ospf**
4.0.0.0/32 is subnetted, 1 subnets
O E1 4.4.4.4 [110/929] via 10.0.0.2, 00:00:41, Serial0/0
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.8 [110/128] via 10.0.0.2, 00:05:42, Serial0/0
O 10.0.0.12 [110/909] via 10.0.0.2, 00:05:42, Serial0/0

R2#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O E1 1.1.1.1 [110/84] via 10.0.0.1, 00:01:07, Serial0/0
4.0.0.0/32 is subnetted, 1 subnets
O E1 4.4.4.4 [110/865] via 10.0.0.10, 00:01:14, Serial0/1
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.12 [110/845] via 10.0.0.10, 00:06:08, Serial0/1

R3#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O E1 1.1.1.1 [110/865] via 10.0.0.9, 00:01:22, Serial1/1
4.0.0.0/32 is subnetted, 1 subnets
O E1 4.4.4.4 [110/801] via 10.0.0.14, 00:01:29, Serial1/2
10.0.0.0/30 is subnetted, 3 subnets
O 10.0.0.0 [110/845] via 10.0.0.9, 00:06:19, Serial1/1

R4#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O E1 1.1.1.1 [110/929] via 10.0.0.13, 00:01:34, Serial0/0
10.0.0.0/30 is subnetted, 3 subnets

https://t.me/learningnets

O 10.0.0.8 [110/845] via 10.0.0.13, 00:06:27, Serial0/0
O 10.0.0.0 [110/909] via 10.0.0.13, 00:06:27, Serial0/0

Task 3

NOTE: Because RIPng uses Link-Local addresses as the NEXT HOP address, like other IPv6 IGPs, you do NOT need to actually configure a global Unicast IPv6 address on the tunnel. However, this is included only as a recommended practice.

R1(config)#**interface tunnel 0**
R1(config-if)#**ipv6 address 2002:abcd:1111:a::1/64**
R1(config-if)#**tunnel source loopback 0**
R1(config-if)#**tunnel destination 4.4.4.4**
R1(config-if)#**tunnel mode gre ip**
R1(config-if)#**exit**

R4(config)#**interface tunnel 0**
R4(config-if)#**ipv6 address 2002:abcd:1111:a::4/64**
R4(config-if)#**tunnel source loopback 0**
R4(config-if)#**tunnel destination 1.1.1.1**
R4(config-if)#**tunnel mode gre ip**
R4(config-if)#**exit**

Verify the tunnel configuration using the **show interfaces** command:

R1#**show interfaces tunnel 0**
Tunnel0 is up, line protocol is up
Hardware is Tunnel
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 1.1.1.1 (Loopback0), destination 4.4.4.4
Tunnel protocol/transport GRE/IP
Key disabled, sequencing disabled
Checksumming of packets disabled
Tunnel TTL 255
Fast tunneling enabled
Tunnel transmit bandwidth 8000 (kbps)
Tunnel receive bandwidth 8000 (kbps)

[Truncated Output]
R4#**show interfaces tunnel 0**

https://t.me/learningnets

Technet24

Tunnel0 is up, line protocol is up
Hardware is Tunnel
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 4.4.4.4 (Loopback0), destination 1.1.1.1
Tunnel protocol/transport GRE/IP
Key disabled, sequencing disabled
Checksumming of packets disabled
Tunnel TTL 255
Fast tunneling enabled
Tunnel transmit bandwidth 8000 (kbps)
Tunnel receive bandwidth 8000 (kbps)

Task 4

To complete this task you must redistribute the connected LAN interfaces and assign a route metric of 9. This will ensure that the prefixes are received with a metric of 10 by the remote router. Because only a single interface exists, you do not necessarily need to use a route map when configuring redistribution. This task is completed as follows:

R1(config)#**ipv6 router rip R1-RIP**
R1(config-rtr)#**redistribute connected metric 9**
R1(config-rtr)#**exit**
R1(config)#**interface tunnel 0**
R1(config-if)#**ipv6 rip R1-RIP enable**
R1(config-if)#**exit**

R4(config)#**ipv6 router rip R4-RIP**
R4(config-rtr)#**redistribute connected metric 9**
R4(config-rtr)#**exit**
R4(config)#**interface tunnel 0**
R4(config-if)#**ipv6 rip R4-RIP enable**
R4(config-if)#**exit**

NOTE: The RIPng Tag is locally significant and does NOT need to be the same on all routers. The only parameters that need be the same are the UDP port number and Multicast group.

Verify RIPng routing configuration using the **show ipv6 route** command:

R1#**show ipv6 route rip**

https://t.me/learningnets

IPv6 Routing Table - 7 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R 3FFE:ABCD:1111:4::/64 [120/10]
via FE80::20F:23FF:FE5E:F120, Tunnel0

R4#**show ipv6 route rip**
IPv6 Routing Table - 7 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
R 3FFE:ABCD:1111:1::/64 [120/10]
via FE80::20F:23FF:FE5E:EC80, Tunnel0

Finally, verify that R1 and R4 can ping each other LAN-to-LAN using an extended ping:

R1#**ping 3FFE:ABCD:1111:4::4 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:4::4, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 404/406/408 ms

R4#**ping 3FFE:ABCD:1111:1::1 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:1::1, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:4::4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 404/407/412 ms

Task 5

To complete this task, you must configure a tunnel ID key. The tunnel ID keys can be used as a form of weak security to prevent incorrect configuration or injection of packets from a foreign source. The tunnel ID key has to be the same on both ends. This task is completed as follows:

R1(config)#**interface tunnel 0**

https://t.me/learningnets
Technet24

R1(config-if)#**tunnel key 1234**
R1(config-if)#**tunnel sequence-datagrams**
R1(config-if)#**tunnel checksum**
R1(config-if)#**exit**

R4(config)#**interface tunnel 0**
R4(config-if)#**tunnel key 1234**
R4(config-if)#**tunnel sequence-datagrams**
R4(config-if)#**tunnel checksum**
R4(config-if)#**exit**

Verify your configuration using the **show interfaces** command:

R1#**show interfaces tunnel 0**
Tunnel0 is up, line protocol is up
Hardware is Tunnel
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 1.1.1.1 (Loopback0), destination 4.4.4.4
Tunnel protocol/transport GRE/IP
Key 0x4D2, Order sequence numbers 49/36 (tx/rx)
Checksumming of packets enabled

[Truncated Output]

R4#**show interfaces tunnel 0**
Tunnel0 is up, line protocol is up
Hardware is Tunnel
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 4.4.4.4 (Loopback0), destination 1.1.1.1
Tunnel protocol/transport GRE/IP
Key 0x4D2, Order sequence numbers 35/46 (tx/rx)
Checksumming of packets enabled

[Truncated Output]

Task 6

R1(config)#**ipv6 router rip R1-RIP**

https://t.me/learningnets

R1(config-rtr)#**timers 5 10 0 15**
R1(config-rtr)#**exit**

R4(config)#**ipv6 router rip R4-RIP**
R4(config-rtr)#**timers 5 10 0 15**
R4(config-rtr)#**exit**

Verify your configuration using the **show ipv6 rip <tag>** command:

R1#**show ipv6 rip R1-RIP**
RIP process "R1-RIP", port 521, multicast-group FF02::9, pid 192
Administrative distance is 120. Maximum paths is 16
Updates every 5 seconds, expire after 10
Holddown lasts 0 seconds, garbage collect after 15
Split horizon is on; poison reverse is off
Default routes are not generated
Periodic updates 50, trigger updates 2
Interfaces:
Tunnel0
Redistribution:
Redistributing protocol connected with metric 9

https://t.me/learningnets

Technet24

CCNP Lab 054: Cisco IOS IP SLA and FHRP Lab

Lab Objective:

The focus of this lab is to understand the Cisco IOS IP SLA Operations and FHRP implementation and configuration in Cisco IOS routers. Additional technologies include EOT and preemption.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology. Next, configure the following Loopback 0 interfaces on R2: Loopback 0 - IP Address 2.2.2.2/32

Task 2

Enable EIGRP on the WAN interfaces of all routers as illustrated in the topology. Advertise the FastEthernet 0/0 and Loopback 0 subnet as External routes. Verify your

https://t.me/learningnets

Technet24

EIGRP configuration.

Task 3

Configure HSRP on the LAN segment between R1 and R4. Use a VIP of 150.1.1.254. Configure R1 with a priority of 200 and R4 with a priority of 150. Verify your HSRP configuration.

Task 4

Configure Cisco IOS IP SLA Operations so that when R1 loses the route to the 2.2.2.2/32 prefix, it reduces its HSRP priority such that R4 becomes the primary gateway for the HSRP group. This solution should be configured as follows:

- R1 should open an HTTP (port 80) session to the IP address 2.2.2.2/32 only every 5 seconds
- The connection should be sourced from Serial 0/0
- The IP SLA Operation should have a timeout of 10 seconds
- R1 should wait for 6 secs after a failed Operation to lower the configured HSRP priority
- R1 should wait for 10 secs after the 2.2.2.2/32 prefix is reachable again to become active
- Do NOT use HSRP-specific commands to influence preemption timers
- Use any Cisco IP SLA Operation number and Cisco EOT number of your choice

Verify your configuration using the appropriate commands. Test your solution by disabling the link between R1 and R2 and verify IP SLA and HSRP operation and functionality.

Task 5

Configure VRRP on the LAN segment between R2 and R3. Use a VIP of 150.2.2.254. Configure R2 with a priority of 200 and R3 with a priority of 150. Verify your VRRP configuration.

Task 6

Configure VRRP on R2 so that when the Serial 0/0 interface goes down, the priority will then be lowered so that R3 can become a master router. Verify and test your VRRP configuration.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname

https://t.me/learningnets

configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP
configuration using the **show ip eigrp neighbors** command:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.2 Se0/0 14 00:00:47 4 200 0 6

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.1 Se0/0 11 00:00:49 3 200 0 3

R3#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.14 Se1/2 14 00:00:20 9 1140 0 5

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.13 Se0/0 10 00:00:22 13 200 0 3

Next, verify that all routing information is correct using the **show ip route** command:

R1#**show ip route eigrp**
2.0.0.0/32 is subnetted, 1 subnets
D 2.2.2.2 [90/2297856] via 10.0.0.2, 00:03:43, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
D EX 150.2.2.0 [170/2172416] via 10.0.0.2, 00:03:41, Serial0/0

R2#**show ip route eigrp**
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/2172416] via 10.0.0.1, 00:03:52, Serial0/0

R3#**show ip route eigrp**
150.1.0.0/24 is subnetted, 1 subnets

https://t.me/learningnets
Technet24

D EX 150.1.1.0 [170/20514560] via 10.0.0.14, 00:03:20, Serial1/2

R4#**show ip route eigrp**
150.2.0.0/24 is subnetted, 1 subnets
D EX 150.2.2.0 [170/2172416] via 10.0.0.13, 00:03:25, Serial0/0

Task 3

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**standby 1 ip 150.1.1.254**
R1(config-if)#**standby 1 priority 200**
R1(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**standby 1 ip 150.1.1.254**
R4(config-if)#**standby 1 priority 150**
R4(config-if)#**exit**

Verify HSRP using the **show standby <group> [brief]** command on the two routers. You should keep in mind that, by default, preemption is not enabled for HSRP:

R1#**show stand brief**
P indicates configured to preempt.
|
Interface Grp Prio P State Active Standby Virtual IP
Fa0/0 1 200 Active local 150.1.1.4 150.1.1.254

R4#**show stand brief**
P indicates configured to preempt.
|
Interface Grp Prio P State Active Standby Virtual IP
Fa0/0 1 150 Standby 150.1.1.1 local 150.1.1.254

Task 4

The requirements for this task are three-fold. First, you need to configure the Cisco IOS IP SLA Operation to ping the 2.2.2.2/32 address every 2 seconds. It is important to remember that the default timeout value is 5 seconds (5000 milliseconds). Therefore, you specify a frequency of 2 seconds, you first need to lower the timeout value to a value less than 5000 milliseconds otherwise Cisco IOS software will print out the following error message on the device console:

R1(config-sla-monitor-echo)#frequency 2
%Illegal Value: Cannot set Frequency to be less than Timeout

This first part of this task, i.e. the IP SLA Operation configuration, is completed as

https://t.me/learningnets

follows (note that older IOSs required slightly different commands to configure this such as **ip sla monitor 1**). Your command prompt may also differ:

```
R1(config)#ip sla 1
R1(config-ip-sla)# tcp-connect 2.2.2.2 80 source-ip 10.0.0.1
R1(config-ip-sla-tcp)#timeout 10
R1(config-ip-sla-tcp)#frequency 5
R1(config-ip-sla-tcp)#exit
R1(config)#ip sla schedule 1 start-time now life forever
R1(config)#exit
```

Because R2 is a Cisco IOS device, you must enable RTR | IP SLA Responder on this device:

```
R2(config)#ip sla responder tcpConnect ipaddress 2.2.2.2 port 80
```

Verify the operation statistics using the **show ip sla statistics** command:

```
R1#show ip sla statistics 1
Round trip time (RTT) Index 1
Latest RTT: 8 ms
Latest operation start time: 21:39:36.295 CST Tue May 31 2011
Latest operation return code: OK
Number of successes: 22
Number of failures: 0
Operation time to live: Forever
```

Verify the responder state using the **show ip sla monitor responder** command:

```
R2#show ip sla responder
IP SLA Monitor Responder is: Enabled
Number of control message received: 29 Number of errors: 0
Recent sources:
10.0.0.1 [12:02:07.595 UTC Sun May 15 2011]
10.0.0.1 [12:02:02.595 UTC Sun May 15 2011]
10.0.0.1 [12:01:57.595 UTC Sun May 15 2011]
10.0.0.1 [12:01:52.595 UTC Sun May 15 2011]
10.0.0.1 [12:01:47.595 UTC Sun May 15 2011]
Recent error sources:

tcpConnect Responder:
IP Address Port
2.2.2.2 80
```

The second part of this task requires that you configure Enhanced Object Tracking or

https://t.me/learningnets

Technet24

EOT. Here is where you specify the up and down delay values. Complete this task as follows:

```
R1(config)#track 1 rtr 1 reachability
R1(config-track)#delay down 6
R1(config-track)#delay up 10
R1(config-track)#exit
```

Verify your configuration using the **show track <object number>** command:

```
R1#show track 1
Track 1
Response Time Reporter 1 reachability
Reachability is Up
7 changes, last change 00:05:00
Delay up 10 secs, down 6 secs
Latest operation return code: OK
Latest RTT (millisecs) 8
```

The final requirement of this configuration is to configure HSRP so that preemption is enabled and that the priority of R1 is lowered enough to allow R4 to become the active gateway. This last task is completed as follows:

```
R1(config)#interface fastethernet 0/0
R1(config-if)#standby 1 preempt
R1(config-if)#standby 1 track 1 decrement 51
R1(config-if)#exit
```

```
R4(config)#interface fastethernet 0/0
R4(config-if)#standby 1 preempt
R4(config-if)#exit
```

Verify your configuration using the **show standby** command on both routers:

```
R1#show standby fastethernet 0/0 1
FastEthernet0/0 - Group 1
State is Active
2 state changes, last state change 00:28:58
Virtual IP address is 150.1.1.254
Active virtual MAC address is 0000.0c07.ac01
Local virtual MAC address is 0000.0c07.ac01 (v1 default)
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.456 secs
Preemption enabled
```

https://t.me/learningnets

Active router is local
Standby router is 150.1.1.4, priority 150 (expires in 7.152 sec)
Priority 200 (configured 200)
Track object 1 state Up decrement 51
IP redundancy name is “hsrp-Fa0/0-1” (default)

R4#**show standby fastethernet 0/0 1**
FastEthernet0/0 - Group 1
State is Standby
1 state change, last state change 00:29:12
Virtual IP address is 150.1.1.254
Active virtual MAC address is 0000.0c07.ac01
Local virtual MAC address is 0000.0c07.ac01 (v1 default)
Hello time 3 sec, hold time 10 sec
Next hello sent in 0.000 secs
Preemption enabled
Active router is 150.1.1.1, priority 200 (expires in 8.288 sec)
Standby router is local
Priority 150 (configured 150)
IP redundancy name is “hsrp-Fa0/0-1” (default)

Finally, test your solution by enabling logging and shutting down the R1-R2 link:

R1(config)#**logging consol debugging**
R1(config)#**interface serial 0/0**
R1(config-if)#**shutdown**
R1(config-if)#
R1(config-if)#
R1(config-if)#
Jun 1 02:46:51.175: %DUAL-5-NBRCHANGE: IP-EIGRP(0) 254: Neighbor 10.0.0.2 (Serial0/0) is down: interface down
Jun 1 02:46:53.151: %LINK-5-CHANGED: Interface Serial0/0, changed state to administratively down
Jun 1 02:46:54.151: %LINEPROTO-5-UPDOWN: Line protocol on Interface Serial0/0, changed state to down
Jun 1 02:47:13.495: %TRACKING-5-STATE: 1 rtr 1 reachability Up->Down
Jun 1 02:47:15.551: %HSRP-5-STATECHANGE: FastEthernet0/0 Grp 1 state Active -> Speak
Jun 1 02:47:25.551: %HSRP-5-STATECHANGE: FastEthernet0/0 Grp 1 state Speak -> Standby

https://t.me/learningnets
Technet24

Next, check the HSRP gateway states using the **show standby** command on both routers:

R1#**show standby fastethernet 0/0 1**
FastEthernet0/0 - Group 1
State is Standby
16 state changes, last state change 00:00:31
Virtual IP address is 150.1.1.254
Active virtual MAC address is 0000.0c07.ac01
Local virtual MAC address is 0000.0c07.ac01 (v1 default)
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.808 secs
Preemption enabled
Active router is 150.1.1.4, priority 150 (expires in 7.808 sec)
Standby router is local
Priority 149 (configured 200)
Track object 1 state Down decrement 51
IP redundancy name is "hsrp-Fa0/0-1" (default)

R4#**show standby fastethernet 0/0 1**
FastEthernet0/0 - Group 1
State is Active
14 state changes, last state change 00:00:49
Virtual IP address is 150.1.1.254
Active virtual MAC address is 0000.0c07.ac01
Local virtual MAC address is 0000.0c07.ac01 (v1 default)
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.076 secs
Preemption enabled
Active router is local
Standby router is 150.1.1.1, priority 149 (expires in 9.072 sec)
Priority 150 (configured 150)
IP redundancy name is "hsrp-Fa0/0-1" (default)

Finally, verify your configuration in the reverse direction by bringing up the Serial 0/0 interface:

R1(config)#**logging console debugging**
R1(config)#**interface serial 0/0**
R1(config-if)#**no shutdown**
Jun 1 02:49:50.243: %LINK-3-UPDOWN: Interface Serial0/0, changed state to up
Jun 1 02:49:51.163: %DUAL-5-NBRCHANGE: IP-EIGRP(0) 254: Neighbor 10.0.0.2

https://t.me/learningnets

(Serial0/0) is up: new adjacency
Jun 1 02:49:51.243: %LINEPROTO-5-UPDOWN: Line protocol on Interface Serial0/0, changed state to up
Jun 1 02:50:02.495: %TRACKING-5-STATE: 1 rtr 1 reachability Down->Up
Jun 1 02:50:03.551: %HSRP-5-STATECHANGE: FastEthernet0/0 Grp 1 state Standby -> Active

Task 5

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**vrrp 1 ip 150.2.2.254**
R2(config-if)#**vrrp 1 priority 200**
R2(config-if)#**exit**

R3(config)#**interface fastethernet 0/0**
R3(config-if)#**vrrp 1 ip 150.2.2.254**
R3(config-if)#**vrrp 1 priority 150**
R3(config-if)#**exit**

Verify VRRP configuration using the **show vrrp** command on both routers:

R2#**show vrrp interface fastethernet 0/0 group 1**
FastEthernet0/0 - Group 1
State is Master
Virtual IP address is 150.2.2.254
Virtual MAC address is 0000.5e00.0101
Advertisement interval is 1.000 sec
Preemption enabled
Priority is 200
Master Router is 150.2.2.2 (local), priority is 200
Master Advertisement interval is 1.000 sec
Master Down interval is 3.218 sec

R3#**show vrrp interface fastethernet 0/0 group 1**
FastEthernet0/0 - Group 1
State is Backup
Virtual IP address is 150.2.2.254
Virtual MAC address is 0000.5e00.0101
Advertisement interval is 1.000 sec
Preemption enabled
Priority is 150
Master Router is 150.2.2.2, priority is 200
Master Advertisement interval is 1.000 sec

https://t.me/learningnets
Technet24

Master Down interval is 3.414 sec (expires in 3.190 sec)

Task 6

To complete this task, you need to configure EOT to track Serial0/0s line protocol. This tracked object should then be referenced under the VRRP interface configuration. By default, VRRP preemption is enabled and no explicit configuration is required. The only other thing required is that the priority is decremented sufficiently to allow R3 to become virtual router master:

R2(config)#**track 1 interface serial 0/0 line-protocol**
R2(config-track)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**vrrp 1 track 1 decrement 51**
R2(config-if)#**exit**

Next, verify your configuration using the **show vrrp** command:

R2#**show vrrp interface fastethernet 0/0 group 1**
FastEthernet0/0 - Group 1
State is Master
Virtual IP address is 150.2.2.254
Virtual MAC address is 0000.5e00.0101
Advertisement interval is 1.000 sec
Preemption enabled
Priority is 200
Track object 1 state Up decrement 51
Master Router is 150.2.2.2 (local), priority is 200
Master Advertisement interval is 1.000 sec
Master Down interval is 3.218 sec

Next, test your configuration by enabling logging and shutting down the Serial0/0 interface:

R2(config)#**logging console debugging**
R2(config)#**interface serial 0/0**
R2(config-if)#**shutdown**
R2(config-if)#
*May 15 12:36:47.011: %TRACKING-5-STATE: 1 interface Se0/0 line-protocol Up->Down
*May 15 12:36:47.039: %DUAL-5-NBRCHANGE: IP-EIGRP(0) 254: Neighbor 10.0.0.1 (Serial0/0) is down: interface down
*May 15 12:36:49.011: %LINK-5-CHANGED: Interface Serial0/0, changed state to

https://t.me/learningnets

administratively down
*May 15 12:36:50.011: %LINEPROTO-5-UPDOWN: Line protocol on Interface Serial0/0, changed state to down
*May 15 12:36:50.183: %VRRP-6-STATECHANGE: Fa0/0 Grp 1 state Master -> Backup

Use the **show vrrp** command again to verify the VRRP states on both routers:

R2#**show vrrp interface fastethernet 0/0 group 1**
FastEthernet0/0 - Group 1
State is Backup
Virtual IP address is 150.2.2.254
Virtual MAC address is 0000.5e00.0101
Advertisement interval is 1.000 sec
Preemption enabled
Priority is 149 (cfgd 200)
Track object 1 state Down decrement 51
Master Router is 150.2.2.3, priority is 150
Master Advertisement interval is 1.000 sec
Master Down interval is 3.218 sec (expires in 3.026 sec)

R3#**show vrrp interface fastethernet 0/0 group 1**
FastEthernet0/0 - Group 1
State is Master
Virtual IP address is 150.2.2.254
Virtual MAC address is 0000.5e00.0101
Advertisement interval is 1.000 sec
Preemption enabled
Priority is 150
Master Router is 150.2.2.3 (local), priority is 150
Master Advertisement interval is 1.000 sec
Master Down interval is 3.414 sec

Finally, test your configuration in the reverse order by bringing up the Serial0/0 interface:

R2(config)#**interface serial 0/0**
R2(config-if)#**no shutdown**
R2(config-if)#
R2(config-if)#
*May 15 12:38:42.939: %LINK-3-UPDOWN: Interface Serial0/0, changed state to up
*May 15 12:38:42.939: %TRACKING-5-STATE: 1 interface Se0/0 line-protocol

https://t.me/learningnets
Technet24

Down->Up
*May 15 12:38:43.939: %LINEPROTO-5-UPDOWN: Line protocol on Interface Serial0/0, changed state to up
*May 15 12:38:44.731: %DUAL-5-NBRCHANGE: IP-EIGRP(0) 254: Neighbor 10.0.0.1 (Serial0/0) is up: new adjacency
*May 15 12:38:45.327: %VRRP-6-STATECHANGE: Fa0/0 Grp 1 state Backup -> Master

https://t.me/learningnets

CCNP Lab 055: Cisco IOS EOT and FHRP Lab

Lab Objective:

The focus of this lab is to understand Enhanced Object Tracking and FHRP implementation and configuration in Cisco IOS routers. Additional technologies include IRDP.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Enable OSPF on the WAN interfaces of all routers as illustrated in the topology. Use OSPF area 0 in your configuration. Advertise the FastEthernet 0/0 subnets as Type 1 OSPF External routes. Verify your OSPF configuration using the appropriate commands.

Task 3

https://t.me/learningnets

Configure VRRP on the LAN segment between R1 and R4. Use a VIP of 150.1.1.254. Configure R1 with a priority of 110 and R4 with a priority of 100. Verify your VRRP configuration.

Task 4

Configure Enhanced Object Tracking so that when BOTH the Serial 0/0 and Serial 0/1 interfaces on R1 fail, R4 assumes the route of virtual router master.

Verify your configuration using the appropriate commands. Test your solution by disabling the R1-R2 and R1-R3 links and verify EOT and VRRP operation and functionality.

Task 5

Configure IRDP on the LAN segment between R2 and R3. R2 should be the preferred gateway for devices residing on this subnet. IRDP Broadcasts should be sent only when the routers are solicited by clients. These advertisements should be valid for no more than 10 seconds. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic OSPF configuration. Following this, verify your OSPF configuration using the **show ip ospf neighbor** and **show ip route** commands.

Task 3

By default, the VRRP priority is 100; therefore, no explicit configuration is required to specify this value of R4. This task is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**vrrp 1 priority 110**
R1(config-if)#**vrrp 1 ip 150.1.1.254**
R1(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**vrrp 1 ip 150.1.1.254**
R4(config-if)#**exit**

Following this configuration, verify VRRP status using the **show vrrp** command:

R1#**show vrrp interface fastethernet 0/0 group 1**

https://t.me/learningnets

Technet24

FastEthernet0/0 - Group 1
State is Master
Virtual IP address is 150.1.1.254
Virtual MAC address is 0000.5e00.0101
Advertisement interval is 1.000 sec
Preemption enabled
Priority is 110
Master Router is 150.1.1.1 (local), priority is 110
Master Advertisement interval is 1.000 sec
Master Down interval is 3.570 sec

R4#**show vrrp interface fastethernet 0/0 group 1**
FastEthernet0/0 - Group 1
State is Backup
Virtual IP address is 150.1.1.254
Virtual MAC address is 0000.5e00.0101
Advertisement interval is 1.000 sec
Preemption enabled
Priority is 100
Master Router is 150.1.1.1, priority is 110
Master Advertisement interval is 1.000 sec
Master Down interval is 3.609 sec (expires in 2.869 sec)

Task 4

This task requires the use of BOOLEAN logic in conjunction with EOT. Cisco IOS supports the Boolean 'AND' and Boolean 'OR' functions. When a tracked list has been assigned a Boolean 'AND' function, it means that each object defined within a subset must be in an up state so that the tracked object can become up. However, when the tracked list has been assigned a Boolean 'OR' function, it means that at least one object defined within a subset must be in an up state so that the tracked object can become up.

Because this task requires that R1 decrement its priority such that R4 becomes virtual router master only after BOTH the Serial0/0 and Serial0/1 interfaces are down, we need to use a Boolean 'OR' function. In other words, as long as one of the interfaces is up, the tracked object, the router should not decrement its VRRP priority. This task is completed as follows:

R1(config)#**track 100 interface serial 0/0 line-protocol**
R1(config-track)#**exit**
R1(config)#**track 101 interface serial 0/1 line-protocol**
R1(config-track)#**exit**

https://t.me/learningnets

```
R1(config)#track 102 list boolean or
R1(config-track)#object 100
R1(config-track)#object 101
R1(config-track)#exit
R1(config)#interface fastethernet 0/0
R1(config-if)#vrrp 1 track 102 decrement 20
R1(config-if)#exit
```

Following this, verify the EOT configuration using the **show track** command:

```
R1#show track
Track 100
Interface Serial0/0 line-protocol
Line protocol is Up
3 changes, last change 00:04:43
Tracked by:
Track-list 102

Track 101
Interface Serial0/1 line-protocol
Line protocol is Up
3 changes, last change 00:04:30
Tracked by:
Track-list 102

Track 102
List boolean or
Boolean OR is Up
2 changes, last change 00:05:22
object 100 Up
object 101 Up
Tracked by:
VRRP FastEthernet0/0 1
```

Next, verify VRRP status using the **show vrrp** command:

```
R1#show vrrp interface fastethernet 0/0 group 1
FastEthernet0/0 - Group 1
State is Master
Virtual IP address is 150.1.1.254
Virtual MAC address is 0000.5e00.0101
Advertisement interval is 1.000 sec
Preemption enabled
```

https://t.me/learningnets

Technet24

Priority is 110
Track object 102 state Up decrement 20
Master Router is 150.1.1.1 (local), priority is 110
Master Advertisement interval is 1.000 sec
Master Down interval is 3.570 sec

Following this, test your configuration by first shutting down the Serial 0/0 interface on R1. Due to the EOT configuration, this will NOT cause the router to decrement its priority:

R1(config)#**interface serial 0/0**
R1(config-if)#**shut**
R1(config-if)#**exit**
R1(config)#**do show track**
Track 100
Interface Serial0/0 line-protocol
Line protocol is Down (hw admin-down)
4 changes, last change 00:00:06
Tracked by:
Track-list 102

Track 101
Interface Serial0/1 line-protocol
Line protocol is Up
3 changes, last change 00:05:16
Tracked by:
Track-list 102

Track 102
List boolean or
Boolean OR is Up
2 changes, last change 00:06:08
object 100 Down
object 101 Up
Tracked by:
VRRP FastEthernet0/0 1
R1(config)#**do show vrrp interface fastethernet 0/0 group 1**
FastEthernet0/0 - Group 1
State is Master
Virtual IP address is 150.1.1.254
Virtual MAC address is 0000.5e00.0101

https://t.me/learningnets

Advertisement interval is 1.000 sec
Preemption enabled
Priority is 110
Track object 102 state Up decrement 20
Master Router is 150.1.1.1 (local), priority is 110
Master Advertisement interval is 1.000 sec
Master Down interval is 3.570 sec

However, if you also shut down the Serial 0/1 interface (not shown), then the tracked object is considered down because BOTH interfaces are down. This, in turn, causes the router to decrement the configured VRRP priority by 20 as specified in the configuration:

R1(config)#**do show track**
Track 100
Interface Serial0/0 line-protocol
Line protocol is Down (hw admin-down)
4 changes, last change 00:02:01
Tracked by:
Track-list 102

Track 101
Interface Serial0/1 line-protocol
Line protocol is Down (hw admin-down)
4 changes, last change 00:00:04
Tracked by:
Track-list 102

Track 102
List boolean or
Boolean OR is Down
3 changes, last change 00:00:03
object 100 Down
object 101 Down
Tracked by:
VRRP FastEthernet0/0 1
R1(config)#**do show vrrp interface fastethernet 0/0 group 1**
FastEthernet0/0 - Group 1
State is Backup
Virtual IP address is 150.1.1.254
Virtual MAC address is 0000.5e00.0101

https://t.me/learningnets
Technet24

Advertisement interval is 1.000 sec
Preemption enabled
Priority is 90 (cfgd 110)
Track object 102 state Down decrement 20
Master Router is 150.1.1.4, priority is 100
Master Advertisement interval is 1.000 sec
Master Down interval is 3.570 sec (expires in 2.938 sec)

Task 5

The ICMP Router Discovery Protocol (IRDP) uses ICMP router advertisements and router solicitation messages to allow a network host to discover the addresses of operational gateways on the subnet. IRDP is an alternative gateway discovery method that eliminates the need for manual configuration of gateway addresses on network hosts and is independent of any specific routing protocol.

It is important to remember that ICMP router discovery messages do not constitute a routing protocol. Instead, they enable hosts to discover the existence of neighboring gateways, but do not determine which gateway is best to reach a particular destination. However, this process can be influenced by specifying a priority for each gateway.

By default, ICMP router advertisements are sent out as Broadcast packets to the destination address 255.255.255.255. However, Cisco IOS allows administrators to configure the gateways to send IRDP messages using IP Multicast, to the destination address 224.0.0.1. By default, Cisco IOS software sends out IRDP advertisements between every 450 and 600 seconds. However, issuing the **ip irdp maxadvertinterval 0** interface configuration command causes the router to advertise only when solicited by clients. This task is completed as follows:

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip irdp**
R2(config-if)#**ip irdp preference 1**
R2(config-if)#**ip irdp maxadvertinterval 0**
R2(config-if)#**ip irdp holdtime 10**
R2(config-if)#**exit**

R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip irdp**
R3(config-if)#**ip irdp maxadvertinterval 0**
R3(config-if)#**ip irdp holdtime 10**
R3(config-if)#**exit**

Following this configuration, verify IRDP using the **show ip irdp** command:

https://t.me/learningnets

R3#**show ip irdp fastethernet 0/0**
FastEthernet0/0 has router discovery enabled

Advertisements will not be sent except upon solicitation.
Advertisements are valid for 10 seconds.
Default preference will be 1.

R2#**show ip irdp fastethernet 0/0**
FastEthernet0/0 has router discovery enabled

Advertisements will not be sent except upon solicitation.
Advertisements are valid for 10 seconds.
Default preference will be 0.

https://t.me/learningnets

CCNP Lab 056: Cisco IOS IP SLA and BGP Lab

Lab Objective:

The focus of this lab is to understand the Cisco IOS IP SLA Operations and BGP implementation and configuration in Cisco IOS routers. Additional technologies include EOT.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Enable BGP on R1, R2 and R3 as illustrated in the topology. Use the physical interfaces for the BGP peering. Advertise the LAN subnets on R2 and R3 via BGP. Do NOT advertise the LAN subnet between R1 and R4 via BGP. Verify the configuration using

https://t.me/learningnets

Technet24

the appropriate commands.

Task 3

Configure R1 so that R2 and R3 are able to reach the LAN subnet between R1 and R4. You must adhere to the following restrictions when completing this task:

1. Do NOT advertise the 150.1.1.0/24 subnet via BGP
2. Do NOT redistribute the connected subnet into BGP
3. Do NOT advertise a default route via BGP
4. Do NOT configure static routes on either R2 or R3

You are allowed one static route, which can NOT be a default route, on R1. This route can be advertised via BGP using the **network x.x.x.x mask y.y.y.y** command. This route should have a network mask no longer than a /16, i.e. a mask no longer than 255.255.0.0. Verify the configuration using the appropriate commands.

Task 4

Configure R4 so that it is able to ping the 150.2.2.0/24 and 150.3.3.0/24 subnets and vice-versa. Verify your configuration using standard and extended pings.

Task 5

Configure a Cisco IOS IP SLA Operation on R1 so that when the LAN connection between R1 and R4 is down, the route advertised in Task 3 is withdrawn and is no longer advertised. Test your solution by disabling the LAN interface on R1.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic BGP configuration. Following this, verify your BGP configuration using the **show ip bgp neighbor** and **show ip route** commands. Following this configuration, your BGP RIBs should show the following path information:

R1#**show ip bgp**
BGP table version is 3, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path

https://t.me/learningnets

*> 150.2.2.0/24 10.0.0.2 0 0 2 i
*> 150.3.3.0/24 10.0.0.6 0 0 3 i

R2#**show ip bgp**
BGP table version is 3, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.2.2.0/24 0.0.0.0 0 32768 i
*> 150.3.3.0/24 10.0.0.1 0 1 3 i

R3#**show ip bgp**
BGP table version is 3, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.2.2.0/24 10.0.0.5 0 1 2 i
*> 150.3.3.0/24 0.0.0.0 0 32768 i

Finally, verify that R2 and R3 can ping each other LAN-to-LAN using an extended ping:

R2#**ping 150.3.3.3 source 150.2.2.2 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 204/204/204 ms

R3#**ping 150.2.2.2 source 150.3.3.3 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 204/204/204 ms

Task 3

To complete this task, you need to configure a static route pointing to Null0. Given the task requirements, feel free to use any static route between 150.0.0.0/8 and 150.1.0.0/16. When complete, this prefix should be advertised via BGP using the

https://t.me/learningnets
Technet24

network command. This will allow R2 and R3 to reach the 150.1.1.0/24 prefix. This task is completed as follows:

R1(config)#**ip route 150.1.0.0 255.255.0.0 null 0**
R1(config)#**router bgp 1**
R1(config-router)#**network 150.1.0.0 mask 255.255.0.0**
R1(config-router)#**exit**

Following this, verify the BGP RIB on R1, R2 and R3 using the **show ip bgp** command:

R1#**show ip bgp**
BGP table version is 4, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
***> 150.1.0.0 0.0.0.0 0 32768 i**
*> 150.2.2.0/24 10.0.0.2 0 0 2 i
*> 150.3.3.0/24 10.0.0.6 0 0 3 i

R2#**show ip bgp**
BGP table version is 4, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
***> 150.1.0.0 10.0.0.1 0 0 1 i**
*> 150.2.2.0/24 0.0.0.0 0 32768 i
*> 150.3.3.0/24 10.0.0.1 0 1 3 i

R3#**show ip bgp**
BGP table version is 4, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
***> 150.1.0.0 10.0.0.5 0 0 1 i**
*> 150.2.2.0/24 10.0.0.5 0 1 2 i
*> 150.3.3.0/24 0.0.0.0 0 32768 i

Complete this task by ensuring that R2 and R3 can ping the 150.1.1.0/24 prefix LAN-to-LAN:

https://t.me/learningnets

R2#**ping 150.1.1.1 source 150.2.2.2 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/15/16 ms

R3#**ping 150.1.1.1 source 150.3.3.3 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 192/192/192 ms

Task 4

To complete this task, you simply need to configure a static default route on R4 pointing to R1:

R4(config)#**ip route 0.0.0.0 0.0.0.0 fastethernet 0/0 150.1.1.1**

Following this, use ping to verify LAN-to-LAN connectivity between R4 and routers R2 and R3:

R2#**ping 150.1.1.4 source 150.2.2.2 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.4, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/15/16 ms

R3#**ping 150.1.1.4 source 150.3.3.3 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.4, timeout is 2 seconds:
Packet sent with a source address of 150.3.3.3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 192/192/192 ms

Task 5

To complete this task, you need to configure an IP SLA Operation to ping the LAN IP address of R4 - since IP SLA Operations cannot monitor interface states. Next, you need to configure EOT to track the IP SLA Operation. And finally, you need to configure the static route to use EOT such that it will be removed if the tracked object is down. This

https://t.me/learningnets

Technet24

is completed as follows:

```
R1(config)#ip sla 1
R1(config-ip-sla)#icmp-echo 150.1.1.4 source-ipaddr 150.1.1.1
R1(config-ip-sla)#exit
R1(config)#ip sla schedule 1 start-time now life forever
R1(config)#track 1 rtr 1 state
R1(config-track)#exit
R1(config)#ip route 150.1.0.0 255.255.0.0 null 0 track 1
R1(config)#exit
```

Verify your Cisco IP SLA Operation statistics using the **show ip sla monitor** command:

```
R1#show ip sla statistics 1
Round trip time (RTT) Index 1
Latest RTT: 1 ms
Latest operation start time: *19:41:43.345 UTC Thu Jun 2 2011
Latest operation return code: OK
Number of successes: 4
Number of failures: 0
Operation time to live: Forever
```

Next, verify your tracking configuration using the **show track** command:

```
R1#show track
Track 1
Response Time Reporter 1 state
State is Up
1 change, last change 00:03:36
Latest operation return code: OK
Latest RTT (millisecs) 1
Tracked by:
STATIC-IP-ROUTING 0
```

Finally, verify static routing EOT using the **show ip route** command:

```
R1#show ip route 150.1.0.0 255.255.0.0
Routing entry for 150.1.0.0/16
Known via “static”, distance 1, metric 0 (connected)
Advertised by bgp 1
Routing Descriptor Blocks:
* directly connected, via Null0
Route metric is 0, traffic share count is 1
```

https://t.me/learningnets

To complete this task, you need to test this solution by disabling the LAN interface on R1:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**shut**
R1(config-if)#**do show ip sla statistics 1**
Round trip time (RTT) Index 1
Latest RTT: NoConnection/Busy/Timeout
Latest operation start time: *19:46:43.345 UTC Thu Jun 2 2011
Latest operation return code: Timeout
Number of successes: 8
Number of failures: 1
Operation time to live: Forever

R1(config-if)#**do show track**
Track 1
Response Time Reporter 1 state
State is Down
2 changes, last change 00:00:25
Latest operation return code: Timeout
Tracked by:
STATIC-IP-ROUTING 0

R1(config-if)#**do show ip route 150.1.0.0 255.255.0.0**
% Network not in table

R1(config-if)#**do show ip bgp**
BGP table version is 7, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.2.2.0/24 10.0.0.2 0 0 2 i
*> 150.3.3.0/24 10.0.0.6 0 0 3 i

https://t.me/learningnets

Technet24

CCNP Lab 057: Cisco Policy-Based Routing Lab

Lab Objective:

The focus of this lab is to understand the Cisco Policy-Based Routing (PBR) implementation and configuration in Cisco IOS routers. Additional technologies include path control.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Enable EIGRP using AS 254 on all routers as illustrated in the topology. Do NOT enable EIGRP on the link between R2 and R3. EIGRP packets should not be sent out of the FastEthernet 0/0 interfaces of either R2 or R3. Verify the EIGRP configuration using the appropriate commands.

https://t.me/learningnets

Technet24

Task 3

Management has requested that traffic sourced from the 150.1.1.0/24 subnet that has a packet size between 0 and 500 bytes and between 1000 and 1500 bytes and is destined to the 150.3.3.0/24 subnet be sent via R2. All other traffic should following the normal routing path. Verify and test your configuration using the appropriate commands.

Task 4

Management has requested that in the event that the R1-R3 link fails, all traffic sourced from the 150.3.3.0/24 subnet destined to the 150.1.1.0/24 and 150.2.2.0/24 subnets be forwarded via the R2-R3 link. This should ONLY happen when the R1-R2 link is down. Ensure that the 150.3.3.0/24 subnet can reach the 150.1.1.0/24 and 150.2.2.0/24 subnets and vice-versa when you complete this task. You are NOT allowed to configure static routes on R3 to complete this task. Additionally, to minimize device configuration, you MUST use a single ACL with a single entry or line. Verify and test your configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following path information:

R1#**show ip route eigrp**
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 10.0.0.2, 00:03:31, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2172416] via 10.0.0.6, 00:02:50, Serial0/1

R2#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.4 [90/2681856] via 10.0.0.1, 00:03:16, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:03:36, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2684416] via 10.0.0.1, 00:02:55, Serial0/0

https://t.me/learningnets

R3#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.0 [90/21024000] via 10.0.0.5, 00:02:57, Serial1/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/20514560] via 10.0.0.5, 00:02:57, Serial1/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/21026560] via 10.0.0.5, 00:02:57, Serial1/0

R4#**show ip route eigrp**
10.0.0.0/30 is subnetted, 2 subnets
D 10.0.0.0 [90/2172416] via 150.1.1.1, 00:01:15, FastEthernet0/0
D 10.0.0.4 [90/2172416] via 150.1.1.1, 00:01:15, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2174976] via 150.1.1.1, 00:01:15, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2174976] via 150.1.1.1, 00:01:15, FastEthernet0/0

Task 3

Several steps are required to complete this task. The first step is that you need to configure an ACL that matches traffic that is sourced from the 150.1.1.0/24 subnet and is destined to the 150.3.3.0/24 subnet. Next, you will need to configure a route map with at least two permit statements. The first permit statement will match traffic in specified in the ACL as long as the packets are between 0 and 500 bytes. The second permit statement will match traffic in the specified ACL as long as the packets are between 1000 and 1500 bytes. Optionally, you can also configure an explicit deny statement for the route map to prevent all other traffic from being policy routed (default behavior). This task is completed as follows:

R1(config)#**access-list 100 permit ip 150.1.1.0 0.0.0.255 150.3.3.0 0.0.0.255**
R1(config)#**route-map LAN-PBR permit 10**
R1(config-route-map)#**match ip address 100**
R1(config-route-map)#**match length 0 500**
R1(config-route-map)#**set ip next-hop 10.0.0.2**
R1(config-route-map)#**exit**
R1(config)#**route-map LAN-PBR permit 20**
R1(config-route-map)#**match length 1000 1500**
R1(config-route-map)#**match ip address 100**
R1(config-route-map)#**set ip next-hop 10.0.0.2**
R1(config-route-map)#**exit**
R1(config)#**route-map LAN-PBR deny 30**

https://t.me/learningnets
Technet24

R1(config-route-map)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip policy route-map LAN-PBR**
R1(config-if)#**exit**

NOTE: You can also use the **set interface** command when configuring the route map. This is because an explicit route to 150.3.3.0/24 exists in the routing table. If no there is no explicit, or if only a default route is present in the routing table, the command will be ignored.

Verify your route map configuration using the **show route-map <name>** command:

R1#**show route-map**
route-map LAN-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): 100
length 0 500
Set clauses:
ip next-hop 10.0.0.2
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, permit, sequence 20
Match clauses:
ip address (access-lists): 100
length 1000 1500
Set clauses:
ip next-hop 10.0.0.2
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, deny, sequence 30
Match clauses:
Set clauses:
Policy routing matches: 0 packets, 0 bytes

Next, test your configuration by pinging the 150.3.3.0/24 subnet from R4 using different packet sizes. The following illustrates a 300-byte ping from R4 to R3s LAN interface address:

R4#**ping 150.3.3.3 size 300**

Type escape sequence to abort.
Sending 5, 300-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
!!!!!

Using the **show route-map** command, we can see matches against the first permit

https://t.me/learningnets

statement:

R1#**show route-map**
route-map LAN-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): 100
length 0 500
Set clauses:
ip next-hop 10.0.0.2
Policy routing matches: 5 packets, 1570 bytes
route-map LAN-PBR, permit, sequence 20
Match clauses:
ip address (access-lists): 100
length 1000 1500
Set clauses:
ip next-hop 10.0.0.2
Policy routing matches: 0 packets, 0 bytes
route-map LAN-PBR, deny, sequence 30
Match clauses:
Set clauses:
Policy routing matches: 0 packets, 0 bytes

Next, a 700-byte ping is sent from R4 to the LAN interface of R3:

R4#**ping 150.3.3.3 size 700**

Type escape sequence to abort.
Sending 5, 700-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 92/92/92 ms

This time, there will be no matches against the PBR configuration. Only the five packets from the previous ping test will have matched the configuration applied to R1:

R1#**show route-map**
route-map LAN-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): 100
length 0 500
Set clauses:
ip next-hop 10.0.0.2
Policy routing matches: 5 packets, 1570 bytes

https://t.me/learningnets

Technet24

route-map LAN-PBR, permit, sequence 20
Match clauses:
ip address (access-lists): 100
length 1000 1500
Set clauses:
ip next-hop 10.0.0.2
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, deny, sequence 30
Match clauses:
Set clauses:
Policy routing matches: 0 packets, 0 bytes

Finally, to complete our validation, a 1300 byte ping is sent from R4 to the LAN interface of R3.

R4#**ping 150.3.3.3 size 1300**

Type escape sequence to abort.
Sending 5, 1300-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 176/179/180 ms

This time the traffic will match the second permit statement in the route map. The only matches will therefore be 5 packets from the 300-byte ping (permit statement 10) and 5 packets from the 1300 byte ping (permit statement 20). This is validated using the **show route-map** command:

R1#**show route-map**
route-map LAN-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): 100
length 0 500
Set clauses:
ip next-hop 10.0.0.2
Policy routing matches: 5 packets, 1570 bytes

route-map LAN-PBR, permit, sequence 20
Match clauses:
ip address (access-lists): 100
length 1000 1500
Set clauses:
ip next-hop 10.0.0.2
Policy routing matches: 5 packets, 6570 bytes

https://t.me/learningnets

route-map LAN-PBR, deny, sequence 30
Match clauses:
Set clauses:
Policy routing matches: 0 packets, 0 bytes

NOTE: You can also verify your configuration using the **debug ip policy** command while sending pings with varying sizes from the 150.1.1.0/24 subnet to the 150.3.3.0/23 subnet.

Task 4

The requirements of this task are two-fold: the first is PBR implementation and the second is IP routing implementation. The PBR requirement is that traffic is only sent across the R2-R3 link when the R1-R3 is down. This means that you must use either the default next hop or default interface route map 'set' statements. Either option is acceptable when completing this task. The first requirement for this task is completed as follows:

R3(config)#**access-list 100 permit ip 150.3.3.0 0.0.0.255 150.0.0.0 0.1.1.255**
R3(config)#**route-map LAN-PBR permit 10**
R3(config-route-map)#**set ip default next-hop 10.0.0.9**
R3(config-route-map)#**match ip address 100**
R3(config-route-map)#**exit**
R3(config)#**route-map LAN-PBR deny 20**
R3(config-route-map)#**exit**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip policy route-map LAN-PBR**
R3(config-if)#**exit**

Following this, you can test PBR while dynamic routing information is still available for use by R3. The output below shows a ping from 150.3.3.254 to 150.1.1.1 while the EIGRP route for the destination network is still in the IP routing table:

R3#**show ip route 150.1.1.0 255.255.255.0**
Routing entry for 150.1.1.0/24
Known via "eigrp 254", distance 90, metric 20514560, type internal
Redistributing via eigrp 254
Last update from 10.0.0.5 on Serial1/0, 00:09:47 ago
Routing Descriptor Blocks:
* 10.0.0.5, from 10.0.0.5, 00:09:47 ago, via Serial1/0
Route metric is 20514560, traffic share count is 1
Total delay is 20100 microseconds, minimum bandwidth is 128 Kbit

https://t.me/learningnets
Technet24

Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1
R3#
R3#**debug ip policy**
Policy routing debugging is on
R3#
R3#
*May 16 17:51:01.863: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy match
***May 16 17:51:01.863: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy rejected(explicit route) - normal forwarding**
*May 16 17:51:01.879: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy match
***May 16 17:51:01.879: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy rejected(explicit route) - normal forwarding**
*May 16 17:51:01.899: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy match
***May 16 17:51:01.899: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy rejected(explicit route) - normal forwarding**
*May 16 17:51:01.919: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy match
***May 16 17:51:01.919: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy rejected(explicit route) - normal forwarding**
*May 16 17:51:01.935: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy match
***May 16 17:51:01.935: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy rejected(explicit route) - normal forwarding**

The second requirement of this task is to ensure that routing between the 150.3.3.0/24 and the 150.1.1.0/24 and 150.2.2.0/24 subnets works when the R1-R3 link is no longer available. While the task requirements stipulate that no static routes can be configured on R3, there is no such restriction imposed on R1 or R2. The simplest solution is therefore to configure a floating static route on R2 which is then redistributed into EIGRP. This will be used to reach the 150.3.3.0/24 subnet when the R1-R3 link is unavailable. This task is completed as follows:

R2(config)#**ip route 150.3.3.0 255.255.255.0 10.0.0.10 254**
R2(config)#**router eigrp 254**
R2(config-router)#**redistribute static**
R2(config-router)#**exit**

https://t.me/learningnets

The following illustrates the same ping when the dynamic routing information is no longer available because, for example, the WAN interface has been disabled:

R3(config)#**interface serial 1/0**
R3(config-if)#**shutdown**
*May 16 18:12:13.147: %DUAL-5-NBRCHANGE: IP-EIGRP(0) 254: Neighbor 10.0.0.5 (Serial1/0) is down: interface down
*May 16 18:12:15.123: %LINK-5-CHANGED: Interface Serial1/0, changed state to administratively down
*May 16 18:12:16.123: %LINEPROTO-5-UPDOWN: Line protocol on Interface Serial1/0, changed state to down
R3(config-if)#**do show ip route 150.1.1.0 255.255.255.0**
% Network not in table
R3(config-if)#**do show ip route 150.2.2.0 255.255.255.0**
% Network not in table
R3(config-if)#
*May 16 18:12:52.171: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy match
***May 16 18:12:52.171: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, g=10.0.0.9, len 100, FIB policy routed**
*May 16 18:12:52.191: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy match
***May 16 18:12:52.191: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, g=10.0.0.9, len 100, FIB policy routed**
*May 16 18:12:52.251: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy match
***May 16 18:12:52.251: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, g=10.0.0.9, len 100, FIB policy routed**
*May 16 18:12:52.271: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy match
***May 16 18:12:52.271: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, g=10.0.0.9, len 100, FIB policy routed**
*May 16 18:12:52.291: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, len 100, FIB policy match
***May 16 18:12:52.291: IP: s=150.3.3.254 (FastEthernet0/0), d=150.1.1.1, g=10.0.0.9, len 100, FIB policy routed**

The successful ping is possible because of the redistributed static route on R2 which is installed into the EIGRP Topology Table and IP routing table on R1 as follows:

R1#**show ip eigrp 254 topology 150.3.3.0 255.255.255.0**

https://t.me/learningnets

Technet24

IP-EIGRP (AS 254): Topology entry for 150.3.3.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 2681856
Routing Descriptor Blocks:
10.0.0.2 (Serial0/0), from 10.0.0.2, Send flag is 0x0
Composite metric is (2681856/2169856), Route is External
Vector metric:
Minimum bandwidth is 1544 Kbit
Total delay is 40000 microseconds
Reliability is 255/255
Load is 1/255
Minimum MTU is 1500
Hop count is 1
External data:
Originating router is 150.2.2.2
AS number of route is 0
External protocol is Static, external metric is 0
Administrator tag is 0 (0x00000000)

https://t.me/learningnets

CCNP Lab 058: Cisco Policy-Based Routing Lab

Lab Objective:

The focus of this lab is to understand the Cisco Policy-Based Routing (PBR) implementation and configuration in Cisco IOS routers. Additional technologies include traffic filtering.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Enable EIGRP using AS 254 on all routers as illustrated in the topology. Do NOT enable EIGRP on the link between R2 and R3. EIGRP packets should NOT be sent out of the LAN interfaces of R2 or R3. Verify the configuration using the appropriate commands.

https://t.me/learningnets

Task 3

Management is concerned about network security and using the default Telnet port of 23. All routers are configured to accept Telnet connections on port 3023 instead as a result. Management would like to ensure that all Telnet traffic received ingressing R1s LAN interface be discarded. However, Telnet traffic using port 3023 should be forwarded via Serial 0/1 with an IP Precedence value of 4. You are NOT allowed to use inbound or bound ACLs to complete this task - you MUST use PBR. Implement the solution required to complete this task on R1 and verify and test your configuration.

Task 4

For security purposes, Management has requested that locally originated Telnet connections from R2 or R3 to R4 only be discarded. However, these routers should be able to Telnet to other devices or subnets. You are NOT allowed to use inbound or outbound ACLs to complete this task - you MUST use PBR. Implement the solution required to complete this task on both R2 and R3 then verify and test your configuration.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following path information:

R1#**show ip route eigrp**
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 10.0.0.2, 01:38:15, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2172416] via 10.0.0.6, 00:07:58, Serial0/1

R2#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.4 [90/2681856] via 10.0.0.1, 00:08:11, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 01:38:28, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2684416] via 10.0.0.1, 00:08:11, Serial0/0

https://t.me/learningnets

Technet24

R3#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.0 [90/21024000] via 10.0.0.5, 00:08:15, Serial1/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/20514560] via 10.0.0.5, 00:08:15, Serial1/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/21026560] via 10.0.0.5, 00:08:15, Serial1/0

R4#**show ip route eigrp**
10.0.0.0/30 is subnetted, 2 subnets
D 10.0.0.0 [90/2172416] via 150.1.1.1, 01:36:10, FastEthernet0/0
D 10.0.0.4 [90/2172416] via 150.1.1.1, 00:08:19, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2174976] via 150.1.1.1, 01:36:10, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2174976] via 150.1.1.1, 00:08:18, FastEthernet0/0

Task 3

The requirements for this task are quite straightforward. First, an ACL is required to match the Telnet traffic (port 23). This should be forwarded to the Null0 interface, which is a bit bucket. All traffic sent to the Null0 interface is discarded.

The second requirement is that Telnet traffic using port 3023 should be forwarded via Serial 0/1 with an IP Precedence value of 4. This task is completed as follows:

R1(config)#**access-list 100 permit tcp any any eq telnet**
R1(config)#**access-list 101 permit tcp any any eq 3023**
R1(config)#**route-map LAN-PBR permit 10**
R1(config-route-map)#**match ip address 100**
R1(config-route-map)#**set interface null0**
%Warning:Use P2P interface for routemap set
interface clause

R1(config-route-map)#**exit**
R1(config)#**route-map LAN-PBR permit 20**
R1(config-route-map)#**match ip address 101**
R1(config-route-map)#**set ip precedence 4**
R1(config-route-map)#**set interface serial 0/1**
R1(config-route-map)#**exit**
R1(config)#**route-map LAN-PBR deny 30**
R1(config-route-map)#**exit**
R1(config)#**interface fastethernet 0/0**

https://t.me/learningnets

R1(config-if)#**ip policy route-map LAN-PBR**
R1(config-if)#**exit**

Next, verify your route map configuration using the show **route-map <name>** command:

R1#**show route-map LAN-PBR**
route-map LAN-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): 100
Set clauses:
interface Null0
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, permit, sequence 20
Match clauses:
ip address (access-lists): 101
Set clauses:
ip precedence flash-override
interface Serial0/1
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, deny, sequence 30
Match clauses:
Set clauses:
Policy routing matches: 0 packets, 0 bytes

Following this, test your configuration by attempting to Telnet from R4 to either R2 or R3 using first the default standard port number (23) and then the custom port number (3023). To configure Cisco IOS routers to accept connections on port xx23, e.g. 1023, 2023, 3023, 4023, etc, you simply add the **rotary 23** command under the VTY configuration as follows:

R2(config)#**line vty 0 4**
R2(config-line)#**rotary 23**
R2(config-line)#**exit**

You can then use the **show line vty <line number>** command to verify the configuration:

R2#**show line vty 0**
Tty Typ Tx/Rx A Modem **Roty** AccO AccI Uses Noise Overruns Int
66 VTY - - **23** - - 0 0 0/0 -

Line 66, Location: "", Type: ""
Length: 24 lines, Width: 80 columns

https://t.me/learningnets

Technet24

Baud rate (TX/RX) is 9600/9600
Status: No Exit Banner
Capabilities: none
Modem state: Idle
Group codes: 0
Special Chars: Escape Hold Stop Start Disconnect Activation
^^x none - - none
Timeouts: Idle EXEC Idle Session Modem Answer Session Dispatch
00:10:00 never none not set
Idle Session Disconnect Warning
never
Login-sequence User Response
00:00:30
Autoselect Initial Wait
not set
Modem type is unknown.
Session limit is not set.
Time since activation: never
Editing is enabled.
History is enabled, history size is 20.
DNS resolution in show commands is enabled
Full user help is disabled
Allowed input transports are lat pad telnet rlogin mop v120 ssh.
Allowed output transports are lat pad telnet rlogin mop v120 ssh.
Preferred transport is lat.
No output characters are padded
No special data dispatching characters

Next, test your configuration by attempting to first Telnet from R4 to either R2 or R3 while you are running PBR debugging (turn the debug on before you telnet):

R4#**telnet 10.0.0.6**
Trying 10.0.0.6 ...
% Connection timed out; remote host not responding

R1#**debug ip policy**
Policy routing debugging is on
R1#
R1#
R1#
*Jun 3 01:49:36.646: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6, len 44, FIB policy

https://t.me/learningnets

match
***Jun 3 01:49:36.646: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6 (Null0), len 44, FIB policy routed(drop)**
*Jun 3 01:49:38.646: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6, len 44, FIB policy match
***Jun 3 01:49:38.646: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6 (Null0), len 44, FIB policy routed(drop)**
*Jun 3 01:49:42.646: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6, len 44, FIB policy match
***Jun 3 01:49:42.646: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6 (Null0), len 44, FIB policy routed(drop)**
*Jun 3 01:49:50.646: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6, len 44, FIB policy match
***Jun 3 01:49:50.646: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6 (Null0), len 44, FIB policy routed(drop)**

Notice that in the output above the traffic is policy routed; however, because it is routed to the Null0 interface, the traffic is essentially dropped, hence the drop in parenthesis (brackets).

Next, initiate a Telnet connection from R4 to R2 or R3, this time using TCP port 3023 instead (turn the debug on before you telnet if it isn't already on):

R4#**telnet 10.0.0.6 3023**
Trying 10.0.0.6, 3023 ... Open

Password required, but none set

R1#**debug ip policy**
Policy routing debugging is on
R1#
R1#
R1#
*Jun 3 01:47:44.138: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6, len 44, FIB policy match
***Jun 3 01:47:44.138: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6 (Serial0/1), len 44, FIB policy routed**
*Jun 3 01:47:44.150: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6, len 40, FIB policy match
***Jun 3 01:47:44.150: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6 (Serial0/1), len 40, FIB policy routed**
*Jun 3 01:47:44.154: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6, len 40, FIB policy

https://t.me/learningnets
Technet24

match
***Jun 3 01:47:44.154: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6 (Serial0/1), len 40, FIB policy routed**
*Jun 3 01:47:44.170: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6, len 43, FIB policy match
***Jun 3 01:47:44.170: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6 (Serial0/1), len 43, FIB policy routed**
*Jun 3 01:47:44.170: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6, len 43, FIB policy match
***Jun 3 01:47:44.170: IP: s=150.1.1.4 (FastEthernet0/0), d=10.0.0.6 (Serial0/1), len 43, FIB policy routed**

Task 4

To complete this task, the PBR configuration must be applied globally using the **ip local policy <route-map-name>** global configuration command, otherwise it will not match traffic originated by the router. This task is completed as follows:

R2(config)#**ip access-list extended NO-TELNET-TO-R4-ONLY**
R2(config-ext-nacl)#**permit tcp any host 150.1.1.4 eq 23**
R2(config-ext-nacl)#**exit**
R2(config)#**route-map LOCAL-PBR-POLICY permit 10**
R2(config-route-map)#**match ip address NO-TELNET-TO-R4-ONLY**
R2(config-route-map)#**set interface null 0**
%Warning:Use P2P interface for routemap set
interface clause
R2(config-route-map)#**exit**
R2(config)#**route-map LOCAL-PBR-POLICY deny 20**
R2(config-route-map)#**exit**
R2(config)#**ip local policy route-map LOCAL-PBR-POLICY**
R2(config)#**exit**

R3(config)#**ip access-list extended NO-TELNET-TO-R4-ONLY**
R3(config-ext-nacl)#**permit tcp any host 150.1.1.4 eq telnet**
R3(config-ext-nacl)#**exit**
R3(config)#**route-map LOCAL-PBR-POLICY permit 10**
R3(config-route-map)#**match ip address NO-TELNET-TO-R4-ONLY**
R3(config-route-map)#**set interface null 0**
%Warning:Use P2P interface for routemap set
interface clause
R3(config-route-map)#**exit**

https://t.me/learningnets

R3(config)#**route-map LOCAL-PBR-POLICY deny 20**
R3(config-route-map)#**exit**
R3(config)#**ip local policy route-map LOCAL-PBR-POLICY**
R3(config)#**exit**

Next, verify your route map configuration using the **show route-map <name>** command:

R2#**show route-map LOCAL-PBR-POLICY**
route-map LOCAL-PBR-POLICY, permit, sequence 10
Match clauses:
ip address (access-lists): NO-TELNET-TO-R4-ONLY
Set clauses:
interface Null0
Policy routing matches: 0 packets, 0 bytes
route-map LOCAL-PBR-POLICY, deny, sequence 20
Match clauses:
Set clauses:
Policy routing matches: 0 packets, 0 bytes

R3#**show route-map LOCAL-PBR-POLICY**
route-map LOCAL-PBR-POLICY, permit, sequence 10
Match clauses:
ip address (access-lists): NO-TELNET-TO-R4-ONLY
Set clauses:
interface Null0
Policy routing matches: 0 packets, 0 bytes
route-map LOCAL-PBR-POLICY, deny, sequence 20
Match clauses:
Set clauses:
Policy routing matches: 0 packets, 0 bytes

Finally, test your solution by attempting to Telnet from R2 or R3 to R4 using the standard TCP port number (23). Use the **debug ip policy** command to view PBR operation real-time:

R2#**debug ip policy**
Policy routing debugging is on
R2#
R2#
R2#
R2#**telnet 150.1.1.4**

https://t.me/learningnets
Technet24

Trying 150.1.1.4 ...

***May 17 08:26:14.323: IP: route map LOCAL-PBR-POLICY, item 10, permit**
***May 17 08:26:14.327: IP: s=10.0.0.2 (local), d=150.1.1.4 (Null0), len 44, policy routed**
***May 17 08:26:14.327: IP: local to Null0 150.1.1.4**
*May 17 08:26:16.327: IP: s=10.0.0.2 (local), d=150.1.1.4, len 44, policy match
***May 17 08:26:16.327: IP: route map LOCAL-PBR-POLICY, item 10, permit**
***May 17 08:26:16.327: IP: s=10.0.0.2 (local), d=150.1.1.4 (Null0), len 44, policy routed**
***May 17 08:26:16.327: IP: local to Null0 150.1.1.4**
*May 17 08:26:20.327: IP: s=10.0.0.2 (local), d=150.1.1.4, len 44, policy match
***May 17 08:26:20.327: IP: route map LOCAL-PBR-POLICY, item 10, permit**
***May 17 08:26:20.327: IP: s=10.0.0.2 (local), d=150.1.1.4 (Null0), len 44, policy routed**
***May 17 08:26:20.327: IP: local to Null0 150.1.1.4**
*May 17 08:26:28.327: IP: s=10.0.0.2 (local), d=150.1.1.4, len 44, policy match
***May 17 08:26:28.327: IP: route map LOCAL-PBR-POLICY, item 10, permit**
***May 17 08:26:28.327: IP: s=10.0.0.2 (local), d=150.1.1.4 (Null0), len 44, policy routed**
***May 17 08:26:28.327: IP: local to Null0 150.1.1.4**

% Connection timed out; remote host not responding

Next, attempt to Telnet to R4 using any other port number, for example, using TCP port 3023:

R2#**telnet 150.1.1.4 3023**
Trying 150.1.1.4, 3023 ... Open

Password required, but none set

*May 17 08:28:09.635: IP: s=10.0.0.2 (local), d=150.1.1.4, len 44, policy match
***May 17 08:28:09.635: IP: route map LOCAL-PBR-POLICY, item 20, deny**
***May 17 08:28:09.635: IP: s=10.0.0.2 (local), d=150.1.1.4, len 44, policy rejected -- normal forwarding**
*May 17 08:28:09.639: IP: s=10.0.0.2 (local), d=150.1.1.4, len 40, policy match
***May 17 08:28:09.643: IP: route map LOCAL-PBR-POLICY, item 20, deny**
***May 17 08:28:09.643: IP: s=10.0.0.2 (local), d=150.1.1.4, len 40, policy rejected -- normal forwarding**
*May 17 08:28:09.643: IP: s=10.0.0.2 (local), d=150.1.1.4, len 40, policy match
***May 17 08:28:09.647: IP: route map LOCAL-PBR-POLICY, item 20, deny**
***May 17 08:28:09.647: IP: s=10.0.0.2 (local), d=150.1.1.4, len 40, policy rejected --**

https://t.me/learningnets

normal forwarding
*May 17 08:28:09.651: IP: s=10.0.0.2 (local), d=150.1.1.4, len 43, policy match
***May 17 08:28:09.651: IP: route map LOCAL-PBR-POLICY, item 20, deny**
***May 17 08:28:09.651: IP: s=10.0.0.2 (local), d=150.1.1.4, len 43, policy rejected -- normal forwarding**

[Connection to 150.1.1.4 closed by foreign host]

https://t.me/learningnets

Technet24

CCNP Lab 059: Cisco Policy-Based Routing Lab

Lab Objective:

The focus of this lab is to understand the Cisco Policy-Based Routing (PBR) implementation and configuration in Cisco IOS routers. Additional technologies include EOT and path control. For later testing, you can add a host connected to F0/0 on R2 (or another router) with IP address 150.2.2.254 (and a default route to R2).

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology. In addition, configure a Loopback 0 interface on R1 with the IP address 1.1.1.1/32.

Task 2

Configure EIGRP as illustrated in the topology. Do NOT enable EIGRP on the R1-R3 link or the R2-R3 link. You should ensure that no EIGRP packets are sent out of the

https://t.me/learningnets

Technet24

FastEthernet0/0 interface on R2. R1 should advertise a default route to R4. Configure a static default route on R2 pointing to R3. Configure three static routes on R3: two static routes for the 150.1.1.0/24 subnet should point to R1; two static routes for 150.2.2.0/24 and 0.0.0.0/0 should point to R2. Verify your configuration using the appropriate commands.

Task 3

Configure IOS PBR on R1 so that all TCP and ICMP traffic from the 150.1.1.0/24 subnet to any subnet is forwarded to 10.0.0.2 (R2). In the event that the path via R2 is unavailable, configure PBR so that the router forwards this traffic to 10.0.0.6 (R3). However, this alternate path should ONLY be used based on the Cisco Discovery Protocol (CDP) reachability information. Finally, ensure that all other traffic from the 150.1.1.0/24 subnet to any subnet should be forwarded via 10.0.0.3 (R3). If this path is down, this traffic should be discarded. Verify your configuration using the appropriate show commands and/or debugging commands.

Task 4

Configure IOS PBR with EOT on R2 and R3 such that when either of the routers' WAN links to R1 is down, all traffic from the local LAN is sent across the R2-R3 link. When the WAN link is up, traffic from the LAN segments should be forwarded to R1. Verify your PBR configuration using the appropriate show and/or debugging commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

```
R1#show ip route
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
```

https://t.me/learningnets

o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

1.0.0.0/32 is subnetted, 1 subnets
C 1.1.1.1 is directly connected, Loopback0
10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.0 is directly connected, Serial0/0
C 10.0.0.4 is directly connected, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 10.0.0.2, 00:01:17, Serial0/0

R2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 10.0.0.10 to network 0.0.0.0

10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.8 is directly connected, Serial0/1
C 10.0.0.0 is directly connected, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:00:24, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0
S* 0.0.0.0/0 [1/0] via 10.0.0.10

R3#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 10.0.0.9 to network 0.0.0.0

https://t.me/learningnets

Technet24

10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.8 is directly connected, Serial1/1
C 10.0.0.4 is directly connected, Serial1/0
150.1.0.0/24 is subnetted, 1 subnets
S 150.1.1.0 [1/0] via 10.0.0.5
150.2.0.0/24 is subnetted, 1 subnets
S 150.2.2.0 [1/0] via 10.0.0.9
150.3.0.0/24 is subnetted, 1 subnets
C 150.3.3.0 is directly connected, FastEthernet0/0
S* 0.0.0.0/0 [1/0] via 10.0.0.9

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.1.1.1 to network 0.0.0.0

150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
D* 0.0.0.0/0 [90/30720] via 150.1.1.1, 00:00:50, FastEthernet0/0

Task 3

The requirements for this task are three-fold. First, all TCP and ICMP traffic should be policy routed via 10.0.0.2 (R2). This can be completed by specifying the next hop or interface for this type of traffic. The second requirement is that in the event that the path to R2 is not available, the same traffic should then be sent via R3; however, this should only be done based on CDP reachability information. In other words, if CDP determines that R3 is unavailable, the traffic should not be sent to this router.

To satisfy this second requirement, we need to use the **verify-availability** keyword. The **verify-availability** keyword is used to force the router to check the Cisco Discovery Protocol (CDP) database to determine if an entry is available for the next hop that is specified by the **set ip default next-hop** command. This command prevents traffic from being blackholed in situations where the specified next hop IP address is not directly connected to the router, for example. In such cases, if the specified next hop IP address does become unreachable, the router would never know and will continue sending

https://t.me/learningnets

packets to it, resulting in a blackholing of traffic. This keyword is applied using a separate line in the route map.

Finally, the third requirement is that all other traffic be policy routed via R3. This can be done by specifying either the next hop address or specifying the egress interface. The requirements within this task are satisfied by configuring R1 as follows:

```
R1(config)#ip access-list extended TCP-AND-ICMP
R1(config-ext-nacl)#permit icmp 150.1.1.0 0.0.0.255 any
R1(config-ext-nacl)#permit tcp 150.1.1.0 0.0.0.255 any
R1(config-ext-nacl)#exit
R1(config)#route-map LAN-PBR permit 10
R1(config-route-map)#match ip address TCP-AND-ICMP
R1(config-route-map)#set ip next-hop 10.0.0.2
R1(config-route-map)#set ip next-hop verify-availability
R1(config-route-map)#set ip default next-hop 10.0.0.6
R1(config-route-map)#exit
R1(config)#route-map LAN-PBR permit 20
R1(config-route-map)#set ip next-hop 10.0.0.6
R1(config-route-map)#exit
R1(config)#interface fastethernet 0/0
R1(config-if)#ip policy route-map LAN-PBR
R1(config-if)#exit
```

Following this, verify your route map using the **show route-map <name>** command:

```
R1#show route-map LAN-PBR
route-map LAN-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): TCP-AND-ICMP
Set clauses:
ip next-hop 10.0.0.2
ip next-hop verify-availability
ip default next-hop 10.0.0.6
Policy routing matches: 0 packets, 0 bytes
route-map LAN-PBR, permit, sequence 20
Match clauses:
Set clauses:
ip next-hop 10.0.0.6
Policy routing matches: 0 packets, 0 bytes
```

Next, verify your solution by pinging or initiating a Telnet session to R3. You can also

https://t.me/learningnets

Technet24

enable debugging for PBR to verify matches against the configured policy (turn the debug on before you ping):

R4#**ping 150.3.3.3**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/18/20 ms

R1#**debug ip policy**
Policy routing debugging is on
*Jun 3 10:54:53.467: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 10:54:53.467: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.2, len 100, FIB policy routed**
*Jun 3 10:54:53.487: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 10:54:53.487: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.2, len 100, FIB policy routed**
*Jun 3 10:54:53.507: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 10:54:53.507: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.2, len 100, FIB policy routed**
*Jun 3 10:54:53.523: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 10:54:53.527: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.2, len 100, FIB policy routed**
*Jun 3 10:54:53.543: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 10:54:53.543: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.2, len 100, FIB policy routed**

Next, verify failover based on CDP reachability by disabling the R1-R2 link and performing the same ping test from R4 to the LAN IP address of R3 (ping before and then after you shut the interface). Please remember to open the interface for traffic after testing:

R4#**ping 150.3.3.3**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
!!!!!

https://t.me/learningnets

Success rate is 100 percent (5/5), round-trip min/avg/max = 16/18/20 ms

R1(config)#**interface serial 0/0**
R1(config-if)#**shut**
R1(config-if)#
***Jun 3 11:23:40.587: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.6, len 100, FIB policy routed**
*Jun 3 11:23:40.607: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 11:23:40.607: CEF-IP-POLICY: fib for addr 10.0.0.2 is default; Nexthop rejected**
***Jun 3 11:23:40.607: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.6, len 100, FIB policy routed**
*Jun 3 11:23:40.623: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 11:23:40.623: CEF-IP-POLICY: fib for addr 10.0.0.2 is default; Nexthop rejected**
***Jun 3 11:23:40.623: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.6, len 100, FIB policy routed**
*Jun 3 11:23:40.643: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 11:23:40.643: CEF-IP-POLICY: fib for addr 10.0.0.2 is default; Nexthop rejected**
***Jun 3 11:23:40.643: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.6, len 100, FIB policy routed**
*Jun 3 11:23:40.659: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 11:23:40.663: CEF-IP-POLICY: fib for addr 10.0.0.2 is default; Nexthop rejected**
***Jun 3 11:23:40.663: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.6, len 100, FIB policy routed**

Task 4

This task requires that Enhanced Object Tracking is used to track the status of each of the routers' WAN connections to R1. This task is completed as follows:

R2(config)#**track 1 interface serial 0/0 line-protocol**
R2(config-track)#**exit**
R2(config)#**route-map LAN-PBR permit 10**
R2(config-route-map)#**set ip next-hop verify-availability 10.0.0.1 1 track 1**

https://t.me/learningnets

Technet24

R2(config-route-map)#**set ip next-hop 10.0.0.10**
R2(config-route-map)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip policy route-map LAN-PBR**
R2(config-if)#**exit**

R3(config)#**track 1 interface serial 1/0 line-protocol**
R3(config-track)#**exit**
R3(config)#**route-map LAN-PBR permit 10**
R3(config-route-map)#**set ip next-hop verify-availability 10.0.0.5 1 track 1**
R3(config-route-map)#**set ip next-hop 10.0.0.9**
R3(config-route-map)#**exit**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip policy route-map LAN-PBR**
R3(config-if)#**exit**

Following this, first verify your EOT configuration using the **show track** command:

R2#**show track**
Track 1
Interface Serial0/0 line-protocol
Line protocol is Up
1 change, last change 00:00:26
Tracked by:
ROUTE-MAP 0

R3#**show track**
Track 1
Interface Serial1/0 line-protocol
Line protocol is Up
1 change, last change 00:00:32
Tracked by:
ROUTE-MAP 0

Next, verify route map configuration using the **show route-map <name>** command:

R2#**show route-map LAN-PBR**
route-map LAN-PBR, permit, sequence 10
Match clauses:
Set clauses:
ip next-hop verify-availability 10.0.0.1 1 track 1 [up]
ip next-hop 10.0.0.10
Policy routing matches: 0 packets, 0 bytes

https://t.me/learningnets

R3#**show route-map LAN-PBR**
route-map LAN-PBR, permit, sequence 10
Match clauses:
Set clauses:
ip next-hop verify-availability 10.0.0.5 1 track 1 [up]
ip next-hop 10.0.0.9
Policy routing matches: 0 packets, 0 bytes

To test your solution, first ping from the R2 or R3 LAN subnet to the R4. To view PBR operation in real time, enable PBR debugging while sending the pings. The following shows host 150.2.2.254 (not shown in the topology) sending pings to 150.1.1.4 (R4s LAN IP) while PBR debugging is enabled on R2:

R2#**debug ip policy**
Policy routing debugging is on
R2#
R2#
R2#
R2#
*May 17 18:08:49.475: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, len 100, FIB policy match
***May 17 18:08:49.475: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, g=10.0.0.1, len 100, FIB policy routed**
*May 17 18:08:49.479: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, len 100, FIB policy match
***May 17 18:08:49.479: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, g=10.0.0.1, len 100, FIB policy routed**
*May 17 18:08:49.487: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, len 100, FIB policy match
***May 17 18:08:49.487: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, g=10.0.0.1, len 100, FIB policy routed**
*May 17 18:08:49.491: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, len 100, FIB policy match
***May 17 18:08:49.491: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, g=10.0.0.1, len 100, FIB policy routed**
*May 17 18:08:49.499: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, len 100, FIB policy match
***May 17 18:08:49.499: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, g=10.0.0.1, len 100, FIB policy routed**

Next, verify redundancy by disabling the R1-R2 link and performing the same test:

https://t.me/learningnets
Technet24

R2(config)#**interface serial 0/0**
R2(config-if)#**shut**
R2(config-if)#
***May 17 18:10:48.739: %TRACKING-5-STATE: 1 interface Se0/0 line-protocol Up->Down**
*May 17 18:10:48.763: %DUAL-5-NBRCHANGE: IP-EIGRP(0) 254: Neighbor 10.0.0.1 (Serial0/0) is down: interface down
*May 17 18:10:50.739: %LINK-5-CHANGED: Interface Serial0/0, changed state to administratively down
*May 17 18:10:51.739: %LINEPROTO-5-UPDOWN: Line protocol on Interface Serial0/0, changed state to down
R2(config-if)#
R2(config-if)#
*May 17 18:10:59.215: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, len 100, FIB policy match
***May 17 18:10:59.215: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, g=10.0.0.10, len 100, FIB policy routed**
*May 17 18:10:59.251: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, len 100, FIB policy match
***May 17 18:10:59.251: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, g=10.0.0.10, len 100, FIB policy routed**
*May 17 18:10:59.283: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, len 100, FIB policy match
***May 17 18:10:59.283: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, g=10.0.0.10, len 100, FIB policy routed**
*May 17 18:10:59.315: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, len 100, FIB policy match
***May 17 18:10:59.315: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, g=10.0.0.10, len 100, FIB policy routed**
*May 17 18:10:59.347: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, len 100, FIB policy match
***May 17 18:10:59.351: IP: s=150.2.2.254 (FastEthernet0/0), d=150.1.1.4, g=10.0.0.10, len 100, FIB policy routed**

https://t.me/learningnets

CCNP Lab 060: Cisco IOS PBR, SLA and EOT Lab

Lab Objective:

The focus of this lab is to understand PBR implementation and configuration in Cisco IOS routers. Additional technologies include IP SLA Operations and Enhanced Object Tracking.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology. In addition, configure a Loopback 0 interface on R1 with the IP address 1.1.1.1/32.

Task 2

Configure EIGRP as illustrated in the topology. Ensure that no EIGRP packets are sent out of the LAN interfaces of R2 and R3. Do NOT enable EIGRP for the R2-R3 link. Ensure that R1 advertises a default route to R4. Next, configure static default routes on

https://t.me/learningnets

R2 and R3 as follows:

- R2 should have a default static route pointing to R3
- R3 should have a default static route pointing to R2

Verify your configuration using the appropriate commands on all routers in the network.

Task 3

Configure IOS PBR on R1 so that when R1 loses the EIGRP route to the 150.2.2.0/24 subnet, all traffic sourced from the 150.1.1.0/24 subnet to this destination is sent via R3. In addition to this, configure IOS PBR on R1 so that when R1 loses the EIGRP route to the 150.3.3.0/24 subnet, all traffic sourced from the 150.1.1.0/24 subnet to this destination is sent via R2. To avoid blackholing traffic, configure R1 to check the CDP database to determine if an entry is available for the specified next hop address. Verify your configuration using the appropriate commands.

Task 4

Configure PBR on R2 and R3 so that when either of their WAN connections to R1 is down, only HTTP and HTTPS should be permitted from the local LAN segment and sent across the R2-R3 WAN link. Assuming that QoS is enabled on the R2-R3 link, this traffic should be forwarded using an IP Precedence of 4. All other traffic from the LAN subnet of the router that lost its WAN connection to R1 should be forwarded with an IP Precedence of 2.

When the WAN link to R1 is up, all traffic should follow the EIGRP route through R1. When completing this task, you MUST adhere to the following restrictions:

- You MUST use Cisco Enhanced Object Tracking (EOT) in your solution
- You MUST use Cisco IOS IP SLA Operations and in your solution
- The Cisco IOS IP SLA Operation should ping the connected IP address of R1
- As long as EIGRP routing information is present, PBR should be inactive

Verify the PBR configuration using the appropriate show commands or debugging commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

https://t.me/learningnets

Technet24

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

R1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 0.0.0.0 to network 0.0.0.0

10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.0 is directly connected, Serial0/0
C 10.0.0.4 is directly connected, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 10.0.0.2, 00:05:52, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2172416] via 10.0.0.6, 00:03:51, Serial0/1
D* 0.0.0.0/0 is a summary, 00:00:05, Null0

R2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 10.0.0.10 to network 0.0.0.0

10.0.0.0/30 is subnetted, 3 subnets
C 10.0.0.8 is directly connected, Serial0/1
C 10.0.0.0 is directly connected, Serial0/0

https://t.me/learningnets

D 10.0.0.4 [90/2681856] via 10.0.0.1, 00:03:58, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:05:58, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2684416] via 10.0.0.1, 00:03:58, Serial0/0
S* 0.0.0.0/0 [1/0] via 10.0.0.10

R3#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 10.0.0.9 to network 0.0.0.0

10.0.0.0/30 is subnetted, 3 subnets
C 10.0.0.8 is directly connected, Serial1/1
D 10.0.0.0 [90/21024000] via 10.0.0.5, 00:04:00, Serial1/0
C 10.0.0.4 is directly connected, Serial1/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/20514560] via 10.0.0.5, 00:04:00, Serial1/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/21026560] via 10.0.0.5, 00:04:00, Serial1/0
150.3.0.0/24 is subnetted, 1 subnets
C 150.3.3.0 is directly connected, FastEthernet0/0
S* 0.0.0.0/0 [1/0] via 10.0.0.9

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.1.1.1 to network 0.0.0.0

https://t.me/learningnets

150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
D* 0.0.0.0/0 [90/30720] via 150.1.1.1, 00:00:16, FastEthernet0/0

Task 3

In order to complete this task, we need to use the **set ip default next-ho**p route map set clause. In order to ensure that CDP reachability is verified, we also need to use the **set ip default next-hop verify-availability** set clause. The **verify-availability** keyword forces the router to check the CDP database to determine if an entry is available for the next hop that is specified by the **set ip default next-hop** command. This command prevents traffic from being blackholed in situations where the specified next hop IP address is not directly connected to the router, for example. In such cases, if the specified next hop IP address does become unreachable, the router would never know and will continue sending packets to it, resulting in a blackholing of traffic. This keyword is applied using a separate line in the route map. This task is completed as follows:

R1(config)#**ip access-list extended TO-R2-LAN**
R1(config-ext-nacl)#**permit ip 150.1.1.0 0.0.0.255 150.2.2.0 0.0.0.255**
R1(config-ext-nacl)#**exit**
R1(config)#**ip access-list extended TO-R3-LAN**
R1(config-ext-nacl)#**permit ip 150.1.1.0 0.0.0.255 150.3.3.0 0.0.0.255**
R1(config-ext-nacl)#**exit**
R1(config)#**route-map LAN-PBR permit 10**
R1(config-route-map)#**match ip address TO-R2-LAN**
R1(config-route-map)#**set ip next-hop verify-availability**
R1(config-route-map)#**set ip default next-hop 10.0.0.6**
R1(config-route-map)#**exit**
R1(config)#**route-map LAN-PBR permit 20**
R1(config-route-map)#**match ip address TO-R3-LAN**
R1(config-route-map)#**set ip next-hop verify-availability**
R1(config-route-map)#**set ip default next-hop 10.0.0.2**
R1(config-route-map)#**exit**
R1(config)#**route-map LAN-PBR deny 30**
R1(config-route-map)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip policy route-map LAN-PBR**
R1(config-if)#**exit**
Next, verify your PBR configuration using the **show route-map <name>** command:

https://t.me/learningnets

R1#**show route-map LAN-PBR**
route-map LAN-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): TO-R2-LAN
Set clauses:
ip next-hop verify-availability
ip default next-hop 10.0.0.6
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, permit, sequence 20
Match clauses:
ip address (access-lists): TO-R3-LAN
Set clauses:
ip next-hop verify-availability
ip default next-hop 10.0.0.2
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, deny, sequence 30
Match clauses:
Set clauses:
Policy routing matches: 0 packets, 0 bytes

Test your solution by shutting first shutting down the R1-R2 link and then pinging 150.2.2.0/24 from R4. You can enable PBR debugging to view PBR operation in real time (do so before you issue the ping):

R4#**ping 150.2.2.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 32/32/32 ms

R1#**debug ip policy**
Policy routing debugging is on
R1#**configure terminal**
Enter configuration commands, one per line. End with CNTL/Z.
R1(config)#**interface serial 0/0**
R1(config-if)#**shutdown**
R1(config-if)#**end**
R1#
R1#
*Jun 3 17:58:19.942: IP: s=150.1.1.4 (FastEthernet0/0), d=150.2.2.2, len 100, FIB

https://t.me/learningnets

Technet24

policy match
***Jun 3 17:58:19.942: IP: s=150.1.1.4 (FastEthernet0/0), d=150.2.2.2, g=10.0.0.6, len 100, FIB policy routed**
*Jun 3 17:58:19.974: IP: s=150.1.1.4 (FastEthernet0/0), d=150.2.2.2, len 100, FIB policy match
***Jun 3 17:58:19.974: IP: s=150.1.1.4 (FastEthernet0/0), d=150.2.2.2, g=10.0.0.6, len 100, FIB policy routed**
*Jun 3 17:58:20.006: IP: s=150.1.1.4 (FastEthernet0/0), d=150.2.2.2, len 100, FIB policy match
***Jun 3 17:58:20.006: IP: s=150.1.1.4 (FastEthernet0/0), d=150.2.2.2, g=10.0.0.6, len 100, FIB policy routed**
*Jun 3 17:58:20.038: IP: s=150.1.1.4 (FastEthernet0/0), d=150.2.2.2, len 100, FIB policy match
***Jun 3 17:58:20.038: IP: s=150.1.1.4 (FastEthernet0/0), d=150.2.2.2, g=10.0.0.6, len 100, FIB policy routed**
*Jun 3 17:58:20.070: IP: s=150.1.1.4 (FastEthernet0/0), d=150.2.2.2, len 100, FIB policy match
***Jun 3 17:58:20.070: IP: s=150.1.1.4 (FastEthernet0/0), d=150.2.2.2, g=10.0.0.6, len 100, FIB policy routed**

Next, test the Policy Based Routing operation for the 150.3.3.0/24 subnet by shutting down the R1-R3 link and pinging R3s LAN IP address from R4:

R4#**ping 150.3.3.3**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.3.3.3, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/18/20 ms

R1#**debug ip policy**
Policy routing debugging is on
R1#**configure terminal**
Enter configuration commands, one per line. End with CNTL/Z.
R1(config)#**interface serial 0/1**
R1(config-if)#**shutdown**
R1(config-if)#**end**
R1#
R1#
*Jun 3 18:04:25.286: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match

https://t.me/learningnets

***Jun 3 18:04:25.286: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.2, len 100, FIB policy routed**
*Jun 3 18:04:25.302: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 18:04:25.306: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.2, len 100, FIB policy routed**
*Jun 3 18:04:25.322: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 18:04:25.322: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.2, len 100, FIB policy routed**
*Jun 3 18:04:25.342: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 18:04:25.342: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.2, len 100, FIB policy routed**
*Jun 3 18:04:25.362: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, len 100, FIB policy match
***Jun 3 18:04:25.362: IP: s=150.1.1.4 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.2, len 100, FIB policy routed**

Task 4

This task requires the use of the **set ip next-hop <address>** and the **set ip next-hop verify-availability <address> <sequence> track <object number>]** route map mode subcommands. The issue is that this command supersedes dynamic routing as far as traffic forwarding goes. Therefore, to ensure that PBR is used ONLY when the dynamic routing information is no longer available, while still using the **set ip next-hop [<address> | verify-availability <address> <sequence> track <object number>]** route map mode subcommand, we need to use the NOT command with a Boolean tracked object.

The NOT keyword negates the state of the object, which means that when the object is up, the tracked list detects the object as down. In other words, what will happen is that when the tracked object (tracked via IP SLA Operation) is up, PBR will see it as down, therefore using the dynamic routing information. Inversely, when the tracked object is down, PBR will see it as up and therefore implement policy routing. This task is completed as follows:

R1(config)#**ip sla responder**

R2(config)#**ip sla responder**
R2(config)#**ip access-list extended HTTP-AND-HTTPS**
R2(config-ext-nacl)#**permit tcp any any eq www**

https://t.me/learningnets

Technet24

R2(config-ext-nacl)#**permit tcp any any eq 443**
R2(config-ext-nacl)#**exit**
R2(config)#**ip sla 1**
R2(config-ip-sla)#**Icmp-echo 10.0.0.1 source-ip 10.0.0.2**
R2(config-ip-sla-echo)#**exit**
R2(config)#**ip sla schedule 1 start-time now life forever**
R2(config)#**track 1 rtr 1**
R2(config-track)#**exit**
R2(config)#**track 2 list boolean or**
R2(config-track)#**object 1 not**
R2(config-track)#**exit**
R2(config)#**route-map LAN-PBR permit 10**
R2(config-route-map)#**match ip address HTTP-AND-HTTPS**
R2(config-route-map)#**set ip next-hop verify-availability 10.0.0.10 1 track 2**
R2(config-route-map)#**set ip precedence 4**
R2(config-route-map)#**exit**
R2(config)#**route-map LAN-PBR permit 20**
R2(config-route-map)#**set ip next-hop verify-availability 10.0.0.10 1 track 2**
R2(config-route-map)#**set ip precedence 2**
R2(config-route-map)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip policy route-map LAN-PBR**
R2(config-if)#**exit**

R3(config)#**ip sla responder**
R3(config)#**ip sla 1**
R3(config-ip-sla)#**Icmp-echo 10.0.0.5 source-ipaddr 10.0.0.6**
R3(config-ip-sla-echo)#**exit**
R3(config)#**ip sla schedule 1 life forever start-time now**
R3(config)#**track 1 rtr 1**
R3(config-track)#**exit**
R3(config)#**track 2 list boolean or**
R3(config-track)#**object 1 not**
R3(config-track)#**exit**
R3(config)#**ip access-list extended HTTP-AND-HTTPS**
R3(config-ext-nacl)#**permit tcp any any eq www**
R3(config-ext-nacl)#**permit tcp any any eq 443**
R3(config-ext-nacl)#**route-map LAN-PBR permit 10**
R3(config-route-map)#**match ip address HTTP-AND-HTTPS**

https://t.me/learningnets

R3(config-route-map)#**set ip next-hop verify-availability 10.0.0.9 1 track 2**
R3(config-route-map)#**set ip precedence 4**
R3(config-route-map)#**exit**
R3(config)#**route-map LAN-PBR permit 20**
R3(config-route-map)#**set ip next-hop verify-availability 10.0.0.9 1 track 2**
R3(config-route-map)#**set ip precedence 2**
R3(config-route-map)#**exit**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip policy route-map LAN-PBR**
R3(config-if)#**exit**

Given this configuration, as long as the IP SLA Operation reports success, the tracked object will show up as down, which in turn means that PBR will NOT be used. The IP SLA Operation has been configured to ping directly connected R1 WAN interface from both routers. The assumption here is that if R2 and R3 both cannot ping the WAN interfaces to which they are connected to R1, then it is safe to assume that EIGRP is also down between these two routers and R1. Following this configuration, first verify the IP SLA Operation state using the **show ip sla statistics** command on both routers:

R2#**show ip sla statistics 1**
Round trip time (RTT) Index 1
Latest RTT: 11 ms
Latest operation start time: *01:22:54.466 UTC Wed May 18 2011
Latest operation return code: OK
Number of successes: 9
Number of failures: 0
Operation time to live: Forever

R3#**show ip sla statistics 1**
Round trip time (RTT) Index 1
Latest RTT: 12 ms
Latest operation start time: *12:21:00.694 UTC Tue May 17 2011
Latest operation return code: OK
Number of successes: 6
Number of failures: 0
Operation time to live: Forever

Next, verify the EOT configuration using the **show track** command on both routers:

R2#**show track**
Track 1
Response Time Reporter 1 state

https://t.me/learningnets
Technet24

State is Up
4 changes, last change 00:09:25
Latest operation return code: OK
Latest RTT (millisecs) 11
Tracked by:
Track-list 2

Track 2
List boolean or
Boolean OR is Down
5 changes, last change 00:09:25
object 1 not Up
Tracked by:
ROUTE-MAP 0

R3#**show track**
Track 1
Response Time Reporter 1 state
State is Up
2 changes, last change 00:06:45
Latest operation return code: OK
Latest RTT (millisecs) 12
Tracked by:
Track-list 2

Track 2
List boolean or
Boolean OR is Down
3 changes, last change 00:06:45
object 1 not Up
Tracked by:
ROUTE-MAP 0

Note in the output above that track-list 2, which is tracking track list 1 and is also being tracked in the PBR configuration shows a down state. This is because of the Boolean NOT keyword in the EOT configuration which inverses the logic. As long as track list 1 shows up, track list 2 will show as down. When track list 1 shows down, track list 2 will show up. This can be verified by looking at the route maps configured on both routers using the **show route-map** command:

R2#**show route-map LAN-PBR**
route-map LAN-PBR, permit, sequence 10

https://t.me/learningnets

Match clauses:
ip address (access-lists): HTTP-AND-HTTPS
Set clauses:
ip precedence flash-override
ip next-hop verify-availability 10.0.0.10 1 track 2 [down]
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, permit, sequence 20
Match clauses:
Set clauses:
ip precedence immediate
ip next-hop verify-availability 10.0.0.10 1 track 2 [down]
Policy routing matches: 0 packets, 0 bytes

R3#**show route-map LAN-PBR**
route-map LAN-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): HTTP-AND-HTTPS
Set clauses:
ip precedence flash-override
ip next-hop verify-availability 10.0.0.9 1 track 2 [down]
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, permit, sequence 20
Match clauses:
Set clauses:
ip next-hop verify-availability 10.0.0.9 1 track 2 [down]
Policy routing matches: 0 packets, 0 bytes

To test our configuration, first initiate an HTTP or HTTPS session from LAN-to-LAN between R2 and R3. As long as the EIGRP is up and IP SLA Operations reports an OK, the PBR configuration will be ignored and normal forwarding will be used. You can enable HTTP and HTTPS functionality on Cisco IOS routers using the **ip http server** or **ip http secure-server** global configuration commands on the routers. The following shows forwarding for an HTTP connection from host 150.2.2.254 (connected to R2) to 150.3.3.3 (R3) while EIGRP is up and Policy-Based Routing debugging is enabled on R2:

R2#**debug ip policy**
Policy routing debugging is on
*May 18 01:36:14.670: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, len 44, FIB policy match

https://t.me/learningnets

Technet24

***May 18 01:36:14.670: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, len 44, FIB policy rejected - normal forwarding**
*May 18 01:36:14.686: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, len 40, FIB policy match
***May 18 01:36:14.686: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, len 40, FIB policy rejected - normal forwarding**
*May 18 01:36:14.686: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, len 40, FIB policy match
***May 18 01:36:14.686: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, len 40, FIB policy rejected - normal forwarding**

Next, shut down BOTH of the WAN interfaces on R1 and verify the route maps configured on R2 and R3 using the **show route-map <name>** command:

R1(config)#**interface serial 0/0**
R1(config-if)#**shutdown**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**shutdown**
R1(config-if)#**exit**

R2#**show route-map LAN-PBR**
route-map LAN-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): HTTP-AND-HTTPS
Set clauses:
ip precedence flash-override
ip next-hop verify-availability 10.0.0.10 1 track 2 [up]
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, permit, sequence 20
Match clauses:
Set clauses:
ip precedence immediate
ip next-hop verify-availability 10.0.0.10 1 track 2 [up]
Policy routing matches: 0 packets, 0 bytes

R3#**show route-map LAN-PBR**
route-map LAN-PBR, permit, sequence 10
Match clauses:
ip address (access-lists): HTTP-AND-HTTPS
Set clauses:

https://t.me/learningnets

ip precedence flash-override
ip next-hop verify-availability 10.0.0.9 1 track 2 [up]
Policy routing matches: 0 packets, 0 bytes

route-map LAN-PBR, permit, sequence 20
Match clauses:
Set clauses:
ip next-hop verify-availability 10.0.0.9 1 track 2 [up]
Policy routing matches: 0 packets, 0 bytes

Next, an HTTP connection is again initiated from the 150.2.2.254 host to 150.3.3.3 while Policy Based Routing (PBR) debugging is enabled on R2:

R2#**debug ip policy**
Policy routing debugging is on
R2#
R2#
*May 18 02:28:12.477: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, len 44, FIB policy match
***May 18 02:28:12.477: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.10, len 44, FIB policy routed**
*May 18 02:28:12.493: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, len 40, FIB policy match
***May 18 02:28:12.493: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.10, len 40, FIB policy routed**
*May 18 02:28:12.493: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, len 40, FIB policy match
***May 18 02:28:12.493: IP: s=150.2.2.254 (FastEthernet0/0), d=150.3.3.3, g=10.0.0.10, len 40, FIB policy routed**

https://t.me/learningnets

Technet24

CCNP Lab 061: Cisco IOS GLBP Lab

Lab Objective:

The focus of this lab is to understand the Gateway Load Balancing Protocol (GLBP) implementation and configuration in Cisco IOS routers. Additional technologies include security and timers.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Configure EIGRP as illustrated in the topology. Redistribute the LAN subnets into EIGRP.

https://t.me/learningnets

Technet24

Verify your configuration using the appropriate commands on all routers in the network.

Task 3

Configure GLBP on R1, R2, and R4. Ensure that R1 is elected AVG. R2 should be standby. The gateway IP should be 150.1.1.254. Verify your configuration using the appropriate commands.

Task 4

Configure MD5 authentication for GLBP. Use a password of 'CCNP' for authentication and a key chain named GLBP. Verify your configuration using the appropriate commands.

Task 5

In the future, NAT will be implemented on R1, R2, and R4. In preparation for this, configure GLBP so that a host will be guaranteed to use the same virtual MAC address as long as the number of Virtual Forwarders (VFs) in the GLBP group is constant. Verify your configuration using the appropriate commands.

Task 6

To allow for faster failover of GLBP, configure R1, R2 and R4 so that the gateways send five Hellos every second. If four Hellos are missed, then GLBP should be declared down. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/21024000] via 10.0.0.6, 00:03:06, Serial0/1
D 10.0.0.12 [90/21024000] via 10.0.0.6, 00:02:11, Serial0/1
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.6, 00:03:06, Serial0/1

R2#**show ip route eigrp**

https://t.me/learningnets

10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.12 [90/21024000] via 10.0.0.10, 00:02:15, Serial0/1
D 10.0.0.4 [90/21024000] via 10.0.0.10, 00:03:10, Serial0/1
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.10, 00:03:10, Serial0/1

R3#**show ip route eigrp**
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/20514560] via 10.0.0.14, 00:02:16, Serial1/2
[170/20514560] via 10.0.0.9, 00:02:16, Serial1/1
[170/20514560] via 10.0.0.5, 00:02:16, Serial1/0

R4#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/21024000] via 10.0.0.13, 00:02:22, Serial0/0
D 10.0.0.4 [90/21024000] via 10.0.0.13, 00:02:22, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.13, 00:02:22, Serial0/0

Task 3

To complete this task, you need to configure R1 with the highest priority. In order to ensure that R2 is elected standby, this router should be assigned the second highest priority. By default, GLBP assigns a priority of 100. Finally, you need to explicitly enable preemption as it is disabled by default. This task is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**glbp 1 priority 110**
R1(config-if)#**glbp 1 ip 150.1.1.254**
R1(config-if)#**glbp 1 preempt**
R1(config-if)#**exit**

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**glbp 1 priority 105**
R2(config-if)#**glbp 1 ip 150.1.1.254**
R2(config-if)#**glbp 1 preempt**
R2(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**glbp 1 preempt**
R4(config-if)#**glbp 1 ip 150.1.1.254**
R4(config-if)#**exit**

Following this, verify your configuration using the **show glbp** command:

https://t.me/learningnets
Technet24

R1#**show glbp fastethernet 0/0 1 brief**
Interface Grp Fwd Pri State Address Active router Standby router
Fa0/0 1 - 110 Active 150.1.1.254 local 150.1.1.2
Fa0/0 1 1 - Active 0007.b400.0101 local -
Fa0/0 1 2 - Listen 0007.b400.0102 150.1.1.2 -
Fa0/0 1 3 - Listen 0007.b400.0103 150.1.1.4 -

R2#**show glbp fastethernet 0/0 1 brief**
Interface Grp Fwd Pri State Address Active router Standby router
Fa0/0 1 - 105 Standby 150.1.1.254 150.1.1.1 local
Fa0/0 1 1 - Listen 0007.b400.0101 150.1.1.1 -
Fa0/0 1 2 - Active 0007.b400.0102 local -
Fa0/0 1 3 - Listen 0007.b400.0103 150.1.1.4 -

R4#**show glbp fastethernet 0/0 1 brief**
Interface Grp Fwd Pri State Address Active router Standby router
Fa0/0 1 - 100 Listen 150.1.1.254 150.1.1.1 150.1.1.2
Fa0/0 1 1 - Listen 0007.b400.0101 150.1.1.1 -
Fa0/0 1 2 - Listen 0007.b400.0102 150.1.1.2 -
Fa0/0 1 3 - Active 0007.b400.0103 local -

Task 4

R1(config)#**key chain GLBP**
R1(config-keychain)#**key 1**
R1(config-keychain-key)#**key-string CCNP**
R1(config-keychain-key)#**exit**
R1(config-keychain)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**glbp 1 authentication md5 key-chain GLBP**
R1(config-if)#**exit**
R1(config)#**end**

R2(config)#**key chain GLBP**
R2(config-keychain)#**key 1**
R2(config-keychain-key)#**key-string CCNP**
R2(config-keychain-key)#**exit**
R2(config-keychain)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**glbp 1 authentication md5 key-chain GLBP**
R2(config-if)#**exit**
R2(config)#**end**

https://t.me/learningnets

R4(config)#**key chain GLBP**
R4(config-keychain)#**key 1**
R4(config-keychain-key)#**key-string CCNP**
R4(config-keychain-key)#**exit**
R4(config-keychain)#**exit**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**glbp 1 authentication md5 key-chain GLBP**
R4(config-if)#**exit**
R4(config)#**end**

Next, verify your configuration using the **show key chain** and **show glbp** commands:

R1#**show key chain GLBP**
Key-chain GLBP:
key 1 -- text "CCNP"
accept lifetime (always valid) - (always valid) [valid now]
send lifetime (always valid) - (always valid) [valid now]

R1#**show glbp fastethernet 0/0 1**
FastEthernet0/0 - Group 1
State is Active
2 state changes, last state change 00:11:27
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 2.780 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Authentication MD5, key-chain "GLBP"
Preemption enabled, min delay 0 sec
Active is local
Standby is 150.1.1.2, priority 105 (expires in 8.620 sec)
Priority 110 (configured)
Weighting 100 (default 100), thresholds: lower 1, upper 100
Load balancing: round-robin
Group members:
000d.289e.f940 (150.1.1.2) authenticated
000f.235e.ec80 (150.1.1.1) local
000f.235e.f120 (150.1.1.4) authenticated
There are 3 forwarders (1 active)

[Truncated Output]

Task 5

https://t.me/learningnets

Stateful applications such as Network Address Translation (NAT) require that state information is maintained for each connection. It is therefore important to ensure that a host will use the same gateway as this is where the NAT translations will exist. By default, GLBP will use round-robin load balancing. This can cause issues when NATing. To ensure that a host will be guaranteed to use the same virtual MAC address as long as the number of Virtual Forwarders (VFs) in the GLBP group is constant we need to configure GLBP to use host dependent load balancing. This task is completed on R1 and R2. The only reason R4 would ever become GLBP AVG would be when R1 and R2 are down. In this case, there is no need to implement any type of load balancing as it will be the only gateway.

The reason that this command is required on R2 is that if R1 fails, it assumes roles of AVG. It should therefore be configured to use this load balancing method for itself and R4:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**glbp 1 load-balancing host-dependent**
R1(config-if)#**exit**

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**glbp 1 load-balancing host-dependent**
R2(config-if)#**exit**

Verify the adjusted load balancing method using the **show glbp** command:

R1#**show glbp fastethernet 0/0 1**
FastEthernet0/0 - Group 1
State is Active
2 state changes, last state change 00:19:44
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 0.888 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Authentication MD5, key-chain “GLBP”
Preemption enabled, min delay 0 sec
Active is local
Standby is 150.1.1.2, priority 105 (expires in 9.740 sec)
Priority 110 (configured)
Weighting 100 (default 100), thresholds: lower 1, upper 100
Load balancing: host-dependent
Group members:
000d.289e.f940 (150.1.1.2) authenticated

https://t.me/learningnets

000f.235e.ec80 (150.1.1.1) local
000f.235e.f120 (150.1.1.4) authenticated
There are 3 forwarders (1 active)

[Truncated Output]

R2#**show glbp fastethernet 0/0 1**
FastEthernet0/0 - Group 1
State is Standby
1 state change, last state change 00:16:48
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 0.000 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Authentication MD5, key-chain "GLBP"
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 8.096 sec)
Standby is local
Priority 105 (configured)
Weighting 100 (default 100), thresholds: lower 1, upper 100
Load balancing: host-dependent
Group members:
000d.289e.f940 (150.1.1.2) local
000f.235e.ec80 (150.1.1.1) authenticated
000f.235e.f120 (150.1.1.4) authenticated
There are 3 forwarders (1 active)

[Truncated Output]

Task 6

The requirements for this task are straightforward. To ensure that routers send five Hellos every two seconds, we need to perform basic mathematical calculations. First, there are 1000 milliseconds in a second, therefore, GLBP should be configured to send Hellos every 200 ms. Next, if four Hellos are missed, GLBP should be declared down. This means we need to configure a hold time of 800 ms. This task is completed on all four GLBP routers as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**glbp 1 timers msec 200 msec 800**
R1(config-if)#**exit**

R2(config)#**interface fastethernet 0/0**

https://t.me/learningnets

Technet24

R2(config-if)#**glbp 1 timers msec 200 msec 800**
R2(config-if)#**exit**

R3(config)#**interface fastethernet 0/0**
R3(config-if)#**glbp 1 timers msec 200 msec 800**
R3(config-if)#**exit**

Next, verify your GLBP configuration using the **show glbp** command:

R1#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Active
2 state changes, last state change 01:15:11
Virtual IP address is 150.1.1.254
Hello time 200 msec, hold time 800 msec
Next hello sent in 0.004 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Authentication MD5, key-chain "GLBP"
Preemption enabled, min delay 0 sec
Active is local
Standby is 150.1.1.2, priority 105 (expires in 0.744 sec)
Priority 110 (configured)
Weighting 100 (default 100), thresholds: lower 1, upper 100
Load balancing: host-dependent
Group members:
000d.289e.f940 (150.1.1.2) authenticated
000f.235e.ec80 (150.1.1.1) local
000f.235e.f120 (150.1.1.4) authenticated
There are 3 forwarders (1 active)

[Truncated Output]

R2#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Standby
4 state changes, last state change 00:08:54
Virtual IP address is 150.1.1.254
Hello time 200 msec, hold time 800 msec
Next hello sent in 0.000 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Authentication MD5, key-chain "GLBP"
Preemption enabled, min delay 0 sec

https://t.me/learningnets

Active is 150.1.1.1, priority 110 (expires in 0.608 sec)
Standby is local
Priority 105 (configured)
Weighting 100 (default 100), thresholds: lower 1, upper 100
Load balancing: host-dependent
Group members:
000d.289e.f940 (150.1.1.2) local
000f.235e.ec80 (150.1.1.1) authenticated
000f.235e.f120 (150.1.1.4) authenticated
There are 3 forwarders (1 active)

[Truncated Output]

R4#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Listen
2 state changes, last state change 00:08:57
Virtual IP address is 150.1.1.254
Hello time 200 msec, hold time 800 msec
Next hello sent in 0.056 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Authentication MD5, key-chain “GLBP”
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 0.568 sec)
Standby is 150.1.1.2, priority 105 (expires in 0.560 sec)
Priority 100 (default)
Weighting 100 (default 100), thresholds: lower 1, upper 100
Load balancing: round-robin
Group members:
000d.289e.f940 (150.1.1.2) authenticated
000f.235e.ec80 (150.1.1.1) authenticated
000f.235e.f120 (150.1.1.4) local
There are 3 forwarders (1 active)

[Truncated Output]

https://t.me/learningnets

Technet24

CCNP Lab 062: Cisco IOS GLBP Lab

Lab Objective:

The focus of this lab is to understand the Gateway Load Balancing Protocol (GLBP) implementation and configuration in Cisco IOS routers. Additional technologies include GLBP load balancing.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Configure EIGRP as illustrated in the topology. Redistribute the LAN subnets into EIGRP.

https://t.me/learningnets

Technet24

Verify your configuration using the appropriate commands on all routers in the network.

Task 3

Configure GLBP on R1, R2, and R4. Ensure that R1 is elected AVG. R2 should be standby. The gateway IP should be 150.1.1.254. Verify your configuration using the appropriate commands.

Task 4

Configure load balancing for GLBP so that traffic is distributed between R1, R2 and R4 using a ratio of 50:30:20. In the event that R1 fails, R2 should use the default load balancing method. Verify your configuration using the appropriate commands.

Task 5

Management has requested that when R2 becomes AVG, old forwarder MAC address that was assigned to R1 ceases being used and hosts have migrated away from this address as soon as possible. Configure GLBP so that when R2 becomes AVG, it stops using the old virtual forwarder MAC address in ARP replies within one minute.
To allow for dynamic host ARP cache timeout, ensure that R2 continues to forward packets that were sent to the old virtual forwarder MAC address for no more than five hours. Verify your configuration using the appropriate commands.

Task 6

In the future, multiple GLBP groups will be configured on the LAN segment connecting routers R1, R2, and R4. To allow for easier identification as to what these groups are for, configure the current GLBP group with a group name of 'SERVER-GLBP-GROUP'. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/21024000] via 10.0.0.6, 00:03:06, Serial0/1

https://t.me/learningnets

D 10.0.0.12 [90/21024000] via 10.0.0.6, 00:02:11, Serial0/1
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.6, 00:03:06, Serial0/1

R2#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.12 [90/21024000] via 10.0.0.10, 00:02:15, Serial0/1
D 10.0.0.4 [90/21024000] via 10.0.0.10, 00:03:10, Serial0/1
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.10, 00:03:10, Serial0/1

R3#**show ip route eigrp**
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/20514560] via 10.0.0.14, 00:02:16, Serial1/2
[170/20514560] via 10.0.0.9, 00:02:16, Serial1/1
[170/20514560] via 10.0.0.5, 00:02:16, Serial1/0

R4#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/21024000] via 10.0.0.13, 00:02:22, Serial0/0
D 10.0.0.4 [90/21024000] via 10.0.0.13, 00:02:22, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.13, 00:02:22, Serial0/0

Task 3

To complete this task, you need to configure R1 with the highest priority. In order to ensure that R2 is elected standby, this router should be assigned the second highest priority. By default, GLBP assigns a priority of 100. Finally, you need to explicitly enable preemption as it is disabled by default. This task is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**glbp 1 priority 110**
R1(config-if)#**glbp 1 ip 150.1.1.254**
R1(config-if)#**glbp 1 preempt**
R1(config-if)#**exit**

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**glbp 1 priority 105**
R2(config-if)#**glbp 1 ip 150.1.1.254**
R2(config-if)#**glbp 1 preempt**
R2(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**

https://t.me/learningnets

Technet24

R4(config-if)#**glbp 1 preempt**
R4(config-if)#**glbp 1 ip 150.1.1.254**
R4(config-if)#**exit**

Following this, verify your configuration using the **show glbp** command:

R1#**show glbp fastethernet 0/0 1 brief**
Interface Grp Fwd Pri State Address Active router Standby router
Fa0/0 1 - 110 Active 150.1.1.254 local 150.1.1.2
Fa0/0 1 1 - Active 0007.b400.0101 local -
Fa0/0 1 2 - Listen 0007.b400.0102 150.1.1.2 -
Fa0/0 1 3 - Listen 0007.b400.0103 150.1.1.4 -

R2#**show glbp fastethernet 0/0 1 brief**
Interface Grp Fwd Pri State Address Active router Standby router
Fa0/0 1 - 105 Standby 150.1.1.254 150.1.1.1 local
Fa0/0 1 1 - Listen 0007.b400.0101 150.1.1.1 -
Fa0/0 1 2 - Active 0007.b400.0102 local -
Fa0/0 1 3 - Listen 0007.b400.0103 150.1.1.4 -

R4#**show glbp fastethernet 0/0 1 brief**
Interface Grp Fwd Pri State Address Active router Standby router
Fa0/0 1 - 100 Listen 150.1.1.254 150.1.1.1 150.1.1.2
Fa0/0 1 1 - Listen 0007.b400.0101 150.1.1.1 -
Fa0/0 1 2 - Listen 0007.b400.0102 150.1.1.2 -
Fa0/0 1 3 - Active 0007.b400.0103 local -

Task 4

GLBP uses a weighting scheme to determine the forwarding capacity of each gateway that is in the GLBP group. The weighting assigned to a gateway in the GLBP group can be used to determine whether it will forward packets and, if so, the proportion of hosts in the LAN for which it will forward packets.

By default, each gateway is assigned a weight of 100. Administrators can additionally configure the gateways to make dynamic weighting adjustments by configuring object tracking, such as for interfaces and IP prefixes, in conjunction with GLBP. If an interface fails, the weighting is dynamically decreased by the specified value, allowing gateways with higher weighting values to be used to forward more traffic than those with lower weighting values.

In addition to this, thresholds can be set to disable forwarding when the weighting for a GLBP group falls below a certain value, and then when it rises above another threshold, forwarding is automatically re-enabled. A backup virtual forwarder can become the

https://t.me/learningnets

AVF if the current AVF weighting falls below the low weighting threshold for 30 seconds. This is the ability GLBP to place a weight on each device when calculating the amount of load sharing that will occur through MAC assignment. Each GLBP router in the group will advertise its weighting and assignment; the AVG will act based on that value.

To complete this task, we need to change the load balancing method from round robin (default) to weighted. Next, we need to specify the ratios on the AVG (R1). This is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**glbp 1 weighting 50**
R1(config-if)#**glbp 1 load-balancing weighted**
R1(config-if)#**exit**

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**glbp 1 weighting 30**
R2(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**glbp 1 weighting 20**
R4(config-if)#**exit**

Following this, verify your configuration using the **show glbp** command:

R1#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Active
2 state changes, last state change 01:57:27
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.716 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is local
Standby is 150.1.1.2, priority 105 (expires in 9.656 sec)
Priority 110 (configured)
Weighting 50 (configured 50), thresholds: lower 1, upper 50
Load balancing: weighted
Group members:
000d.289e.f940 (150.1.1.2)
000f.235e.ec80 (150.1.1.1) local
000f.235e.f120 (150.1.1.4)

https://t.me/learningnets
Technet24

There are 3 forwarders (1 active)
Forwarder 1
State is Active
1 state change, last state change 01:57:17
MAC address is 0007.b400.0101 (default)
Owner ID is 000f.235e.ec80
Redirection enabled
Preemption enabled, min delay 30 sec
Active is local, weighting 50
Forwarder 2
State is Listen
8 state changes, last state change 00:32:27
MAC address is 0007.b400.0102 (learnt)
Owner ID is 000d.289e.f940
Redirection enabled, 57.128 sec remaining (maximum 60 sec)
Time to live: 17997.124 sec (maximum 18000 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.2 (primary), weighting 30 (expires in 7.124 sec)
Forwarder 3
State is Listen
4 state changes, last state change 00:32:20
MAC address is 0007.b400.0103 (learnt)
Owner ID is 000f.235e.f120
Redirection enabled, 599.192 sec remaining (maximum 600 sec)
Time to live: 14399.192 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.4 (primary), weighting 20 (expires in 9.188 sec)

R2#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Standby
7 state changes, last state change 00:34:18
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 0.012 secs
Redirect time 60 sec, forwarder time-out 18000 sec
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 9.048 sec)
Standby is local

https://t.me/learningnets

Priority 105 (configured)
Weighting 30 (configured 30), thresholds: lower 1, upper 30
Load balancing: round-robin
Group members:
000d.289e.f940 (150.1.1.2) local
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4)
There are 3 forwarders (1 active)
Forwarder 1
State is Listen
6 state changes, last state change 00:34:48
MAC address is 0007.b400.0101 (learnt)
Owner ID is 000f.235e.ec80
Time to live: 14399.000 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.1 (primary), weighting 50 (expires in 8.996 sec)
Forwarder 2
State is Active
1 state change, last state change 01:56:41
MAC address is 0007.b400.0102 (default)
Owner ID is 000d.289e.f940
Preemption enabled, min delay 30 sec
Active is local, weighting 30
Forwarder 3
State is Listen
8 state changes, last state change 00:34:13
MAC address is 0007.b400.0103 (learnt)
Owner ID is 000f.235e.f120
Time to live: 14399.004 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.4 (primary), weighting 20 (expires in 9.000 sec)

R4#show glbp fastethernet 0/0
FastEthernet0/0 - Group 1
State is Listen
7 state changes, last state change 00:36:37
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.904 secs

https://t.me/learningnets
Technet24

Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 8.892 sec)
Standby is 150.1.1.2, priority 105 (expires in 9.852 sec)
Priority 100 (default)
Weighting 20 (configured 20), thresholds: lower 1, upper 20
Load balancing: round-robin
Group members:
000d.289e.f940 (150.1.1.2)
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4) local
There are 3 forwarders (1 active)
Forwarder 1
State is Listen
4 state changes, last state change 00:36:37
MAC address is 0007.b400.0101 (learnt)
Owner ID is 000f.235e.ec80
Time to live: 14399.596 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.1 (primary), weighting 50 (expires in 9.592 sec)
Forwarder 2
State is Listen
8 state changes, last state change 00:36:38
MAC address is 0007.b400.0102 (learnt)
Owner ID is 000d.289e.f940
Time to live: 17997.552 sec (maximum 18000 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.2 (primary), weighting 30 (expires in 7.552 sec)
Forwarder 3
State is Active
1 state change, last state change 01:58:08
MAC address is 0007.b400.0103 (default)
Owner ID is 000f.235e.f120
Preemption enabled, min delay 30 sec
Active is local, weighting 20

Task 5

Within the GLBP group, a single gateway is elected as the AVG, and another gateway is elected as the standby virtual gateway. All other remaining gateways in the group are

https://t.me/learningnets

placed in a listen state. If an AVG fails, the standby virtual gateway will assume responsibility for the virtual IP address. At the same time, an election is held and a new standby virtual gateway is then elected from the gateways currently in the listen state.

In the event the AVF fails, one of the secondary virtual forwarders in the listen state assumes responsibility for the virtual MAC address. However, because the new AVF is already a forwarder using another virtual MAC address, GLBP needs to ensure that the old forwarder MAC address ceases being used and hosts are migrated away from this address. This is achieved using two timers:

1. The redirect timer
2. The timeout timer

The redirect time is the interval during which the AVG continues to redirect hosts to the old virtual forwarder MAC address. When this timer expires, the AVG stops using the old virtual forwarder MAC address in ARP replies, although the virtual forwarder will continue to forward packets that were sent to the old virtual forwarder MAC address.

When the timeout timer expires, the virtual forwarder is removed from all the gateways in the GLBP group. Any clients still using the old MAC address within their ARP caches must refresh the entry to obtain the new virtual MAC address. GLBP uses the hello messages to communicate the current state of these two timers. This task is completed on R2 as follows:

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**glbp 1 timers redirect 60 18000**
R2(config-if)#**exit**
Next, verify your configuration using the **show glbp** command:

R2#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Standby
7 state changes, last state change 00:21:39
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 2.360 secs
Redirect time 60 sec (active 600 sec), forwarder time-out 18000 sec (active 14400 sec)
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 8.328 sec)
Standby is local

https://t.me/learningnets

Technet24

[Truncated Output]

Task 6

The requirement for this task is straightforward and is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**glbp 1 name SERVER-GLBP-GROUP**
R1(config-if)#**exit**

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**glbp 1 name SERVER-GLBP-GROUP**
R2(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**glbp 1 name SERVER-GLBP-GROUP**
R4(config-if)#**exit**

Following this, verify your configuration using the **show glbp** command:

R1#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Active
2 state changes, last state change 01:52:39
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 2.096 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is local
Standby is 150.1.1.2, priority 105 (expires in 7.124 sec)
Priority 110 (configured)
Weighting 50 (configured 50), thresholds: lower 1, upper 50
Load balancing: weighted
IP redundancy name is "SERVER-GLBP-GROUP"
Group members:
000d.289e.f940 (150.1.1.2)
000f.235e.ec80 (150.1.1.1) local
000f.235e.f120 (150.1.1.4)

[Truncated Output]

R2#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Standby

https://t.me/learningnets

7 state changes, last state change 00:27:53
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 0.980 secs
Redirect time 60 sec (active 600 sec), forwarder time-out 18000 sec (active 14400 sec)
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 6.944 sec)
Standby is local
Priority 105 (configured)
Weighting 30 (configured 30), thresholds: lower 1, upper 30
Load balancing: round-robin
IP redundancy name is "SERVER-GLBP-GROUP"
Group members:
000d.289e.f940 (150.1.1.2) local
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4)

[Truncated Output]

R4#**show glbp fastethernet 0**/0
FastEthernet0/0 - Group 1
State is Listen
7 state changes, last state change 00:27:49
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.564 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 8.460 sec)
Standby is 150.1.1.2, priority 105 (expires in 9.488 sec)
Priority 100 (default)
Weighting 20 (configured 20), thresholds: lower 1, upper 20
Load balancing: round-robin
IP redundancy name is "SERVER-GLBP-GROUP"
Group members:
000d.289e.f940 (150.1.1.2)
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4) local

[Truncated Output]

https://t.me/learningnets

Technet24

https://t.me/learningnets

CCNP Lab 063: Cisco IOS IP SLA and GLBP Lab

Lab Objective:

The focus of this lab is to understand the Gateway Load Balancing Protocol (GLBP) implementation and configuration in Cisco IOS routers. Additional technologies include GLBP load balancing.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Configure EIGRP as illustrated in the topology. Redistribute the LAN subnets into EIGRP.

https://t.me/learningnets

Verify your configuration using the appropriate commands on all routers in the network.

Task 3

Configure GLBP on R1, R2, and R4. Ensure that R1 is elected AVG. R2 should be standby. The gateway IP should be 150.1.1.254. Verify your configuration using the appropriate commands.

Task 4

Configure load balancing for GLBP so that traffic is distributed between R1, R2 and R4 using a ratio of 50:30:20. Configure weighting thresholds on R1 as follows:

- Should R1s weighting value fall below 30, it should give up its role as a Virtual Forwarder
- When R1s weighting value rises above 45, it should assume its role as a Virtual Forwarder
- Should R1s weighting value fall below 20, it should give up its role as a Virtual Forwarder
- When R1s weighting value rises above 25, it should assume its role as a Virtual Forwarder

R4 should use default thresholds. Verify your configuration using the appropriate commands.

Task 5

Configure Cisco IOS IP SLA Operations on R1 and R2 that ping the connected WAN interface to R3. Should R1s WAN link go down, its weight should be reduced to 25. Should R2s WAN link go down, its weighting value should be reduced to 15. Verify your configuration using the appropriate commands. Next, test the configuration by shutting down R1s WAN link and then checking the GLBP status on R1, R2 and R4. Next, with R1s WAN interface still disabled, shut R2s WAN interface and check the GLBP status on R2 and R4.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands.

https://t.me/learningnets

Technet24

Following this configuration, your route tables should show the following route information:

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/21024000] via 10.0.0.6, 00:03:06, Serial0/1
D 10.0.0.12 [90/21024000] via 10.0.0.6, 00:02:11, Serial0/1
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.6, 00:03:06, Serial0/1

R2#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.12 [90/21024000] via 10.0.0.10, 00:02:15, Serial0/1
D 10.0.0.4 [90/21024000] via 10.0.0.10, 00:03:10, Serial0/1
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.10, 00:03:10, Serial0/1

R3#**show ip route eigrp**
150.1.0.0/24 is subnetted, 1 subnets
D EX 150.1.1.0 [170/20514560] via 10.0.0.14, 00:02:16, Serial1/2
[170/20514560] via 10.0.0.9, 00:02:16, Serial1/1
[170/20514560] via 10.0.0.5, 00:02:16, Serial1/0

R4#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/21024000] via 10.0.0.13, 00:02:22, Serial0/0
D 10.0.0.4 [90/21024000] via 10.0.0.13, 00:02:22, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
D EX 150.3.3.0 [170/2172416] via 10.0.0.13, 00:02:22, Serial0/0

Task 3

To complete this task, you need to configure R1 with the highest priority. In order to ensure that R2 is elected standby, this router should be assigned the second highest priority. By default, GLBP assigns a priority of 100. Finally, you need to explicitly enable preemption as it is disabled by default. This task is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**glbp 1 priority 110**
R1(config-if)#**glbp 1 ip 150.1.1.254**
R1(config-if)#**glbp 1 preempt**
R1(config-if)#**exit**

R2(config)#**interface fastethernet 0/0**

https://t.me/learningnets

R2(config-if)#**glbp 1 priority 105**
R2(config-if)#**glbp 1 ip 150.1.1.254**
R2(config-if)#**glbp 1 preempt**
R2(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**glbp 1 preempt**
R4(config-if)#**glbp 1 ip 150.1.1.254**
R4(config-if)#**exit**

Following this, verify your configuration using the **show glbp** command:

R1#**show glbp fastethernet 0/0 1 brief**
Interface Grp Fwd Pri State Address Active router Standby router
Fa0/0 1 - 110 Active 150.1.1.254 local 150.1.1.2
Fa0/0 1 1 - Active 0007.b400.0101 local -
Fa0/0 1 2 - Listen 0007.b400.0102 150.1.1.2 -
Fa0/0 1 3 - Listen 0007.b400.0103 150.1.1.4 -

R2#**show glbp fastethernet 0/0 1 brief**
Interface Grp Fwd Pri State Address Active router Standby router
Fa0/0 1 - 105 Standby 150.1.1.254 150.1.1.1 local
Fa0/0 1 1 - Listen 0007.b400.0101 150.1.1.1 -
Fa0/0 1 2 - Active 0007.b400.0102 local -
Fa0/0 1 3 - Listen 0007.b400.0103 150.1.1.4 -

R4#**show glbp fastethernet 0/0 1 brief**
Interface Grp Fwd Pri State Address Active router Standby router
Fa0/0 1 - 100 Listen 150.1.1.254 150.1.1.1 150.1.1.2
Fa0/0 1 1 - Listen 0007.b400.0101 150.1.1.1 -
Fa0/0 1 2 - Listen 0007.b400.0102 150.1.1.2 -
Fa0/0 1 3 - Active 0007.b400.0103 local -

Task 4

To complete this task, we need to configure weighted load balancing. When configuring this method, Cisco IOS software allows you to specify upper and lower thresholds. If the weighting of a router falls from the specified maximum threshold to a value below the lower threshold, the router gives up its role as a Virtual Forwarder. When the weighting value of the router rises above the upper threshold, the router can resume its active Virtual Forwarder role. This task is completed by implementing the following configuration on all routers:

R1(config)#**interface fastethernet 0/0**

https://t.me/learningnets

Technet24

R1(config-if)#**glbp 1 weighting 50 lower 30 upper 45**
R1(config-if)#**glbp 1 load-balancing weighted**
R1(config-if)#**exit**

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**glbp 1 weighting 30 lower 10 upper 25**
R2(config-if)#**glbp 1 load-balancing weighted**
R2(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**glbp 1 weighting 20**
R4(config-if)#**exit**

Next, verify your configuration on all routers using the **show glbp** command:

R1#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Active
2 state changes, last state change 00:00:25
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.972 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is local
Standby is 150.1.1.2, priority 105 (expires in 7.972 sec)
Priority 110 (configured)
Weighting 50 (configured 50), thresholds: lower 30, upper 45
Load balancing: weighted
Group members:
000d.289e.f940 (150.1.1.2)
000f.235e.ec80 (150.1.1.1) local
000f.235e.f120 (150.1.1.4)
There are 3 forwarders (1 active)
Forwarder 1
State is Active
1 state change, last state change 00:00:15
MAC address is 0007.b400.0101 (default)
Owner ID is 000f.235e.ec80
Redirection enabled
Preemption enabled, min delay 30 sec

https://t.me/learningnets

Active is local, weighting 50
Forwarder 2
State is Listen
MAC address is 0007.b400.0102 (learnt)
Owner ID is 000d.289e.f940
Redirection enabled, 598.112 sec remaining (maximum 600 sec)
Time to live: 14398.112 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.2 (primary), weighting 30 (expires in 8.112 sec)
Forwarder 3
State is Listen
MAC address is 0007.b400.0103 (learnt)
Owner ID is 000f.235e.f120
Redirection enabled, 599.008 sec remaining (maximum 600 sec)
Time to live: 14399.008 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.4 (primary), weighting 20 (expires in 9.004 sec)

R2#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Standby
1 state change, last state change 00:00:30
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 2.424 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 7.424 sec)
Standby is local
Priority 105 (configured)
Weighting 30 (configured 30), thresholds: lower 20, upper 25
Load balancing: weighted
Group members:
000d.289e.f940 (150.1.1.2) local
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4)
There are 3 forwarders (1 active)
Forwarder 1
State is Listen

https://t.me/learningnets
Technet24

MAC address is 0007.b400.0101 (learnt)
Owner ID is 000f.235e.ec80
Time to live: 14397.420 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.1 (primary), weighting 50 (expires in 9.628 sec)
Forwarder 2
State is Active
1 state change, last state change 00:00:35
MAC address is 0007.b400.0102 (default)
Owner ID is 000d.289e.f940
Preemption enabled, min delay 30 sec
Active is local, weighting 30
Forwarder 3
State is Listen
MAC address is 0007.b400.0103 (learnt)
Owner ID is 000f.235e.f120
Time to live: 14399.520 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.4 (primary), weighting 20 (expires in 9.520 sec)

R4#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Listen
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.100 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 8.204 sec)
Standby is 150.1.1.2, priority 105 (expires in 7.200 sec)
Priority 100 (default)
Weighting 20 (configured 20), thresholds: lower 1, upper 20
Load balancing: round-robin
Group members:
000d.289e.f940 (150.1.1.2)
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4) local
There are 3 forwarders (1 active)
Forwarder 1

https://t.me/learningnets

State is Listen
MAC address is 0007.b400.0101 (learnt)
Owner ID is 000f.235e.ec80
Time to live: 14398.200 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.1 (primary), weighting 50 (expires in 7.228 sec)
Forwarder 2
State is Listen
MAC address is 0007.b400.0102 (learnt)
Owner ID is 000d.289e.f940
Time to live: 14399.228 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.2 (primary), weighting 30 (expires in 9.228 sec)
Forwarder 3
State is Active
1 state change, last state change 00:00:37
MAC address is 0007.b400.0103 (default)
Owner ID is 000f.235e.f120
Preemption enabled, min delay 30 sec
Active is local, weighting 20

Task 5

This task requires the configuration of Cisco IOS IP SLA Operations on R1 and R2. In addition to this, Enhanced Object Tracking (EOT) should also be configured. The EOT configuration should track the configured Cisco IOS IP SLA Operation and should be used to decrement the GLBP weight as specified on both R1 and R2. This task is completed as follows:

R1(config)#**ip sla 1**
R1(config-ip-sla)#**Icmp-echo 10.0.0.6 source-interface serial 0/0**
R1(config-ip-sla)#**exit**
R1(config)#**ip sla schedule 1 start-time now life forever**
R1(config)#**track 1 rtr 1**
R1(config-track)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**glbp 1 weighting track 1 decrement 25**
R1(config-if)#**exit**

R2(config)#**ip sla 1**
R2(config-ip-sla)#**Icmp-echo 10.0.0.10 source-ipaddr 10.0.0.9**

https://t.me/learningnets
Technet24

R2(config-ip-sla)#**exit**
R2(config)#**ip sla schedule 1 start-time now life forever**
R2(config)#**track 1 rtr 1**
R2(config-track)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**glbp 1 weighting track 1 decrement 15**
R2(config-if)#**exit**

Next, verify the Cisco IOS IP SLA Operations using the **show ip sla** command:

R1#**show ip sla monitor 1**
Round trip time (RTT) Index 1
Latest RTT: 8 ms
Latest operation start time: *06:29:12.561 UTC Sat Jun 4 2011
Latest operation return code: OK
Number of successes: 6
Number of failures: 0
Operation time to live: Forever

R2#**show ip sla monitor 1**
Round trip time (RTT) Index 1
Latest RTT: 8 ms
Latest operation start time: *19:56:26.883 UTC Wed May 18 2011
Latest operation return code: OK
Number of successes: 3
Number of failures: 0
Operation time to live: Forever

Next, verify your EOT configuration on R1 and R2 using the **show track** command:

R1#**show track**
Track 1
Response Time Reporter 1 state
State is Up
2 changes, last change 00:06:00
Latest operation return code: OK
Latest RTT (millisecs) 8
Tracked by:
GLBP FastEthernet0/0 1

R2#**show track**
Track 1
Response Time Reporter 1 state

https://t.me/learningnets

State is Up
1 change, last change 00:03:24
Latest operation return code: OK
Latest RTT (millisecs) 8
Tracked by:
GLBP FastEthernet0/0 1

Finally, before you begin testing, verify GLBP using the **show glbp** command:

R1#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Active
2 state changes, last state change 00:17:56
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 0.016 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is local
Standby is 150.1.1.2, priority 105 (expires in 9.036 sec)
Priority 110 (configured)
Weighting 50 (configured 50), thresholds: lower 30, upper 45
Track object 1 state Up decrement 25
Load balancing: weighted
Group members:
000d.289e.f940 (150.1.1.2)
000f.235e.ec80 (150.1.1.1) local
000f.235e.f120 (150.1.1.4)

[Truncated Output]

R2#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Standby
1 state change, last state change 00:18:11
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 0.168 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 8.144 sec)

https://t.me/learningnets

Technet24

Standby is local
Priority 105 (configured)
Weighting 30 (configured 30), thresholds: lower 20, upper 25
Track object 1 state Up decrement 15
Load balancing: weighted
Group members:
000d.289e.f940 (150.1.1.2) local
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4)
There are 3 forwarders (1 active)

[Truncated Output]

At this point, we can begin testing GLBP. First, as requested, shut down the WAN link on R1 and verify the GLBP status on R1, R2 and R4 using the **show glbp** command:

R1(config)#**interface serial 0/1**
R1(config-if)#**shutdown**
R1(config-if)#**exit**
R1(config)#**exit**
R1#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Active
2 state changes, last state change 00:29:55
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.116 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is local
Standby is 150.1.1.2, priority 105 (expires in 7.164 sec)
Priority 110 (configured)
Weighting 25, low (configured 50), thresholds: lower 30, upper 45
Track object 1 state Down decrement 25
Load balancing: weighted
Group members:
000d.289e.f940 (150.1.1.2)
000f.235e.ec80 (150.1.1.1) local
000f.235e.f120 (150.1.1.4)
There are 3 forwarders (0 active)
Forwarder 1

https://t.me/learningnets

State is Listen
2 state changes, last state change 00:04:10
MAC address is 0007.b400.0101 (default)
Owner ID is 000f.235e.ec80
Redirection enabled
Preemption enabled, min delay 30 sec
Active is 150.1.1.4 (secondary), weighting 20 (expires in 7.144 sec)
Forwarder 2
State is Listen
MAC address is 0007.b400.0102 (learnt)
Owner ID is 000d.289e.f940
Redirection enabled, 599.232 sec remaining (maximum 600 sec)
Time to live: 14399.228 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.2 (primary), weighting 30 (expires in 9.228 sec)
Forwarder 3
State is Listen
MAC address is 0007.b400.0103 (learnt)
Owner ID is 000f.235e.f120
Redirection enabled, 597.140 sec remaining (maximum 600 sec)
Time to live: 14397.140 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.4 (primary), weighting 20 (expires in 7.136 sec)

Notice in the output above that R1 is no longer being used as a Virtual Forwarder. Next, check that the same is also depicted on routers R2 and R4:

R2#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Standby
1 state change, last state change 00:31:40
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.424 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 9.404 sec)
Standby is local
Priority 105 (configured)
Weighting 30 (configured 30), thresholds: lower 20, upper 25

https://t.me/learningnets
Technet24

Track object 1 state Up decrement 15
Load balancing: weighted
Group members:
000d.289e.f940 (150.1.1.2) local
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4)
There are 3 forwarders (1 active)
Forwarder 1
State is Listen
MAC address is 0007.b400.0101 (learnt)
Owner ID is 000f.235e.ec80
Time to live: 14398.760 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.4 (secondary), weighting 25 (expires in 8.728 sec)
Forwarder 2
State is Active
1 state change, last state change 00:31:45
MAC address is 0007.b400.0102 (default)
Owner ID is 000d.289e.f940
Preemption enabled, min delay 30 sec
Active is local, weighting 30
Forwarder 3
State is Listen
MAC address is 0007.b400.0103 (learnt)
Owner ID is 000f.235e.f120
Time to live: 14398.724 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.4 (primary), weighting 20 (expires in 8.724 sec)

R4#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Listen
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 0.544 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 7.524 sec)
Standby is 150.1.1.2, priority 105 (expires in 9.548 sec)

https://t.me/learningnets

Priority 100 (default)
Weighting 20 (configured 20), thresholds: lower 1, upper 20
Load balancing: round-robin
Group members:
000d.289e.f940 (150.1.1.2)
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4) local
There are 3 forwarders (2 active)
Forwarder 1
State is Active
1 state change, last state change 00:07:05
MAC address is 0007.b400.0101 (learnt)
Owner ID is 000f.235e.ec80
Time to live: 14397.520 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is local, weighting 20
Forwarder 2
State is Listen
MAC address is 0007.b400.0102 (learnt)
Owner ID is 000d.289e.f940
Time to live: 14398.308 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.2 (primary), weighting 30 (expires in 8.308 sec)
Forwarder 3
State is Active
1 state change, last state change 00:32:32
MAC address is 0007.b400.0103 (default)
Owner ID is 000f.235e.f120
Preemption enabled, min delay 30 sec
Active is local, weighting 20

Finally, shut down the WAN link on R2 and verify the GLBP status on routers R2 and R4:

R2(config)#**interface serial 0/1**
R2(config-if)#**shutdown**
R2(config-if)#**exit**
R2(config)#**exit**
R2#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1

https://t.me/learningnets
Technet24

State is Standby
1 state change, last state change 00:38:21
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 2.500 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 7.476 sec)
Standby is local
Priority 105 (configured)
Weighting 15, low (configured 30), thresholds: lower 20, upper 25
Track object 1 state Down decrement 15
Load balancing: weighted
Group members:
000d.289e.f940 (150.1.1.2) local
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4)
There are 3 forwarders (0 active)
Forwarder 1
State is Listen
MAC address is 0007.b400.0101 (learnt)
Owner ID is 000f.235e.ec80
Time to live: 14398.892 sec (maximum 14399 sec)
Preemption enabled, min delay 30 sec
Active is 150.1.1.4 (secondary), weighting 20 (expires in 9.892 sec)
Forwarder 2
State is Listen
2 state changes, last state change 00:01:34
MAC address is 0007.b400.0102 (default)
Owner ID is 000d.289e.f940
Preemption enabled, min delay 30 sec
Active is 150.1.1.4 (secondary), weighting 20 (expires in 9.888 sec)
Forwarder 3
State is Listen
MAC address is 0007.b400.0103 (learnt)
Owner ID is 000f.235e.f120
Time to live: 14399.888 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec

https://t.me/learningnets

Active is 150.1.1.4 (primary), weighting 20 (expires in 9.888 sec)

Notice that R4 is not AVF for all three GLBP MAC addresses. Verify the same on R4:

R4#**show glbp fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Listen
Virtual IP address is 150.1.1.254
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.936 secs
Redirect time 600 sec, forwarder time-out 14400 sec
Preemption enabled, min delay 0 sec
Active is 150.1.1.1, priority 110 (expires in 8.916 sec)
Standby is 150.1.1.2, priority 105 (expires in 7.940 sec)
Priority 100 (default)
Weighting 20 (configured 20), thresholds: lower 1, upper 20
Load balancing: round-robin
Group members:
000d.289e.f940 (150.1.1.2)
000f.235e.ec80 (150.1.1.1)
000f.235e.f120 (150.1.1.4) local
There are 3 forwarders (3 active)
Forwarder 1
State is Active
1 state change, last state change 00:14:01
MAC address is 0007.b400.0101 (learnt)
Owner ID is 000f.235e.ec80
Time to live: 14398.912 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is local, weighting 20
Forwarder 2
State is Active
1 state change, last state change 00:02:37
MAC address is 0007.b400.0102 (learnt)
Owner ID is 000d.289e.f940
Time to live: 14398.256 sec (maximum 14400 sec)
Preemption enabled, min delay 30 sec
Active is local, weighting 20
Forwarder 3
State is Active

https://t.me/learningnets

Technet24

1 state change, last state change 00:39:29
MAC address is 0007.b400.0103 (default)
Owner ID is 000f.235e.f120
Preemption enabled, min delay 30 sec
Active is local, weighting 20

https://t.me/learningnets

CCNP Lab 064: Embedded Event Manager Lab

Lab Objective:

The focus of this lab is to understand the Embedded Event Manager (EEM) implementation and configuration in Cisco IOS routers. Additional technologies include SNMP security.

Lab Topology:

This lab requires only a single router running, at a minimum, Cisco IOS Software 12.4 Mainline. The router should have at least one Ethernet interface. The primary purpose of this lab is to reinforce configuration knowledge of the stated chapter.

IMPORTANT NOTE

If you have multiple devices and servers / hosts in your home lab and you would like to test solutions for topics such as Syslog, SNMP and NetFlow by setting up a host and viewing charts or logging information, for example, please feel free to do so. While these labs include logging to 'supposed' hosts, there are no SNMP or Syslog servers in the http://www.101labs.net racks and so you will not be able to test the solutions in those racks. If you only have a single router, you can bring up the Ethernet interface by implementing the following configuration:

```
!
interface fastethernet 0/0
loopback
no keepalive
no shut
!
```

Task 1

Configure the router with a hostname of R1. Next, enable the LAN interface of the router and assign it the IP address 150.1.1.1/24. Ensure that this interface is in an up / up state.

Task 2

Configure an EEM applet on the router such that following any configuration change, the log message 'SAVING CONFIGURATION' is printed and the router automatically saves the configuration. The router should also send an SNMP trap to host 150.1.1.254 using an SNMPv2 community string of 'SECURITY'. This trap should include the message 'CONFIG SAVED'. Verify your configuration using the appropriate commands.

https://t.me/learningnets

Technet24

Task 3

Management is concerned about the device being reloaded accidentally. Until they get an ACS server running TACACS+, which will be used to restrict commands at the user level, they have requested that the 'reload' command is ignored when executed on the router. They also request that the shortened form of this command, 'relo' is also ignored. Configure an EEM applet to satisfy this request. Ensure that the router prints the message 'NOT ALLOWED' whenever this command is attempted. Test and verify your configuration using the appropriate commands.

Task 4

In the future, assume that OSPF will be enabled on the router. To facilitate OSPF adjacency flap troubleshooting, configure an EEM applet that captures the contents of the **show processes cpu** command to an existing file named PROC_UTIL that is stored in Flash memory. It is important to ensure that this file is not overwritten, but instead, additional data is simply added to it. Next, configure the same applet so that the output of the **show interface serial 0/0** command. This information should be added to an existing file named SERIAL_STATS that is stored in Flash memory. Verify your configuration.

Lab Validation:

Task 1

If your routers interface is not connected to a switch or hub, you need to complete this task as is shown below. If you do have a hub or switch, you can omit the **loopback** and **no keepalive** commands under the LAN interface. This example assumes a standalone router.

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**loopback**
Loopback is a traffic-affecting operation
R1(config-if)#**no keepalive**
R1(config-if)#**no shutdown**
R1(config-if)#**exit**

Next, verify your configuration using the **show ip interface brief** command:

R1#**show ip interface brief**
Interface IP-Address OK? Method Status Protocol
FastEthernet0/0 150.1.1.1 YES manual up up

https://t.me/learningnets

Serial0/0 unassigned YES unset administratively down down
Serial0/1 unassigned YES unset administratively down down

Task 2

In order to complete this task we need to configure both EEM and SNMP on the router. Ensure that the EEM applet matches the Syslog message '%SYS-5-CONFIG_I:' which indicates that the router has been configured. Next, specify the actions the EEM applet should take. These will include logging a message and sending an SNMP trap which includes the string or data stated in the task. This task is completed as follows:

R1(config)#**event manager applet CONFIGURATION-CHANGE-APPLET**
R1(config-applet)#**event syslog pattern %SYS-5-CONFIG_I:**
R1(config-applet)#**action 1.0 syslog msg "SAVING CONFIGURATION"**
R1(config-applet)#**action 1.1 snmp-trap strdata "CONFIG SAVED"**
R1(config-applet)#**action 1.2 cli command "enable"**
R1(config-applet)#**action 1.3 cli command "write memory"**
R1(config-applet)#**exit**
R1(config)#**snmp-server community SECURITY RO**
R1(config)#**snmp-server host 150.1.1.254 traps SECURITY event-manager**
R1(config)#**snmp-server enable traps event-manager**
R1(config)#**exit**

Next, verify the EEM configuration using the **show event manager** command:

R1(config)#**do show event manager policy registered**
No. Class Type Event Type Trap Time Registered Name
1 applet user syslog Off Sat Jun 4 07:10:40 2011 CONFIGURATION-CHANGE-APPLET
pattern {%SYS-5-CONFIG_I:}
action 1.0 syslog msg "SAVING CONFIGURATION"
action 1.1 snmp-trap strdata "CONFIG SAVED"
action 1.2 cli command "enable"
action 1.3 cli command "write memory"

Following this, verify SNMP configuration using the **show snmp** command:

R1(config)#**do show snmp**
Chassis: JAE08020Z7T
0 SNMP packets input
0 Bad SNMP version errors
0 Unknown community name
0 Illegal operation for community name supplied

https://t.me/learningnets
Technet24

0 Encoding errors
0 Number of requested variables
0 Number of altered variables
0 Get-request PDUs
0 Get-next PDUs
0 Set-request PDUs
0 Input queue packet drops (Maximum queue size 1000)
0 SNMP packets output
0 Too big errors (Maximum packet size 1500)
0 No such name errors
0 Bad values errors
0 General errors
0 Response PDUs
0 Trap PDUs

SNMP logging: enabled
Logging to 150.1.1.254.162, 0/10, 0 sent, 0 dropped.

Next, test your Embedded Event Manager configuration by exiting configuration mode:

R1(config)#**exit**
R1#
*Jun 4 07:24:50.379: %SYS-5-CONFIG_I: Configured from console by console
***Jun 4 07:24:50.391: %HA_EM-6-LOG: CONFIGURATION-CHANGE-APPLET: SAVING CONFIGURATION**
R1#
R1#

Finally, ensure that the router generated and sent an SNMP trap to host 150.1.1.254:

R1#**show snmp**
Chassis: JAE08020Z7T
0 SNMP packets input
0 Bad SNMP version errors
0 Unknown community name
0 Illegal operation for community name supplied
0 Encoding errors
0 Number of requested variables
0 Number of altered variables
0 Get-request PDUs
0 Get-next PDUs
0 Set-request PDUs

https://t.me/learningnets

0 Input queue packet drops (Maximum queue size 1000)
2 SNMP packets output
0 Too big errors (Maximum packet size 1500)
0 No such name errors
0 Bad values errors
0 General errors
0 Response PDUs
2 Trap PDUs

SNMP logging: enabled
Logging to 150.1.1.254.162, 0/10, 2 sent, 0 dropped.

Task 3

In order to complete this task, you need to configure EEM to skip the specified commands when they are issued on the router. This task is completed as follows:

R1(config)#**event manager applet NO-RELOAD**
R1(config-applet)#**event cli pattern "relo*" sync no skip yes**
R1(config-applet)#**action 1.0 syslog msg "NOT ALLOWED"**
R1(config-applet)#**exit**

Next, verify your EEM applet using the **show event manager** command:

R1#**show event manager policy registered**
No. Class Type Event Type Trap Time Registered Name
1 applet user syslog Off Sat Jun 4 07:10:40 2011 CONFIGURATION-CHANGE-APPLET
pattern {%SYS-5-CONFIG_I:}
action 1.0 syslog msg "SAVING CONFIGURATION"
action 1.1 snmp-trap strdata "CONFIG SAVED"
action 1.2 cli command "enable"
action 1.3 cli command "write memory"

2 applet user cli Off Sat Jun 4 07:32:20 2011 NO-RELOAD
pattern {relo} sync no skip yes
action 1.0 syslog msg "NOT ALLOWED"

Finally, test your configuration by attempting to reboot the router from the console using either the **reload** or **relo** commands. If you have completed this successfully, neither one will work:

R1#**reload**
R1#
*Jun 4 07:36:54.031: %HA_EM-6-LOG: NO-RELOAD: NOT ALLOWED

https://t.me/learningnets

R1#
R1#**relo**
R1#
*Jun 4 07:37:01.567: %HA_EM-6-LOG: NO-RELOAD: NOT ALLOWED
R1#

Task 4

The requirements for this task are straightforward. To include the output of a command to an existing file, you need to use output redirection, specifically, the **append** keyword:

R1(config)#**event manager applet OSPF**
R1(config-applet)#**event syslog pattern "Neighbor Down: Dead timer expired"**
R1(config-applet)#**action 1.0 cli command "enable"**
R1(config-applet)#**$cli command "show processes cpu | append flash:PROC_UTIL"**
R1(config-applet)#**$d "show interfaces serial 0/0 | append flash:SERIAL_STATS"**
R1(config-applet)#**exit**

Next, verify your EEM applet using the **show event manager** command:

R1#**show event manager policy registered**
No. Class Type Event Type Trap Time Registered Name
1 applet user syslog Off Sat Jun 4 07:10:40 2011 CONFIGURATION-CHANGE-APPLET
pattern {%SYS-5-CONFIG_I:}
action 1.0 syslog msg "SAVING CONFIGURATION"
action 1.1 snmp-trap strdata "CONFIG SAVED"
action 1.2 cli command "enable"
action 1.3 cli command "write memory"

2 applet user cli Off Sat Jun 4 07:32:20 2011 NO-RELOAD
pattern {relo} sync no skip yes
action 1.0 syslog msg "NOT ALLOWED"

3 applet user syslog Off Sat Jun 4 07:41:21 2011 OSPF
pattern {Neighbor Down: Dead timer expired}
action 1.0 cli command "enable"
action 1.1 cli command "show processes cpu | append flash:PROC_UTIL"
action 1.2 cli command "show interfaces serial 0/0 | append flash:SERIAL_STATS"

If you have more than one router, you can test the applet by enabling OSPF and then shutting down an interface so that the neighbor adjacency goes down.

https://t.me/learningnets

https://t.me/learningnets

Technet24

CCNP Lab 065: Embedded Event Manager Lab

Lab Objective:

The focus of this lab is to understand the Embedded Event Manager (EEM) implementation and configuration in Cisco IOS routers. Additional technologies include Cisco IOS ERM.

Lab Topology:

This lab requires only a single router running, at a minimum, Cisco IOS Software 12.4 Mainline. The router should have at least one Ethernet interface. The primary purpose of this lab is to reinforce configuration knowledge of the stated chapter.

IMPORTANT NOTE

If you have multiple devices and servers / hosts in your home lab and you would like to test solutions for topics such as Syslog, SNMP and NetFlow by setting up a host and viewing charts or logging information, for example, please feel free to do so. While these labs include logging to 'supposed' hosts, there are no SNMP or Syslog servers in the http://www.101labs.net racks and so you will not be able to test the solutions in those racks. If you only have a single router, you can bring up the Ethernet interface by implementing the following configuration:

```
!
interface fastethernet 0/0
loopback
no keepalive
no shut
!
```

Task 1

Configure the router with a hostname of R1. Next, enable the LAN interface of the router and assign it the IP address 150.1.1.1/24. Ensure that this interface is in an up / up state.

Task 2

Configure a Cisco IOS Embedded Resource Manager (ERM) policy for critical CPU and memory utilization. The router should generate a critical Syslog message when the CPU and memory utilization exceeds 80% within a 15-second interval. Additionally, a Syslog message should also be generated when the CPU and memory utilization falls below 50% within a 15-second interval. Verify the Embedded Resource Manager

https://t.me/learningnets

configuration using appropriate commands.

Task 3

Management is worried about someone accidentally shutting down an interface and locking themselves (and everyone) out of the router. They have requested that you configure an EEM script so that if the FastEthernet0/0 interface is shut down, the router will automatically re-enable the interface. Verify and test your configuration using the appropriate commands.

Task 4

Configure the following static routes on the router (NOTE: ensure that interface Fa0/0 is up):

- 10.0.0.0/24 via 150.1.1.254
- 10.0.1.0/24 via 150.1.1.254

Management has requested that until they get the Cisco ACS server installed, the router should not allow anyone to delete the static routes. Write an EEM applet that prevents these, and any other, static routes from being deleted until AAA is configured on the router. The router should print the message 'ACTION NOT ALLOWED' . Verify your EEM configuration and test the applet by attempting to delete a static route.

Lab Validation:

Task 1

If your routers interface is not connected to a switch or hub, you need to complete this task as is shown below. If you do have a hub or switch, you can omit the **loopback** and **no keepalive** commands under the LAN interface. This example assumes a standalone router.

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**loopback**
Loopback is a traffic-affecting operation
R1(config-if)#**no keepalive**
R1(config-if)#**no shutdown**
R1(config-if)#**exit**

Next, verify your configuration using the **show ip interface brief** command:

R1#**show ip interface brief**

https://t.me/learningnets

Technet24

Interface IP-Address OK? Method Status Protocol
FastEthernet0/0 150.1.1.1 YES manual up up
Serial0/0 unassigned YES unset administratively down down
Serial0/1 unassigned YES unset administratively down down

Task 2

Embedded Resource Manager (ERM), while technically beyond the scope of the CCNP course, is an important tool that can be used to leverage additional monitoring tools in the real world. ERM allows you to monitor internal system resource utilization for specific resources such as the buffer, memory, and CPU. ERM monitors resource utilization from the perspective of various subsystems within the Cisco IOS software such as resource owners (ROs) and resource users (RUs). Additionally, ERM allows you to configure threshold values for system resources which allows alarm or Syslog generation when these thresholds are exceeded or fall belong specified values. Additional information on ERM can be found on the Cisco website. The URL for this information is located below (at the time of the writing of this guide):

http://www.cisco.com/en/US/docs/ios/12_3t/12_3t14/feature/guide/gt_rmimg.html

This task is completed on the router as follows:

R1(config)#**resource policy**
R1(config-erm)#**policy HIGH-CPU-AND-MEMORY global**
R1(config-erm-policy)#**system**
R1(config-policy-node)#**cpu total**
R1(config-owner-cpu)#**critical rising 80 interval 15 falling 50 interval 15**
R1(config-owner-cpu)#**exit**
R1(config-policy-node)#**memory processor**
R1(config-owner-memory)#**critical rising 80 interval 15 falling 50 interval 15**
R1(config-owner-memory)#**exit**
R1(config-erm-policy)#**exit**
R1(config-erm)#**user global HIGH-CPU-AND-MEMORY**
R1(config-erm)#**exit**

Next, verify the ERM configuration using the **show running-config** command:

R1#**show run | section resource policy**
resource policy
policy HIGH-CPU-AND-MEMORY global
system
cpu total
critical rising 80 interval 15 falling 50 interval 15

https://t.me/learningnets

!
memory processor
critical rising 80 interval 15 falling 50 interval 15
!
!
!
user global HIGH-CPU-AND-MEMORY
!

Task 3

R1(config)#**event manager applet NO-SHUT**
R1(config-applet)#**event syslog pattern "FastEthernet0/0, changed state to administratively down"**
R1(config-applet)#**action 1.0 cli command "enable"**
R1(config-applet)#**action 1.1 cli command "configure terminal"**
R1(config-applet)#**action 1.2 cli command "interface fastethernet 0/0"**
R1(config-applet)#**action 1.3 cli command "no shutdown"**
R1(config-applet)#**action 1.4 cli command "end"**
R1(config-applet)#**exit**

Following this, verify the EEM configuration using the **show event manager** command:

R1#**show event manager policy registered**
No. Class Type Event Type Trap Time Registered Name
1 applet user syslog Off Sat Jun 4 18:43:26 2011 NO-SHUT
pattern {FastEthernet0/0, changed state to administratively down}
action 1.0 cli command "enable"
action 1.1 cli command "configure terminal"
action 1.2 cli command "interface fastethernet 0/0"
action 1.3 cli command "no shutdown"
action 1.4 cli command "end"

Finally, test the applet by attempting to shut down the FastEthernet0/0 interface on the router:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**shutdown**
R1(config-if)#
*Jun 4 18:45:14.945: %LINK-5-CHANGED: Interface FastEthernet0/0, changed state to administratively down
***Jun 4 18:45:15.133: %SYS-5-CONFIG_I: Configured from console by on vty0 (EEM:NO-SHUT)**

https://t.me/learningnets
Technet24

*Jun 4 18:45:17.113: %LINK-3-UPDOWN: Interface FastEthernet0/0, changed state to up
R1(config-if)#**do sh interfaces fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Hardware is AmdFE, address is 000f.235e.ec80 (bia 000f.235e.ec80)
Internet address is 150.1.1.1/24
MTU 1500 bytes, BW 100000 Kbit/sec, DLY 100 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation ARPA, loopback set
Keepalive not set

[Truncated Output]

Task 4

R1(config)#**ip route 10.0.0.0 255.255.255.0 fastethernet 0/0 150.1.1.254**
R1(config)#**ip route 10.0.1.0 255.255.255.0 fastethernet 0/0 150.1.1.254**
R1(config)#**event manager applet NO-DELETING-ROUTES**
R1(config-applet)#**event cli pattern "no ip route *" sync no skip yes**
R1(config-applet)#**action 1.0 syslog msg "ACTION NOT ALLOWED"**
R1(config-applet)#**exit**

Next, verify the EEM applet configuration using the **show event manager** command:

R1#show event manager policy registered
No. Class Type Event Type Trap Time Registered Name
1 applet user syslog Off Sat Jun 4 18:43:26 2011 NO-SHUT
pattern {FastEthernet0/0, changed state to administratively down}
action 1.0 cli command "enable"
action 1.1 cli command "configure terminal"
action 1.2 cli command "interface fastethernet 0/0"
action 1.3 cli command "no shutdown"
action 1.4 cli command "end"

2 applet user cli Off Sat Jun 4 18:48:47 2011 NO-DELETING-ROUTES
pattern {no ip route *} sync no skip yes
action 1.0 syslog msg "ACTION NOT ALLOWED"

Next, verify that the static routes are installed into the IP routing table:

R1#**show ip route static**
10.0.0.0/24 is subnetted, 2 subnets
S 10.0.0.0 [1/0] via 150.1.1.254, FastEthernet0/0
S 10.0.1.0 [1/0] via 150.1.1.254, FastEthernet0/0

https://t.me/learningnets

Finally, test your solution by attempting to delete a static route:

R1(config)#**no ip route 10.0.1.0 255.255.255.0 fastethernet 0/0 150.1.1.254**
R1(config)#
*Jun 4 18:51:52.113: %HA_EM-6-LOG: NO-DELETING-ROUTES: ACTION NOT ALLOWED

R1(config)#**no ip route 10.0.0.0 255.255.255.0 fastethernet 0/0 150.1.1.254**
R1(config)#
*Jun 4 18:52:08.205: %HA_EM-6-LOG: NO-DELETING-ROUTES: ACTION NOT ALLOWED

R1(config)#**do show ip route static**
10.0.0.0/24 is subnetted, 2 subnets
S 10.0.0.0 [1/0] via 150.1.1.254, FastEthernet0/0
S 10.0.1.0 [1/0] via 150.1.1.254, FastEthernet0/0
R1(config)#

https://t.me/learningnets

CCNP Lab 066: Syslog and NTP Lab

Lab Objective:

The focus of this lab is to understand Syslog implementation and configuration in Cisco IOS routers. Additional technologies include the Network Time Protocol.

Lab Topology:

https://t.me/learningnets



Task 1

Configure hostnames and IP address on all routers as illustrated in the topology.

Task 2

To ensure that all logging messages have the correct timestamps, configure R1 as a Network Time Protocol (NTP) server. R1 should have a stratum of 5. All routers should synchronize their time with R1. Assume that all routers reside in the Central Standard (CST) time zone - 6 hours behind Greenwich Mean Time (GMT). Verify your configuration using appropriate commands.

Task 3

Configure all routers so that all logging messages contain the following pertinent information:

- All messages should include date and time information, up to the millisecond
- The local time zone should be used for timestamps

In the future, multiple subinterfaces will be configured off the FastEthernet0/0 interface. These subinterfaces will be used for critical test networks and it is important that any transitions be logged. Therefore, configure the routers so that subinterface up/down transitions are logged. All routers should log to 150.1.1.254. Verify the configuration using the appropriate commands.

Task 4

Management has requested messages also be logged to an NMS with the IP address 150.1.1.254. Only log messages with a severity level of 3 and below should be logged and sent to the NMS. The SNMP NMS is using RO community ‘LOGGING’. Next, verify your configuration using the appropriate commands.

https://t.me/learningnets

Technet24

Lab Validation:

Task 1

This task is straightforward and is completed as follows:

Router(config)#**hostname R1**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**no shutdown**
R1(config-if)#**exit**

Router(config)#**hostname R2**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip address 150.1.1.2 255.255.255.0**
R2(config-if)#**no shutdown**
R2(config-if)#**exit**

Router(config)#**hostname R3**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip address 150.1.1.3 255.255.255.0**
R3(config-if)#**no shutdown**
R3(config-if)#**exit**

Router(config)#**hostname R4**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip address 150.1.1.4 255.255.255.0**
R4(config-if)#**no shutdown**
R4(config-if)#**exit**

Task 2

This task requires that R1 and R2 be configured as both NTP masters (servers) and NTP clients. R3 and R4 should only be configured as NTP clients. This task is completed as follows:

R1(config)#**clock timezone CST -6**
R1(config)#**ntp master 5**
R1(config)#**ntp server 150.1.1.2**
R1(config)#**exit**

R2(config)#**clock timezone CST -6**
R2(config)#**ntp master 8**
R2(config)#**ntp server 150.1.1.1**
R2(config)#**exit**

https://t.me/learningnets

R3(config)#**clock timezone CST -6**
R3(config)#**ntp server 150.1.1.1**
R3(config)#**ntp server 150.1.1.2**
R3(config)#**exit**

R4(config)#**clock timezone CST -6**
R4(config)#**ntp server 150.1.1.1**
R4(config)#**ntp server 150.1.1.2**
R4(config)#**exit**

Next, verify your NTP configuration using the **show ntp status** command:

R1#**show ntp status**
Clock is synchronized, stratum 5, reference is 127.127.7.1
nominal freq is 250.0000 Hz, actual freq is 250.0000 Hz, precision is 2**16
reference time is D1A2BDD7.1DBB5D77 (23:12:55.116 CST Tue Jun 14 2011)
clock offset is 0.0000 msec, root delay is 0.00 msec
root dispersion is 7875.02 msec, peer dispersion is 7875.02 msec

R2#**show ntp status**
Clock is synchronized, stratum 6, reference is 150.1.1.1
nominal freq is 250.0000 Hz, actual freq is 250.0000 Hz, precision is 2**18
reference time is D1A2BEDE.F4959A1C (23:17:18.955 CST Tue Jun 14 2011)
clock offset is 0.1005 msec, root delay is 2.59 msec
root dispersion is 375.15 msec, peer dispersion is 0.03 msec

R3#**show ntp status**
Clock is synchronized, stratum 6, reference is 150.1.1.1
nominal freq is 250.0000 Hz, actual freq is 250.0000 Hz, precision is 2**18
reference time is D1A2BEE4.10F17933 (23:17:24.066 CST Tue Jun 14 2011)
clock offset is 0.0323 msec, root delay is 2.61 msec
root dispersion is 375.09 msec, peer dispersion is 0.03 msec

R4#**show ntp status**
Clock is synchronized, stratum 6, reference is 150.1.1.1
nominal freq is 250.0000 Hz, actual freq is 250.0000 Hz, precision is 2**18
reference time is D1A2BEE9.9B64AC3B (23:17:29.607 CST Tue Jun 14 2011)
clock offset is -0.0265 msec, root delay is 2.49 msec
root dispersion is 1250.08 msec, peer dispersion is 875.02 msec

Task 3

This task requires that you use the **service timestamps** command. Additionally, to allow the logging of subinterface transitions, you need to enable logging for such events under

https://t.me/learningnets
Technet24

the FastEthernet0/0 interface of all routers. Finally, enable logging and specify the destination host:

```
R1(config)#service timestamps log datetime msec localtime show-timezone
R1(config)#interface fastethernet 0/0
R1(config-if)#logging event subif-link-status
R1(config-if)#exit
R1(config)#logging on
R1(config)#logging 150.1.1.254
R1(config)#exit
```

```
R2(config)#service timestamps log datetime msec localtime show-timezone
R2(config)#interface fastethernet 0/0
R2(config-if)#logging event subif-link-status
R2(config-if)#exit
R2(config)#logging on
R2(config)#logging 150.1.1.254
R2(config)#exit
```

```
R3(config)#service timestamps log datetime msec localtime show-timezone
R3(config)#interface fastethernet 0/0
R3(config-if)#logging event subif-link-status
R3(config-if)#exit
R3(config)#logging on
R3(config)#logging 150.1.1.254
R3(config)#exit
```

```
R4(config)#service timestamps log datetime msec localtime show-timezone
R4(config)#interface fastethernet 0/0
R4(config-if)#logging event subif-link-status
R4(config-if)#exit
R4(config)#logging on
R4(config)#logging 150.1.1.254
R4(config)#exit
```

Next, verify your configuration using the **show logging** command on any of the routers:

```
R4#show logging
Syslog logging: enabled (11 messages dropped, 0 messages rate-limited,
0 flushes, 0 overruns, xml disabled, filtering disabled)
Console logging: disabled
Monitor logging: level debugging, 0 messages logged, xml disabled,
filtering disabled
```

https://t.me/learningnets

Buffer logging: level debugging, 1 messages logged, xml disabled,
filtering disabled
Logging Exception size (4096 bytes)
Count and timestamp logging messages: disabled

No active filter modules.

Trap logging: level informational, 35 message lines logged
Logging to 150.1.1.254(global) (udp port 514, audit disabled, link up), 3 message lines logged, xml disabled,
filtering disabled

Log Buffer (4096 bytes):

Jun 14 23:41:40.294 CST: **%SYS-5-CONFIG_I: Configured from console by console**

To verify logging parameters under the FastEthernet0/0 interface, view the configuration:

R4#**more system:running-config | section FastEthernet0/0**
interface FastEthernet0/0
ip address 150.1.1.4 255.255.255.0
logging event subif-link-status
duplex auto
speed auto

Task 4

To complete this task, you need to configure basic SNMP parameters and then configure SNMP to send Syslog traps. To specify the severity level of messages sent to the history table on the router and an SNMP NMS, you need to use the **logging history <severity>** command. This task is completed on all routers as follows:

R1(config)#**snmp-server enable traps syslog**
R1(config)#**logging history 3**
R1(config)#**snmp-server host 150.1.1.254 traps LOGGING syslog**
R1(config)#**snmp-server community LOGGING RO**
R1(config)#**exit**

R2(config)#**snmp-server enable traps syslog**
R2(config)#**logging history 3**
R2(config)#**snmp-server host 150.1.1.254 traps LOGGING syslog**
R2(config)#**snmp-server community LOGGING RO**
R2(config)#**exit**

https://t.me/learningnets

Technet24

R3(config)#**snmp-server enable traps syslog**
R3(config)#**logging history 3**
R3(config)#**snmp-server host 150.1.1.254 traps LOGGING syslog**
R3(config)#**snmp-server community LOGGING RO**
R3(config)#**exit**

R4(config)#**snmp-server enable traps syslog**
R4(config)#**logging history 3**
R4(config)#**snmp-server host 150.1.1.254 traps LOGGING syslog**
R4(config)#**snmp-server community LOGGING RO**
R1(config)#**exit**

https://t.me/learningnets

CCNP Lab 067: SNMP Traps and Informs Lab

Lab Objective:

The focus of this lab is to understand the Simple Network Management Protocol implementation and configuration in Cisco IOS routers. Additional technologies include security.

Lab Topology:

This lab requires only a single router running, at a minimum, Cisco IOS Software 12.4 Mainline. The router should have at least one Ethernet interface. The primary purpose of this lab is to reinforce configuration knowledge of the stated chapter.

IMPORTANT NOTE

If you have multiple devices and servers / hosts in your home lab and you would like to test solutions for topics such as Syslog, SNMP and NetFlow by setting up a host and viewing charts or logging information, for example, please feel free to do so. While these labs include logging to 'supposed' hosts, there are no SNMP or Syslog servers in the http://www.101labs.net racks and so you will not be able to test the solutions in those racks. If you only have a single router, you can bring up the Ethernet interface by implementing the following configuration:

```
!
interface fastethernet 0/0
loopback
no keepalive
no shut
!
```

Task 1

Configure two SNMP communities on the device: one RO community named STANDARD and one RW community named ADVANCED. The RO community should be accessible only by NMSs 150.2.2.253 and 150.2.2.254. The RW community should be accessible only by NMSs 150.3.3.253 and 150.3.3.254. Verify your SNMP configuration using the appropriate commands.

Task 2

Management recently purchased a CiscoWorks LMS solution. They would like to use RME for the device configuration file and software image management. This will be

https://t.me/learningnets

Technet24

performed via the Trivial File Transfer Protocol (TFTP). Configure the device so that only host 150.1.1.254 is allowed TFTP access to perform these actions.

Task 3

Management has requested that, for easier identification, SNMP traps and informs be sent from the device using a source IP address of 1.1.1.1. In addition to this, management has also requested that CiscoWorks be allowed to initiate a remote reload (reboot) of this device. This is important as this tool will be used for software upgrades in the future. Configure the device as requested. Verify your configuration using the appropriate commands.

Task 4

Configure the router to send SNMPv2 traps to hosts 150.2.2.253 and 150.2.2.254. These should be sent with the community string STANDARD. Verify your configuration using the appropriate commands. The device should only send environmental monitor traps to host 150.2.2.253 and Syslog traps to host 150.2.2.254. Verify your SNMP configuration using the appropriate commands.

Task 5

Configure the router to send SNMPv2 informs to hosts 150.3.3.253 and 150.3.3.254. These should be sent with the community string ADVANCED. To ensure that informs are received, the router should be configured to resend an inform at least 10 times while waiting at least 60 seconds between retries. And finally, to prevent the premature discarding of pending informs due to a lack of acknowledgment, configure the router to store up to 50 unacknowledged informs. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

This task is straightforward and requires ACLs with SNMP. This is completed as follows:

R1(config)#**access-list 1 permit host 150.2.2.253**

R1(config)#**access-list 1 permit host 150.2.2.254**

R1(config)#**access-list 2 permit host 150.3.3.253**

R1(config)#**access-list 2 permit host 150.3.3.254**

R1(config)#**snmp-server community STANDARD RO 1**

R1(config)#**snmp-server community ADVANCED RW 2**

https://t.me/learningnets

Verify your configuration using the **show snmp community** command on the router:

R1#**show snmp community**

Community name: ILMI
Community Index: cisco0
Community SecurityName: ILMI
storage-type: read-only active

Community name: STANDARD
Community Index: cisco1
Community SecurityName: STANDARD
storage-type: nonvolatile active access-list: 1

Community name: ADVANCED
Community Index: cisco2
Community SecurityName: ADVANCED
storage-type: nonvolatile active access-list: 2

Task 2

The CiscoWorks LAN Management Solution (LMS) is comprised of several individual software applications that can be used for the configuration and administration of campus networks. LMS also provides monitoring, and troubleshooting capabilities. The following applications are included in the CiscoWorks LAN Management Solution suite:

- Resource Manager Essentials (RME)
- CiscoWorks Health and Utilization Monitor
- Device Fault Manager (DFM)
- Internetwork Performance Monitor (IPM)

Resource Manager can also be used for network monitoring and fault information for tracking devices that are critical to network uptime. RME can also be used for device configuration and software image management via TFTP. This task is completed in one of two ways. The legacy methods of implementing this configuration are shown below:

R1(config)#**access-list 3 permit host 150.3.3.254**
R1(config)#**snmp-server tftp-server-list 3**
R1(config)#**exit**

In current versions of software, this task would be completed as follows:

R1(config)#**access-list 3 permit host 150.3.3.254**
R1(config)#**snmp-server file-transfer access-group 3 protocol tftp**

https://t.me/learningnets

Technet24

R1(config)#**exit**

While there is no explicit command to view the configured parameters, you can always view the device configuration file to verify your configuration:

R1#**more system:running-config | section snmp**
snmp-server community STANDARD RO 1
snmp-server community ADVANCED RW 2
snmp-server file-transfer access-group 3 protocol tftp

Task 3

In order to specify a source IP address, you must configure an interface with this IP address and then specify that as the SNMP source interface. To complete the second requirement, you need to use the **system-shutdown** SNMP command. This command allows a certain SNMP set operation to trigger a router reboot and can be used by CiscoWorks LMS Resource Manager Essentials (RME). This task is completed as follows:

R1(config)#**interface loopback 0**
R1(config-if)#**ip address 1.1.1.1 255.255.255.255**
R1(config-if)#**exit**
R1(config)#**snmp-server trap-source loopback 0**
R1(config)#**snmp-server source-interface informs loopback 0**
R1(config)#**snmp-server system-shutdown**
R1(config)#**exit**

Again, view the device configuration to verify your solution:

R1#**more system:running-config | section snmp**
snmp-server community STANDARD RO 1
snmp-server community ADVANCED RW 2
snmp-server trap-source Loopback0
snmp-server source-interface informs Loopback0
snmp-server system-shutdown
snmp-server file-transfer access-group 3 protocol tftp

Task 4

The requirements of this task are straightforward and are completed as follows:

R1(config)#**snmp-server host 150.2.2.253 traps version 2c STANDARD envmon**
R1(config)#**snmp-server host 150.2.2.254 traps version 2c STANDARD syslog**
R1(config)#**snmp-server enable traps envmon**
R1(config)#**snmp-server enable traps syslog**

https://t.me/learningnets

Next, verify your configuration using the **show snmp host** command:

R1#**show snmp host**

Notification host: 150.2.2.253 udp-port: 162 type: trap
user: STANDARD security model: v2c

Notification host: 150.2.2.254 udp-port: 162 type: trap
user: STANDARD security model: v2c

Task 5

The requirements for this task are straightforward. To configure SNMP inform parameters, we need to use the **snmp-server inform** command. This task is completed as follows:

R1(config)#**snmp-server host 150.3.3.253 informs version 2c ADVANCED**
R1(config)#**snmp-server host 150.3.3.254 informs version 2c ADVANCED**
R1(config)#**snmp-server inform retries 10**
R1(config)#**snmp-server inform timeout 60**
R1(config)#**snmp-server inform pending 50**

Following this, verify your configuration using the **show snmp** command:

R1#**show snmp**
Chassis: JAE08020Z7T
0 SNMP packets input
0 Bad SNMP version errors
0 Unknown community name
0 Illegal operation for community name supplied
0 Encoding errors
0 Number of requested variables
0 Number of altered variables
0 Get-request PDUs
0 Get-next PDUs
0 Set-request PDUs
0 Input queue packet drops (Maximum queue size 1000)
0 SNMP packets output
0 Too big errors (Maximum packet size 1500)
0 No such name errors
0 Bad values errors
0 General errors
0 Response PDUs
0 Trap PDUs

https://t.me/learningnets

Technet24

SNMP logging: enabled
Logging to 150.2.2.253.162, 0/10, 0 sent, 0 dropped.
Logging to 150.2.2.254.162, 0/10, 0 sent, 0 dropped.

SNMP Manager-role output packets
0 Get-request PDUs
0 Get-next PDUs
0 Get-bulk PDUs
0 Set-request PDUs
0 Inform-request PDUs
0 Timeouts
0 Drops
SNMP Manager-role input packets
0 Inform request PDUs
0 Trap PDUs
0 Response PDUs
0 Responses with errors

SNMP informs: enabled
Informs in flight 0/50 (current/max)
Logging to 150.3.3.253.162
0 sent, 0 in-flight, 0 retries, 0 failed, 0 dropped
Logging to 150.3.3.254.162
0 sent, 0 in-flight, 0 retries, 0 failed, 0 dropped

You can also use the **show snmp host** command for verification:

R1#**show snmp host**

Notification host: 150.3.3.253 udp-port: 162 type: inform
user: ADVANCED security model: v2c

Notification host: 150.3.3.254 udp-port: 162 type: inform
user: ADVANCED security model: v2c

Notification host: 150.2.2.253 udp-port: 162 type: trap
user: STANDARD security model: v2c

Notification host: 150.2.2.254 udp-port: 162 type: trap
user: STANDARD security model: v2c

Finally, you can also verify your configuration by looking at the device configuration file:

R1#**show running-config | section include inform**
snmp-server source-interface informs Loopback0

https://t.me/learningnets

```
snmp-server host 150.3.3.253 inform version 2c ADVANCED
snmp-server host 150.3.3.254 inform version 2c ADVANCED
snmp-server inform retries 10 timeout 60 pending 50
```

https://t.me/learningnets

CCNP Lab 068: NetFlow and Accounting Lab

Lab Objective:

The focus of this lab is to understand the Cisco IOS NetFlow implementation and configuration in Cisco IOS routers. Additional technologies include Cisco IOS IP Accounting.

Lab Topology:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP address on all routers as illustrated in the topology.

Task 2

https://t.me/learningnets

Technet24

Configure OSPF on all routers as illustrated in the topology. Verify your configuration using the appropriate commands.

Task 3

Configure Cisco IOS IP accounting on all router WAN interfaces. All routers should store IP accounting information for all packets egressing the WAN interfaces. Verify your IP accounting configuration using the appropriate commands.

Task 4

Configure Cisco IOS NetFlow on all routers. All routers should collect forward statistics for all ingress flows to host 192.168.1.254 using NetFlow version 5 and a destination port of 8000. This traffic should be sourced from the FastEthernet 0/0 interface of all routers.

Task 5

Assume that R1 is a core Internet router. To ensure that as much NetFlow information is stored, configure the router to store up to 128K (131072) entries in the cache. Additionally, configure Cisco IOS NetFlow on this router so that export statistics include the originating autonomous system (AS) for the source and destination. And finally, because R1 will be receiving traffic from multiple hosts on the LAN subnet, configure Cisco IOS NetFlow so that the router captures the MAC addresses of the incoming source and the outgoing destination from the first Layer 2 frame in the flow. Verify your configuration.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic OSPF configuration. Following this, verify your OSPF configuration using the **show ip ospf neighbor** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

```
R1#show ip route ospf
10.0.0.0/30 is subnetted, 2 subnets
O 10.0.0.8 [110/128] via 10.0.0.2, 00:14:34, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 10.0.0.2, 00:14:34, Serial0/0
```

https://t.me/learningnets

150.3.0.0/24 is subnetted, 1 subnets
O 150.3.3.0 [110/129] via 10.0.0.2, 00:14:34, Serial0/0

R2#**show ip route ospf**
150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/65] via 10.0.0.1, 00:14:39, Serial0/0
150.3.0.0/24 is subnetted, 1 subnets
O 150.3.3.0 [110/65] via 10.0.0.10, 00:14:39, Serial0/1

R3#**show ip route ospf**
10.0.0.0/30 is subnetted, 2 subnets
O 10.0.0.0 [110/845] via 10.0.0.9, 00:14:36, Serial1/1
150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/846] via 10.0.0.9, 00:14:36, Serial1/1
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/782] via 10.0.0.9, 00:14:36, Serial1/1

Task 3

While not as granular and detailed as Cisco IOS NetFlow, Cisco IOS IP accounting can be a very powerful troubleshooting tool. IP accounting allows administrators to configure the router to record the number of bytes (IP header and data) and packets switched through the system on a source and destination IP address basis. Only transit IP traffic is measured and only on an outbound basis; traffic generated by the router access server or terminating in this device is not included in the accounting statistics. This task is completed as follows:

R1(config)#**interface serial 0/0**
R1(config-if)#**ip accounting output-packets**
R1(config-if)#**exit**

R2(config)#**interface serial 0/0**
R2(config-if)#**ip accounting output-packets**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip accounting output-packets**
R2(config-if)#**exit**

R3(config)#**interface serial 1/1**
R3(config-if)#**ip accounting output-packets**
R3(config-if)#**exit**

Next, verify your configuration using the **show ip accounting** command. Keep in mind that IP accounting does not capture traffic generated by the local router. Only transit

https://t.me/learningnets
Technet24

traffic statistics are kept. Therefore, to test, you can ping and Telnet, etc, between R1 and R3 and then verify the statistics on R2 as the traffic will transit that router.

R2#**show ip accounting output-packets**
Source Destination Packets Bytes
150.1.1.1 10.0.0.10 100 150000
10.0.0.10 150.1.1.1 100 150000
150.3.3.3 10.0.0.1 105 50500
10.0.0.1 150.3.3.3 105 50500

Task 4

This task is straightforward and is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip flow ingress**
R1(config-if)#**exit**
R1(config)#**ip flow-export destination 192.168.1.254 8000**
R1(config)#**ip flow-export version 5**
R1(config)#**ip flow-export source fastethernet 0/0**

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip flow ingress**
R2(config-if)#**exit**
R2(config)#**ip flow-export destination 192.168.1.254 8000**
R2(config)#**ip flow-export version 5**
R2(config)#**ip flow-export source fastethernet 0/0**

R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip flow ingress**
R3(config-if)#**exit**
R3(config)#**ip flow-export destination 192.168.1.254 8000**
R3(config)#**ip flow-export version 5**
R3(config)#**ip flow-export source fastethernet 0/0**

Next, verify your configuration using the **show ip cache flow** command. If you have hosts that are connected to one of the LAN subnets on any of the routers, you can generate some traffic, e.g. pings, Telnet, HTTP, etc, to view information on traffic statistics that will be sent to the NetFlow Collector specified in the previous lab tasks:

R1#**show ip cache flow**
IP packet size distribution (322 total packets):
1-32 64 96 128 160 192 224 256 288 320 352 384 416 448 480
.000 .183 .000 .099 .000 .000 .000 .000 .000 .000 .000 .000 .000 .000 .000

https://t.me/learningnets

512 544 576 1024 1536 2048 2560 3072 3584 4096 4608
.000 .000 .000 .717 .000 .000 .000 .000 .000 .000 .000

IP Flow Switching Cache, 278544 bytes
1 active, 4095 inactive, 12 added
462 ager polls, 0 flow alloc failures
Active flows timeout in 30 minutes
Inactive flows timeout in 15 seconds
IP Sub Flow Cache, 21640 bytes
1 active, 1023 inactive, 12 added, 12 added to flow
0 alloc failures, 0 force free
1 chunk, 1 chunk added
last clearing of statistics never
Protocol Total Flows Packets Bytes Packets Active(Sec) Idle(Sec)
-------- Flows /Sec /Flow /Pkt /Sec /Flow /Flow
TCP-Telnet 4 0.0 13 42 0.0 1.8 4.9
TCP-WWW 1 0.0 1 44 0.0 0.0 15.0
UDP-other 1 0.0 231 604 0.0 312.0 15.5
ICMP 5 0.0 6 100 0.0 0.7 15.7
Total: 11 0.0 29 454 0.0 29.4 11.7

SrcIf SrcIPaddress DstIf DstIPaddress Pr SrcP DstP Pkts
Fa0/0 150.1.1.252 Se0/0 10.0.0.10 06 2AFA 0017 24
Fa0/0 150.1.1.252 Se0/0 10.0.0.2 06 2AFC 0050 3

Task 5

The requirements for this task are straightforward. In order to change the default cache size from 65535 (64K) to a new value, you need to disable NetFlow on all interfaces first or reboot the router following the change. If not, the router will print the following message on the console:

R1(config)#**ip flow-cache entries 131072**
%The change in number of entries will take effect after either
the next reboot or when netflow is turned off on all interfaces.

By default, with Cisco IOS NetFlow, values from Layer 2 and Layer 3 fields are not captured. This default behavior, however, can be changed by using the **ip flow-capture <option>** command in global configuration mode. This task is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no ip flow ingress**
R1(config-if)#**exit**

https://t.me/learningnets

Technet24

R1(config)#**ip flow-cache entries 131072**
R1(config)#**ip flow-export version 5 origin-as**
R1(config)#**ip flow-capture mac-addresses**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip flow ingress**
R1(config-if)#**exit**

Next, verify your configuration using the **show ip cache verbose flow** command:

R1#**show ip cache verbose flow**
IP packet size distribution (342 total packets):
1-32 64 96 128 160 192 224 256 288 320 352 384 416 448 480
.000 .230 .000 .093 .000 .000 .000 .000 .000 .000 .000 .000 .000 .000 .000

512 544 576 1024 1536 2048 2560 3072 3584 4096 4608
.000 .000 .000 .675 .000 .000 .000 .000 .000 .000 .000

IP Flow Switching Cache, 8913408 bytes
1 active, 131071 inactive, 19 added
551 ager polls, 0 flow alloc failures
Active flows timeout in 30 minutes
Inactive flows timeout in 15 seconds
IP Sub Flow Cache, 672392 bytes
2 active, 32766 inactive, 23 added, 19 added to flow
0 alloc failures, 0 force free
1 chunk, 2 chunks added
last clearing of statistics never
Protocol Total Flows Packets Bytes Packets Active(Sec) Idle(Sec)
-------- Flows /Sec /Flow /Pkt /Sec /Flow /Flow
TCP-Telnet 4 0.0 13 42 0.0 1.8 4.9
TCP-WWW 8 0.0 2 41 0.0 0.6 11.9
UDP-other 1 0.0 231 604 0.0 312.0 15.5
ICMP 5 0.0 6 100 0.0 0.7 15.7
Total: 18 0.0 18 428 0.0 18.2 11.6

SrcIf SrcIPaddress DstIf DstIPaddress Pr TOS Flgs Pkts
Port Msk AS Port Msk AS NextHop B/Pk Active
Fa0/0 150.1.1.252 Se0/0 10.0.0.2 06 C0 10 1
2AFE /24 0 0050 /30 0 10.0.0.0 40 0.0
MAC: 0007.8432.dd00 0000.0000.0000

https://t.me/learningnets

https://t.me/learningnets

Technet24

CCNP Lab 069: Cisco IOS NBAR Lab

Lab Objective:

The focus of this lab is to understand Network-Based Application Recognition implementation and configuration in Cisco IOS routers.

Lab Topology:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP address on all routers as illustrated in the topology.

Task 2

Configure OSPF on all routers as illustrated in the topology. Verify your configuration

https://t.me/learningnets

Technet24

using the appropriate commands.

Task 3

Configure R2 to discover traffic for all protocols known to NBAR on FastEthernet0/0. Verify your configuration using the appropriate commands.

Task 4

Management has decided that, for security purposes, some protocols be configured to use non-default port numbers in addition to their standard port numbers. These protocols and their non-default port numbers are listed below:

- File Transfer Protocol - TCP port 2021
- Telnet - TCP port 3023
- Hypertext Transfer Protocol - TCP port 8080

Configure NBAR so that statistics for these non-default port numbers are correctly collected.

Task 5

You are troubleshooting router performance issues on R2 and observer the following errors:

%NBAR-2-NOMEMORY: No memory available for StILE lmalloc -Traceback= 0x604EFEEC 0x6044AD40 0x6044AE64 0x6044D540 0x60445D28 0x6044E47C 0x6046F858 0x60454BCC 0x6045575C 0x60456748 0x60F1201C 0x6052F44C 0x6054DE80 0x605F4
%NBAR-2-RMNORESOURCE : NBAR resources exhausted
%NBAR-2-NOSTATEMEM : Memory for maintaining state used up
%NBAR-2-RMINVALIDCONFIG: NBAR resource manager : too many buckets

Given this, management has requested that you decrease the idle time to 60 seconds, increase the initial memory size to 2M and allow up to 68K expansion. Verify your configuration using the appropriate commands.

Task 6

Your company is running a custom, in-house application that uses TCP ports 6700 and 6705 as well as UDP port between 6800 and 6900. Configure R2 so that the router monitors and correctly classifies this traffic. Assume the application is named OOMPALOOMPA.

Lab Validation:

https://t.me/learningnets

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 1 subnets
D 10.0.0.8 [90/2172416] via 150.1.1.2, 00:18:09, FastEthernet0/0
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2174976] via 150.1.1.2, 00:17:54, FastEthernet0/0

R2#**show ip route eigrp**
150.3.0.0/24 is subnetted, 1 subnets
D 150.3.3.0 [90/2172416] via 10.0.0.10, 00:18:00, Serial0/1

R3#**show ip route eigrp**
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/20514560] via 10.0.0.9, 00:18:02, Serial1/1

Task 3

The requirements for this task are straightforward. Prior to configuring NBAR, it is important to remember that you must also enable CEF on the router. This task is completed as follows:

R2(config)#**ip cef**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip nbar protocol-discovery**
R2(config-if)#**exit**

Verify your configuration using the **show ip nbar protocol-discovery** command. This command can be used to view statistics for a single protocol, all known protocols, etc. You can generate additional traffic, e.g. Telnet, HTTP, HTTPS, etc in your lab to view statistics about those protocols. Assuming only EIGRP is running on the LAN segment between R1 and R2, use the following command to view the EIGRP protocol statistics:

R2#**show ip nbar protocol-discovery protocol eigrp**

FastEthernet0/0
Input Output

https://t.me/learningnets

Technet24

----- ------
Protocol Packet Count Packet Count
Byte Count Byte Count
5min Bit Rate (bps) 5min Bit Rate (bps)
5min Max Bit Rate (bps) 5min Max Bit Rate (bps)
---------------------- ----------------------- -----------------------
eigrp 526 265
38790 19580
0 0
0 0
unknown 0 0
0 0
0 0
0 0
Total 2604 291
1308854 22052
7000 0
7000 0

Task 4

The requirements for this task are straightforward. To configure NBAR to search for a protocol or protocol name using a port number other than the well-known port, use the **ip nbar port-map** global configuration command. This task is completed as follows on router R2:

R2(config)#**ip nbar port-map ftp tcp 21 2021**
R2(config)#**ip nbar port-map telnet tcp 23 2023**
R2(config)#**ip nbar port-map http tcp 80 8080**

Next, verify the configuration using the **show ip nbar port-map <protocol>** command:

R2#**show ip nbar port-map**
port-map bgp udp 179
port-map bgp tcp 179
port-map citrix udp 1604
port-map citrix tcp 1494
port-map cuseeme udp 7648 7649 24032
port-map cuseeme tcp 7648 7649
port-map dhcp udp 67 68
port-map dns udp 53
port-map dns tcp 53

https://t.me/learningnets

port-map edonkey tcp 4662
port-map exchange tcp 135
port-map fasttrack tcp 1214
port-map finger tcp 79
port-map ftp tcp 21 2021
port-map gnutella tcp 6346 6347 6348 6349 6355 5634
port-map gopher udp 70
port-map gopher tcp 70
port-map h323 udp 1300 1718 1719 1720 11720
port-map h323 tcp 1300 1718 1719 1720 11000 - 11999
port-map http tcp 80 8080
port-map imap udp 143 220
port-map imap tcp 143 220
port-map irc udp 194
port-map irc tcp 194
port-map kerberos udp 88 749
port-map kerberos tcp 88 749
port-map l2tp udp 1701
port-map ldap udp 389
port-map ldap tcp 389
port-map mgcp udp 2427 2727
port-map mgcp tcp 2427 2428 2727
port-map netbios udp 137 138
port-map netbios tcp 137 139
port-map netshow tcp 1755
port-map nfs udp 2049
port-map nfs tcp 2049
port-map nntp udp 119
port-map nntp tcp 119
port-map notes udp 1352
port-map notes tcp 1352
port-map novadigm udp 3460 3461 3462 3463 3464 3465
port-map novadigm tcp 3460 3461 3462 3463 3464 3465
port-map ntp udp 123
port-map ntp tcp 123
port-map pcanywhere udp 22 5632
port-map pcanywhere tcp 65301 5631
port-map pop3 udp 110

https://t.me/learningnets

Technet24

port-map pop3 tcp 110
port-map pptp tcp 1723
port-map printer udp 515
port-map printer tcp 515
port-map rcmd tcp 512 513 514
port-map rip udp 520
port-map rsvp udp 1698 1699
port-map rtsp tcp 554
port-map secure-ftp tcp 990
port-map secure-http tcp 443
port-map secure-imap udp 585 993
port-map secure-imap tcp 585 993
port-map secure-irc udp 994
port-map secure-irc tcp 994
port-map secure-ldap udp 636
port-map secure-ldap tcp 636
port-map secure-nntp udp 563
port-map secure-nntp tcp 563
port-map secure-pop3 udp 995
port-map secure-pop3 tcp 995
port-map secure-telnet tcp 992
port-map sip udp 5060
port-map sip tcp 5060
port-map skinny tcp 2000 2001 2002
port-map smtp tcp 25
port-map snmp udp 161 162
port-map snmp tcp 161 162
port-map socks tcp 1080
port-map sqlnet tcp 1521
port-map sqlserver tcp 1433
port-map ssh tcp 22
port-map streamwork udp 1558
port-map sunrpc udp 111
port-map sunrpc tcp 111
port-map syslog udp 514
port-map telnet tcp 23 2023
port-map tftp udp 69
port-map vdolive tcp 7000

https://t.me/learningnets

port-map winmx tcp 6699
port-map xwindows tcp 6000 6001 6002 6003

Task 5

NBAR consumes a lot of memory, which may cause adverse performance issues on the router. It is always important to understand the platform on which you are going to be implementing NBAR on prior to doing so - especially in production environments with a lot of traffic. The NBAR resource allocations and idle timeout values can be viewed using the **show ip nbar resources** command, the output of which is shown below:

R2#**show ip nbar resources**
NBAR memory usage for tracking Stateful sessions
Max-age : 120 secs
Initial memory : 1369 KBytes
Max initial memory : 4566 KBytes
Memory expansion : 68 KBytes
Max memory expansion : 68 KBytes
Memory in use : 1369 KBytes
Max memory allowed : 9132 KBytes
Active links : 0
Total links : 20144

To complete this task, you need to use the **ip nbar resources** global configuration command on R2. This task is completed as follows:

R2(config)#**ip nbar resources 60 2048 2000**

Next, use the **show ip nbar resources** command to verify the modified NBAR allocations:

2#**show ip nbar resources**
NBAR memory usage for tracking Stateful sessions
Max-age : 60 secs
Initial memory : 2048 KBytes
Max initial memory : 4566 KBytes
Memory expansion : 68 KBytes
Max memory expansion : 68 KBytes
Memory in use : 2047 KBytes
Max memory allowed : 9132 KBytes
Active links : 0
Total links : 30117

Task 6

https://t.me/learningnets

Technet24

To complete this task, you must use the **ip nbar custom** command to classify the TCP and the UDP ports to be used by the OOMPALOOMPA application. Because you cannot create a custom map for two unlike protocols, you must configure two custom maps - one for TCP and the other for UDP. This is completed as follows:

```
R2(config)#ip nbar custom OOMPALOOMPA_TCP tcp 6701 6705
R2(config)#ip nbar custom OOMPALOOMPA_UDP udp range 6800 6900
```

Next, verify your configuration using the **show ip nbar port-map** command:

```
R2#show ip nbar port-map OOMPALOOMPA_TCP
port-map OOMPALOOMPA_TCP tcp 6701 6705
R2#
R2#show ip nbar port-map OOMPALOOMPA_UDP
port-map OOMPALOOMPA_UDP udp 6800 - 6900
R2#
```

https://t.me/learningnets

CCNP Lab 070: Cisco IOS RITE and SPAN Lab

Lab Objective:

The focus of this lab is to understand Router IP Traffic Export (RITE) and Switched Port Analyzer (SPAN) implementation and configuration in Cisco IOS routers.

Lab Topology:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all devices as illustrated in the topology. In addition, configure VLAN 100 on switch ALS1. Assign R1s FastEthernet0/0 to this VLAN and configure a VLAN interface (SVI) with the IP address 150.1.1.254 on switch ALS1. Following this, confirm that switch ALS1 pings router R1.

Task 2

Configure OSPF on R1 and R2 as illustrated in the topology. Ensure that R2 can ping switch ALS1. Verify your configuration using the appropriate commands.

https://t.me/learningnets

Task 3

There have been some network issues experienced on the LAN segment between R1 and ALS1. Configure SPAN on ALS1 so that all ingress and egress traffic from R1s LAN interface is mirrored to FastEthernet 0/8. FastEthernet 0/8 will have an administrator workstation running Wire Shark. In addition to being used for monitoring, this workstation will also need to reach other network devices and all received frames should be assigned to VLAN 100. Verify your configuration using the appropriate commands.

Task 4

R2 is connected to a hub, which makes implementing SPAN impossible. However, users that are connected to this hub are also complaining of network latency. Configure RITE on R2 so that all ingress and egress traffic from the LAN interface is sent to a host with the MAC address 00-24-E7-47-32-40. R1 should only capture inbound and outbound HTTP traffic. All other types should be ignored. Ensure that one in two packets are exported. Verify your configuration.

Lab Validation:

Task 1

Please refer to previous tasks for basic VLAN and IP addressing configuration. These will not be included in this section for brevity and to avoid being redundant. Following your configuration, switch ALS1 should be able to ping R1. This is illustrated in the output below:

ALS1#**ping 150.1.1.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/202/1000 ms

Task 2

Please refer to previous labs for basic OSPF configuration. Following this, verify your OSPF configuration using the **show ip ospf neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

R1#**show ip route ospf**
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 10.0.0.2, 00:00:00, Serial0/0

https://t.me/learningnets

Technet24

R2#**show ip route ospf**
150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/65] via 10.0.0.1, 00:00:21, Serial0/0

In order to allow R2 to ping ALS1, you need to configure a default gateway on switch ALS1:

ALS1(config)#**ip default-gateway 150.1.1.1**

Following this, R2 will be able to ping switch ALS1 and vice-versa:

R2#**ping 150.1.1.254 repeat 10 size 1500 source fastethernet 0/0**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.254, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/16/20 ms

Task 3

While the core requirements of this task are simple, it is important to remember that when a port is specified as a SPAN destination port, by default, it is a receive-only port and cannot transmit data. The state of the SPAN destination port is up/down by design. This state is used in order to make it evident that the port is currently not usable as a production port. To allow ingress traffic, you must use the **ingress**, **encapsulation <isl|dot1q>** and **vlan <tag>** keywords. These keywords enable ingress traffic forwarding on the SPAN destination port, specify the ingress encapsulation and type and VLAN ID respectively. Keep in mind, however, that most Cisco IOS switches now only support 802.1Q; therefore, you do not necessarily need to specify this default encapsulation type. This task is completed as follows:

ALS1(config)#**monitor session 1 source interface fastethernet 0/1 both**
ALS1(config)#**monitor session 1 destination interface fastethernet 0/8 encapsulation dot1q ingress vlan 100**

Next, verify your configuration using the show monitor session command:

ALS1#**show monitor session 1**
Session 1

Type : Local Session
Source Ports :
Both : Fa0/1
Destination Ports : Fa0/8
Encapsulation : DOT1Q

https://t.me/learningnets

Ingress: Enabled, default VLAN = 100
Ingress encapsulation: DOT1Q

You can also append the **detail** keyword for additional information on the session:

ALS1#**show monitor session 1 detail**
Session 1

Type : Local Session
Source Ports :
RX Only : None
TX Only : None
Both : Fa0/1
Source VLANs :
RX Only : None
TX Only : None
Both : None
Source RSPAN VLAN : None
Destination Ports : Fa0/8
Encapsulation : DOT1Q
Ingress: Enabled, default VLAN = 100
Ingress encapsulation: DOT1Q
Reflector Port : None
Filter VLANs : None
Dest RSPAN VLAN : None

Task 4

While the core requirements of this task are straightforward, it is important to remember that you can use ACLs with RITE. The requirement that all ingress and egress HTTP traffic be mirrored means that you must use ACLs that matches both ingress and egress HTTP traffic. You cannot accomplish this with a single ACL. This is completed as follows:

R2(config)#**ip access-list extended INBOUND-HTTP-TRAFFIC**
R2(config-ext-nacl)#**permit tcp any any eq www**
R2(config-ext-nacl)#**exit**
R2(config)#**ip access-list extended OUTBOUND-HTTP-TRAFFIC**
R2(config-ext-nacl)#**permit tcp any eq www any**
R2(config-ext-nacl)#**exit**
R2(config)#**ip traffic-export profile IOS-RITE**
R2(conf-rite)#**bidirectional**

https://t.me/learningnets
Technet24

R2(conf-rite)#**incoming access-list INBOUND-HTTP-TRAFFIC**
R2(conf-rite)#**outgoing access-list OUTBOUND-HTTP-TRAFFIC**
R2(conf-rite)#**mac-address 0024.E747.3240**
R2(conf-rite)#**incoming sample one-in-every 2**
R2(conf-rite)#**outgoing sample one-in-every 2**
R2(conf-rite)#**exit**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip traffic-export apply IOS-RITE**
*Jun 15 21:48:53.999: %RITE-5-ACTIVATE: Activated IP traffic export on interface FastEthernet0/0
R2(config-if)#**exit**

Next, view the router configuration to verify that your solution is configured correctly:

R2#**more system:running-config | section traffic-export**
ip traffic-export profile IOS-RITE
interface FastEthernet0/0
bidirectional
incoming access-list INBOUND-HTTP-TRAFFIC
outgoing access-list OUTBOUND-HTTP-TRAFFIC
mac-address 0024.e747.3240
incoming sample one-in-every 2
outgoing sample one-in-every 2
ip traffic-export apply IOS-RITE

Following this, use the **show ip traffic-export** command to verify statistics:

R2#**show ip traffic-export interface fastethernet 0/0**
Router IP Traffic Export Parameters
Monitored Interface FastEthernet0/0
Export Interface FastEthernet0/0
Destination MAC address 0024.e747.3240
bi-directional traffic export is on
Output IP Traffic Export Information Packets/Bytes Exported 0/0
Packets Dropped 0
Sampling Rate one-in-every 2 packets
Access List OUTBOUND-HTTP-TRAFFIC [named extended IP]
Input IP Traffic Export Information Packets/Bytes Exported 0/0
Packets Dropped 119
Sampling Rate one-in-every 2 packets
Access List INBOUND-HTTP-TRAFFIC [named extended IP]

https://t.me/learningnets

Profile IOS-RITE is Active

To test RITE, assuming you have a device connected to the same segment as R2, you can use the **traffic-export interface <interface> start** and **traffic-export interface <interface> stop** privileged EXEC commands**.**

https://t.me/learningnets

CCNP Lab 071: Cisco IOS RITE and RSPAN Lab

Lab Objective:

The focus of this lab is to understand Router IP Traffic Export (RITE) and Remote Switched Port Analyzer (SPAN) implementation and configuration in Cisco IOS routers.

Lab Topology:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames and IP addresses on all devices as illustrated in the topology. In addition, configure VLAN 100 on switches ALS1 and DLS1. Assign R1s FastEthernet0/0 to this VLAN as well as F0/7-8 on ALS1 and DLS1. Next, configure a VLAN interface (SVI) with the IP address 150.1.1.253 on ALS1 and a VLAN interface (SVI) with the IP address 150.1.1.254 on DLS1. Verify that switches ALS1 and DLS1 can ping each other as well as router R1.

Task 2

https://t.me/learningnets

Technet24

Configure OSPF on R1 and R2 as illustrated in the topology. Ensure that R2 can ping switch ALS1 and DLS1. Verify your configuration using the appropriate commands.

Task 3

In the future, switch DLS1 will have a FastEthernet0/1 configured as a trunk link. There will be multiple VLANs traversing this trunk link. Management has requested that you configure an RSPAN session to monitor ingress and egress traffic received from FastEthernet0/1. However, in the interim, they have requested that the captured traffic be restricted to that from VLANs 200, 400, and 600. This traffic should be sent to FastEthernet0/5 on switch ALS1. The RSPAN session should be configured to use VLAN 456. Implement this solution and verify the RSPAN configuration using the appropriate commands on both switches.

Task 4

VLAN 100 is used as a transit VLAN to the rest of the network. The security team has a NIPS (Network-based Intrusion Prevention System) connected to port FastEthernet 0/3 on switch DLS1. The request that all traffic in VLAN 100 (receive) be mirrored to this port. To allow the IPS to be able to reset sessions, ensure that ingress traffic is permitted on this port. This traffic should be assigned to VLAN 200. Configure a local SPAN session on switch DLS1 to satisfy this requirement. Verify your configuration using the appropriate commands.

Task 5

In the future, R2 will have several WAN links turned on. Serial 0/0 will be the only link that will be connected to the Internet. The other WAN links will be used for spoke connectivity across a private Frame Relay network. Management has requested that you monitor all bidirectional traffic coming into and leaving out of the Serial 0/0 interface on R2. This traffic should be sent to a Network-based Intrusion Prevention System (NIPS) residing on the LAN segment of R2. This NIPS has the MAC address 00-24-E7-47-32-40. To ensure as much traffic is captured as possible, configure R2 so that every other packet is sent to the NIPS. Assume that all ICMP traffic is denied. Configure R2 so that only TCP and UDP traffic is exported. Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous tasks for basic VLAN and IP addressing configuration. These will not be included in this section for brevity and to avoid being redundant. Following your configuration, switch ALS1 should be able to ping R1. This is illustrated in the

https://t.me/learningnets

output below:

ALS1#**ping 150.1.1.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.0, timeout is 2 seconds:

Reply to request 0 from 150.1.1.1, 1 ms
Reply to request 1 from 150.1.1.254, 1 ms
Reply to request 1 from 150.1.1.1, 1 ms
Reply to request 2 from 150.1.1.254, 1 ms
Reply to request 2 from 150.1.1.1, 1 ms
Reply to request 3 from 150.1.1.254, 4 ms
Reply to request 3 from 150.1.1.1, 4 ms
Reply to request 4 from 150.1.1.254, 4 ms
Reply to request 4 from 150.1.1.1, 4 ms

DLS1#**ping 150.1.1.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.0, timeout is 2 seconds:

Reply to request 0 from 150.1.1.1, 4 ms
Reply to request 1 from 150.1.1.1, 1 ms
Reply to request 1 from 150.1.1.253, 1 ms
Reply to request 2 from 150.1.1.1, 1 ms
Reply to request 2 from 150.1.1.253, 1 ms
Reply to request 3 from 150.1.1.1, 1 ms
Reply to request 3 from 150.1.1.253, 1 ms
Reply to request 4 from 150.1.1.1, 1 ms
Reply to request 4 from 150.1.1.253, 1 ms

Task 2

Please refer to previous labs for basic OSPF configuration. Following this, verify your OSPF configuration using the **show ip ospf neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

R1#**show ip route ospf**
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 10.0.0.2, 00:03:57, Serial0/0

R2#**show ip route ospf**
150.1.0.0/24 is subnetted, 1 subnets
O 150.1.1.0 [110/65] via 10.0.0.1, 00:04:08, Serial0/0

https://t.me/learningnets

Technet24

In order to allow R2 to ping ALS1 and DLS1, you need to configure a default gateway on switch ALS1 as well as on DLS1:

ALS1(config)#**ip default-gateway 150.1.1.1**

DLS1(config)#**ip default-gateway 150.1.1.1**

Following this, R2 will be able to ping switch ALS1 and vice-versa:

R2#**ping 150.1.1.253 source fastethernet 0/0 size 1500 repeat 10**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.253, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
.!!!!!!!!!
Success rate is 90 percent (9/10), round-trip min/avg/max = 16/16/20 ms

R2#**ping 150.1.1.254 source fastethernet 0/0 size 1500 repeat 10**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.254, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
.!!!!!!!!!
Success rate is 90 percent (9/10), round-trip min/avg/max = 12/12/16 ms

Task 3

The core requirements for this task are straightforward. Basically, what is required is an RSPAN session between DLS1 and ALS1 using VLAN 456. The source port should be FastEthernernt0/1 on switch DLS1 and the destination port should be FastEthernet0/5 on switch ALS1. The caveat here is that when monitoring a trunk link, ALL traffic, i.e. for all VLANs, will be monitored. The task, however, requests that only traffic for VLANs 200, 400, and 600 be monitored. To do this, we need to filter the VLANs that will be monitored in the RSPAN session configured on switch DLS1 using the **monitor session <session> filter vlan <list>** command on switch DLS1. This task is completed as follows:

DLS1(config)#**vlan 456**
DLS1(config-vlan)#**remote-span**
DLS1(config-vlan)#**exit**
DLS1(config)#**monitor session 1 source interface fastethernet 0/1 both**
DLS1(config)#**monitor session 1 destination remote vlan 456**
DLS1(config)#**monitor session 1 filter vlan 1 - 199 , 201 - 399 , 401 - 455 , 457 - 599 , 601 - 4094**

IMPORTANT NOTE

https://t.me/learningnets

If you are using the www.101labs.net racks, the current switches, as of the time of the writing of this guide, are 3550 series switches. Therefore, when completing this lab, you must configure a reflector port for the RSPAN destination. A reflector port is a mechanism that copies packets onto an RSPAN VLAN. The reflector port forwards only the traffic from the RSPAN source session with which it is affiliated. Any device connected to a port set as a reflector port loses connectivity until the RSPAN source session is disabled. Any unused port can be specified as a reflector port. This port will simply loop back untagged traffic to the switch.

The traffic is then placed on the RSPAN VLAN and flooded to any trunk ports that carry the RSPAN VLAN. The Catalyst 2970, 3560, 3750, 4500 and 6500 series switches do not require the configuration of a reflector port when you configure an RSPAN session. If you are completing this lab on one of these switches, omit the **reflector-port** keyword. If configured on 2950 / 3550, use the following configuration to complete this task:

vlan 456
remote-span
!
monitor ses 1 source interface fastethenet 0/1 both
monitor ses 1 dest rem vl 456 reflector-port fa 0/2
!

ALS1(config)#**vlan 456**
ALS1(config-vlan)#**remote-span**
ALS1(config-vlan)#**exit**
ALS1(config)#**monitor session 1 source remote vlan 456**
ALS1(config)#**monitor session 1 destination interface fastethernet 0/5**

Next, verify your RSPAN configuration using the **show monitor session** command:

ALS1#**show monitor session 1**
Session 1

Type : Remote Destination Session
Source RSPAN VLAN : 456
Destination Ports : Fa0/5
Encapsulation : Native
Ingress: Disabled

DLS1#**show monitor session 1**
Session 1
---

https://t.me/learningnets

Type : Remote Source Session
Source Ports :
Both : Fa0/1
Reflector Port : Fa0/2
Filter VLANs : 1-199,201-399,401-455,457-599,601-4094
Dest RSPAN VLAN : 456

Additionally, you can append the **detail** keyword for more information:

DLS1#**show monitor session 1 detail**
Session 1

Type : Remote Source Session
Description : -
Source Ports :
RX Only : None
TX Only : None
Both : Fa0/1
Source VLANs :
RX Only : None
TX Only : None
Both : None
Source RSPAN VLAN : None
Destination Ports : None
Reflector Port : Fa0/2
Filter VLANs : 1-199,201-399,401-455,457-599,601-4094
Dest RSPAN VLAN : 456

Task 4

The requirements for this task are straightforward. This task is completed as follows on DLS1:

DLS1(config)#**monitor session 2 source vlan 100 rx**
DLS1(config)#**monitor session 2 destination interface Fa0/3 encapsulation dot1q ingress vlan 200**
DLS1(config)#**exit**

Next, verify your configuration using the **show monitor session** command:

DLS1#**show monitor session 2 detail**
Session 2
---

https://t.me/learningnets

Type : Local Session
Description : -
Source Ports :
RX Only : None
TX Only : None
Both : None
Source VLANs :
RX Only : 100
TX Only : None
Both : None
Source RSPAN VLAN : None
Destination Ports : Fa0/3
Encapsulation : DOT1Q
Ingress : Enabled, default VLAN = 200
Reflector Port : None
Filter VLANs : None
Dest RSPAN VLAN : None

Task 5

The core requirements for this task are straightforward. However, in order to monitor traffic that is received and sent via Serial 0/0, we need to apply the RITE profile to this interface. Within the RITE profile, we need to specify FastEthernet0/0 as the egress interface as this is where the Network-based Intrusion Prevention System be connected. This task is completed as follows:

R2(config)#**access-list 100 permit tcp any any**
R2(config)#**access-list 100 permit udp any any**
R2(config)#**access-list 101 permit tcp any any**
R2(config)#**access-list 101 permit udp any any**
R2(config)#**ip traffic-export profile INTERNET-MONITORING**
R2(conf-rite)#**bidirectional**
R2(conf-rite)#**incoming access-list 100**
R2(conf-rite)#**incoming sample one-in-every 2**
R2(conf-rite)#**outgoing access-list 101**
R2(conf-rite)#**outgoing sample one-in-every 2**
R2(conf-rite)#**mac-address 0024.E747.3240**
R2(conf-rite)#**interface fastethernet 0/0**
R2(conf-rite)#**exit**
R2(config)#**interface s0/0**

https://t.me/learningnets
Technet24

R2(config-if)#**ip traffic-export apply INTERNET-MONITORING**
R2(config-if)#
*Jun 15 11:31:47.843: %RITE-5-ACTIVATE: Activated IP traffic export on interface Serial0/0
R2(config-if)#**exit**

Following this, use the **show ip traffic-export** command to verify statistics:

R2#**show ip traffic-export interface serial 0/0**
Router IP Traffic Export Parameters
Monitored Interface Serial0/0
Export Interface FastEthernet0/0
Destination MAC address 0024.e747.3240
bi-directional traffic export is on
Output IP Traffic Export Information Packets/Bytes Exported 0/0
Packets Dropped 0
Sampling Rate one-in-every 2 packets
Access List 101 [extended IP]
Input IP Traffic Export Information Packets/Bytes Exported 0/0
Packets Dropped 0
Sampling Rate one-in-every 2 packets
Access List 100 [extended IP]
Profile INTERNET-MONITORING is Active

To test RITE, assuming you have a device connected to the same segment as R2, you can use the **traffic-export interface <interface> start** and **traffic-export interface <interface> stop** privileged EXEC commands**.**

https://t.me/learningnets

CCNP Lab 072: Syslog and SNMP Lab

Lab Objective:

The focus of this lab is to understand Syslog and Simple Network Management Protocol implementation and configuration in Cisco IOS routers.

Lab Topology:

This lab requires only a single router running, at a minimum, Cisco IOS Software 12.4 Mainline. The router should have at least one Ethernet interface. The primary purpose of this lab is to reinforce configuration knowledge of the stated chapter.

IMPORTANT NOTE

If you have multiple devices and servers / hosts in your home lab and you would like to test solutions for topics such as Syslog, SNMP and NetFlow by setting up a host and viewing charts or logging information, for example, please feel free to do so. While these labs include logging to 'supposed' hosts, there are no SNMP or Syslog servers in the http://www.101labs.net racks and so you will not be able to test the solutions in those racks. If you only have a single router, you can bring up the Ethernet interface by implementing the following configuration:

```
!
interface fastethernet 0/0
loopback
no keepalive
no shut
!
```

Task 1

Configure local login for the Console port on the router. Next, configure two user accounts on the router. The first user account should be for user STANDARD with a password of CCNP1. The second user account should be for user ADVANCED with a password of CCNP2. User STANDARD should be assigned the lowest privilege level, while user ADVANCED should be assigned the highest privilege level. Verify and test your configuration appropriately.

Task 2

Configure the router so that all informational messages are sent to Syslog server 150.1.1.254. These messages should include user information. Verify and test your

https://t.me/learningnets

Technet24

configuration using the appropriate commands.

Task 3

In the future, multiple devices will be added to the network and they will all be logging to the 150.1.1.254 host. Management has requested Syslog messages contain the actual hostname of the device, as well as the location, e.g. Dallas, TX or Atlanta, GA for easier identification. Assuming that this device resides in Dallas, TX, configure the router to include its hostname as well as the location Dallas, TX is Syslog messages. Verify your configuration.

Task 4

Management has requested that you implement SNMPv3 on the router. Configure the router for SNMPv3 using the following guidelines:

- Using a view named NOC that includes all MIB objects within the system group
- A group named SWITCH which uses no authentication and has read-only access
- A remote engine ID of 1a2b3c4d5e for host 150.1.1.254
- A user named PASS in group SWITCH using MD5 and with a password of h@rd!

Verify your configuration using the appropriate commands.

Task 5

Configure the router to send SNMP traps to host 150.1.1.254 as follows:

- Use the SNMPv3 authNoPriv Security Level and the SNMPv3 username PASS
- Send only the environmental monitor traps and send traps from FastEthernet 0/0

Verify your configuration using the appropriate commands.

Lab Validation:

Task 1

The requirements of this task are straightforward and should be very well known at this level. This task is completed as follows:

R1(config)#**username STANDARD privilege 0 password CCNP1**

R1(config)#**username ADVANCED privilege 15 password CCNP2**

R1(config)#**line console 0**

R1(config-line)#**login local**

https://t.me/learningnets

R1(config-line)#**exit**

You can verify your configuration by looking at the router configuration file:

R1#**more system:running-config | section username|line**

username STANDARD privilege 0 password 0 CCNP1

username ADVANCED privilege 15 password 0 CCNP2

line con 0

login local

line aux 0

line vty 0 4

login

Next, test your solution by exiting and logging in first as user STANDARD:

R1#**exit**

R1 con0 is now available

Press RETURN to get started.

User Access Verification

Username: **STANDARD**

Password:

R1>

Finally , test your solution by exiting and logging in as user ADVANCED:

R1#**exit**

R1 con0 is now available

Press RETURN to get started.

User Access Verification

Username: **ADVANCED**

Password:

R1#

Task 2

The requirements of this task are straightforward and have been described in previous labs. The only exception is the logging of user events. In current versions of Cisco IOS Software, you can use the **logging userinfo** command to enable the logging of user information. This command allows for the logging of user information when the user

https://t.me/learningnets

Technet24

invokes the enable privilege mode or when the user changes the privilege level. The information logged includes username, line and privileged level. This task is completed as follows:

R1(config)#**logging on**

R1(config)#**logging trap informational**

R1(config)#**logging host 150.1.1.254**

R1(config)#**logging userinfo**

R1(config)#**exit**

Following this, assuming you are consoled in and console logging is also enabled on the router, you will see a message similar to the following printed on the console:

*Jun 15 12:19:02.463: %SYS-5-CONFIG_I: Configured from console by ADVANCED on console

*Jun 15 12:19:03.463: %SYS-6-LOGGINGHOST_STARTSTOP: Logging to host 150.1.1.254 started - CLI initiated

Notice that the output includes the username (ADVANCED) as well as the line from which the configuration was performed (Console). A similar message would also be printed if, for example, the STANDARD user navigated from user EXEC to privileged EXEC mode on R1:

R1 con0 is now available

Press RETURN to get started.

User Access Verification

Username: **STANDARD**
Password:
R1>**enable**
R1#
*Jun 15 12:21:38.451: %SYS-5-PRIV_AUTH_PASS: Privilege level set to 15 by STANDARD on console
R1#
R1#
R1#**disable**
R1>
*Jun 15 12:22:51.555: %SYS-5-PRIV_AUTH_PASS: Privilege level set to 1 by STANDARD on console
R1>

Task 3

https://t.me/learningnets

In most cases, when configuring logging, a source-interface is specified. This allows network administrators to determine which host sent the information - based on the IP address of the source interface. Cisco IOS Software enhances this functionality even further by allowing an identifier to be added to the beginning of all Syslog messages sent to remote hosts.

This identifier is specified using the **logging origin-id string <identifier>** global configuration command. The identifier can be the hostname, the IPv4 address, the IPv6 address, or any custom text. When specifying a custom text, you must use an underscore (_) if using multiple words. For example, howtonetwork_rack1, as spaces are not allowed. If you need to specify a custom string or text that will have spaces, you need to use parenthesis (brackets), for example “howtonetwork rack 1”. When using this feature, it is important to remember that the specified custom text is only sent to remote destinations. It will NOT be included for local destinations, such as the Console or local buffer, for example. This task is completed as follows:

R1(config)#**logging origin-id string “R1 - Dallas, TX”**

You can verify your configuration by looking at the device configuration:

R1#**more system:running-config | section logging**
logging userinfo
logging origin-id string “R1 - Dallas, TX”
logging 150.1.1.254

Task 4

Because SNMPv3 configuration is technically beyond the scope of the current CCNP course, the same example used in the SWITCH certification guide is used here. If you read the section, you would have no problem completing this task. This task is completed as follows:

R1(config)#**snmp-server view NOC system included**
R1(config)#**snmp-server group SWITCH v3 noauth read NOC**
R1(config)#**snmp-server engineID remote 150.1.1.254 1a2b3c4d5e**
R1(config)#**snmp-server user PASS SWITCH v3 auth md5 h@rd!**

*Jun 15 12:50:36.331: Configuring snmpv3 USM user, persisting snmpEngineBoots. Please Wait...

R1(config)#

You can view configured and default SNMP views using the **show snmp view** command:

R1#**show snmp view**

https://t.me/learningnets

Technet24

NOC system - included nonvolatile active
*ilmi system - included permanent active
*ilmi atmForumUni - included permanent active
v1default iso - included permanent active
v1default internet.6.3.15 - excluded permanent active
v1default internet.6.3.16 - excluded permanent active
v1default internet.6.3.18 - excluded permanent active
v1default ciscoMgmt.394 - excluded permanent active
v1default ciscoMgmt.395 - excluded permanent active
v1default ciscoMgmt.399 - excluded permanent active
v1default ciscoMgmt.400 - excluded permanent active

You can view configured groups using the **show snmp group** command:

R1#**show snmp group**
groupname: ILMI security model:v1
readview : *ilmi writeview: *ilmi
notifyview: <no notifyview specified>
row status: active

groupname: ILMI security model:v2c
readview : *ilmi writeview: *ilmi
notifyview: <no notifyview specified>
row status: active

groupname: SWITCH security model:v3 noauth
readview : NOC writeview: <no writeview specified>
notifyview: <no notifyview specified>
row status: active

Task 5

The requirements for this task are straightforward. This task is completed as follows:

R1(config)#**snmp-server host 150.1.1.254 version 3 auth PASS envmon**
R1(config)#**snmp-server enable traps envmon**
R1(config)#**snmp-server source-interface traps fastethernet 0/0**

Next, verify your configuration using the **show snmp** commands:

R1#**show snmp**
Chassis: JAE08020Z7T
0 SNMP packets input
0 Bad SNMP version errors
0 Unknown community name

https://t.me/learningnets

0 Illegal operation for community name supplied
0 Encoding errors
0 Number of requested variables
0 Number of altered variables
0 Get-request PDUs
0 Get-next PDUs
0 Set-request PDUs
0 Input queue packet drops (Maximum queue size 1000)
0 SNMP packets output
0 Too big errors (Maximum packet size 1500)
0 No such name errors
0 Bad values errors
0 General errors
0 Response PDUs
0 Trap PDUs

SNMP logging: enabled
Logging to 150.1.1.254.162, 0/10, 0 sent, 0 dropped.

To view host configuration parameters, use the **show snmp host** command:

R1#**show snmp host**
Notification host: 150.1.1.254 udp-port: 162 type: trap
user: PASS security model: v3 auth

https://t.me/learningnets

Technet24

CCNP Lab 073: Multicast - PIM Dense Mode Lab

Lab Objective:

The focus of this lab is to understand IP Multicast Dense Mode forwarding in Cisco IOS routers. Additional technologies include the Internet Group Management Protocol (IGMP).

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure the hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Technet24

Enable EIGRP on all routers as illustrated in the topology. Verify your EIGRP configuration.

Task 3

Enable Internet Group Management Protocol on the LAN interfaces of R1 and R4. Ensure that the configuration allows the host to request traffic from a specific host in the network. Next, enable Dense Mode forwarding on the interfaces. Verify your solution using the appropriate commands.

Task 4

Enable Dense Mode forwarding on all router WAN interfaces. Verify your configuration using the appropriate commands.

Task 5

Configure R1 so that its LAN interface is joined to Multicast group 227.1.1.1. Configure R4 so that its LAN interface is joined to Multicast group 227.4.4.4. Verify that R1 can ping R4s Multicast group and that R4 can ping R1s Multicast group.

Lab Validation:

Task 1

Please refer to previous tasks for basic VLAN and IP addressing configuration. These will not be included in this section for brevity and to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/2681856] via 10.0.0.2, 00:00:12, Serial0/0
D 10.0.0.12 [90/21536000] via 10.0.0.2, 00:00:12, Serial0/0
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/21538560] via 10.0.0.2, 00:00:12, Serial0/0

R2#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.12 [90/21024000] via 10.0.0.10, 00:00:22, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:00:17, Serial0/0

https://t.me/learningnets

150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/21026560] via 10.0.0.10, 00:00:22, Serial0/1

R3#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.0 [90/21024000] via 10.0.0.9, 00:00:25, Serial1/1
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/21026560] via 10.0.0.9, 00:00:20, Serial1/1
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/20514560] via 10.0.0.14, 00:00:31, Serial1/2

R4#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/21024000] via 10.0.0.13, 00:00:34, Serial0/0
D 10.0.0.0 [90/21536000] via 10.0.0.13, 00:00:28, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/21538560] via 10.0.0.13, 00:00:23, Serial0/0

Task 3

The core requirement of this task is straightforward. However, in order to complete this task as required you need to understand, from the wording, what version of IGMP is required. Specifically, the task is requiring that IGMPv3 be enabled. IGMP version 3, the most recent modification of the IGMP specification, is defined in RFC 3376. This version now allows the host to request traffic from a specific host in the network. Hosts can also specify a list of sources that they should not receive Multicast traffic from. These changes provide support for the use of Source-Specific Multicast within the 232.0.0.0 /8 Multicast group address range. Given this understanding, this task is completed as follows:

R1(config)#**ip multicast-routing**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip igmp version 3**
R1(config-if)#**ip pim dense-mode**
R1(config-if)#**exit**

R4(config)#**ip multicast-routing**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip igmp version 3**
R4(config-if)#**ip pim dense-mode**
R4(config-if)#**exit**

Next, verify your configuration using the **show ip igmp interface** command:

https://t.me/learningnets

Technet24

R1#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.1.1.1/24
IGMP is enabled on interface
Current IGMP host version is 3
Current IGMP router version is 3
IGMP query interval is 60 seconds
IGMP querier timeout is 120 seconds
IGMP max query response time is 10 seconds
Last member query count is 2
Last member query response interval is 1000 ms
Inbound IGMP access group is not set
IGMP activity: 1 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.1.1.1 (this system)
IGMP querying router is 150.1.1.1 (this system)
Multicast groups joined by this system (number of users):
224.0.1.40(1)

R4#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.4.4.4/24
IGMP is enabled on interface
Current IGMP host version is 3
Current IGMP router version is 3
IGMP query interval is 60 seconds
IGMP querier timeout is 120 seconds
IGMP max query response time is 10 seconds
Last member query count is 2
Last member query response interval is 1000 ms
Inbound IGMP access group is not set
IGMP activity: 1 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.4.4.4 (this system)
IGMP querying router is 150.1.1.1
Multicast groups joined by this system (number of users):
224.0.1.40(1)

https://t.me/learningnets

Notice in the last line of the output that the interface is automatically joined to group 224.0.1.40. This group is for Cisco RP Discovery messages. The interface is automatically joined to this group because Dense mode assumes that all hosts want to receive Multicast traffic, unless they explicitly state that they do not. This group is enabled by default; however, it is not applicable in this section because there is no RP when PIM dense mode is enabled. It simply indicates that the interface is listening for packets that may be sent to this group address.

Task 4

The requirements for this task are straightforward. This task is completed as follows:

R1(config)#**interface serial 0/0**
R1(config-if)#**ip pim dense-mode**
R1(config-if)#**exit**

R2(config)#**ip multicast-routing**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip pim dense-mode**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip pim dense-mode**
R2(config-if)#**exit**

R3(config)#**ip multicast-routing**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip pim dense-mode**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip pim dense-mode**
R3(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**ip pim dense-mode**
R4(config-if)#**exit**

Next, verify PIM Dense Mode parameters using the **show ip pim** interface command:

R4#**show ip pim interface serial 0/0 detail**
Serial0/0 is up, line protocol is up
Internet address is 10.0.0.14/30
Multicast switching: fast
Multicast packets in/out: 254/0
Multicast TTL threshold: 0

https://t.me/learningnets
Technet24

PIM: enabled
PIM version: 2, mode: dense
PIM DR: 0.0.0.0
PIM neighbor count: 1
PIM Hello/Query interval: 30 seconds
PIM Hello packets in/out: 4/5
PIM State-Refresh processing: enabled
PIM State-Refresh origination: disabled
PIM NBMA mode: disabled
PIM ATM multipoint signalling: disabled
PIM domain border: disabled
Multicast Tagswitching: disabled

Task 5

To configure a router interface to join a Multicast group, a technique commonly used to test the Multicast configuration, use the **ip igmp join-group <group>** interface command:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip igmp join-group 227.1.1.1**
R1(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip igmp join-group 227.4.4.4**
R4(config-if)#**exit**

Next, verify your configuration using the **show ip igmp interface** command:

R1#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.1.1.1/24
IGMP is enabled on interface
Current IGMP host version is 3
Current IGMP router version is 3
IGMP query interval is 60 seconds
IGMP querier timeout is 120 seconds
IGMP max query response time is 10 seconds
Last member query count is 2
Last member query response interval is 1000 ms
Inbound IGMP access group is not set
IGMP activity: 3 joins, 0 leaves
Multicast routing is enabled on interface

https://t.me/learningnets

Multicast TTL threshold is 0
Multicast designated router (DR) is 150.4.4.4
IGMP querying router is 150.1.1.1 (this system)
Multicast groups joined by this system (number of users):
224.0.1.40(1) 227.1.1.1(1)

R4#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.4.4.4/24
IGMP is enabled on interface
Current IGMP host version is 3
Current IGMP router version is 3
IGMP query interval is 60 seconds
IGMP querier timeout is 120 seconds
IGMP max query response time is 10 seconds
Last member query count is 2
Last member query response interval is 1000 ms
Inbound IGMP access group is not set
IGMP activity: 2 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.4.4.4 (this system)
IGMP querying router is 150.1.1.1
Multicast groups joined by this system (number of users):
224.0.1.40(1) 227.4.4.4(1)

Finally, complete the task by pinging the Multicast groups from routers R1 and R4:

R1#**ping 227.4.4.4**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 227.4.4.4, timeout is 2 seconds:

Reply to request 0 from 10.0.0.14, 40 ms

R4#**ping 227.1.1.1**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 227.1.1.1, timeout is 2 seconds:

Reply to request 0 from 10.0.0.1, 40 ms

https://t.me/learningnets

Technet24

CCNP Lab 074: Multicast - PIM Sparse Mode Lab

Lab Objective:

The focus of this lab is to understand IP Multicast-Sparse Mode forwarding in Cisco IOS routers. Additional technologies include the Internet Group Management Protocol (IGMP).

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure the hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Technet24

Enable EIGRP on all routers as illustrated in the topology. Verify your EIGRP configuration.

Task 3

Enable Internet Group Management Protocol on the LAN interfaces of R1 and R4. These LAN interfaces are connected to legacy hosts that only understand basic IGMP. Configure the version that provides the most basic services. Finally, enable Sparse Mode forwarding on the router LAN interfaces. Verify your solution using the appropriate commands.

Task 4

Enable Sparse Mode forwarding on all router WAN interfaces. Verify your configuration using the appropriate commands.

Task 5

Configure R1 so that its LAN interface is joined to Multicast group 227.1.1.1. Configure R4 so that its LAN interface is joined to Multicast group 227.4.4.4. Verify that R1 can ping R4s Multicast group and that R4 can ping R1s Multicast group.

Task 6

Given that the network will be running Sparse Mode, configure R2 as the Rendezvous Point, or RP. Configure a Loopback 0 interface with the IP address 2.2.2.2/32 on this router. This Loopback address should be configured as the RP for all routers in the network. HINT: Use the **ip pim rp-address <address>** command on all routers. Verify your configuration and test your solution by pinging 227.4.4.4 from R1 and 227.1.1.1 from R4.

Lab Validation:

Task 1

Please refer to previous tasks for basic VLAN and IP addressing configuration. These will not be included in this section for brevity and to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/2681856] via 10.0.0.2, 00:00:12, Serial0/0

https://t.me/learningnets

D 10.0.0.12 [90/21536000] via 10.0.0.2, 00:00:12, Serial0/0
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/21538560] via 10.0.0.2, 00:00:12, Serial0/0

R2#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.12 [90/21024000] via 10.0.0.10, 00:00:22, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:00:17, Serial0/0
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/21026560] via 10.0.0.10, 00:00:22, Serial0/1

R3#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.0 [90/21024000] via 10.0.0.9, 00:00:25, Serial1/1
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/21026560] via 10.0.0.9, 00:00:20, Serial1/1
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/20514560] via 10.0.0.14, 00:00:31, Serial1/2

R4#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/21024000] via 10.0.0.13, 00:00:34, Serial0/0
D 10.0.0.0 [90/21536000] via 10.0.0.13, 00:00:28, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/21538560] via 10.0.0.13, 00:00:23, Serial0/0

Task 3

The core requirement of this task is straightforward. IGMPv1 provides the most basic services. Given this understanding, this task is completed as follows:

R1(config)#**ip multicast-routing**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip igmp version 1**
R1(config-if)#**ip pim sparse-mode**
R1(config-if)#**exit**

R4(config)#**ip multicast-routing**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip igmp version 1**
R4(config-if)#**ip pim sparse-mode**
R4(config-if)#**exit**

https://t.me/learningnets

Technet24

Next, verify your configuration using the **show ip igmp interface** command:

R1#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.1.1.1/24
IGMP is enabled on interface
Current IGMP host version is 1
Current IGMP router version is 1
IGMP query interval is 60 seconds
Inbound IGMP access group is not set
IGMP activity: 0 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.4.4.4
IGMP querying router is 150.4.4.4 (this system)
No multicast groups joined by this system

R4#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.4.4.4/24
IGMP is enabled on interface
Current IGMP host version is 1
Current IGMP router version is 1
IGMP query interval is 60 seconds
Inbound IGMP access group is not set
IGMP activity: 0 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.4.4.4 (this system)
IGMP querying router is 150.4.4.4 (this system)
No multicast groups joined by this system

Notice that unlike Dense Mode, the interfaces are NOT automatically joined to any Multicast groups. This is because Sparse mode forwarding operates in a manner that is opposite to dense mode forwarding. That is, while dense mode assumes that all Multicast-enabled interfaces are interested in receiving Multicast packets unless explicitly configured otherwise, sparse mode assumes that no Multicast interfaces are interested in receiving Multicast packets unless explicitly configured otherwise; that is to say, unless a PIM join message is received on the interface. As such, routers in a sparse-mode network must explicitly request that the data stream be forwarded to them.

https://t.me/learningnets

Task 4

The requirements of this task are straightforward. This task is completed as follows:

R1(config)#**interface serial 0/0**
R1(config-if)#**ip pim sparse-mode**
R1(config-if)#**exit**

R2(config)#**ip multicast-routing**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip pim sparse-mode**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip pim sparse-mode**
R2(config-if)#**exit**

R3(config)#**ip multicast-routing**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip pim sparse-mode**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip pim sparse-mode**
R3(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**ip pim sparse-mode**
R4(config-if)#**exit**

Next, verify PIM Sparse Mode parameters using the **show ip pim** interface command:

R1#**show ip pim interface serial 0/0 detail**
Serial0/0 is up, line protocol is up
Internet address is 10.0.0.1/30
Multicast switching: fast
Multicast packets in/out: 667/1
Multicast TTL threshold: 0
PIM: enabled
PIM version: 2, mode: sparse
PIM DR: 0.0.0.0
PIM neighbor count: 1
PIM Hello/Query interval: 30 seconds
PIM Hello packets in/out: 61/63
PIM State-Refresh processing: enabled

https://t.me/learningnets

Technet24

PIM State-Refresh origination: disabled
PIM NBMA mode: disabled
PIM ATM multipoint signalling: disabled
PIM domain border: disabled
Multicast Tagswitching: disabled

Task 5

To configure a router interface to join a Multicast group, a technique commonly used to test the Multicast configuration, use the **ip igmp join-group <group>** interface command:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip igmp join-group 227.1.1.1**
R1(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip igmp join-group 227.4.4.4**
R4(config-if)#**exit**

Next, verify your configuration using the **show ip igmp interface** command:

R1#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.1.1.1/24
IGMP is enabled on interface
Current IGMP host version is 1
Current IGMP router version is 1
IGMP query interval is 60 seconds
Inbound IGMP access group is not set
IGMP activity: 2 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.4.4.4
IGMP querying router is 150.4.4.4
Multicast groups joined by this system (number of users):
227.1.1.1(1)

R4#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.4.4.4/24
IGMP is enabled on interface
Current IGMP host version is 1

https://t.me/learningnets

Current IGMP router version is 1
IGMP query interval is 60 seconds
Inbound IGMP access group is not set
IGMP activity: 3 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.4.4.4 (this system)
IGMP querying router is 150.4.4.4 (this system)
Multicast groups joined by this system (number of users):
227.4.4.4(1)

Task 6

When sparse-mode is enabled, one of the routers in the network performs a special function as a connection point between the source and the receiver. This router is referred to as the Rendezvous Point, or RP. The RP combines knowledge of the group source with the requests from the receiver. The RP is where the sender and the receiver first meet before the shortest-path tree is established. In other words, once the sender and receiver are aware of each other via the use of the RP, they use the shortest path between sender and receiver, based on routing protocol metric, to send and receive Multicast packets.

Once the Multicast traffic from the source and the requests from the receivers connect at the RP, the traffic is forwarded through the network. This shared tree has the RP at the top of the forwarding tree with the network segments and receivers as the branches and leaves, respectively. This is often referred to as the Rendezvous Point Tree (RPT). The shared-tree used by sparse mode is represented with the (*, G) notation. The * is used as a wildcard because the actual source of the Multicast stream is never known until registered with the RP.

In Cisco IOS Software, there are three ways in which the location of the RP can be specified:

- By statically configuring the router or switch with the RP IP address
- Automatically, using the Cisco Auto-RP mechanism
- Automatically, using the Bootstrap Router mechanism with PIMv2

This task requires that you statically configure the RP address on all routers using the **ip pim rp-address <address>** command. This task is completed as follows:

R1(config)#**ip pim rp-address 2.2.2.2**

R2(config)#**interface loopback 0**

https://t.me/learningnets

Technet24

R2(config-if)#**ip address 2.2.2.2 255.255.255.255**
R2(config-if)#**ip pim sparse-mode**
R2(config-if)#**exit**
R2(config)#**ip pim rp-address 2.2.2.2**
R2(config)#**exit**
NOTE: You MUST advertise the Loopback 0 interface via EIGRP. If you enabled EIGRP for all networks using the **network 0.0.0.0** command, no additional configuration is necessary. However, if you explicitly enabled EIGRP for specific subnets, you need to also advertise the configured Loopback 0 interface via EIGRP; otherwise, no other router can reach this address.

R3(config)#**ip pim rp-address 2.2.2.2**

R4(config)#**ip pim rp-address 2.2.2.2**

Next, verify static RP configuration using the **show ip pim rp** command:

R1#**show ip pim rp**
Group: 227.4.4.4, RP: 2.2.2.2, uptime 00:02:09, expires never
Group: 227.1.1.1, RP: 2.2.2.2, uptime 00:00:47, expires never
Group: 224.0.1.40, RP: 2.2.2.2, uptime 00:02:09, expires never

R2#**show ip pim rp**
Group: 227.4.4.4, RP: 2.2.2.2, next RP-reachable in 00:00:52
Group: 227.1.1.1, RP: 2.2.2.2, next RP-reachable in 00:00:16
Group: 224.0.1.40, RP: 2.2.2.2, next RP-reachable in 00:01:21

R3#**show ip pim rp**
Group: 227.4.4.4, RP: 2.2.2.2, uptime 00:02:18, expires never
Group: 227.1.1.1, RP: 2.2.2.2, uptime 00:01:24, expires never
Group: 224.0.1.40, RP: 2.2.2.2, uptime 00:02:21, expires never

R4#**show ip pim rp**
Group: 227.4.4.4, RP: 2.2.2.2, uptime 00:02:30, expires never
Group: 227.1.1.1, RP: 2.2.2.2, uptime 00:01:36, expires never
Group: 224.0.1.40, RP: 2.2.2.2, uptime 00:02:30, expires never

In addition to the two statically defined Multicast groups, also notice that group 224.0.1.40 is also listed in the output of this command. This is the group address used for RP Discovery messages. This group is enabled by default as is used for RP Discovery. Finally, complete the task by pinging 227.4.4.4 from R1 and 227.1.1.1 from R4:

R1#**ping 227.4.4.4**

Type escape sequence to abort.

https://t.me/learningnets

Sending 1, 100-byte ICMP Echos to 227.4.4.4, timeout is 2 seconds:

Reply to request 0 from 10.0.0.14, 32 ms

R4#**ping 227.1.1.1**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 227.1.1.1, timeout is 2 seconds:

Reply to request 0 from 10.0.0.1, 48 ms

https://t.me/learningnets

Technet24

CCNP Lab 075: Multicast - PIM Auto RP Lab

Lab Objective:

The focus of this lab is to understand IP Multicast Auto RP implementation Cisco IOS routers. Additional technologies include the Internet Group Management Protocol (IGMP).

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure the hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

https://t.me/learningnets

Technet24

Enable EIGRP on all routers as illustrated in the topology. Verify your EIGRP configuration.

Task 3

Enable Internet Group Management Protocol version 2 on the LAN interfaces of routers R1 and R4. Next, enable Sparse-Dense Mode forwarding on the interfaces. Verify your solution using the appropriate commands.

Task 4

Enable Sparse-Dense Mode forwarding on all router WAN interfaces. Verify your configuration using the appropriate commands.

Task 5

Configure R1 so that its LAN interface is joined to Multicast group 227.1.1.1. Configure R4 so that its LAN interface is joined to Multicast group 227.4.4.4. Verify that R1 can ping R4s Multicast group and that R4 can ping R1s Multicast group.

Task 6

Configure Cisco Auto RP functionality on all routers. Use the following guidelines:

- R2 should be configured with a Loopback 0 interface of 2.2.2.2/32
- R2 should be configured to announce Loopback 0 as the candidate RP for all groups
- R3 should be configured with a Loopback 0 interface of 3.3.3.3/32
- R3 should be configured to advertise the RP information to all other routers
- R3 should use its Loopback 0 interface to send these advertisements
- R1 and R4 should be configured to listen to advertised RP Discovery messages

To complete this task, use the following commands on the routers. It will be up to you to determine which command(s) will need to be enabled on which router.

- The ip pim send-rp-discovery command
- The ip pim send-rp-announce command
- The ip pim accept-rp auto-rp command

Finally, complete this task by pinging from R1 to 227.4.4.4 and from R4 to 227.1.1.1.

Lab Validation:

Task 1

Please refer to previous tasks for basic VLAN and IP addressing configuration. These

https://t.me/learningnets

will not be included in this section for brevity and to avoid being redundant.

Task 2

Please refer to previous labs for basic EIGRP configuration. Following this, verify your EIGRP configuration using the **show ip eigrp neighbors** and **show ip route** commands. Following this configuration, your route tables should show the following route information:

R1#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/2681856] via 10.0.0.2, 00:00:12, Serial0/0
D 10.0.0.12 [90/21536000] via 10.0.0.2, 00:00:12, Serial0/0
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/21538560] via 10.0.0.2, 00:00:12, Serial0/0

R2#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.12 [90/21024000] via 10.0.0.10, 00:00:22, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/2172416] via 10.0.0.1, 00:00:17, Serial0/0
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/21026560] via 10.0.0.10, 00:00:22, Serial0/1

R3#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.0 [90/21024000] via 10.0.0.9, 00:00:25, Serial1/1
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/21026560] via 10.0.0.9, 00:00:20, Serial1/1
150.4.0.0/24 is subnetted, 1 subnets
D 150.4.4.0 [90/20514560] via 10.0.0.14, 00:00:31, Serial1/2

R4#**show ip route eigrp**
10.0.0.0/30 is subnetted, 3 subnets
D 10.0.0.8 [90/21024000] via 10.0.0.13, 00:00:34, Serial0/0
D 10.0.0.0 [90/21536000] via 10.0.0.13, 00:00:28, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/21538560] via 10.0.0.13, 00:00:23, Serial0/0

Task 3

The requirement for this task is straightforward. This task is completed as follows:

R1(config)#**ip multicast-routing**
R1(config)#**interface fastethernet 0/0**

https://t.me/learningnets

Technet24

R1(config-if)#**ip igmp version 2**
R1(config-if)#**ip pim sparse-dense-mode**
R1(config-if)#**exit**

R4(config)#**ip multicast-routing**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip igmp version 2**
R4(config-if)#**ip pim sparse-dense-mode**
R4(config-if)#**exit**

Next, verify your configuration using the **show ip igmp interface** command:

R1#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.1.1.1/24
IGMP is enabled on interface
Current IGMP host version is 2
Current IGMP router version is 2
IGMP query interval is 60 seconds
IGMP querier timeout is 120 seconds
IGMP max query response time is 10 seconds
Last member query count is 2
Last member query response interval is 1000 ms
Inbound IGMP access group is not set
IGMP activity: 1 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.1.1.4
IGMP querying router is 150.1.1.1 (this system)
Multicast groups joined by this system (number of users):
224.0.1.40(1)

Notice in the last line of the output that the interface is automatically joined to group 224.0.1.40. This group is for Cisco RP Discovery messages. The interface is automatically joined to this group because Dense mode assumes that all hosts want to receive Multicast traffic, unless they explicitly state that they do not. This group is enabled by default; it simply indicates that the interface is listening for packets that may be sent to this group address. You can verify the PIM operational mode using the **show ip pim interface** command:

R1#**show ip pim interface fastethernet 0/0 detail**
FastEthernet0/0 is up, line protocol is up

https://t.me/learningnets

Internet address is 150.1.1.1/24
Multicast switching: fast
Multicast packets in/out: 326/0
Multicast TTL threshold: 0
PIM: enabled
PIM version: 2, mode: sparse-dense
PIM DR: 150.1.1.4
PIM neighbor count: 0
PIM Hello/Query interval: 30 seconds
PIM Hello packets in/out: 19/21
PIM State-Refresh processing: enabled
PIM State-Refresh origination: disabled
PIM NBMA mode: disabled
PIM ATM multipoint signalling: disabled
PIM domain border: disabled
Multicast Tagswitching: disabled

Task 4

The requirements for this task are straightforward. This task is completed as follows:

R1(config)#**interface serial 0/0**
R1(config-if)#**ip pim sparse-dense-mode**
R1(config-if)#**exit**

R2(config)#**ip multicast-routing**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip pim sparse-dense-mode**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip pim sparse-dense-mode**
R2(config-if)#**exit**

R3(config)#**ip multicast-routing**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip pim sparse-dense-mode**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip pim sparse-dense-mode**
R3(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**ip pim sparse-dense-mode**

https://t.me/learningnets
Technet24

R4(config-if)#**exit**

Next, verify PIM Sparse-Dense Mode parameters using the **show ip pim** interface command:

R4#**show ip pim interface serial 0/0 detail**
Serial0/0 is up, line protocol is up
Internet address is 10.0.0.14/30
Multicast switching: fast
Multicast packets in/out: 332/0
Multicast TTL threshold: 0
PIM: enabled
PIM version: 2, mode: sparse-dense
PIM DR: 0.0.0.0
PIM neighbor count: 1
PIM Hello/Query interval: 30 seconds
PIM Hello packets in/out: 2/3
PIM State-Refresh processing: enabled
PIM State-Refresh origination: disabled
PIM NBMA mode: disabled
PIM ATM multipoint signalling: disabled
PIM domain border: disabled
Multicast Tagswitching: disabled

Task 5

To configure a router interface to join a Multicast group, a technique commonly used to test the Multicast configuration, use the **ip igmp join-group <group>** interface command:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip igmp join-group 227.1.1.1**
R1(config-if)#**exit**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip igmp join-group 227.4.4.4**
R4(config-if)#**exit**

Next, verify your configuration using the **show ip igmp interface** command:

R1#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.1.1.1/24
IGMP is enabled on interface

https://t.me/learningnets

Current IGMP host version is 2
Current IGMP router version is 2
IGMP query interval is 60 seconds
IGMP querier timeout is 120 seconds
IGMP max query response time is 10 seconds
Last member query count is 2
Last member query response interval is 1000 ms
Inbound IGMP access group is not set
IGMP activity: 3 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.4.4.4
IGMP querying router is 150.1.1.1 (this system)
Multicast groups joined by this system (number of users):
224.0.1.40(1) 227.1.1.1(1)

R4#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.4.4.4/24
IGMP is enabled on interface
Current IGMP host version is 2
Current IGMP router version is 2
IGMP query interval is 60 seconds
IGMP querier timeout is 120 seconds
IGMP max query response time is 10 seconds
Last member query count is 2
Last member query response interval is 1000 ms
Inbound IGMP access group is not set
IGMP activity: 3 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.4.4.4 (this system)
IGMP querying router is 150.1.1.1
Multicast groups joined by this system (number of users):
224.0.1.40(1) 227.4.4.4(1)

Task 6

This task requires the configuration of auto RP. As stated in the TSHOOT guide, in Cisco IOS Software, there are three ways in which the location of the RP can be

https://t.me/learningnets

Technet24

specified:

- By statically configuring the router or switch with the RP IP address
- Automatically, using the Cisco Auto-RP mechanism
- Automatically, using the Bootstrap Router mechanism with PIMv2

While the concept of Auto-RP seems very complex, the operation of auto RP is actually fairly straightforward. Each router that you configure to be an RP begins generating Cisco-RP-Announce messages addressed to the 224.0.1.39 group address. These announce messages are flooded through the network in a dense-mode fashion, ensuring that each router receives a copy. Next, the mapping agent for the network listens for the various announce messages and makes a decision as to which router is the RP.

In the event that there are multiple RPs (for redundancy), the candidate RP with the highest IP address is chosen as the RP for the network. The mapping agent then advertises this decision to the network in a Cisco-RP-Discovery message addressed to the 224.0.1.40 group address. Like the announce message, the discovery message is propagated in a dense-mode fashion throughout the network. Once all routers in the network receive the RP, Multicast operates using sparse-mode. This is the reason we need to enable Sparse-Dense mode forwarding. To complete this task, use the **ip pim accept-rp auto-rp** command on R1 and R4. This command configures these routers to accept join and register messages only for RPs that are in the Auto-RP cache. These cache entries are created after the RP information is flooded:

R1(config)#**ip pim accept-rp auto-rp**

R4(config)#**ip pim accept-rp auto-rp**

Next, use the **ip pim send-rp-announce** command on the router you want to become the RP. In this lab, that would be R1. This command causes the router to send an Auto-RP announcement message to the well-known group CISCO-RP-ANNOUNCE (224.0.1.39). This message announces the router as a candidate RP for all or specified Multicast groups:

R2(config)#**interface loopback 0**
R2(config-if)#**ip address 2.2.2.2 255.255.255.255**
R2(config-if)#**ip pim sparse-dense-mode**
R2(config-if)#**exit**
R2(config)#**ip pim send-rp-announce loopback 0 scope 255**

NOTE: You MUST advertise the Loopback 0 interface via EIGRP. If you enabled EIGRP for all networks using the **network 0.0.0.0** command, no additional configuration is necessary. However, if you explicitly enabled EIGRP for specific

https://t.me/learningnets

subnets, you need to also advertise the configured Loopback 0 interface via EIGRP; otherwise, no other router can reach this address.

When using this command, the scope specifies the TTL of these announcements. For example, if you specified a scope of 1, the packet would be sent out with a TTL of 1.

Finally, use the **ip pim send-rp-discovery** command on the router you want to become the RP mapping agent. In this lab, that would be R3. When Auto-RP is used, the following sequence of events occur:

- The RP mapping agent (R3) listens on well-known group address CISCO-RP-ANNOUNCE (224.0.1.39), which candidate RPs (R2) send announcements to.
- The RP mapping agent (R3) sends RP-to-group mappings in an Auto-RP discovery message to the well-known group CISCO-RP-DISCOVERY (224.0.1.40). The TTL value (determined by the scope) limits how many hops the message can take.
- PIM designated routers (R1 and R4) listen to this group and use the RPs they learn about from the discovery message.

This task is completed on R3 as follows:

R3(config)#**interface loopback 0**
R3(config-if)#**ip address 3.3.3.3 255.255.255.255**
R3(config-if)#**ip pim sparse-dense-mode**
R3(config-if)#**exit**
R3(config)#**ip pim send-rp-discovery loopback 0 scope 255**

NOTE: You MUST advertise the Loopback 0 interface via EIGRP. If you enabled EIGRP for all networks using the **network 0.0.0.0** command, no additional configuration is necessary. However, if you explicitly enabled EIGRP for specific subnets, you need to also advertise the configured Loopback 0 interface via EIGRP; otherwise, no other router can reach this address.

Next, use the **show ip pim autorp** command to view auto RP received and sent packets:

R1#**show ip pim autorp**
AutoRP Information:
AutoRP is enabled.

PIM AutoRP Statistics: Sent/Received
RP Announce: 0/0, RP Discovery: 0/3

Notice that R1 has received RP-Discovery messages. It has not sent out any other RP

https://t.me/learningnets

Technet24

messages:

R2#**show ip pim autorp**
AutoRP Information:
AutoRP is enabled.

PIM AutoRP Statistics: Sent/Received
RP Announce: 24/0, RP Discovery: 0/3

Notice that R2 has sent out RP-Announce packets. It has also received RP-Discovery packets.

R3#**show ip pim autorp**
AutoRP Information:
AutoRP is enabled.

PIM AutoRP Statistics: Sent/Received
RP Announce: 0/6, RP Discovery: 9/0

Notice that R3 has received RP-Announce messages, and has sent out RP-Discovery messages:

R4#**show ip pim autorp**
AutoRP Information:
AutoRP is enabled.

PIM AutoRP Statistics: Sent/Received
RP Announce: 0/0, RP Discovery: 0/3

And finally, notice that R4 has only received RP-Discovery messages and sent out none:

Following this, verify RP-to-Group mappings using the **show ip pim rp** command:

R1#**show ip pim rp**
Group: 227.4.4.4, RP: 2.2.2.2, v2, v1, uptime 00:07:19, expires 00:02:40
Group: 227.1.1.1, RP: 2.2.2.2, v2, v1, uptime 00:07:19, expires 00:02:40

R2#**show ip pim rp**
Group: 227.4.4.4, RP: 2.2.2.2, v2, v1, next RP-reachable in 00:00:14
Group: 227.1.1.1, RP: 2.2.2.2, v2, v1, next RP-reachable in 00:00:14

R3#**show ip pim rp**
Group: 227.4.4.4, RP: 2.2.2.2, v2, v1, uptime 00:07:12, expires 00:02:43
Group: 227.1.1.1, RP: 2.2.2.2, v2, v1, uptime 00:07:12, expires 00:02:43

R4#**show ip pim rp**
Group: 227.4.4.4, RP: 2.2.2.2, v2, v1, uptime 00:07:07, expires 00:02:47
Group: 227.1.1.1, RP: 2.2.2.2, v2, v1, uptime 00:07:07, expires 00:02:47

Finally, complete this task by pinging from R1 to 227.4.4.4 and from R4 to 227.1.1.1

https://t.me/learningnets

R1#**ping 227.4.4.4**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 227.4.4.4, timeout is 2 seconds:

Reply to request 0 from 10.0.0.14, 32 ms

R4#**ping 227.1.1.1**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 227.1.1.1, timeout is 2 seconds:

Reply to request 0 from 10.0.0.1, 48 ms

https://t.me/learningnets

Technet24

CCNP Lab 076: Branch Office Connectivity Lab

Lab Objective:

The focus of this lab is to understand branch office connectivity implementation and configuration. Additional technologies include IP routing, FHRPs, and IPsec VPNs.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Configure IP routing as illustrated in the topology. Use AS 65500 for both BGP and EIGRP. Use OSPF process ID 1 for OSPF. Do NOT enable any dynamic routing protocols on the R3-R4 link. However, ensure that R1 and R2 know about this subnet.

https://t.me/learningnets

Technet24

Ensure that all routers can ping each other. Implement the necessary route redistribution so that all routers can ping each other. However, you are NOT allowed to redistribute anything into BGP. Verify the solution using the appropriate commands on all routers.

Task 3

Configure HSRP on the LAN segment between R1 and R4. Use a VIP of 150.1.1.254. Configure R1 with a priority of 105 and R4 with a priority of 100. Ensure that R4 becomes active gateway when R1s Serial 0/0 interface goes down. When R1s Serial0/0 interface comes up, R1 should wait 30 seconds before it assumes the role of the active gateway. Verify your HSRP configuration.

Task 4

Assume that the link between R1 and R2 is secure; however, the link between R3 and R4 is not. Management requests that you configure an IPsec tunnel so that when the R1-R2 link is down, traffic between the 150.1.1.0/24 and 150.2.2.0/24 subnets is encrypted and sent across the R3-R4 link. Do NOT configure a GRE Tunnel. Configure the IPsec solution as follows:

- Use Advanced Encryption Standard (AES) as the encryption algorithm
- Use a 256-bit AES encryption key
- Use pre-shared key authentication with a shared key of CCNP2011
- Use Diffie-Hellman group 5

Test your solution and verify that R1 and R2 can ping each other from their LAN interfaces.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

The requirements of this task are straightforward. OSPF, EIGRP and BGP configuration as well as redistribution have been illustrated in previous labs. This task is completed as follows:

R1(config)#**router eigrp 65500**
R1(config-router)#**no auto-summary**
R1(config-router)#**network 150.1.1.1 0.0.0.0**
R1(config-router)#**redistribute connected**

https://t.me/learningnets

R1(config-router)#**redistribute bgp 65500**
R1(config-router)#**default-metric 1544 2000 255 1 1500**
R1(config-router)#**exit**
R1(config)#**router bgp 65500**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**neighbor 10.0.0.2 remote-as 65500**
R1(config-router)#**network 150.1.1.0 mask 255.255.255.0**
R1(config-router)#**bgp redistribute-internal**
R1(config-router)#**exit**

R2(config)#**router ospf 1**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**network 150.2.2.2 0.0.0.0 area 0**
R2(config-router)#**redistribute connected subnets**
R2(config-router)#**redistribute bgp 65500 subnets**
R2(config-router)#**exit**
R2(config)#**router bgp 65500**
R2(config-router)#**bgp router-id 2.2.2.2**
R2(config-router)#**neighbor 10.0.0.1 remote-as 65500**
R2(config-router)#**bgp redistribute-internal**
R2(config-router)#**network 150.2.2.0 mask 255.255.255.0**
R2(config-router)#**exit**

R3(config)#**router ospf 1**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**network 150.2.2.3 0.0.0.0 area 0**
R3(config-router)#**redistribute connected subnets**
R3(config-router)#**exit**

R4(config)#**router eigrp 65500**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 150.1.1.4 0.0.0.0**
R4(config-router)#**redistribute connected**
R4(config-router)#**exit**

Following this, verify IP routing using the **show ip route** command on all routers:

R1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2

https://t.me/learningnets
Technet24

i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 2 subnets
D EX 10.0.0.12 [170/2172416] via 150.1.1.4, 00:01:28, FastEthernet0/0
C 10.0.0.0 is directly connected, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
B 150.2.2.0 [200/0] via 10.0.0.2, 00:04:33

R2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 2 subnets
O E2 10.0.0.12 [110/20] via 150.2.2.3, 00:02:41, FastEthernet0/0
C 10.0.0.0 is directly connected, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
B 150.1.1.0 [200/0] via 10.0.0.1, 00:04:36
150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0

R3#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

https://t.me/learningnets

10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.12 is directly connected, Serial1/2
O E2 10.0.0.0 [110/20] via 150.2.2.2, 00:02:43, FastEthernet0/0
150.1.0.0/24 is subnetted, 1 subnets
O E2 150.1.1.0 [110/1] via 150.2.2.2, 00:02:43, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.12 is directly connected, Serial0/0
D EX 10.0.0.0 [170/2172416] via 150.1.1.1, 00:01:38, FastEthernet0/0
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
D EX 150.2.2.0 [170/2172416] via 150.1.1.1, 00:01:38, FastEthernet0/0

Finally, ping from all routers to every other router to verify your solution. For brevity, the solution will show pings from R4 to every other router in the network:

R4#**ping 150.1.1.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms

R4#**ping 10.0.0.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.0.0.2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/3/4 ms

R4#**ping 150.2.2.3**

https://t.me/learningnets

Technet24

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.3, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/3/4 ms

Task 3

The core requirements for this task are straightforward. To ensure that R1 re-assumes its role as the primary gateway after its Serial0/0 link comes up, you can specify this parameter in the Enhanced Object Tracking configuration or using HSRP commands. This lab solution shows the delay value being specified using HSRP commands:

R1(config)#**track 1 interface serial 0/0 line-protocol**
R1(config-track)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**standby 1 ip 150.1.1.254**
R1(config-if)#**standby 1 priority 105**
R1(config-if)#**standby 1 preempt**
R1(config-if)#**standby 1 preempt delay minimum 30**
R1(config-if)#**standby 1 track 1 decrement 10**
R1(config-if)#**exit**

If you wanted to use EOT, you could also complete this section as follows:

R1(config)#**track 1 interface serial 0/0 line-protocol**
R1(config-track)#**delay up 30**
R1(config-track)#**exit**

Complete this task on R4 as follows:

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**standby 1 ip 150.1.1.254**
R4(config-if)#**standby 1 preempt**
R4(config-if)#**exit**

Verify your HSRP configuration using the **show standby** commands:

R1#**show standby fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Active
2 state changes, last state change 00:03:08
Virtual IP address is 150.1.1.254
Active virtual MAC address is 0000.0c07.ac01
Local virtual MAC address is 0000.0c07.ac01 (v1 default)
Hello time 3 sec, hold time 10 sec

https://t.me/learningnets

Next hello sent in 0.820 secs
Preemption enabled, delay min 30 secs
Active router is local
Standby router is 150.1.1.4, priority 100 (expires in 9.916 sec)
Priority 105 (configured 105)
Track object 1 state Up decrement 10
IP redundancy name is "hsrp-Fa0/0-1" (default)

R4#**show standby fastethernet 0/0**
FastEthernet0/0 - Group 1
State is Standby
1 state change, last state change 00:00:34
Virtual IP address is 150.1.1.254
Active virtual MAC address is 0000.0c07.ac01
Local virtual MAC address is 0000.0c07.ac01 (v1 default)
Hello time 3 sec, hold time 10 sec
Next hello sent in 1.484 secs
Preemption enabled
Active router is 150.1.1.1, priority 105 (expires in 9.384 sec)
Standby router is local
Priority 100 (default 100)
IP redundancy name is "hsrp-Fa0/0-1" (default)

Task 4

The requirements for this task are two-fold. First, you need to configure a site-to-site IPsec VPN between R3 and R4. Second, you need to ensure that traffic is sent across this tunnel when the WAN link between R1 and R2 is down. Additionally, because the subnets are advertised by internal BGP, they will have an administrative distance of 200. To ensure that this path is only used as a backup, you need to modify the default administrative distance values on R1 and R2 as well. This task is completed as follows:

R1(config)#**router eigrp 65500**
R1(config-router)#**distance eigrp 90 210**
R1(config-router)#**exit**

R2(config)#**router ospf 1**
R2(config-router)#**distance ospf external 210**
R2(config-router)#**exit**

R3(config)#**ip route 150.1.1.0 255.255.255.0 10.0.0.14 254**
R3(config)#**router ospf 1**
R3(config-router)#**redistribute static subnets**

https://t.me/learningnets
Technet24

R3(config-router)#**exit**
R3(config)#**ip access-list extended SECURE-TRAFFIC**
R3(config-ext-nacl)#**permit ip 150.2.2.0 0.0.0.255 150.1.1.0 0.0.0.255**
R3(config-ext-nacl)#**exit**
R3(config)#**crypto isakmp policy 1**
R3(config-isakmp)#**encryption aes 256**
R3(config-isakmp)#**authentication pre-share**
R3(config-isakmp)#**group 5**
R3(config-isakmp)#**exit**
R3(config)#**crypto isakmp key CCNP2011 address 10.0.0.14**
R3(config)#**crypto ipsec transform-set AES-SECURE esp-aes 256**
R3(cfg-crypto-trans)#**exit**
R3(config)#**crypto map BACKUP-SOLUTION 1 ipsec-isakmp**
% NOTE: This new crypto map will remain disabled until a peer
and a valid access list have been configured.
R3(config-crypto-map)#**set peer 10.0.0.14**
R3(config-crypto-map)#**set transform-set AES-SECURE**
R3(config-crypto-map)#**match address SECURE-TRAFFIC**
R3(config-crypto-map)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**crypto map BACKUP-SOLUTION**
R3(config-if)#**exit**

R4(config)#**ip route 150.2.2.0 255.255.255.0 10.0.0.13 254**
R4(config)#**router eigrp 65500**
R4(config-router)#**redistribute static**
R4(config-router)#**exit**
R4(config)#**ip access-list extended SECURE-TRAFFIC**
R4(config-ext-nacl)#**permit ip 150.1.1.0 0.0.0.255 150.2.2.0 0.0.0.255**
R4(config-ext-nacl)#**exit**
R4(config)#**crypto isakmp policy 1**
R4(config-isakmp)#**encryption aes 256**
R4(config-isakmp)#**authentication pre-share**
R4(config-isakmp)#**group 5**
R4(config-isakmp)#**exit**
R4(config)#**crypto isakmp key CCNP2011 address 10.0.0.13**
R4(config)#**crypto ipsec transform-set AES-SECURE esp-aes 256**
R4(cfg-crypto-trans)#**exit**
R4(config)#**crypto map BACKUP-SOLUTION 1 ipsec-isakmp**

https://t.me/learningnets

% NOTE: This new crypto map will remain disabled until a peer
and a valid access list have been configured.
R4(config-crypto-map)#**set peer 10.0.0.13**
R4(config-crypto-map)#**set transform-set AES-SECURE**
R4(config-crypto-map)#**match address SECURE-TRAFFIC**
R4(config-crypto-map)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**crypto map BACKUP-SOLUTION**
R4(config-if)#**exit**

Next, verify your configuration using the **show crypto** commands:

R4#**show crypto isakmp policy**

Global IKE policy
Protection suite of priority 1
encryption algorithm: AES - Advanced Encryption Standard (256 bit keys).
hash algorithm: Secure Hash Standard
authentication method: Pre-Shared Key
Diffie-Hellman group: #5 (1536 bit)
lifetime: 86400 seconds, no volume limit
Default protection suite
encryption algorithm: DES - Data Encryption Standard (56 bit keys).
hash algorithm: Secure Hash Standard
authentication method: Rivest-Shamir-Adleman Signature
Diffie-Hellman group: #1 (768 bit)
lifetime: 86400 seconds, no volume limit

R4#**show crypto map**
Crypto Map "BACKUP-SOLUTION" 1 ipsec-isakmp
Peer = 10.0.0.13
Extended IP access list SECURE-TRAFFIC
access-list SECURE-TRAFFIC permit ip 150.1.1.0 0.0.0.255 150.2.2.0 0.0.0.255
Current peer: 10.0.0.13
Security association lifetime: 4608000 kilobytes/3600 seconds
PFS (Y/N): N
Transform sets={
AES-SECURE,
}
Interfaces using crypto map BACKUP-SOLUTION:
Serial0/0

https://t.me/learningnets
Technet24

Finally, test your solution by disabling the R1-R2 link and checking the routing on R1 and R2 for the 150.2.2.0/24 and 150.1.1.0/24 subnets. Prior to this, the routing for the subnets is as follows:

R1#**show ip route 150.2.2.0 255.255.255.0**
Routing entry for 150.2.2.0/24
Known via "bgp 65500", distance 200, metric 0, type internal
Redistributing via eigrp 65500
Advertised by eigrp 65500
Last update from 10.0.0.2 00:02:10 ago
Routing Descriptor Blocks:
* 10.0.0.2, from 10.0.0.2, 00:02:10 ago
Route metric is 0, traffic share count is 1
AS Hops 0

R2#**show ip route 150.1.1.0 255.255.255.0**
Routing entry for 150.1.1.0/24
Known via "bgp 65500", distance 200, metric 0, type internal
Redistributing via ospf 1
Advertised by ospf 1 subnets
Last update from 10.0.0.1 00:01:30 ago
Routing Descriptor Blocks:
* 10.0.0.1, from 10.0.0.1, 00:01:30 ago
Route metric is 0, traffic share count is 1
AS Hops 0

R3#show ip route 150.1.1.0 255.255.255.0
Routing entry for 150.1.1.0/24
Known via "ospf 1", distance 110, metric 1, type extern 2, forward metric 1
Last update from 150.2.2.2 on FastEthernet0/0, 00:01:45 ago
Routing Descriptor Blocks:
* 150.2.2.2, from 2.2.2.2, 00:01:45 ago, via FastEthernet0/0
Route metric is 1, traffic share count is 1

R4#**show ip route 150.2.2.0 255.255.255.0**
Routing entry for 150.2.2.0/24
Known via "eigrp 65500", distance 170, metric 2172416, type external
Redistributing via eigrp 65500
Last update from 150.1.1.1 on FastEthernet0/0, 00:03:48 ago
Routing Descriptor Blocks:
* 150.1.1.1, from 150.1.1.1, 00:03:48 ago, via FastEthernet0/0

https://t.me/learningnets

Route metric is 2172416, traffic share count is 1
Total delay is 20100 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1
Next, shut down the WAN link that connects routers R1 and R2:

R1(config)#**interface serial 0/0**
R1(config-if)#**shutdown**

After this, verify that routing information is correct:

R1#**show ip route 150.2.2.0 255.255.255.0**
Routing entry for 150.2.2.0/24
Known via "eigrp 65500", distance 170, metric 2172416, type external
Redistributing via eigrp 65500
Last update from 150.1.1.4 on FastEthernet0/0, 00:00:09 ago
Routing Descriptor Blocks:
*** 150.1.1.4, from 150.1.1.4, 00:00:09 ago, via FastEthernet0/0**
Route metric is 2172416, traffic share count is 1
Total delay is 20100 microseconds, minimum bandwidth is 1544 Kbit
Reliability 255/255, minimum MTU 1500 bytes
Loading 1/255, Hops 1

R2#**show ip route 150.1.1.0 255.255.255.0**
Routing entry for 150.1.1.0/24
Known via "ospf 1", distance 110, metric 20, type extern 2, forward metric 1
Last update from 150.2.2.3 on FastEthernet0/0, 00:00:56 ago
Routing Descriptor Blocks:
* 150.2.2.3, from 3.3.3.3, 00:00:56 ago, via FastEthernet0/0
Route metric is 20, traffic share count is 1

Next, ping between R1 and R2:

R1#**ping 150.2.2.2 repeat 20 size 1500**

Type escape sequence to abort.
Sending 20, 1500-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!!!!!!!!!!!!!!!!
Success rate is 100 percent (20/20), round-trip min/avg/max = 220/222/224 ms

R2#**ping 150.1.1.1 repeat 20 size 1500**

Type escape sequence to abort.
Sending 20, 1500-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
!!!!!!!!!!!!!!!!!!!!

https://t.me/learningnets

Technet24

Success rate is 100 percent (20/20), round-trip min/avg/max = 220/222/224 ms

Finally, view encryption status and statistics using the **show crypto** commands:

R3#**show crypto ipsec sa**

interface: Serial1/2
Crypto map tag: BACKUP-SOLUTION, local addr 10.0.0.13

protected vrf: (none)
local ident (addr/mask/prot/port): (150.2.2.0/255.255.255.0/0/0)
remote ident (addr/mask/prot/port): (150.1.1.0/255.255.255.0/0/0)
current_peer 10.0.0.14 port 500
PERMIT, flags={origin_is_acl,}
#pkts encaps: 80, #pkts encrypt: 80, #pkts digest: 80
#pkts decaps: 80, #pkts decrypt: 80, #pkts verify: 80
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts compr. failed: 0
#pkts not decompressed: 0, #pkts decompress failed: 0
#send errors 0, #recv errors 0

local crypto endpt.: 10.0.0.13, remote crypto endpt.: 10.0.0.14
path mtu 1500, ip mtu 1500, ip mtu idb Serial1/2
current outbound spi: 0x8E8C5624(2391561764)

inbound esp sas:
spi: 0x127922C2(309928642)
transform: esp-256-aes ,
in use settings ={Tunnel, }
conn id: 2001, flow_id: SW:1, crypto map: BACKUP-SOLUTION
sa timing: remaining key lifetime (k/sec): (4607493/3273)
IV size: 16 bytes
replay detection support: N
Status: ACTIVE

inbound ah sas:

inbound pcp sas:

outbound esp sas:
spi: 0x8E8C5624(2391561764)
transform: esp-256-aes ,
in use settings ={Tunnel, }
conn id: 2002, flow_id: SW:2, crypto map: BACKUP-SOLUTION
sa timing: remaining key lifetime (k/sec): (4607495/3265)

https://t.me/learningnets

IV size: 16 bytes
replay detection support: N
Status: ACTIVE

outbound ah sas:

outbound pcp sas:

R4#**show crypto ipsec sa**

interface: Serial0/0
Crypto map tag: BACKUP-SOLUTION, local addr 10.0.0.14

protected vrf: (none)
local ident (addr/mask/prot/port): (150.1.1.0/255.255.255.0/0/0)
remote ident (addr/mask/prot/port): (150.2.2.0/255.255.255.0/0/0)
current_peer 10.0.0.13 port 500
PERMIT, flags={origin_is_acl,}
#pkts encaps: 80, #pkts encrypt: 80, #pkts digest: 80
#pkts decaps: 80, #pkts decrypt: 80, #pkts verify: 80
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts compr. failed: 0
#pkts not decompressed: 0, #pkts decompress failed: 0
#send errors 0, #recv errors 0

local crypto endpt.: 10.0.0.14, remote crypto endpt.: 10.0.0.13
path mtu 1500, ip mtu 1500, ip mtu idb Serial0/0
current outbound spi: 0x127922C2(309928642)

inbound esp sas:
spi: 0x8E8C5624(2391561764)
transform: esp-256-aes ,
in use settings ={Tunnel, }
conn id: 2001, flow_id: SW:1, crypto map: BACKUP-SOLUTION
sa timing: remaining key lifetime (k/sec): (4482975/3270)
IV size: 16 bytes
replay detection support: N
Status: ACTIVE

inbound ah sas:

inbound pcp sas:

outbound esp sas:
spi: 0x127922C2(309928642)
transform: esp-256-aes ,

https://t.me/learningnets

Technet24

in use settings ={Tunnel, }
conn id: 2002, flow_id: SW:2, crypto map: BACKUP-SOLUTION
sa timing: remaining key lifetime (k/sec): (4482973/3269)
IV size: 16 bytes
replay detection support: N
Status: ACTIVE

outbound ah sas:

outbound pcp sas:

R3#**show crypto session detail**
Crypto session current status

Code: C - IKE Configuration mode, D - Dead Peer Detection
K - Keepalives, N - NAT-traversal, X - IKE Extended Authentication

Interface: Serial1/2
Session status: UP-ACTIVE
Peer: 10.0.0.14 port 500 fvrf: (none) ivrf: (none)
Phase1_id: 10.0.0.14
Desc: (none)
IKE SA: local 10.0.0.13/500 remote 10.0.0.14/500 Active
Capabilities:(none) connid:1 lifetime:23:53:37
IPSEC FLOW: permit ip 150.2.2.0/255.255.255.0 150.1.1.0/255.255.255.0
Active SAs: 2, origin: crypto map
Inbound: #pkts dec'ed 80 drop 0 life (KB/Sec) 4607493/3219
Outbound: #pkts enc'ed 80 drop 0 life (KB/Sec) 4607495/3219

R4#**show crypto session detail**
Crypto session current status

Code: C - IKE Configuration mode, D - Dead Peer Detection
K - Keepalives, N - NAT-traversal, X - IKE Extended Authentication

Interface: Serial0/0
Session status: UP-ACTIVE
Peer: 10.0.0.13 port 500 fvrf: (none) ivrf: (none)
Phase1_id: 10.0.0.13
Desc: (none)
IKE SA: local 10.0.0.14/500 remote 10.0.0.13/500 Active
Capabilities:(none) connid:1 lifetime:23:53:49
IPSEC FLOW: permit ip 150.1.1.0/255.255.255.0 150.2.2.0/255.255.255.0
Active SAs: 2, origin: crypto map

https://t.me/learningnets

Inbound: #pkts dec’ed 80 drop 0 life (KB/Sec) 4482975/3230
Outbound: #pkts enc’ed 80 drop 0 life (KB/Sec) 4482973/3230

https://t.me/learningnets

CCNP Lab 077: Branch Office Connectivity Lab

Lab Objective:

The focus of this lab is to understand branch office connectivity implementation and configuration. Additional technologies include IP routing, tunnels, and IPsec VPNs.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

https://t.me/learningnets

Technet24

R1 and R4 have two secondary addresses.

Task 2

Configure BGP on R2 and R3 as illustrated in the topology. Ensure that the R1-R2 and the R3-R4 WAN subnets are advertised. Verify your configuration using the appropriate commands.

Task 3

Configure a GRE tunnel between R1 and R4. Enable OSPF and advertise the LAN subnets that are connected to these routers. Verify your configuration using the appropriate commands.

Task 4

Management is concerned about security over the GRE tunnel. They have requested that the GRE tunnel itself be encrypted using IPsec to allow for secure connectivity between the R1 and R4 subnets across this tunnel. Configure the IPsec solution as follows:

- Use Triple Digital Encryption Standard (3DES) as the encryption algorithm
- Use pre-shared key authentication with a shared key of CCNP2011
- Use Diffie-Hellman group 2

Due to the relatively complex nature of this task, the following section includes a bank of commands that you can use to complete this task. Your task is to figure out which of these commands to apply where. The bank of available commands is as follows:

- The crypto isakmp policy command
- The crypto isakmp key command
- The crypto ipsec transform-set command and mode transport subcommand
- The crypto ipsec profile command and set transform-set subcommand
- The tunnel mode ipsec ipv4 command
- The tunnel protection ipsec profile command

Test your solution and verify that R1 and R2 can ping each other from their LAN interfaces.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

https://t.me/learningnets

Task 2

The requirements of this task are straightforward. Because basic BGP configuration has been illustrated in detail in previous labs, this configuration is omitted for brevity. Following the configuration, your routing tables on R2 and R3 should show the following IP route entries:

R2#**show ip route bgp**
150.2.0.0/16 is variably subnetted, 3 subnets, 2 masks
B 150.2.4.0/28 [200/0] via 150.2.2.3, 00:00:14

R3#**show ip route bgp**
150.2.0.0/16 is variably subnetted, 3 subnets, 2 masks
B 150.2.1.0/28 [200/0] via 150.2.2.2, 00:00:26

Task 3

In order to complete this task, several actions are required. First, to allow for the configuration of a GRE tunnel between R1 and R4, you need to configure static routes for these routers' links to R2 and R3, i.e. their WAN links. Next, configure the GRE tunnel and enable OSPF for all the connected subnets. This task is completed as follows:

R1(config)#**ip route 150.2.4.4 255.255.255.255 serial 0/0**
R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**exit**
R1(config)#**interface tunnel 0**
R1(config-if)#**ip address 192.168.1.1 255.255.255.0**
R1(config-if)#**tunnel source serial 0/0**
R1(config-if)#**tunnel destination 150.2.4.4**
R1(config-if)#**ip ospf 1 area 0**
R1(config-if)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip ospf 1 area 1**
R1(config-if)#**exit**

R4(config)#**ip route 150.2.1.1 255.255.255.255 serial 0/0**
R4(config)#**router ospf 4**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**exit**
R4(config)#**interface tunnel 0**
R4(config-if)#**ip address 192.168.1.4 255.255.255.0**

https://t.me/learningnets
Technet24

R4(config-if)#**tunnel source serial 0/0**
R4(config-if)#**tunnel destination 150.2.1.1**
R4(config-if)#**ip ospf 4 area 0**
R4(config-if)#**exit**
R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip ospf 4 area 4**
R4(config-if)#**exit**

Next, verify your configuration by checking OSPF adjacency states. This also confirms whether the GRE tunnel between R1 and R4 is up and operational as well:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:35 192.168.1.4 Tunnel0

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - 00:00:32 192.168.1.1 Tunnel0

Finally, verify that the LAN subnets are advertised as configured:

R1#**show ip route ospf**
10.0.0.0/24 is subnetted, 6 subnets
O IA 10.4.2.0 [110/11112] via 192.168.1.4, 00:03:40, Tunnel0
O IA 10.4.3.0 [110/11112] via 192.168.1.4, 00:03:40, Tunnel0
O IA 10.4.1.0 [110/11112] via 192.168.1.4, 00:03:40, Tunnel0

R4#**show ip route ospf**
10.0.0.0/24 is subnetted, 6 subnets
O IA 10.1.3.0 [110/11112] via 192.168.1.1, 00:03:52, Tunnel0
O IA 10.1.2.0 [110/11112] via 192.168.1.1, 00:03:52, Tunnel0
O IA 10.1.1.0 [110/11112] via 192.168.1.1, 00:03:52, Tunnel0

Additionally, ping between the LAN subnets to confirm LAN-to-LAN reachability:

R1#**ping 10.4.1.4 source 10.1.1.1 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 10.4.1.4, timeout is 2 seconds:
Packet sent with a source address of 10.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 208/212/216 ms

Task 4

The requirements of this task are a little complex; however, you have the bank of

https://t.me/learningnets

commands to use to complete this task. Using this bank, this task is completed as follows:

```
R1(config)#crypto isakmp policy 1
R1(config-isakmp)#encryption 3des
R1(config-isakmp)#authentication pre-share
R1(config-isakmp)#group 2
R1(config-isakmp)#exit
R1(config)#crypto isakmp key CCNP2011 address 150.2.4.4
R1(config)#crypto ipsec transform-set TRIPLE-DES esp-3des
R1(cfg-crypto-trans)#mode transport
R1(cfg-crypto-trans)#exit
R1(config)#crypto ipsec profile ENCRYPT-GRE
R1(ipsec-profile)#set transform-set TRIPLE-DES
R1(ipsec-profile)#exit
R1(config)#interface tunnel 0
R1(config-if)#tunnel mode ipsec ipv4
R1(config-if)#tunnel protection ipsec profile ENCRYPT-GRE
R1(config-if)#exit
```

```
R4(config)#crypto isakmp policy 1
R4(config-isakmp)#encryption 3des
R4(config-isakmp)#authentication pre-share
R4(config-isakmp)#group 2
R4(config-isakmp)#exit
R4(config)#crypto isakmp key CCNP2011 address 150.2.1.1
R4(config)#crypto ipsec transform-set TRIPLE-DES esp-3des
R4(cfg-crypto-trans)#mode transport
R4(cfg-crypto-trans)#exit
R4(config)#crypto ipsec profile ENCRYPT-GRE
R4(ipsec-profile)#set transform-set TRIPLE-DES
R4(ipsec-profile)#exit
R4(config)#interface tunnel 0
R4(config-if)#tunnel mode ipsec ipv4
R4(config-if)#tunnel protection ipsec profile ENCRYPT-GRE
R4(config-if)#exit
```

Following this, verify your configuration using the show crypto commands:

```
R1#show crypto ipsec profile
IPSEC profile ENCRYPT-GRE
```

https://t.me/learningnets

Technet24

Security association lifetime: 4608000 kilobytes/3600 seconds
PFS (Y/N): N
Transform sets={
TRIPLE-DES,
}

R1#**show crypto isakmp policy**

Global IKE policy
Protection suite of priority 1
encryption algorithm: Three key triple DES
hash algorithm: Secure Hash Standard
authentication method: Pre-Shared Key
Diffie-Hellman group: #2 (1024 bit)
lifetime: 86400 seconds, no volume limit
Default protection suite
encryption algorithm: DES - Data Encryption Standard (56 bit keys).
hash algorithm: Secure Hash Standard
authentication method: Rivest-Shamir-Adleman Signature
Diffie-Hellman group: #1 (768 bit)
lifetime: 86400 seconds, no volume limit

R1#**show crypto session detail**
Crypto session current status

Code: C - IKE Configuration mode, D - Dead Peer Detection
K - Keepalives, N - NAT-traversal, X - IKE Extended Authentication

Interface: Tunnel0
Session status: UP-ACTIVE
Peer: 150.2.4.4 port 500 fvrf: (none) ivrf: (none)
Phase1_id: 150.2.4.4
Desc: (none)
IKE SA: local 150.2.1.1/500 remote 150.2.4.4/500 Active
Capabilities:(none) connid:1 lifetime:23:55:37
IPSEC FLOW: permit ip 0.0.0.0/0.0.0.0 0.0.0.0/0.0.0.0
Active SAs: 2, origin: crypto map
Inbound: #pkts dec'ed 37 drop 0 life (KB/Sec) 4536717/3338
Outbound: #pkts enc'ed 37 drop 0 life (KB/Sec) 4536717/3338

Next, verify that the Tunnel interface is up following the modified configuration parameters:

R1#**show interfaces tunnel 0**

https://t.me/learningnets

Tunnel0 is up, line protocol is up
Hardware is Tunnel
Internet address is 192.168.1.1/24
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 150.2.1.1 (Serial0/0), destination 150.2.4.4
Tunnel protocol/transport IPSEC/IP
Tunnel TTL 255
Fast tunneling enabled
Tunnel transmit bandwidth 8000 (kbps)
Tunnel receive bandwidth 8000 (kbps)
Tunnel protection via IPSec (profile "ENCRYPT-GRE")
Last input 00:19:17, output 00:19:18, output hang never
Last clearing of "show interface" counters never
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: fifo
Output queue: 0/0 (size/max)
5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec
174 packets input, 31060 bytes, 0 no buffer
Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
188 packets output, 32492 bytes, 0 underruns
0 output errors, 0 collisions, 0 interface resets
0 unknown protocol drops
0 output buffer failures, 0 output buffers swapped out

Following that, verify your OSPF neighbor adjacencies and dynamic routing information:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:31 192.168.1.4 Tunnel0

R1#**show ip route ospf**
10.0.0.0/24 is subnetted, 6 subnets
O IA 10.4.2.0 [110/11112] via 192.168.1.4, 00:07:07, Tunnel0
O IA 10.4.3.0 [110/11112] via 192.168.1.4, 00:07:07, Tunnel0

https://t.me/learningnets
Technet24

O IA 10.4.1.0 [110/11112] via 192.168.1.4, 00:07:07, Tunnel0

Next, ping between router R1 and router R4s LAN subnets using an extended ping:

R1#**ping 10.4.1.4 source 10.1.1.1 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 10.4.1.4, timeout is 2 seconds:
Packet sent with a source address of 10.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 244/246/248 ms

Finally, verify encryption statistics (and configuration) on the router(s):

R1#**show crypto ipsec sa**

interface: Tunnel0
Crypto map tag: Tunnel0-head-0, local addr 150.2.1.1

protected vrf: (none)
local ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
remote ident (addr/mask/prot/port): (0.0.0.0/0.0.0.0/0/0)
current_peer 150.2.4.4 port 500
PERMIT, flags={origin_is_acl,}
#pkts encaps: 122, #pkts encrypt: 122, #pkts digest: 122
#pkts decaps: 102, #pkts decrypt: 102, #pkts verify: 102
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts compr. failed: 0
#pkts not decompressed: 0, #pkts decompress failed: 0
#send errors 0, #recv errors 0

local crypto endpt.: 150.2.1.1, remote crypto endpt.: 150.2.4.4
path mtu 1500, ip mtu 1500, ip mtu idb Serial0/0
current outbound spi: 0xD1D1D721(3520190241)

inbound esp sas:
spi: 0x4CE1DAD9(1289870041)
transform: esp-3des ,
in use settings ={Tunnel, }
conn id: 2001, flow_id: SW:1, crypto map: Tunnel0-head-0
sa timing: remaining key lifetime (k/sec): (4536696/2881)
IV size: 8 bytes
replay detection support: N
Status: ACTIVE

inbound ah sas:

https://t.me/learningnets

inbound pcp sas:

outbound esp sas:
spi: 0xD1D1D721(3520190241)
transform: esp-3des ,
in use settings ={Tunnel, }
conn id: 2002, flow_id: SW:2, crypto map: Tunnel0-head-0
sa timing: remaining key lifetime (k/sec): (4536680/2879)
IV size: 8 bytes
replay detection support: N
Status: ACTIVE

outbound ah sas:

outbound pcp sas:

Finally, you can use the **show crypto isakmp sa [detail]** command to verify SA status:

R1#**show crypto isakmp sa detail**
Codes: C - IKE configuration mode, D - Dead Peer Detection
K - Keepalives, N - NAT-traversal
X - IKE Extended Authentication
psk - Preshared key, rsig - RSA signature
renc - RSA encryption

C-id Local Remote I-VRF Status Encr Hash Auth DH Lifetime Cap.
1 150.2.1.1 150.2.4.4 ACTIVE 3des sha psk 2 23:27:11
Connection-id:Engine-id = 1:1(software)

This solution is commonly used in branch office solutions where you need to enable dynamic IP routing protocols over a GRE tunnel across the Internet. If you were to debug IP traffic traversing either R2 or R3, for example, while traffic was traversing the LAN subnets of R1 and R4, you would see ESP packets going back and forth. In other words, the GRE packets are encapsulation using IPsec in a manner that would be similar to encapsulating and transporting voice packets using IP, i.e. VoIP. Alternatively, you could also configure an ACL and enable logging and view the matches against the ACL as illustrated below on R3:

R3(config)#**access-list 100 permit ip any any log-input**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip access-group 100 out**
R3(config-if)#**ip access-group 100 in**
*Jun 15 20:19:51.427: %SEC-6-IPACCESSLOGNP: list 100 permitted 50 150.2.4.4 -> 150.2.1.1, 1 packet

https://t.me/learningnets

Technet24

*Jun 15 20:21:32.351: %SEC-6-IPACCESSLOGNP: list 100 permitted 50 150.2.1.1 -> 150.2.4.4, 1 packet

If you were to send multiple pings or transfer data between the LAN subnets connected to R1 and R4, you would see multiple packets being sent instead of just the single packet:

*Jun 15 20:25:37.139: %SEC-6-IPACCESSLOGNP: list 100 permitted 50 150.2.4.4 -> 150.2.1.1, 135 packets
*Jun 15 20:26:37.139: %SEC-6-IPACCESSLOGNP: list 100 permitted 50 150.2.1.1 -> 150.2.4.4, 138 packets

In the output above, IP protocol 50 is being permitted between R1 and R4. IP protocol number 50 is Encapsulating Security Payload (ESP). In both transport and tunnel mode, IPsec adds a new header to all the IP packets to provide the required information for securing the data within the original IP datagram. This header may either be an Encapsulating Security Payload (ESP) or Authentication Header (AH) header.

- ESP is an IP-based protocol that uses IP port 50 for communication between IPsec peers. ESP is used to provide confidentiality, integrity, and authenticity of the data, i.e. secure data via encryption and authentication. Additionally, ESP also provides anti-replay protection services. ESP does not provide any kind of protection for the outer IP header

- AH, is an IP-based protocol that uses IP port 51 for communication between IPsec peers. AH is used to protect the integrity and authenticity of data, and also offers anti-replay protection; however, AH does not provide confidentiality protection. In other words, AH does not provide encryption like ESP. AH does provide protection to the IP header; however, it should be noted that not all fields in the IP header, e.g. TTL, are protected

https://t.me/learningnets

CCNP Lab 078: PPP over Ethernet (PPPoE) Lab

Lab Objective:

The focus of this lab is to understand PPP over Ethernet (PPPoE) implementation and configuration. Additional technologies tested include PAP authentication and security.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology. Configure an IP address of 150.1.1.1/24 on the LAN interface of R1. Do NOT configure an address on the LAN interface of R4.

Task 2

Configure BGP between R1 and R2 as illustrated in the topology. Advertise the 150.2.2.0/24 subnet via BGP and verify that R1 can reach this subnet. Advertise the

https://t.me/learningnets

150.1.1.0/24 subnet connected to R1 via BGP and verify that R2 can reach this subnet.

Task 3

Assume that router R1 is an ISP router. This router will be a 'server' for client router R4. This router should have the following PPPoE configuration applied to it:

NOTE: This task is provided to you because these configurations are beyond the scope of the current CCNP curriculum. Simple copy and paste this configuration or manually type it in to complete the task. There are no additional configurations required to complete this task.

username ROUTER4 password CCNP2011

!

bba-group pppoe global

virtual-template 1

!

interface fastethernet0/0

pppoe enable group global

!

interface virtual-template1

mtu 1492

ip unnumbered fastethernet0/0

peer default ip address pool CLIENT-POOL

ppp authentication pap

!

ip local pool CLIENT-POOL 150.1.1.100 150.1.1.254

Task 4

Given the configuration above on R1 (ISP Router), implement PPPoE on R4. Next, verify your configuration using the appropriate commands. Test your solution by ensuring that R4 is able to ping the LAN subnet of R2 and vice-versa.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

https://t.me/learningnets

Technet24

Task 2

Please refer to previous labs for basic BGP configuration. Next, verify your BGP configuration using the **show ip bgp summary** and **show ip route** commands. Following this configuration, your routing tables on R1 and R2 should show the following route information:

R1#**show ip route bgp**
150.2.0.0/16 is variably subnetted, 2 subnets, 2 masks
B 150.2.2.0/24 [20/0] via 150.2.1.2, 00:02:10

R2#**show ip route bgp**
150.1.0.0/24 is subnetted, 1 subnets
B 150.1.1.0 [20/0] via 150.2.1.1, 00:00:09

Next, verify LAN-to-LAN connectivity between the subnets using an extended ping:

R1#**ping 150.2.2.2 source 150.1.1.1 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 12/15/16 ms

Task 3

The requirements for this task are straightforward. Simply paste the configuration into the router as specified. No additional configuration is required to complete this task.

Task 4

This task requires a fair amount of configuration; however, all necessary commands can be found in the ROUTE guide. This task is completed as follows:

R4(config)#**interface fastfthernet0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**no ip address**
R4(config-if)#**pppoe enable**
R4(config-if)#**pppoe-client dial-pool-number 1**
R4(config-if)#**exit**
R4(config)#**interface dialer 1**
R4(config-if)#**ip mtu 1492**
R4(config-if)#**ip address negotiated**
R4(config-if)#**encapsulation ppp**
R4(config-if)#**dialer pool 1**

https://t.me/learningnets

R4(config-if)#**dialer-group 1**
R4(config-if)#**ppp authentication pap callin**
R4(config-if)#**ppp pap sent-username ROUTER4 password CCNP2011**
R4(config-if)#**ppp ipcp route default**
R4(config-if)#**exit**

Following this, verify that R4 has received an IP address from the pool configured on R1:

R4#**show ip interface brief**
Interface IP-Address OK? Method Status Protocol
FastEthernet0/0 unassigned YES manual up up
Serial0/0 unassigned YES manual administratively down down
Serial0/1 unassigned YES TFTP administratively down down
Virtual-Access1 unassigned YES unset up up
Virtual-Access2 unassigned YES unset up up
Dialer1 150.1.1.100 YES IPCP up up

When PPPoE is enabled, the router automatically creates one or more Virtual-Access interfaces. You can view which Virtual-Access interface is associated with the Dialer interface using the **show interfaces dialer <number>** command as follows:

R4#**show interfaces dialer 1**
Dialer1 is up, line protocol is up (spoofing)
Hardware is Unknown
Internet address is 150.1.1.100/32
MTU 1500 bytes, BW 56 Kbit/sec, DLY 20000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation PPP, loopback not set
Keepalive set (10 sec)
DTR is pulsed for 1 seconds on reset
Interface is bound to Vi2
Last input never, output never, output hang never
Last clearing of "show interface" counters 00:15:06
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: weighted fair
Output queue: 0/1000/64/0 (size/max total/threshold/drops)
Conversations 0/0/16 (active/max active/max total)
Reserved Conversations 0/0 (allocated/max allocated)
Available Bandwidth 42 kilobits/sec
5 minute input rate 0 bits/sec, 0 packets/sec

https://t.me/learningnets
Technet24

5 minute output rate 0 bits/sec, 0 packets/sec
146 packets input, 2044 bytes
148 packets output, 2072 bytes
Bound to:
Virtual-Access2 is up, line protocol is up
Hardware is Virtual Access interface
MTU 1500 bytes, BW 56 Kbit/sec, DLY 20000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation PPP, LCP Open
Listen: CDPCP
Open: IPCP
PPPoE vaccess, cloned from Dialer1
Vaccess status 0x44, loopback not set
Keepalive set (10 sec)
Interface is bound to Di1 (Encapsulation PPP)
Last input 00:07:24, output never, output hang never
Last clearing of "show interface" counters 00:08:13
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: fifo
Output queue: 0/40 (size/max)
5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec
96 packets input, 1339 bytes, 0 no buffer
Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
96 packets output, 1339 bytes, 0 underruns
0 output errors, 0 collisions, 0 interface resets
0 unknown protocol drops
0 output buffer failures, 0 output buffers swapped out
0 carrier transitions

Next, verify that the default route is installed. In the solution example, the **ppp ipcp route default** interface configuration command is applied under the Dialer interface. This command instructs the router to add a default route to the routing table during PPP negotiation. This command is NOT supported in older IOS versions; therefore, you would complete the same solution using the **ip route 0.0.0.0 0.0.0.0 dialer [number]** global configuration command instead. Keep in mind that these commands are mutually exclusive. Use one or the other. You can NOT use both! Use the **show ip route** command to verify the default route:

https://t.me/learningnets

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.1.1.1 to network 0.0.0.0

150.1.0.0/32 is subnetted, 2 subnets
C 150.1.1.1 is directly connected, Dialer1
C 150.1.1.100 is directly connected, Dialer1
S* 0.0.0.0/0 [1/0] via 150.1.1.1

Notice that the static route is installed into the routing table with a metric of 1, which is the same metric that would be assigned to a manually configured static route. Finally, complete task requirements by pinging from R4 to R2s LAN subnet address of 150.2.2.2/24:

R4#**ping 150.2.2.2 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 16/18/24 ms

NOTE: You can perform additional checks using the show pppoe commands. The options that are available with these commands include:

R4#**show pppoe ?**
derived Cached PPPoE configuration information
relay PPPoE relay information
session PPPoE Session information
summary PPPoE sessions summary
throttled PPPoE Throttled information

For example, to view session information, append the **session** keyword to this command:

R4#**show pppoe session**
1 client session

Uniq ID PPPoE RemMAC Port Source VA State
SID LocMAC VA-st

https://t.me/learningnets

Technet24

N/A 6 000f.235e.ec80 Fa0/0 Di1 Vi2 UP
000f.235e.f120 UP

And to view detailed statistics, including byte and packet counts, append the **all** keyword:

R4#**show pppoe session all**
Total PPPoE sessions 1

session id: 6
local MAC address: 000f.235e.f120, remote MAC address: 000f.235e.ec80
virtual access interface: Vi2, outgoing interface: Fa0/0
403 packets sent, 401 received
20788 bytes sent, 21324 received

https://t.me/learningnets

CCNP Lab 079: PPP over Ethernet (PPPoE) Lab

Lab Objective:

The focus of this lab is to understand PPP over Ethernet (PPPoE) implementation and configuration. Additional technologies tested include CHAP authentication and NAT.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology. Configure an IP address of 150.1.1.1/24 on the LAN interface of R1. Do NOT configure an address on the LAN interface of R4.

Task 2

Configure BGP between R1 and R2 as illustrated in the topology. Advertise the

https://t.me/learningnets

150.2.2.0/24 subnet via BGP and verify that R1 can reach this subnet. Do NOT advertise the 150.1.1.0/24 subnet connected to R1 via BGP. Verify the configuration using the appropriate commands.

Task 3

Assume that router R1 is an ISP router. This router will be a 'server' for client router R4. This router should have the following PPPoE configuration applied to it:

NOTE: This task is provided to you because these configurations are beyond the scope of the current CCNP curriculum. Simple copy and paste this configuration or manually type it in to complete the task. There are no additional configurations required to complete this task.

```
username ROUTER4 password CCNP2011
!
bba-group pppoe global
virtual-template 1
!
interface fastethernet0/0
pppoe enable group global
!
interface virtual-template1
mtu 1492
ip unnumbered fastethernet0/0
peer default ip address pool CLIENT-POOL
ppp authentication chap
!
ip local pool CLIENT-POOL 150.1.1.100 150.1.1.254
```

Task 4

Given the configuration above on R1 (ISP Router), implement PPPoE with CHAP on R4. Next, verify your configuration using the appropriate commands. Test your solution by ensuring that R4 is able to ping 150.1.1.1 (R1), which should be its default gateway.

Task 5

Configure R1 so that R4 is able to reach R2s LAN subnet; however, R2 should never be able to initiate a connection to R4. Verify your configuration using the appropriate

https://t.me/learningnets

Technet24

commands. When completing this task, you MUST adhere to the following restrictions:

- You are NOT allowed to use any static routes on any routers
- You are NOT allowed to advertise a default via BGP
- You are NOT allowed to advertise the 150.1.1.0/24 subnet via BGP
- You are NOT allowed to redistribute any routes

Following completion, ensure that R1 can ping R2s LAN subnet, but not vice-versa.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic BGP configuration. Next, verify your BGP configuration using the **show ip bgp summary** and **show ip route** commands. Following this configuration, the BTP routing tables on R1 and R2 should show the following route entries:

R1#**show ip bgp**
BGP table version is 4, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.2.2.0/24 150.2.1.2 0 0 201 i

R2#**show ip bgp**
BGP table version is 5, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 150.2.2.0/24 0.0.0.0 0 32768 i

Task 3

The requirements for this task are straightforward. Simply paste the configuration into the router as specified. No additional configuration is required to complete this task.

Task 4

https://t.me/learningnets

The requirements of this task are similar to those of the previous lab with the only difference being that this time CHAP security is used instead of PAP This task is completed as follows:

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**no shutdown**
R4(config-if)#**no ip address**
R4(config-if)#**pppoe enable**
R4(config-if)#**pppoe-client dial-pool-number 1**
R4(config-if)#**exit**
R4(config)#**interface dialer 1**
R4(config-if)#**ip mtu 1492**
R4(config-if)#**ip address negotiated**
R4(config-if)#**encapsulation ppp**
R4(config-if)#**dialer pool 1**
R4(config-if)#**dialer-group 1**
R4(config-if)#**ppp authentication pap callin**
R4(config-if)#**ppp chap hostname ROUTER4**
R4(config-if)#**ppp chap password CCNP2011**
R4(config-if)#**ppp ipcp route default**
R4(config-if)#**exit**

Following this, verify that R4 has received an IP address from the pool configured on R1:

R4#**show ip interface brief**
Interface IP-Address OK? Method Status Protocol
FastEthernet0/0 unassigned YES manual up up
Serial0/0 unassigned YES manual administratively down down
Serial0/1 unassigned YES TFTP administratively down down
Virtual-Access1 unassigned YES unset up up
Virtual-Access2 unassigned YES unset up up
Dialer1 150.1.1.100 YES IPCP up up

When PPPoE is enabled, the router automatically creates one or more Virtual-Access interfaces. You can view which Virtual-Access interface is associated with the Dialer interface using the **show interfaces dialer <number>** command as follows:

R4#**show interfaces dialer 1**
Dialer1 is up, line protocol is up (spoofing)
Hardware is Unknown
Internet address is 150.1.1.100/32

https://t.me/learningnets
Technet24

MTU 1500 bytes, BW 56 Kbit/sec, DLY 20000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation PPP, loopback not set
Keepalive set (10 sec)
DTR is pulsed for 1 seconds on reset
Interface is bound to Vi2
Last input never, output never, output hang never
Last clearing of "show interface" counters 00:03:48
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: weighted fair
Output queue: 0/1000/64/0 (size/max total/threshold/drops)
Conversations 0/0/16 (active/max active/max total)
Reserved Conversations 0/0 (allocated/max allocated)
Available Bandwidth 42 kilobits/sec
5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec
44 packets input, 616 bytes
44 packets output, 616 bytes
Bound to:
Virtual-Access2 is up, line protocol is up
Hardware is Virtual Access interface
MTU 1500 bytes, BW 56 Kbit/sec, DLY 20000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation PPP, LCP Open
Listen: CDPCP
Open: IPCP
PPPoE vaccess, cloned from Dialer1
Vaccess status 0x44, loopback not set
Keepalive set (10 sec)
DTR is pulsed for 5 seconds on reset
Interface is bound to Di1 (Encapsulation PPP)
Last input 00:03:43, output never, output hang never
Last clearing of "show interface" counters 00:03:44
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: fifo
Output queue: 0/40 (size/max)
5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec

https://t.me/learningnets

53 packets input, 749 bytes, 0 no buffer
Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
52 packets output, 731 bytes, 0 underruns
0 output errors, 0 collisions, 0 interface resets
0 unknown protocol drops
0 output buffer failures, 0 output buffers swapped out
0 carrier transitions

Next, verify that the default route is installed. In the solution example, the **ppp ipcp route default** interface configuration command is applied under the Dialer interface. This command instructs the router to add a default route to the routing table during PPP negotiation. This command is NOT supported in older IOS versions; therefore, you would complete the same solution using the **ip route 0.0.0.0 0.0.0.0 dialer [number]** global configuration command instead. Keep in mind that these commands are mutually exclusive. Use one or the other. You can NOT use both! Use the **show ip route** command to verify the default route:

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.1.1.1 to network 0.0.0.0

150.1.0.0/32 is subnetted, 2 subnets
C 150.1.1.1 is directly connected, Dialer1
C 150.1.1.100 is directly connected, Dialer1
S* 0.0.0.0/0 [1/0] via 150.1.1.1

Notice that the static route is installed into the routing table with a metric of 1, which is the same metric that would be assigned to a manually configured static route. Finally, complete task requirements by pinging from R4 to 150.1.1.1 (R1):

R4#**ping 150.1.1.1 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 4/6/12 ms

https://t.me/learningnets

Technet24

Task 5

If you ignore the unnecessary banter, you will notice that this task requires that Port Address Translation, or NAT Overload, is required. This will allow R4 to ping R2, but not allow R2 to initiate inbound connections destined to R4. This task is completed as follows:

R1(config)#**interface virtual-template 1**
R1(config-if)#**ip nat inside**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip nat outside**
R1(config-if)#**exit**
R1(config)#**ip nat inside source list 100 interface serial 0/0 overload**
R1(config)#**access-list 100 permit ip 150.1.1.0 0.0.0.255 any**
R1(config)#**exit**

Following this configuration, test your solution by pinging between R4 and R2:

R4#**ping 150.2.2.2 repeat 10**

Type escape sequence to abort.
Sending 10, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 4/4/4 ms

Next, verify NAT / PAT operation using the **show ip nat translations** command on R1:

R1#**show ip nat translations**
Pro Inside global Inside local Outside local Outside global
icmp 150.2.1.1:1 150.1.1.100:1 150.2.2.2:1 150.2.2.2:1

Additional Information

To test or verify the PPP authentication method, simply enable PPP debugging on the router and the disable and re-enable the Dialer interface on R1, for example:

R4(config)#**logging console**
R4(config)#**interface dialer 1**
R4(config-if)#**shutdown**
*Jun 16 05:04:26.099: Di1 DDR: dialer shutdown complete
R4(config-if)#**do debug ppp negotiation**
PPP protocol negotiation debugging is on
R4(config-if)#**do debug ppp authentication**
PPP authentication debugging is on

https://t.me/learningnets

R4(config-if)#**no shutdown**
***Jun 16 05:04:59.271: %LINK-3-UPDOWN: Interface Dialer1, changed state to up**
***Jun 16 05:05:11.359: %DIALER-6-BIND: Interface Vi2 bound to profile Di1**
*Jun 16 05:05:11.363: Vi2 PPP: Phase is DOWN, Setup
*Jun 16 05:05:11.363: Vi2 PPP: Using dialer call direction
*Jun 16 05:05:11.363: Vi2 PPP: Treating connection as a callout
*Jun 16 05:05:11.363: Vi2 PPP: Session handle[71000007] Session id[0]
*Jun 16 05:05:11.363: Vi2 PPP: Phase is ESTABLISHING, Active Open
*Jun 16 05:05:11.363: Vi2 PPP: Authorization required
*Jun 16 05:05:11.363: Vi2 PPP: No remote authentication for call-out
*Jun 16 05:05:11.363: Vi2 LCP: O CONFREQ [Closed] id 1 len 10
*Jun 16 05:05:11.367: Vi2 LCP: MagicNumber 0x0F516A40 (0x05060F516A40)
*Jun 16 05:05:11.367: %LINK-3-UPDOWN: Interface Virtual-Access2, changed state to up
*Jun 16 05:05:11.367: Vi2 LCP: I CONFREQ [REQsent] id 1 len 19
*Jun 16 05:05:11.371: Vi2 LCP: MRU 1492 (0x010405D4)
*Jun 16 05:05:11.371: Vi2 LCP: AuthProto CHAP (0x0305C22305)
*Jun 16 05:05:11.371: Vi2 LCP: MagicNumber 0x0F515128 (0x05060F515128)
*Jun 16 05:05:11.371: Vi2 LCP: O CONFNAK [REQsent] id 1 len 8
*Jun 16 05:05:11.371: Vi2 LCP: MRU 1500 (0x010405DC)
*Jun 16 05:05:11.371: Vi2 LCP: I CONFACK [REQsent] id 1 len 10
*Jun 16 05:05:11.371: Vi2 LCP: MagicNumber 0x0F516A40 (0x05060F516A40)
*Jun 16 05:05:11.375: Vi2 LCP: I CONFREQ [ACKrcvd] id 2 len 19
*Jun 16 05:05:11.375: Vi2 LCP: MRU 1500 (0x010405DC)
*Jun 16 05:05:11.375: Vi2 LCP: AuthProto CHAP (0x0305C22305)
*Jun 16 05:05:11.375: Vi2 LCP: MagicNumber 0x0F515128 (0x05060F515128)
*Jun 16 05:05:11.375: Vi2 LCP: O CONFACK [ACKrcvd] id 2 len 19
*Jun 16 05:05:11.375: Vi2 LCP: MRU 1500 (0x010405DC)
*Jun 16 05:05:11.375: Vi2 LCP: AuthProto CHAP (0x0305C22305)
*Jun 16 05:05:11.375: Vi2 LCP: MagicNumber 0x0F515128 (0x05060F515128)
*Jun 16 05:05:11.379: Vi2 LCP: State is Open
*Jun 16 05:05:11.379: Vi2 PPP: No authorization without authentication
***Jun 16 05:05:11.379: Vi2 PPP: Phase is AUTHENTICATING, by the peer**
***Jun 16 05:05:11.379: Vi2 CHAP: I CHALLENGE id 1 len 23 from "R1"**
***Jun 16 05:05:11.383: Vi2 CHAP: Using hostname from interface CHAP**
***Jun 16 05:05:11.383: Vi2 CHAP: Using password from interface CHAP**
***Jun 16 05:05:11.383: Vi2 CHAP: O RESPONSE id 1 len 28 from "ROUTER4"**

https://t.me/learningnets
Technet24

***Jun 16 05:05:11.411: Vi2 CHAP: I SUCCESS id 1 len 4**
*Jun 16 05:05:11.415: Vi2 PPP: Phase is FORWARDING, Attempting Forward
*Jun 16 05:05:11.415: Vi2 PPP: Queue IPCP code[1] id[1]
*Jun 16 05:05:11.415: Vi2 PPP SSS: Receive SSS-Mgr Connect-Local
*Jun 16 05:05:11.419: Vi2 PPP: Phase is ESTABLISHING, Finish LCP
*Jun 16 05:05:11.419: Vi2 PPP: Phase is UP
*Jun 16 05:05:11.419: Vi2 IPCP: O CONFREQ [Closed] id 1 len 10
*Jun 16 05:05:11.419: Vi2 IPCP: Address 0.0.0.0 (0x030600000000)
*Jun 16 05:05:11.423: Vi2 CDPCP: O CONFREQ [Closed] id 1 len 4
*Jun 16 05:05:11.423: Vi2 PPP: Process pending ncp packets
*Jun 16 05:05:11.423: Vi2 IPCP: Redirect packet to Vi2
*Jun 16 05:05:11.423: Vi2 IPCP: I CONFREQ [REQsent] id 1 len 10
*Jun 16 05:05:11.423: Vi2 IPCP: Address 150.1.1.1 (0x030696010101)
*Jun 16 05:05:11.423: Vi2 IPCP: O CONFACK [REQsent] id 1 len 10
*Jun 16 05:05:11.423: Vi2 IPCP: Address 150.1.1.1 (0x030696010101)
*Jun 16 05:05:11.427: Vi2 LCP: I PROTREJ [Open] id 3 len 10 protocol CDPCP (0x820701010004)
*Jun 16 05:05:11.427: Vi2 CDPCP: State is Closed
*Jun 16 05:05:11.427: Vi2 CDPCP: State is Listen
*Jun 16 05:05:11.427: Vi2 IPCP: I CONFNAK [ACKsent] id 1 len 10
*Jun 16 05:05:11.427: Vi2 IPCP: Address 150.1.1.100 (0x030696010164)
*Jun 16 05:05:11.427: Vi2 IPCP: O CONFREQ [ACKsent] id 2 len 10
*Jun 16 05:05:11.431: Vi2 IPCP: Address 150.1.1.100 (0x030696010164)
*Jun 16 05:05:11.431: Vi2 IPCP: I CONFACK [ACKsent] id 2 len 10
*Jun 16 05:05:11.431: Vi2 IPCP: Address 150.1.1.100 (0x030696010164)
***Jun 16 05:05:11.431: Vi2 IPCP: State is Open**
***Jun 16 05:05:11.435: Di1 IPCP: Install negotiated IP interface address 150.1.1.100**
***Jun 16 05:05:11.439: Di1 IPCP: Install default route thru 150.1.1.1**
***Jun 16 05:05:11.439: Di1 IPCP: Install route to 150.1.1.1**
***Jun 16 05:05:11.443: Vi2 IPCP: Add link info for cef entry 150.1.1.1**
***Jun 16 05:05:12.419: %LINEPROTO-5-UPDOWN: Line protocol on Interface Virtual-Access2, changed state to up**

To test or verify PPPoE operation, simply perform the same actions and instead enable PPPoE debugging on the router, for example:

R4(config)#**logging console**
R4(config)#**interface dialer 1**
R4(config-if)#**shut**

https://t.me/learningnets

*Jun 16 05:09:19.015: %DIALER-6-UNBIND: Interface Vi2 unbound from profile Di1
*Jun 16 05:09:19.015: Di1 DDR: dialer shutdown complete
*Jun 16 05:09:19.047: %LINK-3-UPDOWN: Interface Virtual-Access2, changed state to down
*Jun 16 05:09:20.011: %LINEPROTO-5-UPDOWN: Line protocol on Interface Virtual-Access2, changed state to down
*Jun 16 05:09:21.015: %LINK-5-CHANGED: Interface Dialer1, changed state to administratively down
R4(config-if)#**do debug pppoe events**
PPPoE protocol events debugging is on
R4(config-if)#**do debug pppoe packets**
PPPoE control packets debugging is on
R4(config-if)#**no shut**
R4(config-if)#
*Jun 16 05:09:58.183: %LINK-3-UPDOWN: Interface Dialer1, changed state to up
*Jun 16 05:09:59.511: Sending PADI: Interface = FastEthernet0/0
*Jun 16 05:09:59.511: pppoe_send_padi:
FF FF FF FF FF FF 00 0F 23 5E F1 20 88 63 11 09
00 00 00 0C 01 01 00 00 01 03 00 04 85 06 8D 4C ...
*Jun 16 05:09:59.511: PPPoE 0: I PADO R:000f.235e.ec80 L:000f.235e.f120 Fa0/0
00 0F 23 5E F1 20 00 0F 23 5E EC 80 88 63 11 07
00 00 00 26 01 01 00 00 01 03 00 04 85 06 8D 4C ...
*Jun 16 05:10:01.559: PPPOE: we've got our pado and the pado timer went off
*Jun 16 05:10:01.559: OUT PADR from PPPoE Session
00 0F 23 5E EC 80 00 0F 23 5E F1 20 88 63 11 19
00 00 00 26 01 01 00 00 01 03 00 04 85 06 8D 4C ...
*Jun 16 05:10:01.563: PPPoE 4: I PADS R:000f.235e.ec80 L:000f.235e.f120 Fa0/0
00 0F 23 5E F1 20 00 0F 23 5E EC 80 88 63 11 65
00 04 00 26 01 01 00 00 01 03 00 04 85 06 8D 4C ...
*Jun 16 05:10:01.563: IN PADS from PPPoE Session
*Jun 16 05:10:01.567: %DIALER-6-BIND: Interface Vi2 bound to profile Di1
*Jun 16 05:10:01.567: PPPoE: Virtual Access interface obtained.
*Jun 16 05:10:01.571: PPPoE : encap string prepared
*Jun 16 05:10:01.571: [0]PPPoE 4: data path set to Virtual Acess
*Jun 16 05:10:01.575: %LINK-3-UPDOWN: Interface Virtual-Access2, changed state to up
*Jun 16 05:10:02.575: %LINEPROTO-5-UPDOWN: Line protocol on Interface Virtual-Access2, changed state to up

https://t.me/learningnets
Technet24

https://t.me/learningnets

CCNP Lab 080: Branch Office Connectivity Lab

Lab Objective:

The focus of this lab is to understand branch office connectivity solutions, implementation and configuration. Additional technologies tested include NAT, PAT and network security.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology. In addition to this, configure Loopback 0 with an IP Address of 160.0.0.4/32 on R4.

https://t.me/learningnets

Task 2

Configure IP routing as illustrated in the topology. Management has requested that only a default route be advertised to R1 from the ISP (R4). Management has requested that redistribution NOT be performed on R1. Additionally, they do not want any non-private IP addresses within the OSPF domain. Configure routing so that R2 and R4 have reachability to all unknown (external) destinations. This should only happen if R1 is receiving the default route from the ISP (R4). Verify the configuration using appropriate commands.

Task 3

Configure Internet access for the spoke subnets connected to routers R2 and R3 as follows:

- All traffic from the 10.2.2.0/24 subnet should appear to originate from 150.1.1.2
- All traffic from the 10.3.3.0/24 subnet should appear to originate from 150.1.1.3

Following this configuration, verify that both R2 and R3 can ping the 160.0.0.4/32 address.

Task 4

Management has advised that they would some of the business' customers on the Internet to access a web server that is connected to the R3 LAN. This server has yet to be installed, but they request that you implement a solution so that all HTTP traffic ONLY destined to address 150.1.1.5 is forwarded to a Loopback 0 interface with the IP address 3.3.3.3 on R3. Implement this solution and test it by connecting to 150.1.1.5, using port 80, from R4.

Task 5

Management is concerned about Internet security, they have compiled a list of activities that they would like you to implement on the Internet-facing router (R1). The list is as follows:

- Router R1 should be configured to discard messages that can be used to inform the source host that the destination Unicast address is unreachable
- Router R1 should be configured so that all IP packets that contain IP options should be discarded by the router
- Router R1 should be configured so that the source of an IP packet is not allowed to specify the network path a packet takes
- Router R1 should be configured so that it is not possible to send an IP broadcast

https://t.me/learningnets

Technet24

packet to a remote IP subnet

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

While the requirements of this task are straightforward, and OSPF and BGP configuration has been described in detail in previous labs. This task is completed as follows:

R1(config)#**router ospf 1**
R1(config-router)#**router-id 1.1.1.1**
R1(config-router)#**network 10.0.0.0 0.255.255.255 area 0**
R1(config-router)#**default-information originate**
R1(config-router)#**exit**
R1(config)#**router bgp 65501**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**neighbor 150.1.1.4 remote-as 254**
R1(config-router)#**exit**

R2(config)#**router ospf 2**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**network 10.0.0.0 0.255.255.255 area 0**
R2(config-router)#**exit**

R3(config)#**router ospf 3**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**network 10.0.0.0 0.255.255.255 area 0**
R3(config-router)#**exit**

R4(config)#**router bgp 254**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**neighbor 150.1.1.1 remote-as 65501**
R4(config-router)#**neighbor 150.1.1.1 default-originate**
R4(config-router)#**exit**

Next, verify your configurations using the **show ip route** command on R1, R2, and R3:

R1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP

https://t.me/learningnets

D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.1.1.4 to network 0.0.0.0

10.0.0.0/8 is variably subnetted, 4 subnets, 2 masks
O 10.3.3.0/24 [110/65] via 10.0.0.6, 00:02:32, Serial0/1
O 10.2.2.0/24 [110/65] via 10.0.0.2, 00:02:32, Serial0/0
C 10.0.0.0/30 is directly connected, Serial0/0
C 10.0.0.4/30 is directly connected, Serial0/1
150.1.0.0/29 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
B* 0.0.0.0/0 [20/0] via 150.1.1.4, 00:01:10

R2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 10.0.0.1 to network 0.0.0.0

10.0.0.0/8 is variably subnetted, 4 subnets, 2 masks
O 10.3.3.0/24 [110/129] via 10.0.0.1, 00:02:40, Serial0/0
C 10.2.2.0/24 is directly connected, FastEthernet0/0
C 10.0.0.0/30 is directly connected, Serial0/0
O 10.0.0.4/30 [110/128] via 10.0.0.1, 00:02:40, Serial0/0
O*E2 0.0.0.0/0 [110/1] via 10.0.0.1, 00:01:18, Serial0/0

R3#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route

https://t.me/learningnets

o - ODR, P - periodic downloaded static route

Gateway of last resort is 10.0.0.5 to network 0.0.0.0

10.0.0.0/8 is variably subnetted, 4 subnets, 2 masks
C 10.3.3.0/24 is directly connected, FastEthernet0/0
O 10.2.2.0/24 [110/846] via 10.0.0.5, 00:02:44, Serial1/0
O 10.0.0.0/30 [110/845] via 10.0.0.5, 00:02:44, Serial1/0
C 10.0.0.4/30 is directly connected, Serial1/0
O*E2 0.0.0.0/0 [110/1] via 10.0.0.5, 00:01:22, Serial1/0

Because R4 is not receiving any routes, you can simply verify the BGP status:

R4#**show ip bgp summary**
BGP router identifier 4.4.4.4, local AS number 254
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
150.1.1.1 4 65501 6 7 1 0 0 00:03:08 0

Task 3

The requirements of this task are straightforward and require that Port Address Translation, PAT or NAT Overload, be implemented on R1. This task is completed as follows:

R1(config)#**ip nat pool SITE-2-POOL 150.1.1.2 150.1.1.2 prefix-length 29**
R1(config)#**ip nat pool SITE-3-POOL 150.1.1.3 150.1.1.3 prefix-length 29**
R1(config)#**ip access-list extended SITE-2-ONLY**
R1(config-ext-nacl)#**permit ip 10.2.2.0 0.0.0.255 any**
R1(config-ext-nacl)#**exit**
R1(config)#**ip access-list extended SITE-3-ONLY**
R1(config-ext-nacl)#**permit ip 10.3.3.0 0.0.0.255 any**
R1(config-ext-nacl)#**exit**
R1(config)#**ip nat inside source list SITE-2-ONLY pool SITE-2-POOL overload**
R1(config)#**ip nat inside source list SITE-3-ONLY pool SITE-3-POOL overload**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip nat inside**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip nat inside**
R1(config-if)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip nat outside**

https://t.me/learningnets

R1(config-if)#**exit**

Following this configuration, test connectivity from R2s LAN to the 160.0.0.4/32 address:

R2#**ping 160.0.0.4 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 160.0.0.4, timeout is 2 seconds:
Packet sent with a source address of 10.2.2.2
.!!!!!!!!!
Success rate is 90 percent (9/10), round-trip min/avg/max = 16/22/76 ms

Next, perform the same test - this time, however, from R3s LAN:

R3#**ping 160.0.0.4 source fastethernet 0/0 size 1500 repeat 10**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 160.0.0.4, timeout is 2 seconds:
Packet sent with a source address of 10.3.3.3
.!!!!!!!!!
Success rate is 90 percent (9/10), round-trip min/avg/max = 192/192/196 ms

Finally, verify PAT operation using the **show ip nat translations** command on R1:

R1#**show ip nat translations**
Pro Inside global Inside local Outside local Outside global
icmp 150.1.1.2:1 10.2.2.2:1 160.0.0.4:1 160.0.0.4:1
icmp 150.1.1.3:2 10.3.3.3:2 160.0.0.4:2 160.0.0.4:2

Task 4

The requirements for this task are straightforward. All that is required in that you create a static NAT for TCP port 80 on R1. On R3, simply configure a Loopback interface with IP address 3.3.3.3/32 and advertise it via OSPF. To test, enable Cisco IOS HTTP server functionality on R3 using the **ip http server** global configuration command. This task is completed as follows:

R3(config)#**interface loopback 0**
R3(config-if)#**ip address 3.3.3.3 255.255.255.255**
R3(config-if)#**exit**
R3(config)#**router ospf 3**
R3(config-router)#**network 3.3.3.3 0.0.0.0 area 0**
R3(config-router)#**exit**
R3(config)#**ip http server**
R3(config)#**exit**

https://t.me/learningnets

Technet24

R1(config)#**ip nat inside source static tcp 3.3.3.3 80 150.1.1.5 80**

Verify your configuration on R1 using the **show ip nat translations** command:

R1#**show ip nat translations verbose**
Pro Inside global Inside local Outside local Outside global
tcp 150.1.1.5:80 3.3.3.3:80 --- ---
create 00:00:16, use 00:00:16 timeout:0,
flags:
static, extended, extendable, use_count: 0, entry-id: 6, lc_entries: 0

Finally, test your solution by connecting to 150.1.1.5 from R4 using TCP port 80:

R4#**telnet 150.1.1.5 www**
Trying 150.1.1.5, 80 ... Open

quit
HTTP/1.1 400 Bad Request
Date: Thu, 16 Jun 2011 11:59:42 GMT
Server: cisco-IOS
Accept-Ranges: none

400 Bad Request

[Connection to 150.1.1.5 closed by foreign host]

You can use the **show ip nat translations verbose** command to view detailed connection information while the session is in progress:

R1#**show ip nat translations verbose**
Pro Inside global Inside local Outside local Outside global
tcp 150.1.1.5:80 3.3.3.3:80 150.1.1.4:12028 150.1.1.4:12028
create 00:00:04, use 00:00:04 timeout:86400000, left 23:59:55,
flags:
extended, use_count: 0, entry-id: 8, lc_entries: 0

tcp 150.1.1.5:80 3.3.3.3:80 150.1.1.4:15989 150.1.1.4:15989
create 00:00:25, use 00:00:18 timeout:86400000, left 00:00:41,
flags:
extended, timing-out, use_count: 0, entry-id: 7, lc_entries: 0

tcp 150.1.1.5:80 3.3.3.3:80 --- ---
create 00:00:56, use 00:00:04 timeout:0,
flags:
static, extended, extendable, use_count: 2, entry-id: 6, lc_entries: 0

Task 5

https://t.me/learningnets

The requirements for this task are straightforward. To complete it, you need to disable ICMP unreachables, drop packets with IP options, disable source-routing, and disable the directed Broadcast feature. This task is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**no ip unreachables**
R1(config-if)#**no ip directed-broadcast**
R1(config-if)#**exit**
R1(config)#**ip options drop**
R1(config)#**no ip source-route**

https://t.me/learningnets

Technet24

CCNP Lab 081: CCNP Multi-Technology Lab

Lab Objective:

The objective of this lab is to cover all relevant CCNP ROUTE and SWITCH theory. These labs will include topics from each of these guides. It should be noted that not all topics will be included in all labs. Additionally, not all solutions will be illustrated in detail. You can refer to previous labs for assistance with some basic configurations.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please implement the following pre-lab configurations. This is required because of the manner in which the routers and switches are physically cabled to each other. The following configuration should be applied to switch ALS1:

```
!
hostname ALS1
!
vtp mode transparent
!
vlan 100
name R1-VLAN
!
vlan 300
name R3-VLAN
```

https://t.me/learningnets

Technet24

```
!
vlan 400
name R4-VLAN
!
interface fastethernet 0/1
switchport access vlan 100
switchport mode access
!
interface fastethernet 0/2
shutdown
!
interface fastethernet 0/3
switchport access vlan 300
switchport mode access
!
interface fastethernet 0/4
switchport access vlan 400
switchport mode access
!
interface range fastethernet 0/5 - 6
shutdown
!
interface fastethernet0/7
switchport mode trunk
!
interface fastethernet 0/8
switchport mode trunk
!
interface range fastethernet 0/9 - 10
shutdown
!
interface range fastethernet 0/11 - 12
switchport mode trunk
!
interface vlan 400
ip address 10.4.4.254 255.255.255.0
no shutdown
!
```

https://t.me/learningnets

```
ip default-gateway 10.4.4.4
!
line vty 0 4
privilege level 15
password cisco
login
!
end
!
hostname ALS2
!
vtp mode transparent
!
vlan 300
name R3-VLAN
!
interface range fastethernet 0/1 - 10
shutdown
!
interface fastethernet 0/11
switchport mode trunk
!
interface fastethernet 0/12
switchport mode trunk
!
interface vlan 300
ip address 10.3.3.254 255.255.255.0
no shutdown
!
ip default-gateway 10.3.3.3
!
line vty 0 4
privilege level 15
password cisco
login
!
end
!
```

https://t.me/learningnets

Technet24

```
hostname DLS1
!
ip routing
!
vtp mode transparent
!
vlan 100
name R1-VLAN
!
interface range fastethernet 0/1 - 6
shutdown
!
interface range fastethernet 0/7 - 8
switchport trunk encapsulation dot1q
switchport mode trunk
!
interface range fastethernet 0/9 - 10
shutdown
!
interface fastethernet 0/11
switchport mode dynamic desirable
!
interface fastethernet 0/12
switchport mode dynamic desirable
!
interface range fastethernet 0/13 - 48
shutdown
!
interface vlan 100
ip address 150.1.1.254 255.255.255.0
no shutdown
!
ip default-gateway 150.1.1.1
!
line vty 0 4
privilege level 15
password cisco
login
```

https://t.me/learningnets

```
!
end
!
hostname DLS2
!
ip routing
!
vtp mode transparent
!
interface range fastethernet 0/1 - 10
shutdown
!
interface fastethernet 0/11
switchport mode dynamic desirable
!
interface fastethernet 0/12
switchport mode dynamic desirable
!
interface range fastethernet 0/13 - 48
shutdown
!
line vty 0 4
privilege level 15
password cisco
login
!
end
```

If you are using the www.101labs.net racks, please bring up the LAN interface connected to R2 by the following configuration:

```
interface fastethernet 0/0
ip address 150.2.2.2 255.255.255.0
no keepalive
loopback
no shutdown
```

Alternatively, you can simply connect the interface to a hub or one of the switches and bring up the interface in the standard manner.

Task 1

https://t.me/learningnets

Technet24

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Configure an LACP EtherChannel between DLS1 and DLS2. Assign this EtherChannel the IP subnet 192.168.0.0/30. Verify that DLS1 and DLS2 can ping each other across this link.

Task 3

In the future, multiple links will be added to the EtherChannel between DLS1 and DLS2. To mitigate against any potential issues cause my mismatched configurations, ensure that the switches disable the links if such an event happened. Verify your configuration.

Task 4

Management wants to ensure that if any other devices other than R1, R3, and R4 are connected to switch ALS1, the ports should drop packets with unknown MAC addresses, the switch should send out an SNMP trap and a Syslog message, and the violation counter is incremented. The Syslog should and SNMP traps should be sent to host 150.2.2.254. An SNMP read-only community string of CCNP should be used. This configuration should survive a reboot of the switch. Verify your configuration using the appropriate commands.

Task 5

Configure BGP between DLS1 and DLS2. Use the Layer 3 EtherChannel for peering. Configure and advertise the following Loopback interfaces on DLS2 via BGP:

- Loopback 10: IP Address 172.16.10.2/32
- Loopback 11: IP Address 172.16.11.2/32
- Loopback 12: IP Address 172.16.12.2/32

Next, configure BGP between DLS1 and R1. Ensure that R1 is able to receive all of the prefixes advertised by DLS2 and vice-versa. Finally, ensure that R1 is able to ping all of the prefixes advertised by DLS2. You are NOT allowed to use the **neighbor <address> next-hop-self** command in your solution. Also, you are NOT allowed to use static routes. Verify your solution using the appropriate commands.

Task 6

Configure EIGRP between R1 and R2 as illustrated in the topology. Next, configure OSPF area 0 on R1, R2 and R3 as illustrated in the topology. Do NOT enable OSPF for R3s LAN subnet or between R3 and R4. Verify your configuration using the appropriate commands.

https://t.me/learningnets

Task 7

Configure your network so that R2 and R3 can reach the IP subnets advertised by DLS2 and all devices can reach each other. You are NOT allowed to redistribute any routes into OSPF or EIGRP when completing this task. You can, however, redistribute routes into BGP. You are only allowed to configure R1. Verify your solution using the appropriate commands.

Task 8

Configure your network so that if either R2 or R3 loses its link to R1, all other devices are still able to reach the local router. When you implement your solution, keep in mind that when either the R1-R2 or R1-R3 links are up, your solution should ensure that R2 prefers the path via R1 to reach the DLS2 subnets, while R3 prefers the path via R1 to reach the DLS2 subnets.

Test your solution by first disabling the R1-R2 link and pinging from the LAN subnet of R2 to one of the Loopbacks on DLS2. Next, test your solution by disabling the R1-R3 link and pinging from R3 to one of the Loopback subnets on switch DLS2.

Task 9

Configure your network so that the 10.x.x.x subnets connected to R3 and R4 are able to ping all other subnets. You are NOT allowed to advertise these subnets via OSPF. In addition to this, you are NOT allowed to configure any static routes when completing this task. These devices should be able to ping all other devices even if the R1-R3 link fails. Verify your solution by pinging from ALS1 and ALS2 to one of the Loopback subnets on switch DLS2. Finally, disable the R1-R3 link and verify that the switches are still able to ping other devices, e.g. DLS2.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EtherChannel configuration. This will not be included in this section to avoid being redundant. Following your implementation, verify your solution using the **show etherchannel** commands to view the configuration parameters and also the operating mode (channel protocol) being used:

DLS1#**show etherchannel summary**
Flags: D - down P - bundled in port-channel

https://t.me/learningnets

Technet24

I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
------+-------------+-----------+---
10 Po10(RU) LACP Fa0/11(P) Fa0/12(P)

You can verify LACP information using the **show lacp** commands:

DLS1#**show lacp neighbor**
Flags: S - Device is requesting Slow LACPDUs
F - Device is requesting Fast LACPDUs
A - Device is in Active mode P - Device is in Passive mode

Channel group 10 neighbors

Partner's information:

LACP port Admin Oper Port Port
Port Flags Priority Dev ID Age key Key Number State
Fa0/11 SA 32768 000b.fd67.6500 15s 0x0 0xA 0x36 0x3D
Fa0/12 SA 32768 000b.fd67.6500 12s 0x0 0xA 0x37 0x3D

Finally, complete this task by pinging between DLS1 and DLS2 across the EtherChannel.

DLS1#**ping 192.168.0.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.0.2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 4/4/4 ms

Task 3

To complete this task, you need to enable the EtherChannel Guard feature on both switches:

DLS1(config)#**spanning-tree etherchannel guard misconfig**

https://t.me/learningnets

DLS2(config)#**spanning-tree etherchannel guard misconfig**

Verify your configuration using the **show spanning-tree summary** command:

DLS1#**show spanning-tree summary**
Switch is in pvst mode
Root bridge for: none
Extended system ID is enabled
Portfast Default is disabled
PortFast BPDU Guard Default is disabled
Portfast BPDU Filter Default is disabled
Loopguard Default is disabled
EtherChannel misconfig guard is enabled
UplinkFast is disabled
BackboneFast is disabled
Configured Pathcost method used is short

Name Blocking Listening Learning Forwarding STP Active
---------- -------- --------- -------- ---------- ----------
VLAN0001 1 0 0 1 2
VLAN0100 1 0 0 1 2
---------- -------- --------- -------- ---------- ----------
2 vlans 2 0 0 2 4

DLS2#**show spanning-tree summary**
Switch is in pvst mode
Root bridge for: none
Extended system ID is enabled
Portfast Default is disabled
PortFast BPDU Guard Default is disabled
Portfast BPDU Filter Default is disabled
Loopguard Default is disabled
EtherChannel misconfig guard is enabled
UplinkFast is disabled
BackboneFast is disabled
Configured Pathcost method used is short

Name Blocking Listening Learning Forwarding STP Active
---------- -------- --------- -------- ---------- ----------
Total 0 0 0 0 0 0

Task 4

https://t.me/learningnets

Technet24

To complete this task, you need to enable sticky learning and specify a maximum of one MAC address for these ports (default). In addition, change the violation mode to restrict. Finally, you also need to configure Syslogging and SNMP on switch ALS1. This is completed as follows:

```
ALS1(config)#interface range fastethernet 0/1 , fastethernet 0/3 - 4
ALS1(config-if-range)#switchport port-security
ALS1(config-if-range)#switchport port-security mac-address sticky
ALS1(config-if-range)#switchport port-security violation restrict
ALS1(config-if-range)#exit
ALS1(config)#logging on
ALS1(config)#logging 150.2.2.254
ALS1(config)#logging trap informational
ALS1(config)#snmp-server community CCNP RO
ALS1(config)#snmp-server host 150.2.2.254 traps CCNP port-security
ALS1(config)#snmp-server enable traps port-security
```

Verify your port security configuration using the **show port-security** commands:

```
ALS1#show port-security
Secure Port MaxSecureAddr CurrentAddr SecurityViolation Security Action
(Count) (Count) (Count)
---------------------------------------------------------------------
Fa0/1 1 1 0 Restrict
Fa0/3 1 1 0 Restrict
Fa0/4 1 1 0 Restrict
---------------------------------------------------------------------
Total Addresses in System (excluding one mac per port) : 0
Max Addresses limit in System (excluding one mac per port) : 1024
```

To view security sticky learned MAC addresses, append the **address** keyword:

```
ALS1#show port-security address
Secure Mac Address Table
-----------------------------------------------------------
Vlan Mac Address Type Ports Remaining Age
(mins)
---- ----------- ---- ----- ------------
100 000f.235e.ec80 SecureSticky Fa0/1 -
300 0013.7faf.3e00 SecureSticky Fa0/3 -
400 000f.235e.f120 SecureSticky Fa0/4 -
-----------------------------------------------------------
```

https://t.me/learningnets

Total Addresses in System (excluding one mac per port) : 0
Max Addresses limit in System (excluding one mac per port) : 1024
Verify logging using the **show logging** command:

ALS1#**show logging**
Syslog logging: enabled (0 messages dropped, 0 messages rate-limited, 0 flushes, 0 overruns)
Console logging: disabled
Monitor logging: level debugging, 0 messages logged
Buffer logging: level debugging, 112 messages logged
Exception Logging: size (4096 bytes)
File logging: disabled
Trap logging: level informational, 116 message lines logged
Logging to 150.2.2.254, 1 message lines logged

[Truncated Output]

Finally, verify SNMP using the **show snmp** commands:

ALS1#**show snmp**
Chassis: FAB0540Y20Z
0 SNMP packets input
0 Bad SNMP version errors
0 Unknown community name
0 Illegal operation for community name supplied
0 Encoding errors
0 Number of requested variables
0 Number of altered variables
0 Get-request PDUs
0 Get-next PDUs
0 Set-request PDUs
0 SNMP packets output
0 Too big errors (Maximum packet size 1500)
0 No such name errors
0 Bad values errors
0 General errors
0 Response PDUs
0 Trap PDUs
SNMP global trap: disabled

SNMP logging: enabled
Logging to 150.2.2.254.162, 0/10, 0 sent, 0 dropped.

https://t.me/learningnets

Technet24

SNMP agent enabled

Task 5

The basic BGP peering configuration to complete this task is straightforward. There are, some caveats, however, to be aware of. First, to complete this task, you will need to configure switch DLS1 as a Route Reflector. This will allow DLS2 and R1 to receive each others' advertised prefixes. This is configuration is completed as follows:

DLS1(config)#**router bgp 254**
DLS1(config-router)#**neighbor 192.168.0.2 remote-as 254**
DLS1(config-router)#**neighbor 192.168.0.2 route-reflector-client**
DLS1(config-router)#**neighbor 150.1.1.1 remote-as 254**
DLS1(config-router)#**neighbor 150.1.1.1 route-reflector-client**
DLS1(config-router)#**exit**

Next, to complete the specified task without using the **neighbor <address> next-hop-self** command, you need to configure an outbound route map on DLS1 to change the NEXT_HOP attribute. This is the recommended method of changing the NEXT_HOP attribute on a Route Reflector. This is the only supported method when the same command has been applied to clients of the Route Reflector. The **neighbor <address> next-hop-self** is applicable on a Route Reflector from routes received from an external peer. This task is completed as follows:

DLS1(config)#**route-map CHANGE-R1-NEXT-HOP**
DLS1(config-route-map)#**set ip next**
DLS1(config-route-map)#**set ip next-hop 150.1.1.254**
% Warning: Next hop address is our address
DLS1(config-route-map)#**exit**
DLS1(config)#**router bgp 254**
DLS1(config-router)#**neighbor 150.1.1.1 route-map CHANGE-R1-NEXT-HOP out**
DLS1(config-router)#**exit**

Finally, to complete this task, you need to advertise a default route from DLS1 to DLS2:

DLS1(config)#**router bgp 254**
DLS1(config-router)#**neighbor 192.168.0.2 default-originate**
DLS1(config-router)#**exit**

Verify your solution by looking at the BGP RIBs of all devices within Autonomous System 254:

DLS1#**show ip bgp**
BGP table version is 10, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,

https://t.me/learningnets

r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i172.16.10.1/32 192.168.0.2 0 100 0 i
*>i172.16.11.1/32 192.168.0.2 0 100 0 i
*>i172.16.12.1/32 192.168.0.2 0 100 0 i

DLS2#**show ip bgp**
BGP table version is 5, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i0.0.0.0 192.168.0.1 0 100 0 i
*> 172.16.10.1/32 0.0.0.0 0 32768 i
*> 172.16.11.1/32 0.0.0.0 0 32768 i
*> 172.16.12.1/32 0.0.0.0 0 32768 i

R1#**show ip bgp**
BGP table version is 7, local router ID is 1.0.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*>i172.16.10.1/32 150.1.1.254 0 100 0 i
*>i172.16.11.1/32 150.1.1.254 0 100 0 i
*>i172.16.12.1/32 150.1.1.254 0 100 0 i

Finally, verify that R1 can ping the Loopback subnets advertised by switch DLS2:

R1#**ping 172.16.10.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 172.16.10.1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms

R1#**ping 172.16.11.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 172.16.11.1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms

https://t.me/learningnets

Technet24

R1#**ping 172.16.12.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 172.16.12.1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms

Task 6

Please refer to previous labs for basic OSPF and EIGRP configuration. Following configuration, the routing tables on your routers should show the following entries:

R1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

172.16.0.0/32 is subnetted, 3 subnets
B 172.16.12.1 [200/0] via 150.1.1.254, 00:18:00
B 172.16.11.1 [200/0] via 150.1.1.254, 00:18:00
B 172.16.10.1 [200/0] via 150.1.1.254, 00:18:00
150.0.0.0/30 is subnetted, 3 subnets
C 150.0.0.4 is directly connected, Serial0/1
C 150.0.0.0 is directly connected, Serial0/0
O 150.0.0.8 [110/845] via 150.0.0.6, 00:02:39, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 150.0.0.2, 00:03:44, Serial0/0

R2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route

https://t.me/learningnets

o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

150.0.0.0/30 is subnetted, 3 subnets
O 150.0.0.4 [110/845] via 150.0.0.10, 00:02:49, Serial0/1
C 150.0.0.0 is directly connected, Serial0/0
C 150.0.0.8 is directly connected, Serial0/1
150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0

R3#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/24 is subnetted, 1 subnets
C 10.3.3.0 is directly connected, FastEthernet0/0
150.0.0.0/30 is subnetted, 3 subnets
C 150.0.0.4 is directly connected, Serial1/0
C 150.0.0.12 is directly connected, Serial1/2
C 150.0.0.8 is directly connected, Serial1/1

Task 7

To complete this task, you need to redistribute OSPF and EIGRP into BGP. Because we are NOT allowed to redistribute into OSPF or EIGRP, you need to use default routing. This task is completed by implementing the following configuration on R1:

R1(config)#**router bgp 254**
R1(config-router)#**redistribute ospf 1 match**
R1(config-router)#**redistribute eigrp 254**
R1(config-router)#**exit**
R1(config)#**router ospf 1**
R1(config-router)#**default-information originate always**
R1(config-router)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip summary-address eigrp 254 0.0.0.0 0.0.0.0**

https://t.me/learningnets

Technet24

R1(config-if)#**exit**

Next, verify the IP routing tables on all devices using the **show ip route** command:

R1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 0.0.0.0 to network 0.0.0.0

172.16.0.0/32 is subnetted, 3 subnets
B 172.16.12.1 [200/0] via 150.1.1.254, 00:29:25
B 172.16.11.1 [200/0] via 150.1.1.254, 00:29:25
B 172.16.10.1 [200/0] via 150.1.1.254, 00:29:25
150.0.0.0/30 is subnetted, 3 subnets
C 150.0.0.4 is directly connected, Serial0/1
C 150.0.0.0 is directly connected, Serial0/0
O 150.0.0.8 [110/845] via 150.0.0.6, 00:01:23, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 150.0.0.2, 00:15:09, Serial0/0
D* 0.0.0.0/0 is a summary, 00:01:13, Null0

R2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.0.0.1 to network 0.0.0.0

150.0.0.0/30 is subnetted, 3 subnets
O 150.0.0.4 [110/845] via 150.0.0.10, 00:01:31, Serial0/1
C 150.0.0.0 is directly connected, Serial0/0
C 150.0.0.8 is directly connected, Serial0/1

https://t.me/learningnets

150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0
D* 0.0.0.0/0 [90/2681856] via 150.0.0.1, 00:01:20, Serial0/0

R3#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.0.0.5 to network 0.0.0.0

10.0.0.0/24 is subnetted, 1 subnets
C 10.3.3.0 is directly connected, FastEthernet0/0
150.0.0.0/30 is subnetted, 3 subnets
C 150.0.0.4 is directly connected, Serial1/0
C 150.0.0.12 is directly connected, Serial1/2
C 150.0.0.8 is directly connected, Serial1/1
O*E2 0.0.0.0/0 [110/1] via 150.0.0.5, 00:01:34, Serial1/0

DLS1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

172.16.0.0/32 is subnetted, 3 subnets
B 172.16.12.1 [200/0] via 192.168.0.2, 00:41:41
B 172.16.11.1 [200/0] via 192.168.0.2, 00:41:41
B 172.16.10.1 [200/0] via 192.168.0.2, 00:41:41
192.168.0.0/30 is subnetted, 1 subnets
C 192.168.0.0 is directly connected, Port-channel10
150.0.0.0/30 is subnetted, 3 subnets
B 150.0.0.4 [200/0] via 150.1.1.1, 00:02:20
B 150.0.0.0 [200/0] via 150.1.1.1, 00:02:11

https://t.me/learningnets

B 150.0.0.8 [200/845] via 150.0.0.6, 00:02:15
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, Vlan100
150.2.0.0/24 is subnetted, 1 subnets
B 150.2.2.0 [200/2172416] via 150.0.0.2, 00:03:30

DLS2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 192.168.0.1 to network 0.0.0.0

172.16.0.0/32 is subnetted, 3 subnets
C 172.16.12.1 is directly connected, Loopback12
C 172.16.11.1 is directly connected, Loopback11
C 172.16.10.1 is directly connected, Loopback10
192.168.0.0/30 is subnetted, 1 subnets
C 192.168.0.0 is directly connected, Port-channel10
150.0.0.0/30 is subnetted, 3 subnets
B 150.0.0.4 [200/0] via 150.1.1.1, 00:02:01
B 150.0.0.0 [200/0] via 150.1.1.1, 00:01:52
B 150.0.0.8 [200/845] via 150.0.0.6, 00:01:56
150.2.0.0/24 is subnetted, 1 subnets
B 150.2.2.0 [200/2172416] via 150.0.0.2, 00:01:47
B* 0.0.0.0/0 [200/0] via 192.168.0.1, 00:25:14

Task 8

To complete this task, you need to redistribute between EIGRP and OSPF on R2. In addition to this, you must modify the BGP configuration on R1 so that external OSPF routes are also redistributed. By default, only internal OSPF routes are redistributed. This configuration must be modified on R1 and R2 as follows:

R1(config)#**router bgp 254**
R1(config-router)#**redistribute ospf 1 match internal external 2**
R1(config-router)#**exit**

R2(config)#**router eigrp 254**

https://t.me/learningnets

R2(config-router)#**redistribute ospf 2 metric 1544 20000 255 1 1500**
R2(config-router)#**exit**
R2(config)#**router ospf 2**
R2(config-router)#**redistribute eigrp 254 subnets**
R2(config-router)#**default-information originate metric 10**
R2(config-router)#**exit**

When redistributing into OSPF, a default route is not redistributed automatically. Therefore, you must use the **default-information originate <always>** command. The **default-information originate** command used by itself will configure the router to advertise a default route if a default route is already present in the routing table. The **always** keyword can be appended to this command to force the router to generate a default route even when one does not exist in the routing table. This keyword should be used with caution as it may result in the black-holing of traffic within the OSPF domain or the forwarding of packets for all unknown destinations to the configured router.

The metric is appended to this command so that when the R1-R3 link is up, R3 will always use the R1-R3 link to reach the DLS2 subnets. No additional configuration is required for EIGRP.

Following this, perform the first task validation task by disabling the R1-R2 link, verifying the routing information and pinging from the LAN subnet of R2 to one of the Loopbacks on DLS2:

R2#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.0.0.10 to network 0.0.0.0

150.0.0.0/30 is subnetted, 2 subnets
O 150.0.0.4 [110/845] via 150.0.0.10, 00:00:46, Serial0/1
C 150.0.0.8 is directly connected, Serial0/1
150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0
O*E2 0.0.0.0/0 [110/1] via 150.0.0.10, 00:00:12, Serial0/1

R2#**ping 172.16.10.1 source 150.2.2.2 size 1500 repeat 10**

https://t.me/learningnets
Technet24

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 172.16.10.1, timeout is 2 seconds:
Packet sent with a source address of 150.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 380/382/384 ms

Perform the second validation test by disabling the R1-R3 link, verifying the routing information and pinging from R3 to one of the Loopbacks on DLS2:

R3#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.0.0.9 to network 0.0.0.0

10.0.0.0/24 is subnetted, 1 subnets
C 10.3.3.0 is directly connected, FastEthernet0/0
150.0.0.0/30 is subnetted, 3 subnets
O E2 150.0.0.0 [110/20] via 150.0.0.9, 00:00:05, Serial1/1
C 150.0.0.12 is directly connected, Serial1/2
C 150.0.0.8 is directly connected, Serial1/1
150.2.0.0/24 is subnetted, 1 subnets
O E2 150.2.2.0 [110/20] via 150.0.0.9, 00:00:05, Serial1/1
O*E2 0.0.0.0/0 [110/10] via 150.0.0.9, 00:00:05, Serial1/1

R3#**ping 172.16.10.1 size 1500 repeat 10**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 172.16.10.1, timeout is 2 seconds:
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 204/205/208 ms

Task 9

While seemingly complex, the task itself is very simple. First, you need to think outside the box. R4 needs some type of default route to reach the rest of the network, otherwise neither it nor ALS1 will be able to each any other subnets. The task states we cannot use static routes or even enable a dynamic routing protocol. This leave ODR available. ODR is NOT a dynamic routing protocol. It is a CDP extension. This first part is

https://t.me/learningnets

completed as follows:

R3(config)#**router odr**
R3(config-router)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**cdp enable**
R3(config-if)#**exit**

R4(config)#**interface serial 0/0**
R4(config-if)#**cdp enable**
R4(config-if)#**exit**

Following this, verify IP routing information using the **show ip route** command:

R3#**show ip route odr**
10.0.0.0/24 is subnetted, 2 subnets
o 10.4.4.0 [160/1] via 150.0.0.14, 00:00:54, Serial1/2

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 150.0.0.13 to network 0.0.0.0

10.0.0.0/24 is subnetted, 1 subnets
C 10.4.4.0 is directly connected, FastEthernet0/0
150.0.0.0/30 is subnetted, 1 subnets
C 150.0.0.12 is directly connected, Serial0/0
o* 0.0.0.0/0 [160/1] via 150.0.0.13, 00:00:42, Serial0/0

The second requirement is that we cannot advertise any of the 10.x.x.x subnets; however, they should be able to reach all other subnets. Again, thinking outside the box, we can use NAT to satisfy this requirement. The simplest solution would be to PAT everything to a configured IP address, e.g. a Loopback interface on R3. Therefore, even if the R1-R3 link were to fail, the solution would still work. This solution is completed as follows:

R3(config)#**interface loopback 100**
R3(config-if)#**ip address 150.0.0.254 255.255.255.255**
R3(config-if)#**exit**

https://t.me/learningnets

Technet24

R3(config)#**router ospf 3**
R3(config-router)#**network 150.0.0.254 0.0.0.0 area 0**
R3(config-router)#**exit**
R3(config)#**access-list 100 permit ip 10.3.3.0 0.0.0.255 any**
R3(config)#**access-list 100 permit ip 10.4.4.0 0.0.0.255 any**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip nat inside**
R3(config-if)#**interface serial 1/2**
R3(config-if)#**exit**
R3(config-if)#**ip nat inside**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**ip nat outside**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip nat outside**
R3(config-if)#**exit**
R3(config)#**ip nat inside source list 100 interface loopback 100 overload**

Verify your configuration by pinging from ALS1 and ALS2 to a Loopback subnet on DLS2:

ALS1#**ping 172.16.10.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 172.16.10.1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

ALS2#**ping 172.16.10.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 172.16.10.1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/16/20 ms

R3#**show ip nat translations**
Pro Inside global Inside local Outside local Outside global
icmp 150.0.0.254:1491 10.3.3.254:1491 172.16.10.1:1491 172.16.10.1:1491
icmp 150.0.0.254:1492 10.3.3.254:1492 172.16.10.1:1492 172.16.10.1:1492
icmp 150.0.0.254:1493 10.3.3.254:1493 172.16.10.1:1493 172.16.10.1:1493
icmp 150.0.0.254:1494 10.3.3.254:1494 172.16.10.1:1494 172.16.10.1:1494
icmp 150.0.0.254:1495 10.3.3.254:1495 172.16.10.1:1495 172.16.10.1:1495

https://t.me/learningnets

icmp 150.0.0.254:6585 10.4.4.254:6585 172.16.10.1:6585 172.16.10.1:6585
icmp 150.0.0.254:6586 10.4.4.254:6586 172.16.10.1:6586 172.16.10.1:6586
icmp 150.0.0.254:6587 10.4.4.254:6587 172.16.10.1:6587 172.16.10.1:6587
icmp 150.0.0.254:6588 10.4.4.254:6588 172.16.10.1:6588 172.16.10.1:6588
icmp 150.0.0.254:6589 10.4.4.254:6589 172.16.10.1:6589 172.16.10.1:6589

Finally, test redundancy by disabling the R1-R3 link and performing the same test:

R3(config)#**interface serial 1/0**
R3(config-if)#**shut**
R3#**show ip route ospf**
150.0.0.0/16 is variably subnetted, 4 subnets, 2 masks
O E2 150.0.0.0/30 [110/20] via 150.0.0.9, 00:00:22, Serial1/1
150.2.0.0/24 is subnetted, 1 subnets
O E2 150.2.2.0 [110/20] via 150.0.0.9, 00:00:22, Serial1/1
O*E2 0.0.0.0/0 [110/10] via 150.0.0.9, 00:00:22, Serial1/1

ALS2#**ping 172.16.12.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 172.16.12.1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/17/20 ms

ALS1#**ping 172.16.11.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 172.16.10.1, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 32/32/32 ms

Verify NAT translations on R3 using the show ip nat translations command:

R3#**show ip nat translations**
Pro Inside global Inside local Outside local Outside global
icmp 150.0.0.254:5221 10.3.3.254:5221 172.16.12.1:5221 172.16.12.1:5221
icmp 150.0.0.254:5222 10.3.3.254:5222 172.16.12.1:5222 172.16.12.1:5222
icmp 150.0.0.254:5223 10.3.3.254:5223 172.16.12.1:5223 172.16.12.1:5223
icmp 150.0.0.254:5224 10.3.3.254:5224 172.16.12.1:5224 172.16.12.1:5224
icmp 150.0.0.254:5225 10.3.3.254:5225 172.16.12.1:5225 172.16.12.1:5225
icmp 150.0.0.254:2534 10.4.4.254:2534 172.16.11.1:2534 172.16.11.1:2534
icmp 150.0.0.254:2535 10.4.4.254:2535 172.16.11.1:2535 172.16.11.1:2535
icmp 150.0.0.254:2536 10.4.4.254:2536 172.16.11.1:2536 172.16.11.1:2536
icmp 150.0.0.254:2537 10.4.4.254:2537 172.16.11.1:2537 172.16.11.1:2537

https://t.me/learningnets
Technet24

icmp 150.0.0.254:2538 10.4.4.254:2538 172.16.11.1:2538 172.16.11.1:2538

https://t.me/learningnets

CCNP Lab 082: CCNP Multi-Technology Lab

Lab Objective:

The objective of this lab is to cover all relevant CCNP ROUTE and SWITCH theory. These labs will include topics from each of these guides. It should be noted that not all topics will be included in all labs. Additionally, not all solutions will be illustrated in detail. You can refer to previous labs for assistance with some basic configurations.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please implement the following pre-lab configurations. This is required because of the manner in which the routers and switches are physically cabled to each other. The following configuration should be applied to switch ALS1:

```
!
hostname ALS1
!
vtp mode transparent
!
vlan 100
name R1-VLAN
!
vlan 300
name R3-VLAN
```

https://t.me/learningnets

```
!
vlan 400
name R4-VLAN
!
interface fastethernet 0/1
switchport access vlan 100
switchport mode access
!
interface fastethernet 0/2
shutdown
!
interface fastethernet 0/3
switchport access vlan 300
switchport mode access
!
interface fastethernet 0/4
switchport access vlan 400
switchport mode access
!
interface range fastethernet 0/5 - 6
shutdown
!
interface fastethernet0/7
switchport mode trunk
!
interface fastethernet 0/8
switchport mode trunk
!
interface range fastethernet 0/9 - 10
shutdown
!
interface range fastethernet 0/11 - 12
switchport mode trunk
!
!
interface vlan 400
ip address 10.4.4.254 255.255.255.0
no shutdown
```

https://t.me/learningnets

```
!
ip default-gateway 10.4.4.4
!
line vty 0 4
privilege level 15
password cisco
login
!
end
!
hostname ALS2
!
vtp mode transparent
!
vlan 300
name R3-VLAN
!
interface range fastethernet 0/1 - 10
shutdown
!
interface fastethernet 0/11
switchport mode trunk
!
interface fastethernet 0/12
switchport mode trunk
!
interface vlan 300
ip address 10.3.3.254 255.255.255.0
no shutdown
!
ip default-gateway 10.3.3.3
!
line vty 0 4
privilege level 15
password cisco
login
!
end
```

https://t.me/learningnets

```
!
hostname DLS1
!
ip routing
!
vtp mode transparent
!
vlan 100
name R1-VLAN
!
interface range fastethernet 0/1 - 6
shutdown
!
interface range fastethernet 0/7 - 8
switchport trunk encapsulation dot1q
switchport mode trunk
!
interface range fastethernet 0/9 - 10
shutdown
!
interface fastethernet 0/11
switchport mode dynamic desirable
!
interface fastethernet 0/12
switchport mode dynamic desirable
!
interface range fastethernet 0/13 - 48
shutdown
!
interface vlan 100
ip address 150.1.1.254 255.255.255.0
no shutdown
!
ip default-gateway 150.1.1.1
!
line vty 0 4
privilege level 15
password cisco
```

https://t.me/learningnets

Technet24

```
login
!
end
!
hostname DLS2
!
ip routing
!
vtp mode transparent
!
interface range fastethernet 0/1 - 10
shutdown
!
interface fastethernet 0/11
switchport mode dynamic desirable
!
interface fastethernet 0/12
switchport mode dynamic desirable
!
interface range fastethernet 0/13 - 48
shutdown
!
line vty 0 4
privilege level 15
password cisco
login
!
end
```

If you are using the www.101labs.net racks, please bring up the LAN interface connected to R2 by the following configuration:

```
interface fastethernet 0/0
ip address 150.2.2.2 255.255.255.0
no keepalive
loopback
no shutdown
```

Alternatively, you can simply connect the interface to a hub or one of the switches and bring up the interface in the standard manner.

https://t.me/learningnets

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Configure VTP on DLS1 and DLS2 so that DLS2 automatically receives VLAN information from DLS1. Both switches should reside in domain 2011. Secure VTP messages with a password of CCNP2011. Configure an SVI in VLAN 100 for DLS2. Assign this SVI the IP address 150.1.1.253/24. Verify your configuration using the appropriate commands. Also, verify that all devices on the 150.1.1.0/24 subnet can ping each other.

Task 3

Configure switches DLS1 and DLS2 to use the 802.1w and 802.1t standards. In addition to this, configure the switches to use 32 bit based values for default port path costs Verify the solution and configuration using the appropriate commands.

Task 4

In the future, Cisco IP phones will be connected to ports Fa0/1 to Fa0/5 on switches DLS1 and DSL2. Implement QoS so that markings sent by Cisco phones are trusted. In addition to this, configure QoS so that all user data received on these ports is assigned a CoS value of 2. Verify your configuration using the appropriate commands.

Task 5

In the future, non-Cisco IP phones will be connected to ports Fa0/1 to Fa0/5 on switch ALS2. Implement QoS so that the switch rewrites the CoS value for all incoming frames to a configured default value of 1, regardless of any existing CoS value. Verify your configuration using the appropriate commands.

Task 6

Configure OSPF on all routers as illustrated in the topology. You must adhere to the following guidelines and restrictions when implementing OSPF:

- Ensure that no switches will ever participate in the DR/BDR election process
- Ensure that area 1 supports Type 7 LSAs
- Ensure that no Type 3 LSAs are flooded into area 1
- Ensure that no Hellos are sent out the LAN interfaces of R2, R3, and R4

Your solution should take into account a possible R1-R3 or R2-R3 link failure. Routing should work in the event that either one of these links fails. Verify your solution by checking the routing tables of all devices. Next, test your solution by disabling the R1-

https://t.me/learningnets

Technet24

R3 link and verifying that you can ping from R4 to DLS2. Finally, test your solution by disabling the R2-R3 link and verifying that you can ping from R4 to R2s LAN interface.

Task 7

Authenticate the OSPF backbone using the plaintext password CCNP2011. Verify your configuration using the appropriate commands.

Task 8

IP version 6 needs to be integrated into the network. Enable RIPng between switches DLS1 and DSL2 as well as router R1. Use the 3ffe:abcd:1111:1/64 subnet. Verify your configuration.

Task 9

Configure ISATAP tunnels on all routers. Use Loopback interfaces as the tunnel source. These Loopback interfaces should use the router number; for example, the Loopback interface on R1 should be assigned IP address 1.1.1.1/32, the Loopback interface on R2 should be assigned IP address 2.2.2.2/32, etc. The tunnels should be configured using the fec0:abcd:1234:1::/64 subnet. Verify your configuration using the appropriate commands.

Task 10

Configure the following IP version 6 (IPv6) LAN subnets on the following routers:

- R1: IPv6 LAN subnet 3ffe:abcd:1111:1/64
- R2: IPv6 LAN subnet 3ffe:abcd:1111:2/64
- R3: IPv6 LAN subnet 3ffe:abcd:1111:3/64
- R4: IPv6 LAN subnet 3ffe:abcd:1111:4/64

Next, configure MP-BGP on all routers. All routers should use their ISATAP tunnel addresses for peering. Ensure that all routers advertise their LAN subnet via MP-BGP. MP-BGP peering should be configured on all routers as follows:

- R1 - Autonomous System 1: This router will peer with R2
- R2 - Autonomous System 2: This router will peer with R1 and R3
- R3 - Autonomous System 3: This router will peer with R2 and R4
- R4 - Autonomous System 4: This router will peer with R3

Verify your configuration using the appropriate commands. Finally, complete this task by also ensuring that all IPv6 subnets can ping each other. You do not need to be able to ping the switches from the subnets connected to R2, R3, or R4 when completing this

https://t.me/learningnets

task verification.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic VTP configuration. This will not be included in this section to avoid being redundant. Verify your solution using the **show vtp** commands:

DLS1#**show vtp status**
VTP Version : running VTP2
Configuration Revision : 1
Maximum VLANs supported locally : 1005
Number of existing VLANs : 6
VTP Operating Mode : Server
VTP Domain Name : 2011
VTP Pruning Mode : Disabled
VTP V2 Mode : Enabled
VTP Traps Generation : Disabled
MD5 digest : 0xA5 0xC3 0x7F 0x1D 0x9F 0xA2 0xA6 0xC8
Configuration last modified by 150.1.1.254 at 3-1-93 05:53:51
Local updater ID is 150.1.1.254 on interface Vl100 (lowest numbered VLAN interface found)

DLS2#**show vtp status**
VTP Version : running VTP2
Configuration Revision : 1
Maximum VLANs supported locally : 1005
Number of existing VLANs : 6
VTP Operating Mode : Client
VTP Domain Name : 2011
VTP Pruning Mode : Disabled
VTP V2 Mode : Enabled
VTP Traps Generation : Disabled
MD5 digest : 0xA5 0xC3 0x7F 0x1D 0x9F 0xA2 0xA6 0xC8
Configuration last modified by 150.1.1.254 at 3-1-93 05:53:51

DLS1#**show vtp password**

https://t.me/learningnets

Technet24

VTP Password: CCNP2011

DLS2#**show vtp password**
VTP Password: CCNP2011

Next, following the SVI configuration on DLS2, verify connectivity with the 150.1.1.0/24 subnet:

DLS2#**ping 150.1.1.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.0, timeout is 2 seconds:
.
Reply to request 1 from 150.1.1.254, 1 ms
Reply to request 1 from 150.1.1.1, 1 ms
Reply to request 2 from 150.1.1.254, 1 ms
Reply to request 2 from 150.1.1.1, 1 ms
Reply to request 3 from 150.1.1.254, 1 ms
Reply to request 3 from 150.1.1.1, 1 ms
Reply to request 4 from 150.1.1.254, 1 ms
Reply to request 4 from 150.1.1.1, 1 ms

Task 3

The requirements of this task are straightforward, assuming you remember your Spanning Tree standards from the SWITCH guide. IEEE 802.1w is Rapid STP. The 802.1t standard introduced the extended system ID to conserve MAC addresses and reduces the Bridge Priority to 4 bits and adds a 12-bit Extended System ID. No explicit configuration is required on current Cisco IOS Catalyst switches to enable this functionality. In addition to this, the 802.1t standard assigns 32-bit (long) default port cost values to each port. However, this feature must be explicitly enabled in Cisco IOS Catalyst switches. This task is therefore completed as follows:

DLS1(config)#**spanning-tree pathcost method long**
DLS1(config)#**spanning-tree mode rapid-pvst**

DLS2(config)#**spanning-tree pathcost method long**
DLS2(config)#**spanning-tree mode rapid-pvst**

Verify your configuration using the **show spanning-tree** commands:

DLS1#**show spanning-tree summary**
Switch is in rapid-pvst mode
Root bridge for: none
Extended system ID is enabled
Portfast Default is disabled

https://t.me/learningnets

PortFast BPDU Guard Default is disabled
Portfast BPDU Filter Default is disabled
Loopguard Default is disabled
EtherChannel misconfig guard is enabled
UplinkFast is disabled
BackboneFast is disabled
Configured Pathcost method used is long

Name Blocking Listening Learning Forwarding STP Active
---------- -------- --------- -------- ---------- ----------
VLAN0001 1 0 0 3 4
VLAN0100 1 0 0 3 4
---------- -------- --------- -------- ---------- ----------
2 vlans 2 0 0 6 8

DLS1#**show spanning-tree pathcost method**
Spanning tree default pathcost method used is long

DLS1#show spanning-tree interface fastethernet 0/11

Vlan Role Sts **Cost** Prio.Nbr Type
---------- ---- --- --------- -------- --------------------------
VLAN0001 Desg FWD **200000** 128.11 P2p
VLAN0100 Desg FWD **200000** 128.11 P2p

Task 4

To complete this task, the trust boundary needs to be extended to the switch port on the Cisco IP phone. However, instead of trusting the CoS values, specify a default value to be assigned instead. This task is completed on switches DSL1 and DLS2 as follows:

DLS1(config)#**mls qos**
QoS: ensure flow-control on all interfaces are OFF for proper operation.
DLS1(config)#**interface range fastethernet 0/1 - 5**
DLS1(config-if-range)#**mls qos trust cos**
DLS1(config-if-range)#**mls qos trust device cisco-phone**
DLS1(config-if-range)#**switchport priority extend cos 2**
DLS1(config-if-range)#exit

DLS2(config)#**mls qos**
QoS: ensure flow-control on all interfaces are OFF for proper operation.
DLS2(config)#**interface range fastethernet 0/1 - 5**
DLS2(config-if-range)#**mls qos trust cos**
DLS2(config-if-range)#**mls qos trust device cisco-phone**

https://t.me/learningnets
Technet24

DLS2(config-if-range)#**switchport priority extend cos 2**
DLS2(config-if-range)#**exit**

Verify your configuration using the **show mls qos** commands:

DLS2#**show mls qos interface fastethernet 0/1**
FastEthernet0/1
trust state: not trusted
trust mode: trust cos
COS override: dis
default COS: 0
DSCP Mutation Map: Default DSCP Mutation Map
Trust device: cisco-phone

To verify the appliance trust, i.e. the trust settings for the device connected to the Cisco IP phone switch port, use the **show interfaces <name> switchport** command:

DLS2#**show interfaces fastethernet 0/1 switchport**
Name: Fa0/1
Switchport: Enabled
Administrative Mode: dynamic desirable
Operational Mode: down
Administrative Trunking Encapsulation: negotiate
Negotiation of Trunking: On
Access Mode VLAN: 1 (default)
Trunking Native Mode VLAN: 1 (default)
Administrative Native VLAN tagging: enabled
Voice VLAN: none
Administrative private-vlan host-association: none
Administrative private-vlan mapping: none
Administrative private-vlan trunk native VLAN: none
Administrative private-vlan trunk Native VLAN tagging: enabled
Administrative private-vlan trunk encapsulation: dot1q
Administrative private-vlan trunk normal VLANs: none
Administrative private-vlan trunk associations: none
Administrative private-vlan trunk mappings: none
Operational private-vlan: none
Trunking VLANs Enabled: ALL
Pruning VLANs Enabled: 2-1001
Capture Mode Disabled
Capture VLANs Allowed: ALL

https://t.me/learningnets

Protected: false
Unknown unicast blocked: disabled
Unknown multicast blocked: disabled
Appliance trust: 2

Task 5

To complete this task on switch ALS2, you need to override the CoS value for all received incoming frames to the specified or desired value. This task is completed as follows:

ALS2(config)#**interface range fastethernet 0/1 - 5**
ALS2(config-if-range)#**mls qos cos 1**
ALS2(config-if-range)#**mls qos cos override**
ALS2(config-if-range)#**exit**

Verify your configuration using the **show mls qos** commands:

ALS2#**show mls qos interface fastethernet 0/1**
FastEthernet0/1
trust state: not trusted
trust mode: not trusted
COS override: ena
default COS: 1
pass-through: none
trust device: none

Task 6

The requirements of this task are very straightforward. To disable the DR/BDR election on the switches, ensure that they have a priority of 0. Second, OSPF area 1 will need to be configured as a totally stubby NSSA. All other areas follow normal OSPF configuration rules. Keep in mind that you will need to configure virtual links to allow for full IP connectivity. This consideration should factor in a possible R1-R3 link failure, as well as an R2-R3 link failure. Following your configuration, the OSPF Neighbor Tables on all of the routers should show the adjacency states that are printed in the output below:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - - 150.0.0.2 OSPF_VL1
3.3.3.3 0 FULL/ - - 150.0.0.10 OSPF_VL0
150.1.1.253 0 FULL/DROTHER 00:00:33 150.1.1.253 FastEthernet0/0
150.1.1.254 0 FULL/DROTHER 00:00:35 150.1.1.254 FastEthernet0/0

https://t.me/learningnets
Technet24

2.2.2.2 0 FULL/ - 00:00:38 150.0.0.2 Serial0/0
3.3.3.3 0 FULL/ - 00:00:36 150.0.0.6 Serial0/1

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 0 FULL/ - - 150.0.0.1 OSPF_VL1
3.3.3.3 0 FULL/ - - 150.0.0.10 OSPF_VL0
1.1.1.1 0 FULL/ - 00:00:38 150.0.0.1 Serial0/0
3.3.3.3 0 FULL/ - 00:00:30 150.0.0.10 Serial0/1

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
4.4.4.4 0 FULL/ - 00:00:34 150.0.0.14 Serial1/2
2.2.2.2 0 FULL/ - - 150.0.0.9 OSPF_VL1
1.1.1.1 0 FULL/ - - 150.0.0.5 OSPF_VL0
2.2.2.2 0 FULL/ - 00:00:35 150.0.0.9 Serial1/1
1.1.1.1 0 FULL/ - 00:00:37 150.0.0.5 Serial1/0

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:32 150.0.0.13 Serial0/0

DLS1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 1 FULL/DR 00:00:34 150.1.1.1 Vlan100
150.1.1.253 0 2WAY/DROTHER 00:00:30 150.1.1.253 Vlan100

DLS2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
1.1.1.1 1 FULL/DR 00:00:32 150.1.1.1 Vlan100
150.1.1.254 0 2WAY/DROTHER 00:00:31 150.1.1.254 Vlan100

Verify the IP routing tables on all routers and switches using the **show ip route** command:

DLS1#**show ip route ospf**
O*IA 0.0.0.0/0 [110/2] via 150.1.1.1, 00:10:37, Vlan100

DLS2#**show ip route ospf**
O*IA 0.0.0.0/0 [110/2] via 150.1.1.1, 00:10:42, Vlan100

R1#**show ip route ospf**
10.0.0.0/24 is subnetted, 2 subnets
O 10.4.4.0 [110/846] via 150.0.0.6, 00:15:04, Serial0/1

https://t.me/learningnets

O 10.3.3.0 [110/65] via 150.0.0.6, 00:15:04, Serial0/1
150.0.0.0/30 is subnetted, 4 subnets
O 150.0.0.12 [110/845] via 150.0.0.6, 00:15:04, Serial0/1
O 150.0.0.8 [110/845] via 150.0.0.6, 00:15:04, Serial0/1
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 150.0.0.2, 00:15:04, Serial0/0

R2#**show ip route ospf**
10.0.0.0/24 is subnetted, 2 subnets
O 10.4.4.0 [110/846] via 150.0.0.10, 00:15:15, Serial0/1
O 10.3.3.0 [110/65] via 150.0.0.10, 00:15:15, Serial0/1
150.0.0.0/30 is subnetted, 4 subnets
O 150.0.0.4 [110/845] via 150.0.0.10, 00:15:15, Serial0/1
O 150.0.0.12 [110/845] via 150.0.0.10, 00:15:15, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
O IA 150.1.1.0 [110/65] via 150.0.0.1, 00:15:15, Serial0/0

R3#**show ip route ospf**
10.0.0.0/24 is subnetted, 2 subnets
O 10.4.4.0 [110/782] via 150.0.0.14, 00:15:19, Serial1/2
150.0.0.0/30 is subnetted, 4 subnets
O IA 150.0.0.0 [110/845] via 150.0.0.9, 00:15:19, Serial1/1
[110/845] via 150.0.0.5, 00:15:19, Serial1/0
150.1.0.0/24 is subnetted, 1 subnets
O IA 150.1.1.0 [110/782] via 150.0.0.5, 00:15:19, Serial1/0
150.2.0.0/24 is subnetted, 1 subnets
O IA 150.2.2.0 [110/782] via 150.0.0.9, 00:15:19, Serial1/1

R4#**show ip route ospf**
10.0.0.0/24 is subnetted, 2 subnets
O 10.3.3.0 [110/65] via 150.0.0.13, 00:15:21, Serial0/0
150.0.0.0/30 is subnetted, 4 subnets
O IA 150.0.0.4 [110/845] via 150.0.0.13, 00:15:21, Serial0/0
O IA 150.0.0.0 [110/909] via 150.0.0.13, 00:15:21, Serial0/0
O IA 150.0.0.8 [110/845] via 150.0.0.13, 00:15:21, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
O IA 150.1.1.0 [110/846] via 150.0.0.13, 00:15:21, Serial0/0
150.2.0.0/24 is subnetted, 1 subnets
O IA 150.2.2.0 [110/846] via 150.0.0.13, 00:15:21, Serial0/0

Prior to any testing, verify end-to-end connectivity by pinging from the LAN subnet on

https://t.me/learningnets

R4 to the IP address configured on DLS2:

R4#**ping 150.1.1.253 source 10.4.4.4 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.253, timeout is 2 seconds:
Packet sent with a source address of 10.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 380/382/388 ms

Next, test your redundant solution by disabling the R1-R3 link and performing the same test:

R1(config)#**interface serial 0/1**
R1(config-if)#**shut**

R4#**ping 150.1.1.253 source 10.4.4.4 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.253, timeout is 2 seconds:
Packet sent with a source address of 10.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 392/394/396 ms

Optionally, use a Traceroute to verify the path the traffic is taking:

R4#**traceroute ip**

Target IP address: **150.1.1.253**
Source address: **10.4.4.4**
Numeric display [n]: **y**
Timeout in seconds [3]:
Probe count [3]:
Minimum Time to Live [1]:
Maximum Time to Live [30]:
Port Number [33434]:
Loose, Strict, Record, Timestamp, Verbose[none]:
Type escape sequence to abort.
Tracing the route to 150.1.1.253

1 150.0.0.13 8 msec 8 msec 8 msec <<<<<<<<<<<< **R3s Serial1/2 Interface**
2 150.0.0.9 16 msec 16 msec 16 msec <<<<<<<<<< **R2s Serial0/1 Interface**
3 150.0.0.1 16 msec 16 msec 16 msec <<<<<<<<<< **R1s Serial0/0 Interface**
4 150.1.1.253 16 msec * 24 msec <<<<<<<<<< **DLS2s VLAN 100 Interface**

Perform a second failover test by disabling the R2-R3 link and pinging R2s LAN subnet. Prior to this test, verify that R4s LAN subnet can ping R2s LAN subnet:

https://t.me/learningnets

R4#**ping 150.2.2.2 source 10.4.4.4 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 10.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 380/380/384 ms

R2(config)#**interface serial 0/1**
R2(config-if)#**shut**

R4#**ping 150.2.2.2 source 10.4.4.4 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 10.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 392/393/396 ms

Optionally, use a Traceroute to verify the path the traffic is taking:

R4#**traceroute ip**

Target IP address: **150.2.2.2**
Source address: **10.4.4.4**
Numeric display [n]: **y**
Timeout in seconds [3]:
Probe count [3]:
Minimum Time to Live [1]:
Maximum Time to Live [30]:
Port Number [33434]:
Loose, Strict, Record, Timestamp, Verbose[none]:
Type escape sequence to abort.
Tracing the route to 150.2.2.2

1 150.0.0.13 8 msec 8 msec 8 msec <<<<<<<<<<<< **R3s Serial1/2 Interface**
2 150.0.0.5 12 msec 16 msec 16 msec <<<<<<<<<< **R1s Serial0/1 Interface**
3 150.0.0.2 16 msec * 20 msec <<<<<<<<<< **R2s Serial0/0 Interface**

Task 7

When completing this task, it is important to remember that virtual links are a logical extension of the OSPF backbone. Therefore, all routers that have virtual links configured must also have authentication configured for the backbone. This task is completed as follows:

https://t.me/learningnets

Technet24

R1(config)#**router ospf 1**
R1(config-router)#**area 0 authentication**
R1(config-router)#**area 2 virtual-link 2.2.2.2 authentication-key CCNP2011**
R1(config-router)#**area 3 virtual-link 3.3.3.3 authentication-key CCNP2011**

R2(config)#**router ospf 2**
R2(config-router)#**area 0 authentication**
R2(config-router)#**area 2 virtual-link 1.1.1.1 authentication-key CCNP2011**
R2(config-router)#**area 3 virtual-link 3.3.3.3 authentication-key CCNP2011**

R3(config)#**router ospf 3**
R3(config-router)#**area 0 authentication**
R3(config-router)#**area 3 virtual-link 2.2.2.2 authentication-key CCNP2011**
R3(config-router)#**area 3 virtual-link 1.1.1.1 authentication-key CCNP2011**
R3(config-router)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip ospf authentication-key CCNP2011**

R4(config)#**router ospf 4**
R4(config-router)#**area 0 authentication**
R4(config-router)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip ospf authentication-key CCNP2011**

Next, verify OSPF virtual link states on R1, R2 and R3. Additionally, verify OSPF adjacency states between routers R3 and R4:

R1#**show ip ospf virtual-links**
Virtual Link OSPF_VL1 to router 2.2.2.2 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 2, via interface Serial0/0, Cost of using 64
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:02
Adjacency State FULL (Hello suppressed)
Index 1/4, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec
Simple password authentication enabled

Virtual Link OSPF_VL0 to router 3.3.3.3 is up

https://t.me/learningnets

Run as demand circuit
DoNotAge LSA allowed.
Transit area 3, via interface Serial0/1, Cost of using 64
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:00
Adjacency State FULL (Hello suppressed)
Index 2/5, retransmission queue length 0, number of retransmission 7
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 1, maximum is 2
Last retransmission scan time is 0 msec, maximum is 0 msec
Simple password authentication enabled

R2#**show ip ospf virtual-links**
Virtual Link OSPF_VL1 to router 1.1.1.1 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 2, via interface Serial0/0, Cost of using 64
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:01
Adjacency State FULL (Hello suppressed)
Index 1/3, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec
Simple password authentication enabled

Virtual Link OSPF_VL0 to router 3.3.3.3 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 3, via interface Serial0/1, Cost of using 64
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:06
Adjacency State FULL (Hello suppressed)
Index 2/4, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec

https://t.me/learningnets
Technet24

Simple password authentication enabled

R3#**show ip ospf virtual-links**
Virtual Link OSPF_VL1 to router 2.2.2.2 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 3, via interface Serial1/1, Cost of using 781
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:05
Adjacency State FULL (Hello suppressed)
Index 3/5, retransmission queue length 0, number of retransmission 0
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 0, maximum is 0
Last retransmission scan time is 0 msec, maximum is 0 msec
Simple password authentication enabled

Virtual Link OSPF_VL0 to router 1.1.1.1 is up
Run as demand circuit
DoNotAge LSA allowed.
Transit area 3, via interface Serial1/0, Cost of using 781
Transmit Delay is 1 sec, State POINT_TO_POINT,
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
Hello due in 00:00:08
Adjacency State FULL (Hello suppressed)
Index 2/4, retransmission queue length 0, number of retransmission 3
First 0x0(0)/0x0(0) Next 0x0(0)/0x0(0)
Last retransmission scan length is 1, maximum is 1
Last retransmission scan time is 0 msec, maximum is 0 msec
Simple password authentication enabled

R3#**show ip ospf interface serial 1/2**
Serial1/2 is up, line protocol is up
Internet Address 150.0.0.13/30, Area 0
Process ID 3, Router ID 3.3.3.3, Network Type POINT_TO_POINT, Cost: 781
Transmit Delay is 1 sec, State POINT_TO_POINT
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
oob-resync timeout 40
Hello due in 00:00:06
Supports Link-local Signaling (LLS)
Index 4/6, flood queue length 0

https://t.me/learningnets

Next 0x0(0)/0x0(0)
Last flood scan length is 1, maximum is 4
Last flood scan time is 0 msec, maximum is 4 msec
Neighbor Count is 1, Adjacent neighbor count is 1
Adjacent with neighbor 4.4.4.4
Suppress hello for 0 neighbor(s)
Simple password authentication enabled

R4#**show ip ospf interface serial 0/0**
Serial0/0 is up, line protocol is up
Internet Address 150.0.0.14/30, Area 0
Process ID 4, Router ID 4.4.4.4, Network Type POINT_TO_POINT, Cost: 64
Transmit Delay is 1 sec, State POINT_TO_POINT
Timer intervals configured, Hello 10, Dead 40, Wait 40, Retransmit 5
oob-resync timeout 40
Hello due in 00:00:08
Supports Link-local Signaling (LLS)
Index 2/2, flood queue length 0
Next 0x0(0)/0x0(0)
Last flood scan length is 1, maximum is 1
Last flood scan time is 0 msec, maximum is 0 msec
Neighbor Count is 1, Adjacent neighbor count is 1
Adjacent with neighbor 3.3.3.3
Suppress hello for 0 neighbor(s)
Simple password authentication enabled

Task 8

The requirements for this task are straightforward. This is completed as follows:

R1(config)#**ip cef**
R1(config)#**ipv6 unicast-routing**
R1(config)#**ipv6 router rip CCNP**
R1(config-rtr)#**exit**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ipv6 address 3ffe:abcd:1111:1::1/64**
R1(config-if)#**ipv6 rip CCNP enable**
R1(config-if)#**exit**

DLS1(config)#**ip cef**
DLS1(config)#**ipv6 unicast-routing**
DLS1(config)#**ipv6 router rip CCNP**

https://t.me/learningnets
Technet24

DLS1(config-rtr)#**exit**
DLS1(config)#**interface vlan 100**
DLS1(config-if)#**ipv6 address 3ffe:abcd:1111:1::254/64**
DLS1(config-if)#**ipv6 rip CCNP enable**
DLS1(config-if)#**exit**

DLS2(config)#**ip cef**
DLS2(config)#**ipv6 unicast-routing**
DLS2(config)#**ipv6 router rip CCNP**
DLS2(config-rtr)#**exit**
DLS2(config)#**interface vlan 100**
DLS2(config-if)#**ipv6 address 3ffe:abcd:1111:1::253/64**
DLS2(config-if)#**ipv6 rip CCNP enable**
DLS2(config-if)#**exit**

Verify your configuration using the **show ipv6 rip** commands on any of the devices:

R1#**show ipv6 rip database**
RIP process "CCNP", local RIB
3FFE:ABCD:1111:1::/64, metric 2
FastEthernet0/0/FE80::20B:FDFF:FE67:6500, expires in 164 secs
FastEthernet0/0/FE80::20F:23FF:FE03:2D80, expires in 160 secs

Task 9

To complete this task, you first need to configure Loopback interfaces on all routers and advertise these subnets via OSPF. Verify your configuration using the **show ip ospf interfaces** or **show ip route** command on all routers:

R1#**show ip ospf interface brief**
Interface PID Area IP Address/Mask Cost State Nbrs F/C
VL1 1 0 150.0.0.1/30 64 P2P 1/1
VL0 1 0 150.0.0.5/30 64 P2P 1/1
Fa0/0 1 1 150.1.1.1/24 1 DR 2/2
Se0/0 1 2 150.0.0.1/30 64 P2P 1/1
Lo0 1 3 1.1.1.1/32 1 LOOP 0/0
Se0/1 1 3 150.0.0.5/30 64 P2P 1/1

R2#**show ip ospf interface brief**
Interface PID Area IP Address/Mask Cost State Nbrs F/C
VL1 2 0 150.0.0.2/30 64 P2P 1/1
VL0 2 0 150.0.0.9/30 64 P2P 1/1
Lo0 2 2 2.2.2.2/32 1 LOOP 0/0

https://t.me/learningnets

Fa0/0 2 2 150.2.2.2/24 1 DR 0/0
Se0/0 2 2 150.0.0.2/30 64 P2P 1/1
Se0/1 2 3 150.0.0.9/30 64 P2P 1/1

R3#**show ip ospf interface brief**
Interface PID Area IP Address/Mask Cost State Nbrs F/C
Fa0/0 3 0 10.3.3.3/24 1 DR 0/0
Se1/2 3 0 150.0.0.13/30 781 P2P 1/1
VL1 3 0 150.0.0.10/30 781 P2P 1/1
VL0 3 0 150.0.0.6/30 781 P2P 1/1
Lo0 3 3 3.3.3.3/32 1 LOOP 0/0
Se1/1 3 3 150.0.0.10/30 781 P2P 1/1
Se1/0 3 3 150.0.0.6/30 781 P2P 1/1

R4#**show ip ospf interface brief**
Interface PID Area IP Address/Mask Cost State Nbrs F/C
Lo0 4 0 4.4.4.4/32 1 LOOP 0/0
Se0/0 4 0 150.0.0.14/30 64 P2P 1/1
Fa0/0 4 0 10.4.4.4/24 1 DR 0/0

Following this, configure your ISATAP tunnels using the Loopback interfaces as sources:

R1(config)#**interface tunnel 0**
R1(config-if)#**tunnel source loopback 0**
R1(config-if)#**ipv6 address fec0:abcd:1234:1::/64 eui-64**
R1(config-if)#**tunnel mode ipv6ip isatap**
R1(config-if)# **no ipv6 nd ra suppress**
R1(config-if)#**exit**

R2(config)#**interface tunnel 0**
R2(config-if)#**tunnel source loopback 0**
R2(config-if)#**ipv6 address fec0:abcd:1234:1::/64 eui-64**
R2(config-if)#**tunnel mode ipv6ip isatap**
R2(config-if)#**no ipv6 nd ra suppress**
R2(config-if)#**exit**

R3(config)#**interface tunnel 0**
R3(config-if)#**tunnel source loopback 0**
R3(config-if)#**ipv6 address fec0:abcd:1234:1::/64 eui-64**
R3(config-if)#**tunnel mode ipv6ip isatap**
R3(config-if)#**no ipv6 nd ra suppress**
R3(config-if)#**exit**

https://t.me/learningnets
Technet24

R4(config)#**interface tunnel 0**
R4(config-if)#**tunnel source loopback 0**
R4(config-if)#**ipv6 address fec0:abcd:1234:1::/64 eui-64**
R4(config-if)#**tunnel mode ipv6ip isatap**
R4(config-if)#**no ipv6 nd ra suppress**
R4(config-if)#**exit**

Verify your tunnel status using the **show interfaces tunnel <number>** command:

R1#**show interfaces tunnel 0**
Tunnel0 is up, line protocol is up
Hardware is Tunnel
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 1.1.1.1 (Loopback0), destination UNKNOWN
Tunnel protocol/transport IPv6 ISATAP

Fast tunneling enabled
Tunnel transmit bandwidth 8000 (kbps)
Tunnel receive bandwidth 8000 (kbps)
Last input never, output 00:00:35, output hang never
Last clearing of "show interface" counters never
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: fifo
Output queue: 0/0 (size/max)
5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec
0 packets input, 0 bytes, 0 no buffer
Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
4 packets output, 384 bytes, 0 underruns
0 output errors, 0 collisions, 0 interface resets
0 unknown protocol drops
0 output buffer failures, 0 output buffers swapped out

Task 10

Next, configure MP-BGP on the routers as requested in the task. This is completed as follows:

R1(config)#**router bgp 1**

https://t.me/learningnets

R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**address-family ipv6**
R1(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:202:202 remote-as 2**
R1(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:202:202 activate**
R1(config-router-af)#**network 3FFE:ABCD:1111:1::/64**
R1(config-router-af)#**exit-address-family**
R1(config-router)#**exit**

R2(config)#**ip cef**
R2(config)#**ipv6 unicast-routing**
R2(config)#**router bgp 2**
R2(config-router)#**bgp router-id 2.2.2.2**
R2(config-router)#**address-family ipv6**
R2(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:101:101 remote-as 1**
R2(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:101:101 activate**
R2(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:303:303 remote-as 3**
R2(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:303:303 activate**
R2(config-router-af)#**network 3FFE:ABCD:1111:2::/64**
R2(config-router-af)#**exit-address-family**
R2(config-router)#**exit**

R3(config)#**ip cef**
R3(config)#**ipv6 unicast-routing**
R3(config)#**router bgp 3**
R3(config-router)#**bgp router-id 3.3.3.3**
R3(config-router)#**address-family ipv6**
R3(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:202:202 remote-as 2**
R3(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:202:202 activate**
R3(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:404:404 remote-as 4**
R3(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:404:404 activate**
R3(config-router-af)#**network 3FFE:ABCD:1111:3::/64**
R3(config-router-af)#**exit-address-family**
R3(config-router)#**exit**

R4(config)#**ip cef**
R4(config)#**ipv6 unicast-routing**
R4(config)#**router bgp 4**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**address-family ipv6**
R4(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:303:303 remote-as 3**
R4(config-router-af)#**neighbor FEC0:ABCD:1234:1:0:5EFE:303:303 activate**

https://t.me/learningnets

R4(config-router-af)#**network 3FFE:ABCD:1111:4::/64**
R4(config-router-af)#**exit-address-family**
R4(config-router)#**exit**

Verify MP-BGP configuration using the **show bgp ipv6 unicast** commands:

R1#**show bgp ipv6 unicast**
BGP table version is 5, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 3FFE:ABCD:1111:1::/64
:: 0 32768 i
*> 3FFE:ABCD:1111:2::/64
FEC0:ABCD:1234:1:0:5EFE:202:202
0 0 2 i
*> 3FFE:ABCD:1111:3::/64
FEC0:ABCD:1234:1:0:5EFE:303:303
0 2 3 i
*> 3FFE:ABCD:1111:4::/64
FEC0:ABCD:1234:1:0:5EFE:404:404
0 2 3 4 i

R2#**show bgp ipv6 unicast**
BGP table version is 6, local router ID is 2.2.2.2
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 3FFE:ABCD:1111:1::/64
FEC0:ABCD:1234:1:0:5EFE:101:101
0 0 1 i
*> 3FFE:ABCD:1111:2::/64
:: 0 32768 i
*> 3FFE:ABCD:1111:3::/64
FEC0:ABCD:1234:1:0:5EFE:303:303
0 0 3 i
*> 3FFE:ABCD:1111:4::/64
FEC0:ABCD:1234:1:0:5EFE:404:404

https://t.me/learningnets

0 3 4 i

3#**show bgp ipv6 unicast**
BGP table version is 6, local router ID is 3.3.3.3
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 3FFE:ABCD:1111:1::/64
FEC0:ABCD:1234:1:0:5EFE:101:101
0 2 1 i
*> 3FFE:ABCD:1111:2::/64
FEC0:ABCD:1234:1:0:5EFE:202:202
0 0 2 i
*> 3FFE:ABCD:1111:3::/64
:: 0 32768 i
*> 3FFE:ABCD:1111:4::/64
FEC0:ABCD:1234:1:0:5EFE:404:404
0 0 4 i

R4#**show bgp ipv6 unicast**
BGP table version is 6, local router ID is 4.4.4.4
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 3FFE:ABCD:1111:1::/64
FEC0:ABCD:1234:1:0:5EFE:101:101
0 3 2 1 i
*> 3FFE:ABCD:1111:2::/64
FEC0:ABCD:1234:1:0:5EFE:202:202
0 3 2 i
*> 3FFE:ABCD:1111:3::/64
FEC0:ABCD:1234:1:0:5EFE:303:303
0 0 3 i
*> 3FFE:ABCD:1111:4::/64
:: 0 32768 i

Optionally, verify connectivity using extended LAN-to-LAN pings:

R1#**ping 3FFE:ABCD:1111:2::2 source fastethernet 0/0 repeat 10 size 1500**

https://t.me/learningnets

Technet24

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:2::2, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 208/208/212 ms

R1#**ping 3FFE:ABCD:1111:3::3 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:3::3, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 208/208/212 ms

R1#**ping 3FFE:ABCD:1111:4::4 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:ABCD:1111:4::4, timeout is 2 seconds:
Packet sent with a source address of 3FFE:ABCD:1111:1::1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 396/399/400 ms

NOTE: Perform the same tests on R2, R3 and R4 if so desired.

https://t.me/learningnets

CCNP Lab 083: CCNP Multi-Technology Lab

Lab Objective:

The objective of this lab is to cover all relevant CCNP ROUTE and SWITCH theory. These labs will include topics from each of these guides. It should be noted that not all topics will be included in all labs. Additionally, not all solutions will be illustrated in detail. You can refer to previous labs for assistance with some basic configurations.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please implement the following pre-lab configurations. This is required because of the manner in which the routers and switches are physically cabled to each other. The following configuration should be applied to switch ALS1:

```
!
hostname ALS1
!
vtp mode transparent
!
!
!
!
vlan 100
name R1-VLAN
```

https://t.me/learningnets

```
!
vlan 300
name R3-VLAN
!
vlan 400
name R4-VLAN
!
interface fastethernet 0/1
switchport access vlan 100
switchport mode access
!
interface fastethernet 0/2
shutdown
!
interface fastethernet 0/3
switchport access vlan 300
switchport mode access
!
interface fastethernet 0/4
switchport access vlan 400
switchport mode access
!
interface range fastethernet 0/5 - 6
shutdown
!
interface fastethernet0/7
switchport mode trunk
!
interface fastethernet 0/8
switchport mode trunk
!
interface range fastethernet 0/9 - 10
shutdown
!
interface range fastethernet 0/11 - 12
switchport mode trunk
!
!
```

https://t.me/learningnets

```
interface vlan 400
ip address 10.4.4.254 255.255.255.0
no shutdown
!
ip default-gateway 10.4.4.4
!
line vty 0 4
privilege level 15
password cisco
login
!
end
!
hostname ALS2
!
vtp mode transparent
!
!
!
!
!
!
vlan 300
name R3-VLAN
!
!
interface range fastethernet 0/1 - 10
shutdown
!
interface fastethernet 0/11
switchport mode trunk
!
interface fastethernet 0/12
switchport mode trunk
!
interface vlan 300
ip address 10.3.3.254 255.255.255.0
no shutdown
```

https://t.me/learningnets

```
!
ip default-gateway 10.3.3.3
!
line vty 0 4
privilege level 15
password cisco
login
!
end
!
hostname DLS1
!
ip routing
!
vtp mode transparent
!
!
!
!
vlan 100
name R1-VLAN
!
!
!
!
!
!
interface range fastethernet 0/1 - 6
shutdown
!
interface range fastethernet 0/7 - 8
switchport trunk encapsulation dot1q
switchport mode trunk
!
interface range fastethernet 0/9 - 10
shutdown
!
interface fastethernet 0/11
```

https://t.me/learningnets

```
switchport mode dynamic desirable
!
interface fastethernet 0/12
switchport mode dynamic desirable
!
interface range fastethernet 0/13 - 48
shutdown
!
!
interface vlan 100
ip address 150.1.1.254 255.255.255.0
no shutdown
!
line vty 0 4
privilege level 15
password cisco
login
!
end
!
hostname DLS2
!
ip routing
!
vtp mode transparent
!
!
!
!
vlan 100
name R1-VLAN
!
!
!
!
!
!
interface range fastethernet 0/1 - 10
```

https://t.me/learningnets

```
shutdown
!
interface fastethernet 0/11
switchport mode dynamic desirable
!
interface fastethernet 0/12
switchport mode dynamic desirable
!
interface range fastethernet 0/13 - 48
shutdown
!
!
!
line vty 0 4
privilege level 15
password cisco
login
!
end
```

If you are using the www.101labs.net racks, please bring up the LAN interface connected to R2 by the following configuration:

```
interface fastethernet 0/0
ip address 150.2.2.2 255.255.255.0
no keepalive
loopback
no shutdown
```

Alternatively, you can simply connect the interface to a hub or one of the switches and bring up the interface in the standard manner.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Configure an EtherChannel between DLS1 and DLS2. This should be a Layer 2 trunk link that is unconditionally bonded. Configure an SVI with the IP address 150.1.1.253/24 on DLS2. Verify that all devices on the 150.1.1.0/24 subnet can ping each other.

Task 3

https://t.me/learningnets

Technet24

Configure OSPF using process ID 1 on R1, DLS1 and DLS2. Ensure that no DR/BDR election will occur on the 150.1.1.0/24 subnet. All devices should peer with each other. Verify your configuration using the appropriate commands.

Task 4

Configure OSPF using process ID 2 between R1 and R2. Ensure that no OSPF Hellos are sent out the LAN interface of R2. Verify your configuration using the appropriate commands.

Task 5

Configure OSPF using process ID 3 between R1, R2 and R3. Do NOT enable OSPF on the LAN interface of R3. Verify your configuration using the appropriate commands.

Task 6

Configure EIGRP using AS 4 between R3 and R4. No EIGRP Hello packets should be sent out of the LAN interfaces of R3 or R4. R4 should be configured as a stub router. This router should advertise only connected subnets. R3 should advertise only a default route to R4. Verify EIGRP routing configuration using the appropriate commands.

Task 7

Redistribute between the OSPF processes on R1 and R2. Ensure that routes from one process will never be redistributed back into the same process. You are NOT allowed to modify the default administrative distance when completing this task. When completing this task, ensure that the cost of the routes to reflect the entire path. Verify your configuration using the appropriate commands on all routers and ensure that there are no routing loops when done.

Task 8

Configure one-way redistribution of EIGRP into OSPF on R3. Ensure that only a single prefix is advertised to the OSPF domain for the 10.3.3.0/24 and 10.4.4.0/24 subnets. The 150.0.0.12/30 subnet connecting R3 to R4 should never be advertised to the rest of the OSPF domain. You are NOT allowed to use a distribute-list to complete this task. Verify that all other routers are able to reach the R3 and R4 LAN subnets and vice-versa.

Task 9

Management has advised that a new video solution will be implemented in the network. The IP Multicast server will reside on R1s LAN and clients will reside on R4s LAN. Configure PIM Dense Mode and assign R1s LAN interface to the 227.1.1.1 group and verify that you can ping this from R4s LAN interface. This should work even if the R1-R3 or the R2-R3 link is down.

https://t.me/learningnets

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for EtherChannel configuration. This will not be included in this section to avoid being redundant. Verify your solution using the **show etherchannel** commands on both switches:

DLS1#**show etherchannel summary**
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
------+-------------+-----------+---
10 Po10(SU) - Fa0/11(P) Fa0/12(P)

DLS2#show etherchannel summary
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 1
Number of aggregators: 1

https://t.me/learningnets

Technet24

Group Port-channel Protocol Ports
------+-------------+-----------+--
10 Po10(SU) - Fa0/11(P) Fa0/12(P)

After configuring the SVI on switch DLS2, verify reachability on the 150.1.1.0/24 subnet:

DLS2#**ping 150.1.1.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.0, timeout is 2 seconds:
.
Reply to request 1 from 150.1.1.254, 1 ms
Reply to request 1 from 150.1.1.1, 1 ms
Reply to request 2 from 150.1.1.254, 1 ms
Reply to request 2 from 150.1.1.1, 1 ms
Reply to request 3 from 150.1.1.254, 1 ms
Reply to request 3 from 150.1.1.1, 1 ms
Reply to request 4 from 150.1.1.254, 1 ms
Reply to request 4 from 150.1.1.1, 1 ms

Task 3

To complete this task, you need to configure an OSPF point-to-multipoint network type. All of the devices should reside in OSPF area 0. Verify OSPF using the **show ip ospf** commands:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
150.1.1.253 0 FULL/ - 00:01:43 150.1.1.253 FastEthernet0/0
150.1.1.254 0 FULL/ - 00:01:43 150.1.1.254 FastEthernet0/0

DLS1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
150.1.1.253 0 FULL/ - 00:01:47 150.1.1.253 Vlan100
11.11.11.11 0 FULL/ - 00:01:47 150.1.1.1 Vlan100

DLS2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
150.1.1.254 0 FULL/ - 00:01:56 150.1.1.254 Vlan100
11.11.11.11 0 FULL/ - 00:01:57 150.1.1.1 Vlan100

To view the network type, use the **show ip ospf interface** command:

DLS2#**show ip ospf interface vlan 100**

https://t.me/learningnets

Vlan100 is up, line protocol is up
Internet Address 150.1.1.253/24, Area 0
Process ID 1, Router ID 150.1.1.253, Network Type POINT_TO_MULTIPOINT, Cost: 1
Transmit Delay is 1 sec, State POINT_TO_MULTIPOINT
Timer intervals configured, Hello 30, Dead 120, Wait 120, Retransmit 5
oob-resync timeout 120
Hello due in 00:00:28
Supports Link-local Signaling (LLS)
Cisco NSF helper support enabled
IETF NSF helper support enabled
Index 1/1, flood queue length 0
Next 0x0(0)/0x0(0)
Last flood scan length is 1, maximum is 1
Last flood scan time is 0 msec, maximum is 0 msec
Neighbor Count is 2, Adjacent neighbor count is 2
Adjacent with neighbor 11.11.11.11
Adjacent with neighbor 150.1.1.254
Suppress hello for 0 neighbor(s)

Task 4

The same logic applied in the previous task should also be used to complete this task. Following this, verify OSPF configuration using the **show ip ospf** commands:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
22.22.22.11 0 FULL/ - 00:00:34 150.0.0.2 Serial0/0
150.1.1.253 0 FULL/ - 00:01:47 150.1.1.253 FastEthernet0/0
150.1.1.254 0 FULL/ - 00:01:51 150.1.1.254 FastEthernet0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
11.11.11.22 0 FULL/ - 00:00:32 150.0.0.1 Serial0/0

Task 5

The same logic applied in the previous task should also be used to complete this task. Following this, verify OSPF configuration using the **show ip ospf** commands:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
33.33.33.33 0 FULL/ - 00:00:37 150.0.0.6 Serial0/1

https://t.me/learningnets
Technet24

22.22.22.11 0 FULL/ - 00:00:34 150.0.0.2 Serial0/0
150.1.1.253 0 FULL/ - 00:01:31 150.1.1.253 FastEthernet0/0
150.1.1.254 0 FULL/ - 00:01:35 150.1.1.254 FastEthernet0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
33.33.33.33 0 FULL/ - 00:00:35 150.0.0.10 Serial0/1
11.11.11.22 0 FULL/ - 00:00:35 150.0.0.1 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
22.22.22.33 0 FULL/ - 00:00:39 150.0.0.9 Serial1/1
11.11.11.33 0 FULL/ - 00:00:39 150.0.0.5 Serial1/0

To verify which interfaces are enabled under which process, use the **show ip ospf interface** brief command on the router or switch:

R1#**show ip ospf interface brief**
Interface **PID** Area IP Address/Mask Cost State Nbrs F/C
Se0/1 **3** 0 150.0.0.5/30 64 P2P 1/1
Se0/0 **2** 0 150.0.0.1/30 64 P2P 1/1
Fa0/0 **1** 0 150.1.1.1/24 1 P2MP 2/2

Task 6

The configuration requirements of this task are straightforward. To ensure that R3 sends only a default route to R4, you need to enable filtering and configure the router to generate and advertise a default. Once complete, verify the solution using the **show ip eigrp** commands:

R3#**show ip eigrp neighbors detail**
IP-EIGRP neighbors for process 4
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.0.0.14 Se1/2 10 00:01:00 11 1140 0 8
Restart time 00:00:08
Version 12.4/1.2, Retrans: 1, Retries: 0, Prefixes: 1
Stub Peer Advertising (CONNECTED) Routes
Suppressing queries

On R4, use the **show ip route** command to ensure that only a default is received from R3:

R4#**show ip route eigrp**

https://t.me/learningnets

D* 0.0.0.0/0 [90/2172416] via 150.0.0.13, 00:00:28, Serial0/0

Task 7

This task requires some thought. You need to implement route filtering when redistributing between the OSPF processes. EIGRP is great in such situations because external routes are assigned a higher administrative distance than internal routes - meaning that the likelihood of routing loops in such scenarios is very slim. The same concept could also be applied to OSPF; however, the task explicitly states that we should not modify default administrative distance values. Therefore, we must use filtering. This task is completed as follows:

R1(config)#**ip prefix-list PROCESS-1-FILTER seq 5 permit 150.1.1.0/24**
R1(config)#**ip prefix-list PROCESS-2-FILTER seq 5 permit 150.0.0.0/30**
R1(config)#**ip prefix-list PROCESS-2-FILTER seq 7 permit 150.2.2.0/24**
R1(config)#**ip prefix-list PROCESS-3-FILTER seq 5 permit 150.0.0.4/30**
R1(config)#**ip prefix-list PROCESS-3-FILTER seq 7 permit 150.0.0.8/30**
R1(config)#**route-map PROCESS-1-FILTER deny 10**
R1(config-route-map)#**match ip address prefix-list PROCESS-1-FILTER**
R1(config-route-map)#**exit**
R1(config)#**route-map PROCESS-1-FILTER permit 20**
R1(config-route-map)#**exit**
R1(config)#**route-map PROCESS-2-FILTER deny 10**
R1(config-route-map)#**match ip address prefix-list PROCESS-2-FILTER**
R1(config-route-map)#**exit**
R1(config)#**route-map PROCESS-2-FILTER permit 20**
R1(config-route-map)#**exit**
R1(config)#**route-map PROCESS-3-FILTER deny 10**
R1(config-route-map)#**match ip address prefix-list PROCESS-3-FILTER**
R1(config-route-map)#**exit**
R1(config)#**route-map PROCESS-3-FILTER permit 20**
R1(config-route-map)#**exit**
R1(config)#**router ospf 1**
R1(config-router)#**redistribute ospf 2 subnets route-map PROCESS-1-FILTER**
R1(config-router)#**redistribute ospf 3 subnets route-map PROCESS-1-FILTER**
R1(config-router)#**exit**
R1(config)#**router ospf 2**
R1(config-router)#**redistribute ospf 1 subnets route-map PROCESS-2-FILTER**
R1(config-router)#**redistribute ospf 3 subnets route-map PROCESS-2-FILTER**
R1(config-router)#**exit**

https://t.me/learningnets

Technet24

R1(config)#**router ospf 3**
R1(config-router)#**redistribute ospf 1 subnets route-map PROCESS-3-FILTER**
R1(config-router)#**redistribute ospf 2 subnets route-map PROCESS-3-FILTER**

The redistribution configuration on R2 would be implemented similar to the following:

R2(config)#**ip prefix-list PROCESS-2-FILTER seq 5 permit 150.0.0.0/30**
R2(config)#**ip prefix-list PROCESS-2-FILTER seq 7 permit 150.2.2.0/24**
R2(config)#**ip prefix-list PROCESS-3-FILTER seq 5 permit 150.0.0.4/30**
R2(config)#**ip prefix-list PROCESS-3-FILTER seq 7 permit 150.0.0.8/30**
R2(config)#**route-map PROCESS-2-FILTER deny 10**
R2(config-route-map)#**match ip address prefix-list PROCESS-2-FILTER**
R2(config-route-map)#**exit**
R2(config)#**route-map PROCESS-2-FILTER permit 20**
R2(config-route-map)#**exit**
R2(config)#**route-map PROCESS-3-FILTER deny 10**
R2(config-route-map)#**match ip address prefix-list PROCESS-3-FILTER**
R2(config-route-map)#**exit**
R2(config)#**route-map PROCESS-3-FILTER permit 20**
R2(config-route-map)#**exit**
R2(config)#**router ospf 2**
R2(config-router)#**redistribute ospf 3 subnets route-map PROCESS-2-FILTER**
R2(config-router)#**exit**
R2(config)#**router ospf 3**
R2(config-router)#**redistribute ospf 2 subnets route-map PROCESS-3-FILTER**
R2(config-router)#**exit**

Next, verify the Link State Databases of all devices using the **show ip ospf** commands:

DLS1#**show ip ospf database**

OSPF Router with ID (150.1.1.254) (Process ID 1)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
11.11.11.11 11.11.11.11 173 0x80000003 0x00EFCD 3
150.1.1.253 150.1.1.253 90 0x80000008 0x00ADAB 3
150.1.1.254 150.1.1.254 1935 0x80000007 0x00D382 3

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.0.0.0 11.11.11.11 510 0x80000001 0x009E16 0
150.0.0.4 11.11.11.11 500 0x80000001 0x00763A 0

https://t.me/learningnets

150.0.0.8 11.11.11.11 500 0x80000001 0x00EBB0 0
150.2.2.0 11.11.11.11 510 0x80000001 0x008C20 0

DLS2#**show ip ospf database**

OSPF Router with ID (150.1.1.253) (Process ID 1)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
11.11.11.11 11.11.11.11 163 0x80000003 0x00EFCD 3
150.1.1.253 150.1.1.253 79 0x80000008 0x00ADAB 3
150.1.1.254 150.1.1.254 1926 0x80000007 0x00D382 3

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.0.0.0 11.11.11.11 501 0x80000001 0x009E16 0
150.0.0.4 11.11.11.11 491 0x80000001 0x00763A 0
150.0.0.8 11.11.11.11 491 0x80000001 0x00EBB0 0
150.2.2.0 11.11.11.11 501 0x80000001 0x008C20 0

R1#**show ip ospf database**

OSPF Router with ID (11.11.11.33) (Process ID 3)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
11.11.11.33 11.11.11.33 921 0x80000003 0x00FB68 2
22.22.22.33 22.22.22.33 689 0x80000003 0x00F524 2
33.33.33.33 33.33.33.33 2008 0x80000002 0x00C1E4 4

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.0.0.0 11.11.11.33 118 0x80000002 0x009489 0
150.0.0.0 22.22.22.33 106 0x80000002 0x008B71 0
150.1.1.0 11.11.11.33 128 0x80000002 0x001741 0
150.1.1.0 22.22.22.33 106 0x80000003 0x008E67 0
150.1.1.253 11.11.11.33 128 0x80000002 0x002B2F 0
150.1.1.253 22.22.22.33 106 0x80000003 0x00A255 0
150.1.1.254 11.11.11.33 128 0x80000002 0x002138 0
150.1.1.254 22.22.22.33 106 0x80000003 0x00985E 0
150.2.2.0 11.11.11.33 119 0x80000002 0x008293 0
150.2.2.0 22.22.22.33 107 0x80000002 0x00F63E 0

OSPF Router with ID (11.11.11.22) (Process ID 2)

https://t.me/learningnets

Technet24

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
11.11.11.22 11.11.11.22 993 0x80000004 0x003484 2
22.22.22.11 22.22.22.11 731 0x80000002 0x0042B5 3

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.0.0.4 11.11.11.22 173 0x80000002 0x00AE76 0
150.0.0.4 22.22.22.11 154 0x80000002 0x008579 0
150.0.0.8 11.11.11.22 173 0x80000002 0x0024EC 0
150.0.0.8 22.22.22.11 154 0x80000002 0x00BF4B 0
150.1.1.0 11.11.11.22 183 0x80000002 0x00590A 0
150.1.1.253 11.11.11.22 183 0x80000002 0x006DF7 0
150.1.1.254 11.11.11.22 183 0x80000002 0x006301 0

OSPF Router with ID (11.11.11.11) (Process ID 1)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
11.11.11.11 11.11.11.11 678 0x80000003 0x00EFCD 3
150.1.1.253 150.1.1.253 599 0x80000008 0x00ADAB 3
150.1.1.254 150.1.1.254 403 0x80000008 0x00D183 3

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.0.0.0 11.11.11.11 200 0x80000002 0x00191B 0
150.0.0.4 11.11.11.11 190 0x80000002 0x00F03F 0
150.0.0.8 11.11.11.11 190 0x80000002 0x0066B5 0
150.2.2.0 11.11.11.11 200 0x80000002 0x000725 0

R2#**show ip ospf database**

OSPF Router with ID (22.22.22.33) (Process ID 3)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
11.11.11.33 11.11.11.33 914 0x80000003 0x00FB68 2
22.22.22.33 22.22.22.33 678 0x80000003 0x00F524 2
33.33.33.33 33.33.33.33 1998 0x80000002 0x00C1E4 4

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.0.0.0 11.11.11.33 111 0x80000002 0x009489 0

https://t.me/learningnets

150.0.0.0 22.22.22.33 95 0x80000002 0x008B71 0
150.1.1.0 11.11.11.33 121 0x80000002 0x001741 0
150.1.1.0 22.22.22.33 95 0x80000003 0x008E67 0
150.1.1.253 11.11.11.33 121 0x80000002 0x002B2F 0
150.1.1.253 22.22.22.33 95 0x80000003 0x00A255 0
150.1.1.254 11.11.11.33 121 0x80000002 0x002138 0
150.1.1.254 22.22.22.33 95 0x80000003 0x00985E 0
150.2.2.0 11.11.11.33 112 0x80000002 0x008293 0
150.2.2.0 22.22.22.33 96 0x80000002 0x00F63E 0

OSPF Router with ID (22.22.22.11) (Process ID 2)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
11.11.11.22 11.11.11.22 945 0x80000004 0x003484 2
22.22.22.11 22.22.22.11 681 0x80000002 0x0042B5 3

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.0.0.4 11.11.11.22 125 0x80000002 0x00AE76 0
150.0.0.4 22.22.22.11 104 0x80000002 0x008579 0
150.0.0.8 11.11.11.22 125 0x80000002 0x0024EC 0
150.0.0.8 22.22.22.11 104 0x80000002 0x00BF4B 0
150.1.1.0 11.11.11.22 135 0x80000002 0x00590A 0
150.1.1.253 11.11.11.22 135 0x80000002 0x006DF7 0
150.1.1.254 11.11.11.22 135 0x80000002 0x006301 0

R3#**show ip ospf database**

OSPF Router with ID (33.33.33.33) (Process ID 3)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
11.11.11.33 11.11.11.33 928 0x80000003 0x00FB68 2
22.22.22.33 22.22.22.33 694 0x80000003 0x00F524 2
33.33.33.33 33.33.33.33 2012 0x80000002 0x00C1E4 4

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
150.0.0.0 11.11.11.33 125 0x80000002 0x009489 0
150.0.0.0 22.22.22.33 110 0x80000002 0x008B71 0
150.1.1.0 11.11.11.33 135 0x80000002 0x001741 0
150.1.1.0 22.22.22.33 110 0x80000003 0x008E67 0

https://t.me/learningnets

150.1.1.253 11.11.11.33 135 0x80000002 0x002B2F 0
150.1.1.253 22.22.22.33 110 0x80000003 0x00A255 0
150.1.1.254 11.11.11.33 135 0x80000002 0x002138 0
150.1.1.254 22.22.22.33 110 0x80000003 0x00985E 0
150.2.2.0 11.11.11.33 126 0x80000002 0x008293 0
150.2.2.0 22.22.22.33 111 0x80000002 0x00F63E 0

Verify your IP routing tables using the **show ip route** commands:

R1#**show ip route ospf**
150.0.0.0/30 is subnetted, 3 subnets
O 150.0.0.8 [110/845] via 150.0.0.6, 00:12:59, Serial0/1
150.1.0.0/16 is variably subnetted, 3 subnets, 2 masks
O 150.1.1.254/32 [110/1] via 150.1.1.254, 00:17:46, FastEthernet0/0
O 150.1.1.253/32 [110/1] via 150.1.1.253, 00:17:46, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 150.0.0.2, 00:13:00, Serial0/0

R2#**show ip route ospf**
150.0.0.0/30 is subnetted, 3 subnets
O 150.0.0.4 [110/845] via 150.0.0.10, 00:13:04, Serial0/1
150.1.0.0/16 is variably subnetted, 3 subnets, 2 masks
O E1 150.1.1.254/32 [110/65] via 150.0.0.1, 00:04:02, Serial0/0
O E1 150.1.1.253/32 [110/65] via 150.0.0.1, 00:04:02, Serial0/0
O E1 150.1.1.0/24 [110/65] via 150.0.0.1, 00:04:02, Serial0/0

R3#**show ip route ospf**
150.0.0.0/30 is subnetted, 4 subnets
O E1 150.0.0.0 [110/845] via 150.0.0.9, 00:03:28, Serial1/1
[110/845] via 150.0.0.5, 00:03:28, Serial1/0
150.1.0.0/16 is variably subnetted, 3 subnets, 2 masks
O E1 150.1.1.254/32 [110/782] via 150.0.0.5, 00:03:28, Serial1/0
O E1 150.1.1.253/32 [110/782] via 150.0.0.5, 00:03:28, Serial1/0
O E1 150.1.1.0/24 [110/782] via 150.0.0.5, 00:03:28, Serial1/0
150.2.0.0/24 is subnetted, 1 subnets
O E1 150.2.2.0 [110/782] via 150.0.0.9, 00:03:28, Serial1/1

NOTE: Keep in mind that your output may vary slightly from what is printed above depending on the solution you implemented and the manner in which routes were received.

Task 8

https://t.me/learningnets

To complete this task, you need to first use the **summary-address** OSPF command on R3:

R3(config)#**router ospf 3**
R3(config-router)#**summary-address 10.0.0.0 255.0.0.0**
R3(config-router)#**summary-address 150.0.0.12 255.255.255.252 not-advertise**
R3(config-router)#**redistribute eigrp 4 subnets**
R3(config-router)#**exit**

Next, you need to update the redistribution configuration so that this route is not redistributed back into OSPF process ID 3 on either R1 or R2:

R1(config)#**ip prefix-list PROCESS-3-FILTER seq 9 deny 10.0.0.0/8**
R1(config)#**end**
R1#**clear ip ospf redistribution**

R2(config)#**ip prefix-list PROCESS-3-FILTER seq 9 permit 10.0.0.0/8**
R2(config)#**end**
R2#**clear ip ospf redistribution**

Verify your configuration using the **show ip ospf** commands:

R3#**show ip ospf database**

OSPF Router with ID (33.33.33.33) (Process ID 3)

Router Link States (Area 0)

Link ID ADV Router Age Seq# Checksum Link count
11.11.11.33 11.11.11.33 126 0x80000004 0x00F969 2
22.22.22.33 22.22.22.33 1737 0x80000003 0x00F524 2
33.33.33.33 33.33.33.33 476 0x80000004 0x00C3DE 4

Type-5 AS External Link States

Link ID ADV Router Age Seq# Checksum Tag
10.0.0.0 33.33.33.33 241 0x80000001 0x00838E 0

[Truncated Output]

Use the **show ip route** command to ensure that the 150.0.0.12/30 subnet is not advertised:

R1#**show ip route ospf**
O E2 10.0.0.0/8 [110/20] via 150.0.0.6, 00:06:49, Serial0/1
150.0.0.0/30 is subnetted, 3 subnets
O 150.0.0.8 [110/845] via 150.0.0.6, 00:10:39, Serial0/1
150.1.0.0/16 is variably subnetted, 3 subnets, 2 masks
O 150.1.1.254/32 [110/1] via 150.1.1.254, 00:36:27, FastEthernet0/0

https://t.me/learningnets

Technet24

O 150.1.1.253/32 [110/1] via 150.1.1.253, 00:36:27, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 150.0.0.2, 00:31:41, Serial0/0

R2#**show ip route ospf**
O E2 10.0.0.0/8 [110/20] via 150.0.0.10, 00:07:36, Serial0/1
150.0.0.0/30 is subnetted, 3 subnets
O 150.0.0.4 [110/845] via 150.0.0.10, 00:11:25, Serial0/1
150.1.0.0/16 is variably subnetted, 3 subnets, 2 masks
O E1 150.1.1.254/32 [110/65] via 150.0.0.1, 00:04:29, Serial0/0
O E1 150.1.1.253/32 [110/65] via 150.0.0.1, 00:04:29, Serial0/0
O E1 150.1.1.0/24 [110/65] via 150.0.0.1, 00:04:29, Serial0/0

Finally, verify your configurations using simple pings between all routers. For example, ping from switch DLS2 to all other routers, and work through each router:

DLS2#**ping 150.2.2.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/3/4 ms

DLS2#**ping 10.3.3.3**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.3.3.3, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 16/16/16 ms

DLS2#**ping 10.4.4.4**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 10.4.4.4, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/28/32 ms

Repeat the same exercise for all other routers in the network.

Task 9

To complete this task, you need to enable Dense Mode forwarding on ALL interfaces along the path. Next, verify using the **show ip pim** commands:

R1#**show ip pim interface**

Address Interface Ver/ Nbr Query DR DR
Mode Count Intvl Prior

https://t.me/learningnets

150.0.0.1 Serial0/0 v2/D 1 30 1 0.0.0.0
150.0.0.5 Serial0/1 v2/D 1 30 1 0.0.0.0
150.1.1.1 FastEthernet0/0 v2/D 0 30 1 150.1.1.1

R2#**show ip pim interface**

Address Interface Ver/ Nbr Query DR DR
Mode Count Intvl Prior
150.0.0.2 Serial0/0 v2/D 1 30 1 0.0.0.0
150.0.0.9 Serial0/1 v2/D 1 30 1 0.0.0.0

R3#**show ip pim interface**

Address Interface Ver/ Nbr Query DR DR
Mode Count Intvl Prior
150.0.0.6 Serial1/0 v2/D 1 30 1 0.0.0.0
150.0.0.10 Serial1/1 v2/D 1 30 1 0.0.0.0
150.0.0.13 Serial1/2 v2/D 1 30 1 0.0.0.0

R4#**show ip pim interface**

Address Interface Ver/ Nbr Query DR DR
Mode Count Intvl Prior
150.0.0.14 Serial0/0 v2/D 1 30 1 0.0.0.0
10.4.4.4 FastEthernet0/0 v2/D 0 30 1 10.4.4.4

You can also use the **show ip pim neighbor** command for detailed neighbor information:

R2#**show ip pim neighbor**
PIM Neighbor Table
Mode: B - Bidir Capable, DR - Designated Router, N - Default DR Priority,
S - State Refresh Capable
Neighbor Interface Uptime/Expires Ver DR
Address Prio/Mode
150.0.0.1 Serial0/0 00:03:39/00:01:31 v2 1 / S
150.0.0.10 Serial0/1 00:03:54/00:01:16 v2 1 / S

To view Multicast group(s) information, use the **show ip igmp** commands:

R1#**show ip igmp groups detail**

Flags: L - Local, U - User, SG - Static Group, VG - Virtual Group,
SS - Static Source, VS - Virtual Source,
Ac - Group accounted towards access control limit

Interface: FastEthernet0/0
Group: 227.1.1.1

https://t.me/learningnets

Flags: L U
Uptime: 00:04:54
Group mode: EXCLUDE (Expires: 00:02:34)
Last reporter: 150.1.1.1
Source list is empty

Interface: Serial0/0
Group: 224.0.1.40
Flags: L U
Uptime: 00:06:02
Group mode: INCLUDE
Last reporter: 150.0.0.1
Source list is empty

Finally, test your solution by pinging group 227.1.1.1 from the LAN interface of R4:

R4#**ping 227.1.1.1 source fastethernet 0/0**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 227.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 10.4.4.4

Reply to request 0 from 150.0.0.5, 36 ms

https://t.me/learningnets

CCNP Lab 084: CCNP Multi-Technology Lab

Lab Objective:

The objective of this lab is to cover all relevant CCNP ROUTE and SWITCH theory. These labs will include topics from each of these guides. It should be noted that not all topics will be included in all labs. Additionally, not all solutions will be illustrated in detail. You can refer to previous labs for assistance with some basic configurations.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please implement the following pre-lab configurations. This is required because of the manner in which the routers and switches are physically cabled to each other. The following configuration should be applied to switch ALS1:

```
!
hostname ALS1
!
vtp mode transparent
!
vlan 100
name R1-VLAN
!
vlan 300
name R3-VLAN
```

https://t.me/learningnets

```
!
vlan 400
name R4-VLAN
!
interface fastethernet 0/1
switchport access vlan 100
switchport mode access
!
interface fastethernet 0/2
shutdown
!
interface fastethernet 0/3
switchport access vlan 300
switchport mode access
!
interface fastethernet 0/4
switchport access vlan 400
switchport mode access
!
interface range fastethernet 0/5 - 6
shutdown
!
interface fastethernet0/7
switchport mode trunk
!
interface fastethernet 0/8
switchport mode trunk
!
interface range fastethernet 0/9 - 10
shutdown
!
interface range fastethernet 0/11 - 12
switchport mode trunk
!
!
interface vlan 400
ip address 10.4.4.254 255.255.255.0
no shutdown
```

https://t.me/learningnets

```
!
ip default-gateway 10.4.4.4
!
line vty 0 4
privilege level 15
password cisco
login
!
end
!
hostname ALS2
!
vtp mode transparent
!
vlan 300
name R3-VLAN
!
interface range fastethernet 0/1 - 10
shutdown
!
interface fastethernet 0/11
switchport mode trunk
!
interface fastethernet 0/12
switchport mode trunk
!
interface vlan 300
ip address 10.3.3.254 255.255.255.0
no shutdown
!
ip default-gateway 10.3.3.3
!
line vty 0 4
privilege level 15
password cisco
login
!
end
```

https://t.me/learningnets

```
!
hostname DLS1
!
ip routing
!
vtp mode transparent
!
vlan 100
name R1-VLAN
!
interface range fastethernet 0/1 - 6
shutdown
!
interface range fastethernet 0/7 - 8
switchport trunk encapsulation dot1q
switchport mode trunk
!
interface range fastethernet 0/9 - 10
shutdown
!
interface fastethernet 0/11
switchport mode dynamic desirable
!
interface fastethernet 0/12
switchport mode dynamic desirable
!
interface range fastethernet 0/13 - 48
shutdown
!
interface vlan 100
ip address 150.1.1.254 255.255.255.0
no shutdown
!
line vty 0 4
privilege level 15
password cisco
login
!
```

https://t.me/learningnets

Technet24

```
end
!
hostname DLS2
!
ip routing
!
vtp mode transparent
!
vlan 100
name R1-VLAN
!
interface vlan 100
ip address 150.1.1.253 255.255.255.0
no shutdown
!
interface range fastethernet 0/1 - 10
shutdown
!
interface fastethernet 0/11
switchport mode dynamic desirable
!
interface fastethernet 0/12
switchport mode dynamic desirable
!
interface range fastethernet 0/13 - 48
shutdown
!
line vty 0 4
privilege level 15
password cisco
login
!
end
```

If you are using the www.101labs.net racks, please bring up the LAN interface connected to R2 by the following configuration:

```
interface fastethernet 0/0
ip address 150.2.2.2 255.255.255.0
no keepalive
```

https://t.me/learningnets

loopback
no shutdown

Alternatively, you can simply connect the interface to a hub or one of the switches and bring up the interface in the standard manner.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Configure an EtherChannel between DLS1 and DLS2. This should be a Layer 2 trunk link that uses PAgP. Assign IP address 150.1.1.253/24 to switch DLS2. Finally, verify that all devices on the 150.1.1.0/24 subnet can ping each other.

Task 3

To ensure a consistent Spanning Tree topology, ensure that ALS1 will be the root for all of the configured VLANs. Should a superior BPDU be received, the port should be disabled. Verify your configuration using the appropriate commands.

Task 4

Configure the EtherChannel between DLS1 and DLS2 to load distribution based on the destination MAC address. Verify your configuration.

Next, management has requested that all ports on ALS1 that are connected to the routers be configured in such a manner that if a BPDU is received, the ports are disabled. These ports should be re-enabled after 10 minutes. Implement this solution and verify your configuration.

Task 5

Configure BGP using AS 1 on R1, DLS1 and DLS2. Ensure that Non-Stop Forwarding (NSF) for BGP is enabled and all routers peer with each other. Verify your configuration using the appropriate commands.

Task 6

Configure OSPF between R1, R2, and R3 as illustrated in the topology. Ensure that OSPF Hellos are not sent out the LAN interfaces of R2. Do NOT enable OSPF for the LAN segments connected to R1 or R3. Verify your OSPF configuration using the appropriate commands.

Task 7

Configure BGP on router R4. This router should peer with R1. Use Loopback interfaces that are comprised of the router numbers, i.e. 1.1.1.1/32 on R1 and 4.4.4.4/32 on R4. Verify your configuration using the appropriate commands. When completing this task,

https://t.me/learningnets

Technet24

you MUST adhere to these restrictions and guidelines:

- You are allowed only ONE static route on R3 - this route can NOT be a default route
- You are allowed only ONE static route on R4 - this route can NOT be a default route
- You are NOT allowed any static routes on R1 - you can NOT originate a default route

Ensure that the Loopback interfaces are advertised as EXTERNAL routes. Do NOT redistribute any other connected subnets into OSPF when completing this task. Verify your configuration using the appropriate commands.

Task 8

Configure and then advertise the following prefixes via BGP on switches DLS1 and DLS2:

- DLS1: Loopback 0 - IP Address 100.1.1.1/24
- DLS2: Loopback 0 - IP Address 200.2.2.2/24

Next, advertise the 10.4.4.4/24 subnet connected to router R4 via BGP. Do NOT advertise the 150.1.1.0/24 prefix via OSPF or BGP. Verify that the prefixes are received by all BGP speakers.

Task 9

Configure your network so that the 150.1.1.0/24 , 100.1.1.0/24, and 200.2.2.0/24 subnets can ping the 10.4.4.0/24 subnet and vice-versa. Complete this task while adhering to the following:

- You are allowed to use only ONE static route . This can either be on R1 or R3
- You are NOT allowed to use any static or default routes on R4
- You are NOT allowed to advertise the 150.1.1.0/24 subnet via OSPF or BGP

Next, test your configuration by pinging from the 150.1.1.0/24 , 100.1.1.0/24, and 200.2.2.0/24 subnets to the 10.4.4.0/24 subnet and vice-versa. All pings should be successful.

Task 10

Configure Loopback interfaces with the IP addresses 2.2.2.2/32 and 3.3.3.3/32 respectively on R2 and R3. Next, configure 6to4 prefixes on the LAN interfaces of all

https://t.me/learningnets

routers. Use the Loopback addresses to complete the 48-bit global prefix. The router number should complete the next 16-bits, for a complete site prefix. Verify your configuration using the appropriate commands.

Finally, configure 6to4 tunnels on R2 and R3. Ensure that these two routers can ping each other LAN-to-LAN across the 6to4 tunnels. Use the extended ping function for verification.

Task 11

At this point, the 10.3.3.0/24 subnet connected to R3s LAN interface should not be known to any other router, i.e. should not be advertised by OSPF. Management has requested that this subnet remain anonymous. However, they would like devices residing on this subnet to be able to reach the LAN subnets on R2 and R3 only. These devices should appear to be coming from the 150.3.3.0/24 subnet. When completing this task, you MUST adhere to the following restrictions:

- You are NOT allowed to configure any additional interfaces on R3, i.e. Loopbacks
- There should be a one-to-one translation for the 10.3.3.0/24 subnet
- Your configuration should NOT 'break' the current OSPF or BGP routing in place

Verify your configuration by pinging the 150.1.1.0/24 and 150.2.2.0/24 subnets from ALS2

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for EtherChannel configuration. This will not be included in this section to avoid being redundant. Verify your solution using the **show etherchannel** commands on both switches:

DLS1#**show etherchannel summary**
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2

https://t.me/learningnets

Technet24

U - in use f - failed to allocate aggregator

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
------+-------------+-----------+---
10 Po10(SU) PAgP Fa0/11(P) Fa0/12(P)

DLS2#**show etherchannel summary**
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
------+-------------+-----------+---
10 Po10(SU) PAgP Fa0/11(P) Fa0/12(P)

After configuring the SVI on switch DLS2, verify reachability on the 150.1.1.0/24 subnet:

DLS2#**ping 150.1.1.0**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.0, timeout is 2 seconds:
.
Reply to request 1 from 150.1.1.254, 1 ms
Reply to request 1 from 150.1.1.1, 1 ms
Reply to request 2 from 150.1.1.254, 1 ms
Reply to request 2 from 150.1.1.1, 1 ms
Reply to request 3 from 150.1.1.254, 1 ms

https://t.me/learningnets

Reply to request 3 from 150.1.1.1, 1 ms
Reply to request 4 from 150.1.1.254, 1 ms
Reply to request 4 from 150.1.1.1, 1 ms

Task 3

To complete this task you need to configure the Root Guard feature on the switch. The Root Guard feature prevents a Designated Port from becoming a Root Port. If a port on which the Root Guard feature receives a superior BPDU, it moves the port into a root-inconsistent state, thus maintaining the current Root Bridge status quo.

Unlike other STP enhancements, which can also be enabled on a global basis, Root Guard must be manually enabled on all ports where the Root Bridge should not appear. To complete this task successfully, first ensure that switch ALS1 is the root for all VLANs and then enable Root Guard on all designated ports. The first part of this task is completed as follows:

ALS1(config)#**spanning-tree vlan 1 priority 0**
ALS1(config)#**spanning-tree vlan 100 priority 0**
ALS1(config)#**spanning-tree vlan 300 priority 0**
ALS1(config)#**spanning-tree vlan 400 priority 0**

ALS1#**show spanning-tree summary**
Switch is in pvst mode
Root bridge for: VLAN0001, VLAN0100, VLAN0300, VLAN0400

[Truncated Output]

Next, to determine which ports are designated and actively forwarding, use the **show spanning-tree [vlan <number> active [detail]** command:

ALS1#**show spanning-tree vlan 100 active**

VLAN0100
Spanning tree enabled protocol ieee
Root ID Priority 100
Address 0007.8432.dd00
This bridge is the root
Hello Time 2 sec Max Age 20 sec Forward Delay 15 sec

Bridge ID Priority 100 (priority 0 sys-id-ext 100)
Address 0007.8432.dd00
Hello Time 2 sec Max Age 20 sec Forward Delay 15 sec
Aging Time 300

Interface Role Sts Cost Prio.Nbr Type

https://t.me/learningnets

Technet24

--------------- ---- --- -------- -------- ----------------
Fa0/1 Desg FWD 19 128.1 P2p
Fa0/7 Desg FWD 19 128.7 P2p
Fa0/8 Desg FWD 19 128.8 P2p
Fa0/11 Desg FWD 19 128.11 P2p
Fa0/12 Desg FWD 19 128.12 P2p

Port Fa0/1 is irrelevant because it is connected to R1. To complete this task, simply enable the Root Guard feature on the remaining trunk ports:

ALS1(config)#**interface range fastethernet 0/7 - 8 , fastethernet 0/11 - 12**
ALS1(config-if-range)#**spanning-tree guard root**
ALS1(config-if-range)#**exit**

To test Root Guard, you can increase the priority on ALS1 to 4096, for example, and configure a priority of 0 on either DLS1 or ALS2. This will result in the following error message:

06:00:49: %SPANTREE-2-ROOTGUARD_BLOCK: Root guard blocking port FastEthernet0/7 on VLAN0100.

Also, use the **show spanning-tree inconsistentports** to determine which switch the ports have been placed into an inconsistent state (Root Guard or Loop Guard) by the switch:

ALS1#**show spanning-tree inconsistentports**

Name Interface Inconsistency
------------------- ---------------------- ------------------
VLAN0100 FastEthernet0/7 Root Inconsistent
VLAN0100 FastEthernet0/8 Root Inconsistent

Number of inconsistent ports (segments) in the system : 2

Task 4

To complete this task, you need to use the port-channel load-balance command on switches DLS1 and DLS2. Next, implement BPDU Guard on the ports that routers are connected to switch ALS1. Finally, enable the err-disable recovery for BPDU Guard and specify the timer. Complete the first part of this task by configuring switches DLS1 and DLS2 as follows:

DLS1(config)#**port-channel load-balance dst-mac**

DLS2(config)#**port-channel load-balance dst-mac**

Verify load balancing using the **show etherchannel load-balance** command:

DLS1#**show etherchannel load-balance**

https://t.me/learningnets

EtherChannel Load-Balancing Configuration:
dst-mac

EtherChannel Load-Balancing Addresses Used Per-Protocol:
Non-IP: Destination MAC address
IPv4: Destination MAC address

Complete the second part of this task by configuring switch ALS1 as follows:

ALS1(config)#**interface range fastethernet 0/1 , fastethernet 0/3 - 4**
ALS1(config-if-range)#**spanning-tree bpduguard enable**
ALS1(config-if-range)#**exit**
ALS1(config)#**errdisable recovery cause bpduguard**
ALS1(config)#**errdisable recovery interval 600**

Verify BPDU Guard configuration using the **show spanning-tree interface <name> detail** command on switch ALS1:

ALS1#**show spanning-tree interface fastethernet 0/1 detail**
Port 1 (FastEthernet0/1) of VLAN0100 is forwarding
Port path cost 19, Port priority 128, Port Identifier 128.1.
Designated root has priority 100, address 0007.8432.dd00
Designated bridge has priority 100, address 0007.8432.dd00
Designated port id is 128.1, designated path cost 0
Timers: message age 0, forward delay 0, hold 0
Number of transitions to forwarding state: 1
Link type is point-to-point by default
Bpdu guard is enabled
BPDU: sent 3148, received 0

Use the **show errdisable** commands to verify the errdisable recovery reasons and intervals:

ALS1#**show errdisable recovery**
ErrDisable Reason Timer Status
---------------- --------------
udld Disabled
bpduguard Enabled
security-violatio Disabled
channel-misconfig Disabled
vmps Disabled
pagp-flap Disabled
dtp-flap Disabled
link-flap Disabled

https://t.me/learningnets

Technet24

psecure-violation Disabled
gbic-invalid Disabled
dhcp-rate-limit Disabled
unicast-flood Disabled
loopback Disabled

Timer interval: 600 seconds

Interfaces that will be enabled at the next timeout:

Task 5

The requirements for this task are straightforward. To enable NSF for BGP, you need to enable the **bgp graceful-restart** command on all devices under BGP configuration:

R1(config)#**router bgp 1**
R1(config-router)#**bgp router-id 1.1.1.1**
R1(config-router)#**neighbor 150.1.1.253 remote-as 1**
R1(config-router)#**neighbor 150.1.1.254 remote-as 1**
R1(config-router)#**bgp graceful-restart**
R1(config-router)#**exit**

DLS1(config)#**router bgp 1**
DLS1(config-router)#**bgp router-id 150.1.1.254**
DLS1(config-router)#**neighbor 150.1.1.1 remote-as 1**
DLS1(config-router)#**neighbor 150.1.1.253 remote-as 1**
DLS1(config-router)#**bgp graceful-restart**
DLS1(config-router)#**exit**

DLS2(config)#**router bgp 1**
DLS2(config-router)#**bgp router-id 150.1.1.253**
DLS2(config-router)#**neighbor 150.1.1.1 remote-as 1**
DLS2(config-router)#**neighbor 150.1.1.254 remote-as 1**
DLS2(config-router)#**bgp graceful-restart**
DLS2(config-router)#**exit**

Verify the BGP peering configuration using the **show ip bgp summary** command:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 1
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
150.1.1.253 4 1 4 5 1 0 0 00:01:24 0
150.1.1.254 4 1 5 6 1 0 0 00:03:04 0

https://t.me/learningnets

DLS1#**show ip bgp summary**
BGP router identifier 150.1.1.254, local AS number 1
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
150.1.1.1 4 1 5 4 1 0 0 00:02:45 0
150.1.1.253 4 1 3 3 1 0 0 00:00:47 0

DLS2#**show ip bgp summary**
BGP router identifier 150.1.1.253, local AS number 1
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
150.1.1.1 4 1 4 3 1 0 0 00:00:34 0
150.1.1.254 4 1 3 3 1 0 0 00:00:17 0

Verify BGP NSF configuration using the **show ip bgp neighbors <address>** command:

R1#**show ip bgp neighbors**
BGP neighbor is 150.1.1.253, remote AS 1, internal link
BGP version 4, remote router ID 150.1.1.253
BGP state = Established, up for 00:02:26
Last read 00:00:23, last write 00:00:26, hold time is 180, keepalive interval is 60 seconds
Neighbor capabilities:
Route refresh: advertised and received(old & new)
Address family IPv4 Unicast: advertised and received
Graceful Restart Capability: advertised
Message statistics:
InQ depth is 0
OutQ depth is 0
Sent Rcvd
Opens: 1 1
Notifications: 0 0
Updates: 0 0
Keepalives: 5 4
Route Refresh: 0 0
Total: 6 5
Default minimum time between advertisement runs is 0 seconds

[Truncated Output]

Task 6

https://t.me/learningnets

Technet24

Please refer to previous tasks for basic OSPF configuration. Following this, use the **show ip ospf neighbor** command to verify adjacencies:

R1#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:36 150.0.0.6 Serial0/1
2.2.2.2 0 FULL/ - 00:00:38 150.0.0.2 Serial0/0

R2#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:31 150.0.0.10 Serial0/1
1.1.1.1 0 FULL/ - 00:00:33 150.0.0.1 Serial0/0

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:37 150.0.0.9 Serial1/1
1.1.1.1 0 FULL/ - 00:00:34 150.0.0.5 Serial1/0

Next, verify routing using the show ip route command on all three routers:

R1#**show ip route ospf**
150.0.0.0/30 is subnetted, 3 subnets
O 150.0.0.8 [110/845] via 150.0.0.6, 00:00:11, Serial0/1
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 150.0.0.2, 00:00:11, Serial0/0

R2#**show ip route ospf**
150.0.0.0/30 is subnetted, 3 subnets
O 150.0.0.4 [110/845] via 150.0.0.10, 00:00:23, Serial0/1

R3#**show ip route ospf**
150.0.0.0/30 is subnetted, 4 subnets
O IA 150.0.0.0 [110/845] via 150.0.0.9, 00:00:34, Serial1/1
[110/845] via 150.0.0.5, 00:00:34, Serial1/0
150.2.0.0/24 is subnetted, 1 subnets
O IA 150.2.2.0 [110/782] via 150.0.0.9, 00:00:34, Serial1/1

Task 7

This task has several requirements. First, you must configure the specified Loopback interfaces and advertise them via BGP. Next, you need to configure BGP between R1 and R4. You must include the **neighbor <address> ebgp-multihop** command in addition to specifying the Loopback interfaces as update sources. Following that, you need to adhere to the restrictions while ensuring that the BGP session can also be established.

https://t.me/learningnets

This task is completed as follows:

R1(config)#**interface loopback 0**
R1(config-if)#**ip address 1.1.1.1 255.255.255.255**
R1(config-if)#**exit**
R1(config)#**router bgp 1**
R1(config-router)#**neighbor 4.4.4.4 remote-as 4**
R1(config-router)#**neighbor 4.4.4.4 update-source loopback 0**
R1(config-router)#**neighbor 4.4.4.4 ebgp-multihop**
R1(config-router)#**exit**
R1(config-router)#**route-map LOOPBACK0 permit 10**
R1(config-route-map)#**match interface loopback 0**
R1(config-route-map)#**exit**
R1(config)#**router ospf 1**
R1(config-router)#**redistribute connected subnets route-map LOOPBACK0**
R1(config-router)#**exit**

R3(config)#**ip route 4.4.4.4 255.255.255.255 serial 1/2**
R3(config)#**router ospf 3**
R3(config-router)#**redistribute static subnets**
R3(config-router)#**exit**

R4(config)#**interface loopback 0**
R4(config-if)#**ip address 4.4.4.4 255.255.255.255**
R4(config-if)#**exit**
R4(config)#**ip route 1.1.1.1 255.255.255.255 serial 0/0**
R4(config)#**router bgp 4**
R4(config-router)#**bgp router-id 4.4.4.4**
R4(config-router)#**neighbor 1.1.1.1 remote-as 1**
R4(config-router)#**neighbor 1.1.1.1 update-source loopback 0**
R4(config-router)#**neighbor 1.1.1.1 ebgp-multihop**
R4(config-router)#**exit**

Following this, verify BGP peering using the **show ip bgp summary** command:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 1
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
4.4.4.4 4 4 5 5 1 0 0 00:01:01 0
150.1.1.253 4 1 82 84 1 0 0 01:20:05 0
150.1.1.254 4 1 83 84 1 0 0 01:21:45 0

https://t.me/learningnets

Technet24

R4#**show ip bgp summary**
BGP router identifier 4.4.4.4, local AS number 4
BGP table version is 1, main routing table version 1

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
1.1.1.1 4 1 5 5 1 0 0 00:01:19 0

Task 8

This task is straightforward. Verify your BGP RIBs using the **show ip bgp** command:

DLS1#**show ip bgp**
BGP table version is 24, local router ID is 150.1.1.254
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* i10.4.4.0/24 4.4.4.4 0 100 0 4 i
*> 100.1.1.0/24 0.0.0.0 0 32768 i
*>i200.2.2.0 150.1.1.253 0 100 0 i

DLS2#**show ip bgp**
BGP table version is 8, local router ID is 150.1.1.253
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
* i10.4.4.0/24 4.4.4.4 0 100 0 4 i
*>i100.1.1.0/24 150.1.1.254 0 100 0 i
*> 200.2.2.0 0.0.0.0 0 32768 i

R1#**show ip bgp**
BGP table version is 10, local router ID is 1.1.1.1
Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 10.4.4.0/24 4.4.4.4 0 0 4 i
*>i100.1.1.0/24 150.1.1.254 0 100 0 i
*>i200.2.2.0 150.1.1.253 0 100 0 i

R4#**show ip bgp**
BGP table version is 6, local router ID is 4.4.4.4

https://t.me/learningnets

Status codes: s suppressed, d damped, h history, * valid, > best, i - internal,
r RIB-failure, S Stale
Origin codes: i - IGP, e - EGP, ? - incomplete

Network Next Hop Metric LocPrf Weight Path
*> 10.4.4.0/24 0.0.0.0 0 32768 i
*> 100.1.1.0/24 1.1.1.1 0 1 i
*> 200.2.2.0 1.1.1.1 0 1 i

Task 9

This task is not as complex as it might appear if you have a good understanding of BGP and IP routing in general. First, because switches DLS1 and DLS2 do not know about the 4.4.4.4/32 prefix, they will show the route received from R4 as inaccessible. This can be verified as follows:

DLS1#**show ip bgp 10.4.4.0 255.255.255.0**
BGP routing table entry for 10.4.4.0/24, version 24
Paths: (1 available, no best path)
Not advertised to any peer
4
4.4.4.4 (inaccessible) from 150.1.1.1 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, internal

DLS2#**show ip bgp 10.4.4.0 255.255.255.0**
BGP routing table entry for 10.4.4.0/24, version 8
Paths: (1 available, no best path)
Not advertised to any peer
4
4.4.4.4 (inaccessible) from 150.1.1.1 (1.1.1.1)
Origin IGP, metric 0, localpref 100, valid, internal

To resolve this, you will need to modify the BGP NEXT_HOP attribute on R1 so that this field is updated to reflect R1 as the NEXT_HOP instead.

Second, while BOTH the 100.1.1.0/24 and 200.2.2.0/24 prefixes are advertised by R1 to R4, the 150.1.1.0/24 prefix is not. This means that we will instead need to advertise a default route to router R2 and R3 via OSPF. This will allow these routers to forward packets destined to this subnet to R1 - where the subnet resides.

Third, we also need to advertise a default route via BGP to R4. This will allow R4 to reach the 150.1.1.0/24 subnet (via R3). And finally, we are allowed to use a single static route on either R1 or R3. We will choose to use this on R3 and configure a static route for the 10.1.1.0/24 prefix. This prefix will then be redistributed into OSPF,

https://t.me/learningnets
Technet24

allowing all routers to know about the location of this subnet. This task is therefore completed as follows:

R1(config)#**router bgp 1**
R1(config-router)#**neighbor 150.1.1.253 next-hop-self**
R1(config-router)#**neighbor 150.1.1.254 next-hop-self**
R1(config-router)#**neighbor 4.4.4.4 default-originate**
R1(config-router)#**exit**
R1(config)#**router ospf 1**
R1(config-router)#**default-information originate always**
R1(config-router)#**exit**

R3(config)#**ip route 10.4.4.0 255.255.255.0 serial 1/2**
R3(config)#**end**
R3#**clear ip ospf redistribution**

Following this, verify the routing tables of all devices using the **show ip route** command:

R1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

1.0.0.0/32 is subnetted, 1 subnets
C 1.1.1.1 is directly connected, Loopback0
100.0.0.0/24 is subnetted, 1 subnets
B 100.1.1.0 [200/0] via 150.1.1.254, 00:21:26
4.0.0.0/32 is subnetted, 1 subnets
O E2 4.4.4.4 [110/20] via 150.0.0.6, 00:00:27, Serial0/1
B 200.2.2.0/24 [200/0] via 150.1.1.253, 00:20:59
10.0.0.0/24 is subnetted, 1 subnets
B 10.4.4.0 [20/0] via 4.4.4.4, 00:00:22
150.0.0.0/30 is subnetted, 3 subnets
C 150.0.0.4 is directly connected, Serial0/1
C 150.0.0.0 is directly connected, Serial0/0
O 150.0.0.8 [110/845] via 150.0.0.6, 00:17:23, Serial0/1

https://t.me/learningnets

150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/65] via 150.0.0.2, 00:17:25, Serial0/0

R2#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O E2 1.1.1.1 [110/20] via 150.0.0.1, 00:18:22, Serial0/0
4.0.0.0/32 is subnetted, 1 subnets
O E2 4.4.4.4 [110/20] via 150.0.0.10, 00:01:27, Serial0/1
10.0.0.0/24 is subnetted, 1 subnets
O E2 10.4.4.0 [110/20] via 150.0.0.10, 00:01:27, Serial0/1
150.0.0.0/30 is subnetted, 3 subnets
O 150.0.0.4 [110/845] via 150.0.0.10, 00:18:22, Serial0/1
O*E2 0.0.0.0/0 [110/1] via 150.0.0.1, 00:03:20, Serial0/0

R3#**show ip route ospf**
1.0.0.0/32 is subnetted, 1 subnets
O E2 1.1.1.1 [110/20] via 150.0.0.5, 00:20:38, Serial1/0
150.0.0.0/30 is subnetted, 4 subnets
O IA 150.0.0.0 [110/845] via 150.0.0.9, 00:20:48, Serial1/1
[110/845] via 150.0.0.5, 00:20:48, Serial1/0
150.2.0.0/24 is subnetted, 1 subnets
O IA 150.2.2.0 [110/782] via 150.0.0.9, 00:20:48, Serial1/1
O*E2 0.0.0.0/0 [110/1] via 150.0.0.5, 00:05:46, Serial1/0

R4#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is 1.1.1.1 to network 0.0.0.0

1.0.0.0/32 is subnetted, 1 subnets
S 1.1.1.1 is directly connected, Serial0/0
100.0.0.0/24 is subnetted, 1 subnets
B 100.1.1.0 [20/0] via 1.1.1.1, 00:25:01
4.0.0.0/32 is subnetted, 1 subnets

https://t.me/learningnets

Technet24

C 4.4.4.4 is directly connected, Loopback0
B 200.2.2.0/24 [20/0] via 1.1.1.1, 00:24:31
10.0.0.0/24 is subnetted, 1 subnets
C 10.4.4.0 is directly connected, FastEthernet0/0
150.0.0.0/30 is subnetted, 1 subnets
C 150.0.0.12 is directly connected, Serial0/0
B* 0.0.0.0/0 [20/0] via 1.1.1.1, 00:06:12

Following this, verify end-to-end connectivity using the extended ping function on all devices:

R1#**ping 10.4.4.4 source 150.1.1.1 size 1500 repeat 10**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 10.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 150.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 380/380/384 ms

DLS1#**ping 10.4.4.4 source 100.1.1.1 size 1500 repeat 10**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 10.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 100.1.1.1
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 380/380/384 ms

DLS2#**ping 10.4.4.4 source 200.2.2.2 size 1500 repeat 10**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 10.4.4.4, timeout is 2 seconds:
Packet sent with a source address of 200.2.2.2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 380/381/384 ms

Task 10

Unlike static tunnel configuration, 6to4 tunneling has three main characteristics, which make it unique from static tunnel implementation. These characteristics are:

- Automatic or Dynamic Tunneling
- Automatic Prefix Assignment
- There is no IPv6 Route Propagation

6to4 automatic tunneling provides a dynamic method to deploy tunnels between IPv6

https://t.me/learningnets

sites over IPv4 networks. Unlike with manually configured tunnels, there is no need to manually configure tunnel source and destination addresses to establish the tunnels. Instead, the tunneling of IPv6 packets between 6to4 sites is performed dynamically based on the destination IPv6 address of the packets originated by IPv6 hosts. These packets are then encapsulated in IPv4 and IPv4 routing protocols are used to transport the packets between the source and destination hosts.

Automatic prefix assignment provides a global aggregate IPv6 prefix to each 6to4 site which is based on the 2002::/16 prefix assigned by IANA for 6to4 sites. As stated earlier in this section, the tunnel endpoint, or destination is determined by the globally unique IPv4 address embedded in a 6to4 address. This address must be an address that is globally routable. In other words, RFC 191 (private IP addresses) cannot be used for 6to4 tunnels because they are not unique. This 32-bit IPv4 address is converted to Hexadecimal and the final representation is a 48-bit prefix. For example, if the IP address 1.1.1.1 was embedded into the IPv6 6to4 prefix, the final representation would be 2002:0101:0101::/48.

And finally, 6to4 tunneling uses special addresses which are a combination of the unique IPv6 routing prefix 2002::/16 and a globally unique 32-bit IPv4 address. With 6to4 tunneling, the tunnel endpoint (destination) is determined by the globally unique IPv4 address embedded in the 6to4 address. Because 6to4 prefixes are based on unique IPv4 address, the 48-bit IPv6 routes do not need to be propagated between 6to4 sites. This task is completed as follows:

R2(config)#**interface loopback 0**
R2(config-if)#**ip address 2.2.2.2 255.255.255.255**
R2(config-if)#**exit**
R2(config)#**router ospf 2**
R2(config-router)#**redistribute connected subnets**
R2(config-router)#**exit**
R2(config)#**ipv6 unicast-routing**
R2(config)#**ip cef**
R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ipv6 address 2002:202:202:2::2/64**
R2(config-if)#**exit**
R2(config)#**interface tunnel 0**
R2(config-if)#**ipv6 unnumbered fastethernet 0/0**
R2(config-if)#**tunnel source loopback 0**
R2(config-if)#**tunnel mode ipv6ip 6to4**
R2(config-if)#**exit**
R2(config)#**ipv6 route 2002::/16 tunnel 0**

https://t.me/learningnets

R2(config)#**exit**

R3(config)#**interface loopback 0**
R3(config-if)#**ip address 3.3.3.3 255.255.255.255**
R3(config-if)#**exit**
R3(config)#**router ospf 3**
R3(config-router)#**network 3.3.3.3 0.0.0.0 area 0**
R3(config-router)#**exit**
R3(config)#**ipv6 unicast-routing**
R3(config)#**ip cef**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ipv6 address 2002:303:303:3::3/64**
R3(config-if)#**exit**
R3(config)#**interface tunnel 0**
R3(config-if)#**ipv6 unnumbered fastethernet 0/0**
R3(config-if)#**tunnel source loopback 0**
R3(config-if)#**tunnel mode ipv6ip 6to4**
R3(config-if)#**exit**
R3(config)#**ipv6 route 2002::/16 tunnel 0**
R3(config)#**exit**

Verify your IPv6 addressing using the **show ipv6 interface** command on both routers:

R2#**show ipv6 interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::20D:28FF:FE9E:F940
Global unicast address(es):
2002:202:202:2::2, subnet is 2002:202:202:2::/64
Joined group address(es):
FF02::1
FF02::2
FF02::1:FF00:2
FF02::1:FF9E:F940
MTU is 1500 bytes

[Truncated Output]

R3#**show ipv6 interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::213:7FFF:FEAF:3E00
Global unicast address(es):
2002:303:303:3::3, subnet is 2002:303:303:3::/64

https://t.me/learningnets

Joined group address(es):
FF02::1
FF02::2
FF02::1:FF00:3
FF02::1:FFAF:3E00
MTU is 1500 bytes

[Truncated Output]

R2#**show ipv6 interface tunnel 0**
Tunnel0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::202:202
Interface is unnumbered. Using address of FastEthernet0/0
No global unicast address is configured
Joined group address(es):
FF02::1
FF02::2
FF02::1:FF02:202
MTU is 1480 bytes

[Truncated Output]

R3#**show ipv6 interface tunnel 0**
Tunnel0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::303:303
Interface is unnumbered. Using address of FastEthernet0/0
No global unicast address is configured
Joined group address(es):
FF02::1
FF02::2
FF02::1:FF03:303
MTU is 1480 bytes

[Truncated Output]

Next, verify IPv6 routing using the **show ipv6 route** command on both routers:

R2#**show ipv6 route**
IPv6 Routing Table - 5 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2

https://t.me/learningnets

Technet24

S 2002::/16 [1/0]
via ::, Tunnel0
C 2002:202:202:2::/64 [0/0]
via ::, FastEthernet0/0
L 2002:202:202:2::2/128 [0/0]
via ::, FastEthernet0/0
L FE80::/10 [0/0]
via ::, Null0
L FF00::/8 [0/0]
via ::, Null0

R3#**show ipv6 route**
IPv6 Routing Table - 5 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
S 2002::/16 [1/0]
via ::, Tunnel0
C 2002:303:303:3::/64 [0/0]
via ::, FastEthernet0/0
L 2002:303:303:3::3/128 [0/0]
via ::, FastEthernet0/0
L FE80::/10 [0/0]
via ::, Null0
L FF00::/8 [0/0]
via ::, Null0

Finally, verify LAN-to-LAN connectivity between the IPv6 subnets using an extended ping:

R2#**ping 2002:303:303:3::3 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 2002:303:303:3::3, timeout is 2 seconds:
Packet sent with a source address of 2002:202:202:2::2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 204/207/208 ms

R3#**ping 2002:202:202:2::2 source fastethernet 0/0 repeat 10 size 1500**

Type escape sequence to abort.

https://t.me/learningnets

Sending 10, 1500-byte ICMP Echos to 2002:202:202:2::2, timeout is 2 seconds:
Packet sent with a source address of 2002:303:303:3::3
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 204/207/208 ms

Task 11

To complete this task, you need to configure a NAT pool using the 150.1.1.0/24 subnet. In order to allow reachability to this subnet, without creating an additional interface, you need to configure a static route pointing to Null0 and advertise it via OSPF. Complete this as follows:

R3(config)#**ip route 150.3.3.0 255.255.255.0 null 0**
R3(config)#**$at pool R3-LAN-POOL 150.3.3.1 150.3.3.254 netmask 255.255.255.0**
R3(config)#**access-list 100 permit ip 10.3.3.0 0.0.0.255 150.1.1.0 0.0.0.255**
R3(config)#**access-list 100 permit ip 10.3.3.0 0.0.0.255 150.2.2.0 0.0.0.255**
R3(config)#**ip nat inside source list 100 pool R3-LAN-POOL**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip nat inside**
R3(config-if)#**exit**
R3(config)#**interface serial 1/0**
R3(config-if)#**ip nat outside**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip nat outside**
R3(config-if)#**exit**
R3(config)#**end**
R3#**clear ip ospf redistribution**

Following this configuration, ping from R3s LAN subnet to 150.1.1.0/24 and 150.2.2.0/24:

ALS2#**ping 150.1.1.1**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
.!!!!
Success rate is 80 percent (4/5), round-trip min/avg/max = 16/17/20 ms

ALS2#**ping 150.2.2.2**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
!!!!!

https://t.me/learningnets
Technet24

Success rate is 100 percent (5/5), round-trip min/avg/max = 16/16/20 ms

Finally, verify NAT operation using the show ip nat translations command on R3:

R3#**show ip nat translations**

```
Pro Inside global Inside local Outside local Outside global
icmp 150.3.3.1:4484 10.3.3.254:4484 150.1.1.1:4484 150.1.1.1:4484
icmp 150.3.3.1:4485 10.3.3.254:4485 150.1.1.1:4485 150.1.1.1:4485
icmp 150.3.3.1:4486 10.3.3.254:4486 150.1.1.1:4486 150.1.1.1:4486
icmp 150.3.3.1:4487 10.3.3.254:4487 150.1.1.1:4487 150.1.1.1:4487
icmp 150.3.3.1:4488 10.3.3.254:4488 150.1.1.1:4488 150.1.1.1:4488
icmp 150.3.3.1:7980 10.3.3.254:7980 150.2.2.2:7980 150.2.2.2:7980
icmp 150.3.3.1:7981 10.3.3.254:7981 150.2.2.2:7981 150.2.2.2:7981
icmp 150.3.3.1:7982 10.3.3.254:7982 150.2.2.2:7982 150.2.2.2:7982
icmp 150.3.3.1:7983 10.3.3.254:7983 150.2.2.2:7983 150.2.2.2:7983
icmp 150.3.3.1:7984 10.3.3.254:7984 150.2.2.2:7984 150.2.2.2:7984
```

https://t.me/learningnets

CCNP Lab 085: CCNP Multi-Technology Lab

Lab Objective:

The objective of this lab is to cover all relevant CCNP ROUTE and SWITCH theory. These labs will include topics from each of these guides. It should be noted that not all topics will be included in all labs. Additionally, not all solutions will be illustrated in detail. You can refer to previous labs for assistance with some basic configurations.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please implement the following pre-lab configurations. This is required because of the manner in which the routers and switches are physically cabled to each other. The following configuration should be applied to switch ALS1:

```
!
hostname ALS1
!
vtp mode transparent
!
vlan 100
name R1-VLAN
!
vlan 300
```

https://t.me/learningnets

```
name R3-VLAN
!
vlan 400
name R4-VLAN
!
interface fastethernet 0/1
switchport access vlan 100
switchport mode access
!
interface fastethernet 0/2
shutdown
!
interface fastethernet 0/3
switchport access vlan 300
switchport mode access
!
interface fastethernet 0/4
switchport access vlan 400
switchport mode access
!
interface range fastethernet 0/5 - 6
shutdown
!
interface fastethernet0/7
switchport mode trunk
!
interface fastethernet 0/8
switchport mode trunk
!
interface range fastethernet 0/9 - 10
shutdown
!
interface range fastethernet 0/11 - 12
switchport mode trunk
!
interface vlan 400
ip address 10.4.4.254 255.255.255.0
no shutdown
```

https://t.me/learningnets

```
!
ip default-gateway 10.4.4.4
!
line vty 0 4
privilege level 15
password cisco
login
!
end
!
hostname ALS2
!
vtp mode transparent
!
vlan 300
name R3-VLAN
!
interface range fastethernet 0/1 - 10
shutdown
!
interface fastethernet 0/11
switchport mode trunk
!
interface fastethernet 0/12
switchport mode trunk
!
interface vlan 300
ip address 10.3.3.254 255.255.255.0
no shutdown
!
ip default-gateway 10.3.3.3
!
line vty 0 4
privilege level 15
password cisco
login
!
end
```

https://t.me/learningnets

```
!
hostname DLS1
!
ip routing
!
vtp mode transparent
!
vlan 100
name R1-VLAN
!
interface range fastethernet 0/1 - 6
shutdown
!
interface range fastethernet 0/7 - 8
switchport trunk encapsulation dot1q
switchport mode trunk
!
interface range fastethernet 0/9 - 10
shutdown
!
interface fastethernet 0/11
switchport mode dynamic desirable
!
interface fastethernet 0/12
switchport mode dynamic desirable
!
interface range fastethernet 0/13 - 48
shutdown
!
interface vlan 100
ip address 150.1.1.2 255.255.255.0
no shutdown
!
line vty 0 4
privilege level 15
password cisco
login
!
```

https://t.me/learningnets

Technet24

```
end
!
hostname DLS2
!
ip routing
!
vtp mode transparent
!
interface range fastethernet 0/1 - 10
shutdown
!
interface fastethernet 0/11
switchport mode dynamic desirable
!
interface fastethernet 0/12
switchport mode dynamic desirable
!
interface range fastethernet 0/13 - 48
shutdown
!
line vty 0 4
privilege level 15
password cisco
login
!
end
```

If you are using the www.101labs.net racks, please bring up the LAN interface connected to R2 by the following configuration:

```
interface fastethernet 0/0
ip address 150.2.2.2 255.255.255.0
no keepalive
loopback
no shutdown
```

Alternatively, you can simply connect the interface to a hub or one of the switches and bring up the interface in the standard manner.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

https://t.me/learningnets

Task 2

Configure an EtherChannel between DLS1 and DLS2. This should be a Layer 2 access link that uses LACP. Configure interface VLAN 100 on switch DLS2. This interface should receive its IP address information via DHCP. Verify your configuration using the appropriate commands.

Task 3

Configure Cisco IOS DHCP Snooping for all VLANs on switch DLS1. For additional security, configure switch DLS1 to prevent IP spoofing attacks by filtering the traffic based on the DHCP Snooping Binding Database. Finally, ensure that Option 82 is not used. Verify the Cisco IOS DHCP Snooping configuration using the appropriate commands.

Task 4

Configure the Cisco IOS DHCP server on R1. Configure the following DHCP parameters:

- A default gateway of 150.1.1.1 should be configured for this subnet
- Addresses 150.1.1.1 to 10 should never be assigned by R1
- R1 should ping a pool address 10 times before assigning it to a requesting client
- The lease should last for 4 hours
- Switch DLS2 should reside in the 101labs.net domain
- Switch DLS2 should use DNS server 150.1.1.1

Verify your configuration using the appropriate commands.

Task 5

Configure EIGRP illustrated in the topology. You must adhere to the following guidelines:

- R2 should NEVER be used as a transit router, even in the event that the R1-R3 link fails
- R4 should only RECEIVE routes but should be reachable from all other routers
- Switches DLS1 and DLS2 should be reachable from all other devices in the network
- No EIGRP hellos should be sent out the LAN interfaces of any router
- Do NOT advertise the 150.1.1.0/24 subnet via EIGRP; this subnet should not be reachable
- Do NOT advertise the 10.4.4.0/24 subnet via EIGRP; however, ensure that it is

https://t.me/learningnets

Technet24

reachable
- The 10.3.3.0/24 subnet should be advertised as an EXTERNAL EIGRP route

Task 6

Redistribute between the different EIGRP instances on R1, R2, and R3. Do NOT redistribute the 150.1.1.0/24 subnet into EIGRP; however, ensure that all routers are able to reach this subnet. You are NOT allowed to configure static routes or redistribute or advertise this subnet via EIGRP when completing this task. Verify your solution by pinging DLS2 from any other router.

Task 7

In the future, an IP videos solution will be implemented. This video solution will use Multicast. Configure IP Multicast so that R2 is the RP. The RP address should be 2.2.2.2/32. To test Multicast operation, configure R1s LAN interface to join group 227.1.1.1. Enable IP Multicast support on R1, R2, R3, DLS1 and DLS2. Do NOT enable IP Multicast on R4. Ensure that all other devices can ping this Multicast group.

Task 8

In order to ensure that video traffic is protected in the event of network congestion, configure QoS on R1's WAN interfaces so that this type of traffic is allocated 40% of the interface bandwidth. You are NOT allowed to use ACLs in your solution. Verify your configuration using the appropriate commands.

Task 9

In the future, a new application will be integrated into the network. This new application will use TCP ports 2023, 3023, 4023 and 5023. Modify the existing QoS policy on R1 so that this traffic is allocated 10% of the interface bandwidth. You are NOT allowed to use Access Lists to complete this task. Verify your configuration using the appropriate commands.

Task 10

Management would like to integrate IPv6 into the network. Configure the following IPv6 subnets on the LAN interfaces of R2 and R3:

- R2 LAN IPv6 Subnet: 3FFE:2222:2222:2222::/64
- R3 LAN IPv6 Subnet: 3FFE:3333:3333:3333::/64

Next, enable OSPFv3 between R2 and R3 and ensure that these two subnets are reachable from all the two routers. You are NOT allowed to enable IPv6 or OSPFv3 routing on the WAN interfaces of R2 and R3. Ensure that the R2 LAN subnet is assigned

https://t.me/learningnets

to area 2, while the R3 LAN subnet is assigned to area 3. Verify your solution using the extended ping function.

Task 11

For security, configure area authentication for OSPFv3s backbone. Use the following parameters when you are configuring the authentication parameters:

- Use a Security Parameters Index (SPI) of 678
- Use Message Digest 5 (MD5) authentication
- Use a key of 1234567890abcdef1234567890abcdef

Task 12

For security, Management has requested that all ports on switch ALS1 that are not trunk links or connected to routers be configured to adhere to the following restrictions:

- The ports should NOT be able to communicate directly with each other at Layer 2
- All ports should be dynamically allocated to VLANs by server 150.1.1.254

You are NOT allowed to use Private VLANs to complete this task.

Task 13

For security, Management has requested that all ports on switch ALS2 that are not trunk links be configured so that Broadcast traffic should never exceed 5%, Multicast traffic should never exceed 20% and Unicast traffic should never exceed 80%. In the event that these thresholds are exceeded, the switch should send out an SNMP trap to server 150.1.1.254. This server is expecting the switch to use an SNMP community string of CCNP2011. Verify the configuration using the appropriate commands.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4, IPv6 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

Please refer to previous labs for basic EtherChannel configuration. This will not be included in this section to avoid being redundant. Following your configuration, verify EtherChannel operational status using the **show etherchannel** commands:

DLS1#**show etherchannel summary**

https://t.me/learningnets

Technet24

Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
------+-------------+-----------+--
10 Po10(SU) LACP Fa0/11(P) Fa0/12(P)

DLS2#**show etherchannel summary**
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use f - failed to allocate aggregator

M - not in use, minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
------+-------------+-----------+--
10 Po10(SU) LACP Fa0/11(P) Fa0/12(P)

You can verify Layer 2 configuration parameters using the **show interfaces <name> switchport** command on either one or both of the switches:

DLS2#**show interfaces port-channel 10 switchport**
Name: Po10
Switchport: Enabled
Administrative Mode: static access
Operational Mode: static access

https://t.me/learningnets

Administrative Trunking Encapsulation: negotiate
Operational Trunking Encapsulation: native
Negotiation of Trunking: Off
Access Mode VLAN: 100 (R1-VLAN)
Trunking Native Mode VLAN: 1 (default)
Administrative Native VLAN tagging: enabled
Voice VLAN: none
Administrative private-vlan host-association: none
Administrative private-vlan mapping: none
Administrative private-vlan trunk native VLAN: none
Administrative private-vlan trunk Native VLAN tagging: enabled
Administrative private-vlan trunk encapsulation: dot1q
Administrative private-vlan trunk normal VLANs: none
Administrative private-vlan trunk associations: none
Administrative private-vlan trunk mappings: none
Operational private-vlan: none
Trunking VLANs Enabled: ALL
Pruning VLANs Enabled: 2-1001

Protected: false
Unknown unicast blocked: disabled
Unknown multicast blocked: disabled
Appliance trust: none

On switch DLS2, use the **show interfaces** command to verify DHCP client configuration:

DLS2#**show interfaces vlan 100**
Vlan100 is up, line protocol is up
Hardware is EtherSVI, address is 000b.fd67.6500 (bia 000b.fd67.6500)
Internet address will be negotiated using DHCP
MTU 1500 bytes, BW 1000000 Kbit, DLY 10 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation ARPA, loopback not set
Keepalive not supported
ARP type: ARPA, ARP Timeout 04:00:00
Last input never, output 00:00:00, output hang never
Last clearing of "show interface" counters never
Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
Queueing strategy: fifo
Output queue: 0/40 (size/max)

https://t.me/learningnets
Technet24

5 minute input rate 0 bits/sec, 0 packets/sec
5 minute output rate 0 bits/sec, 0 packets/sec
0 packets input, 0 bytes, 0 no buffer
Received 0 broadcasts (0 IP multicasts)
0 runts, 0 giants, 0 throttles
0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored
1 packets output, 618 bytes, 0 underruns
0 output errors, 0 interface resets
0 output buffer failures, 0 output buffers swapped out

Task 3

The requirements for this task are straightforward. In addition to configuring DHCP Snooping, you also need to configure the IP Source Guard feature. This task is completed as follows:

DLS1(config)#**ip dhcp snooping**
DLS1(config)#**ip dhcp snooping vlan 100**
DLS1(config)#**no ip dhcp snooping information option**
DLS1(config)#**interface range fastethernet 0/7 - 8**
DLS1(config-if-range)#**ip dhcp snooping trust**
DLS1(config-if-range)#**exit**
DLS1(config)#**interface port-channel 10**
DLS1(config-if)#**ip verify source**
DLS1(config-if)#**exit**

Following this, verify your configuration using the **show ip dhcp snooping** command:

DLS1(config)#**do show ip dhcp snooping**
Switch DHCP snooping is enabled
DHCP snooping is configured on following VLANs:
100
DHCP snooping is operational on following VLANs:
100
DHCP snooping is configured on the following L3 Interfaces:

Insertion of option 82 is disabled
circuit-id format: vlan-mod-port
remote-id format: MAC
Option 82 on untrusted port is not allowed
Verification of hwaddr field is enabled
Verification of giaddr field is enabled
DHCP snooping trust/rate is configured on the following Interfaces:

https://t.me/learningnets

Interface Trusted Rate limit (pps)
---------- ------- ----------
FastEthernet0/7 yes unlimited
FastEthernet0/8 yes unlimited

Task 4

The requirements for this task are straightforward. This task is completed as follows:

R1(config)#**ip dhcp excluded-address 150.1.1.1 150.1.1.10**
R1(config)#**ip dhcp ping packets 10**
R1(config)#**ip dhcp pool VLAN-100-DHCP-POOL**
R1(dhcp-config)#**network 150.1.1.0 /24**
R1(dhcp-config)#**default-router 150.1.1.1**
R1(dhcp-config)#**lease 0 4 0**
R1(dhcp-config)#**domain-name 101labs.net**
R1(dhcp-config)#**dns-server 150.1.1.1**
R1(dhcp-config)#**exit**

Following your configuration, DLS2 should receive an IP address via DHCP from R1. Verify the DHCP configuration and bindings using the **show ip dhcp** commands:

R1#**show ip dhcp pool VLAN-100-DHCP-POOL**

Pool VLAN-100-DHCP-POOL :
Utilization mark (high/low) : 100 / 0
Subnet size (first/next) : 0 / 0
Total addresses : 254
Leased addresses : 1
Pending event : none
1 subnet is currently in the pool :
Current index IP address range Leased addresses
150.1.1.12 150.1.1.1 - 150.1.1.254 1

R1#**show ip dhcp binding**
Bindings from all pools not associated with VRF:
IP address Client-ID/ Lease expiration Type
Hardware address/
User name
150.1.1.11 0063.6973.636f.2d30. Jun 19 2011 02:07 AM Automatic
3030.622e.6664.3637.
2e36.3530.302d.566c.
3130.30

https://t.me/learningnets
Technet24

```
DLS1#show ip dhcp snooping binding vlan 100
MacAddress IpAddress Lease(sec) Type VLAN Interface
------------------ --------------- --------- ------------ ---- --------------------
00:0B:FD:67:65:00 150.1.1.11 14070 dhcp-snooping 100 Port-channel10
Total number of bindings: 1

DLS1#show ip source binding dhcp-snooping vlan 100
MacAddress IpAddress Lease(sec) Type VLAN Interface
------------------ --------------- --------- ------------ ---- --------------------
00:0B:FD:67:65:00 150.1.1.11 14149 dhcp-snooping 100 Port-channel10
Total number of bindings: 1
```

Task 5

The requirements for this task are straightforward. In order to prevent R2 from being a transit router, even in the event of an R1-R3 link failure, you need to configure this router as a stub router. Additionally, R4 should also be configured as a stub router that will receive routes but never advertise any. This task is completed as follows:

```
R1(config)#router eigrp 1
R1(config-router)#no auto-summary
R1(config-router)#network 150.0.0.1 0.0.0.0
R1(config-router)#exit
R1(config)#router eigrp 2
R1(config-router)#no auto-summary
R1(config-router)#network 150.0.0.5 0.0.0.0
R1(config-router)#exit

R2(config)#router eigrp 1
R2(config-router)#no auto-summary
R2(config-router)#network 150.2.2.2 0.0.0.0
R2(config-router)#network 150.0.0.2 0.0.0.0
R2(config-router)#passive-interface fastethernet 0/0
R2(config-router)#eigrp stub
R2(config-router)#exit
R2(config)#router eigrp 2
R2(config-router)#no auto-summary
R2(config-router)#network 150.0.0.9 0.0.0.0
R2(config-router)#eigrp stub
R2(config-router)#exit

R3(config)#router eigrp 2
R3(config-router)#no auto-summary
```

https://t.me/learningnets

R3(config-router)#**network 150.0.0.6 0.0.0.0**
R3(config-router)#**network 150.0.0.10 0.0.0.0**
R3(config-router)#**exit**
R3(config)#**ip route 10.4.4.0 255.255.255.0 serial 1/2**
R3(config)#**ip route 10.4.4.0 255.255.255.0 serial 1/3**
R3(config)#**router eigrp 3**
R3(config-router)#**no auto-summary**
R3(config-router)#**network 150.0.0.13 0.0.0.0**
R3(config-router)#**network 150.0.0.17 0.0.0.0**
R3(config-router)#**redistribute static**
R3(config-router)#**redistribute connected**
R3(config-router)#**exit**

R4(config)#**router eigrp 3**
R4(config-router)#**no auto-summary**
R4(config-router)#**network 150.0.0.14 0.0.0.0**
R4(config-router)#**network 150.0.0.18 0.0.0.0**
R4(config-router)#**eigrp stub receive-only**
R4(config-router)#**exit**

Following this, verify EIGRP configuration using the **show ip eigrp** commands:

R1#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.0.0.2 Se0/0 12 00:17:26 2 200 0 6

IP-EIGRP neighbors for process 2
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.0.0.6 Se0/1 14 00:16:04 10 200 0 4

R2#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 1
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.0.0.1 Se0/0 10 00:17:32 2 200 0 7

IP-EIGRP neighbors for process 2
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 150.0.0.10 Se0/1 13 00:16:06 13 200 0 7

https://t.me/learningnets

R3#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 2
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 150.0.0.9 Se1/1 11 00:16:08 11 1710 0 3
0 150.0.0.5 Se1/0 12 00:16:14 10 1140 0 3

IP-EIGRP neighbors for process 3
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 150.0.0.18 Se1/3 11 00:05:43 14 1140 0 17
0 150.0.0.14 Se1/2 10 00:13:14 13 1140 0 18

R4#**show ip eigrp neighbors**
IP-EIGRP neighbors for process 3
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
1 150.0.0.17 Se0/1 10 00:05:46 14 200 0 20
0 150.0.0.13 Se0/0 11 00:13:17 15 200 0 21

Task 6

When completing this task, keep in mind that you should NOT configure redistribution on R2 as this is a sub-router under both EIGRP autonomous systems:

R1(config)#**router eigrp 1**
R1(config-router)#**redistribute eigrp 2**
R1(config-router)#**exit**
R1(config)#**router eigrp 2**
R1(config-router)#**redistribute eigrp 1**
R1(config-router)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip summary-address eigrp 1 0.0.0.0 0.0.0.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip summary-address eigrp 2 0.0.0.0 0.0.0.0**
R1(config-if)#**exit**

R3(config)#**router eigrp 2**
R3(config-router)#**redistribute connected**
R3(config-router)#**redistribute static**
R3(config-router)#**exit**
R3(config)#**router eigrp 3**

https://t.me/learningnets

R3(config-router)#**redistribute eigrp 2**
R3(config-router)#**exit**

Finally, configure a static default route on DLS1 to ensure that this is reachable from all the other devices. DLS2 has a default received via DHCP so this step in not necessary:

DLS1(config)#**ip route 0.0.0.0 0.0.0.0 vlan 100 150.1.1.1**

Next, verify routing using the **show ip route** command on all routers:

R1#**show ip route eigrp**
10.0.0.0/24 is subnetted, 2 subnets
D EX 10.4.4.0 [170/21024000] via 150.0.0.6, 00:01:41, Serial0/1
D EX 10.3.3.0 [170/2172416] via 150.0.0.6, 00:01:49, Serial0/1
150.0.0.0/30 is subnetted, 5 subnets
D EX 150.0.0.16 [170/21024000] via 150.0.0.6, 00:01:49, Serial0/1
D EX 150.0.0.12 [170/21024000] via 150.0.0.6, 00:01:49, Serial0/1
D 150.0.0.8 [90/21024000] via 150.0.0.6, 00:21:14, Serial0/1
150.2.0.0/24 is subnetted, 1 subnets
D 150.2.2.0 [90/2172416] via 150.0.0.2, 00:22:40, Serial0/0
D* 0.0.0.0/0 is a summary, 00:01:49, Null0

R2#**show ip route eigrp**
10.0.0.0/24 is subnetted, 2 subnets
D EX 10.4.4.0 [170/21024000] via 150.0.0.10, 00:01:49, Serial0/1
D EX 10.3.3.0 [170/2172416] via 150.0.0.10, 00:01:58, Serial0/1
150.0.0.0/30 is subnetted, 5 subnets
D EX 150.0.0.16 [170/21024000] via 150.0.0.10, 00:01:58, Serial0/1
D 150.0.0.4 [90/21024000] via 150.0.0.10, 00:21:22, Serial0/1
D EX 150.0.0.12 [170/21024000] via 150.0.0.10, 00:01:58, Serial0/1
D* 0.0.0.0/0 [90/2681856] via 150.0.0.1, 00:01:58, Serial0/0

R3#**show ip route eigrp**
D*EX 0.0.0.0/0 [170/21024000] via 150.0.0.5, 00:03:25, Serial1/0

R4#**show ip route eigrp**
10.0.0.0/24 is subnetted, 2 subnets
D EX 10.3.3.0 [170/2172416] via 150.0.0.17, 00:09:06, Serial0/1
[170/2172416] via 150.0.0.13, 00:09:06, Serial0/0
150.0.0.0/30 is subnetted, 4 subnets
D EX 150.0.0.4 [170/21024000] via 150.0.0.17, 00:09:06, Serial0/1
[170/21024000] via 150.0.0.13, 00:09:06, Serial0/0
D EX 150.0.0.8 [170/21024000] via 150.0.0.17, 00:09:06, Serial0/1
[170/21024000] via 150.0.0.13, 00:09:06, Serial0/0

https://t.me/learningnets

D*EX 0.0.0.0/0 [170/21536000] via 150.0.0.17, 00:01:42, Serial0/1
[170/21536000] via 150.0.0.13, 00:01:42, Serial0/0

Complete this task by pinging DLS2 from any other device; for example, the ping from router R4 should be successful as illustrated below:

R4#**ping 150.1.1.11 source fastethernet 0/0 size 1500 repeat 10**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 150.1.1.11, timeout is 2 seconds:
Packet sent with a source address of 10.4.4.4
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 380/382/384 ms

Task 7

To complete this task, you need to configure a Loopback interface on R2 and advertise it via EIGRP. Next, enable PIM Sparse-Mode on all interfaces in the path. Finally, join R1s LAN interface to Multicast group 227.1.1.1 and verify your solution by pinging this group from all other devices within the network. This task is completed as follows:

R1(config)#**ip multicast-routing**
R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip pim sparse-mode**
R1(config-if)#**ip igmp join-group 227.1.1.1**
R1(config-if)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**ip pim sparse-mode**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip pim sparse-mode**
R1(config-if)#**exit**
R1(config)#**ip pim rp-address 2.2.2.2**

R2(config)#**ip multicast-routing**
R2(config)#**interface loopback 0**
R2(config-if)#**ip address 2.2.2.2 255.255.255.255**
R2(config-if)#**ip pim sparse-mode**
R2(config-if)#**exit**
R2(config)#**router eigrp 1**
R2(config-router)#**network 2.2.2.2 0.0.0.0**
R2(config-router)#**exit**
R2(config)#**router eigrp 2**

https://t.me/learningnets

R2(config-router)#**network 2.2.2.2 0.0.0.0**
R2(config-router)#**exit**
R2(config-if)#**exit**
R2(config)#**interface serial 0/0**
R2(config-if)#**ip pim sparse-mode**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip pim sparse-mode**
R2(config-if)#**exit**
R2(config)#**ip pim rp-address 2.2.2.2**

R3(config)#**ip multicast-routing**
R3(config)#**interface serial 1/0**
R3(config-if)#**ip pim sparse-mode**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip pim sparse-mode**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip pim sparse-mode**
R3(config-if)#**exit**
R3(config)#**interface serial 1/3**
R3(config-if)#**ip pim sparse-mode**
R3(config-if)#**exit**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ip pim sparse-mode**
R3(config-if)#**exit**
R3(config)#**ip pim rp-address 2.2.2.2**
R3(config)#**exit**

DLS1(config)#**ip multicast-routing**
DLS1(config)#**interface vlan 100**
DLS1(config-if)#**ip pim sparse-mode**
DLS1(config-if)#**exit**
DLS1(config)#**ip pim rp-address 2.2.2.2**
DLS1(config)#**exit**

DLS2(config)#**ip multicast-routing**
DLS2(config)#**interface vlan 100**
DLS2(config-if)#**ip pim sparse-mode**
DLS2(config-if)#**exit**

https://t.me/learningnets

DLS2(config)#**ip pim rp-address 2.2.2.2**
DLS2(config)#**exit**

Verify your configuration using the **show ip igmp** and **show ip pim** commands:

R1#**show ip igmp interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
Internet address is 150.1.1.1/24
IGMP is enabled on interface
Current IGMP host version is 2
Current IGMP router version is 2
IGMP query interval is 60 seconds
IGMP querier timeout is 120 seconds
IGMP max query response time is 10 seconds
Last member query count is 2
Last member query response interval is 1000 ms
Inbound IGMP access group is not set
IGMP activity: 2 joins, 0 leaves
Multicast routing is enabled on interface
Multicast TTL threshold is 0
Multicast designated router (DR) is 150.1.1.11
IGMP querying router is 150.1.1.1 (this system)
Multicast groups joined by this system (number of users):
224.0.1.40(1) 227.1.1.1(1)

DLS1#**show ip pim rp**
Group: 227.1.1.1, RP: 2.2.2.2, uptime 00:06:27, expires never
Group: 224.0.1.40, RP: 2.2.2.2, uptime 00:06:27, expires never

DLS2#**show ip pim rp**
Group: 227.1.1.1, RP: 2.2.2.2, uptime 00:01:13, expires never
Group: 224.0.1.40, RP: 2.2.2.2, uptime 00:01:13, expires never

R2#**show ip pim rp**
Group: 227.1.1.1, RP: 2.2.2.2, next RP-reachable in 00:00:21
Group: 224.0.1.40, RP: 2.2.2.2, next RP-reachable in 00:00:21

R3#**show ip pim rp**
Group: 227.1.1.1, RP: 2.2.2.2, v2, uptime 00:00:32, expires never
Group: 224.0.1.40, RP: 2.2.2.2, v2, uptime 00:05:56, expires never

Finally, verify reachability to the Multicast group using a simple ping:

R2#**ping 227.1.1.1**

https://t.me/learningnets

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 227.1.1.1, timeout is 2 seconds:

Reply to request 0 from 150.0.0.1, 4 ms
Reply to request 0 from 150.0.0.1, 36 ms
Reply to request 0 from 150.0.0.1, 8 ms

R3#**ping 227.1.1.1**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 227.1.1.1, timeout is 2 seconds:

Reply to request 0 from 150.0.0.5, 20 ms

DLS1#**ping 227.1.1.1**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 227.1.1.1, timeout is 2 seconds:

Reply to request 0 from 150.1.1.1, 8 ms

DLS2#**ping 227.1.1.1**

Type escape sequence to abort.
Sending 1, 100-byte ICMP Echos to 227.1.1.1, timeout is 2 seconds:

Reply to request 0 from 150.1.1.1, 8 ms

Task 8

In order to complete this task without using ACLs for classification, you need to use NBAR on the router. This task is completed as follows:

R1(config)#**ip cef**
R1(config)#**class-map VIDEO**
R1(config-cmap)#**match protocol rtp video**
R1(config-cmap)#**exit**
R1(config)#**policy-map WAN-QoS-Outbound**
R1(config-pmap)#**class VIDEO**
R1(config-pmap-c)#**bandwidth percent 40**
R1(config-pmap-c)#**exit**
R1(config-pmap)#**exit**
R1(config)#**interface serial 0/0**
R1(config-if)#**service-policy output WAN-QoS-Outbound**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**service-policy output WAN-QoS-Outbound**
R1(config-if)#**exit**

https://t.me/learningnets

Technet24

Verify your configuration using the **show policy-map** commands:

R1#**show policy-map WAN-QoS-Outbound**
Policy Map WAN-QoS-Outbound
Class VIDEO
Bandwidth 40 (%) Max Threshold 64 (packets)

R1#**show policy-map interface serial 0/0 output**
Serial0/0

Service-policy output: WAN-QoS-Outbound

Class-map: VIDEO (match-all)
0 packets, 0 bytes
5 minute offered rate 0 bps, drop rate 0 bps
Match: protocol rtp video
Queueing
Output Queue: Conversation 265
Bandwidth 40 (%)
Bandwidth 617 (kbps)Max Threshold 64 (packets)
(pkts matched/bytes matched) 0/0
(depth/total drops/no-buffer drops) 0/0/0

Class-map: class-default (match-any)
45 packets, 2880 bytes
5 minute offered rate 0 bps, drop rate 0 bps
Match: any

Task 9

To complete this task, you need to use NBAR and define a custom application for which you will modify the existing QoS policy. This task is completed as follows:

R1(config)#**ip nbar port-map custom-01 tcp 2023 3023 4023 5023**
R1(config)#**class-map APPLICATION**
R1(config-cmap)#**match protocol custom-01**
R1(config-cmap)#**exit**
R1(config)#**policy-map WAN-QoS-Outbound**
R1(config-pmap)#**class APPLICATION**
R1(config-pmap-c)#**bandwidth percent 10**
R1(config-pmap-c)#**exit**

Verify your NBAR configuration using the **show ip nbar** commands:

R1#**show ip nbar port-map custom-01**
port-map custom-01 tcp 2023 3023 4023 5023

https://t.me/learningnets

Verify QoS configuration using the **show policy-map** commands:

R1#**show policy-map WAN-QoS-Outbound**
Policy Map WAN-QoS-Outbound
Class VIDEO
Bandwidth 40 (%) Max Threshold 64 (packets)
Class APPLICATION
Bandwidth 10 (%) Max Threshold 64 (packets)

R1#**show policy-map interface serial 0/1 output**
Serial0/1

Service-policy output: WAN-QoS-Outbound

Class-map: VIDEO (match-all)
0 packets, 0 bytes
5 minute offered rate 0 bps, drop rate 0 bps
Match: protocol rtp video
Queueing
Output Queue: Conversation 265
Bandwidth 40 (%)
Bandwidth 617 (kbps)Max Threshold 64 (packets)
(pkts matched/bytes matched) 0/0
(depth/total drops/no-buffer drops) 0/0/0

Class-map: APPLICATION (match-all)
0 packets, 0 bytes
5 minute offered rate 0 bps, drop rate 0 bps
Match: protocol custom-01
Queueing
Output Queue: Conversation 266
Bandwidth 10 (%)
Bandwidth 154 (kbps)Max Threshold 64 (packets)
(pkts matched/bytes matched) 0/0
(depth/total drops/no-buffer drops) 0/0/0

Class-map: class-default (match-any)
235 packets, 15208 bytes
5 minute offered rate 0 bps, drop rate 0 bps
Match: any

Task 10

Please refer to previous tasks for basic IPv6 addressing. Following completion, verify

https://t.me/learningnets

Technet24

your configuration using the **show ipv6** commands:

R2#**show ipv6 interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::20D:28FF:FE9E:F940
Global unicast address(es):
3FFE:2222:2222:2222::2, subnet is 3FFE:2222:2222:2222::/64
Joined group address(es):
FF02::1
FF02::2
FF02::1:FF00:2
FF02::1:FF9E:F940
MTU is 1500 bytes

[Truncated Output]

R3#**show ipv6 interface fastethernet 0/0**
FastEthernet0/0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::213:7FFF:FEAF:3E00
Global unicast address(es):
3FFE:3333:3333:3333::3, subnet is 3FFE:3333:3333:3333::/64
Joined group address(es):
FF02::1
FF02::2
FF02::1:FF00:3
FF02::1:FFAF:3E00
MTU is 1500 bytes

[Truncated Output]

To complete the second part of this task, you need to configure a static Tunnel and then enable OSPFv3 across this tunnel. Keep in mind that because IPv6 IGPs use the Link-Local address as the NEXT-HOP IPv6 address, you do not necessarily need to assign a global IPv6 subnet to the tunnel. This is completed as follows (use Tunnel 1 if 0 is in use):

R2(config)#**interface tunnel 0**
R2(config-if)#**tunnel source loopback 0**
R2(config-if)#**tunnel destination 3.3.3.3**
R2(config-if)#**tunnel mode ipv6ip**
R2(config-if)#**ipv6 enable**
R2(config-if)#**ipv6 ospf 2 area 0**
R2(config)#**interface fastethernet 0/0**

https://t.me/learningnets

R2(config-if)#**ipv6 ospf 2 area 2**
R2(config-if)#**exit**
R2(config)#**ipv6 router ospf 2**
R2(config-rtr)#**router-id 2.2.2.2**
R2(config-rtr)#**exit**

R3(config)#**interface loopback 0**
R3(config-if)#**ip address 3.3.3.3 255.255.255.255**
R3(config-if)#**exit**
R3(config)#**router eigrp 2**
R3(config-router)#**network 3.3.3.3 0.0.0.0**
R3(config-router)#**exit**
R3(config)#**router eigrp 3**
R3(config-router)#**network 3.3.3.3 0.0.0.0**
R3(config-router)#**exit**

R3(config)#**interface tunnel 0**
R3(config-if)#**tunnel source loopback 0**
R3(config-if)#**tunnel destination 2.2.2.2**
R3(config-if)#**tunnel mode ipv6ip**
R3(config-if)#**ipv6 enable**
R3(config-if)#**ipv6 ospf 3 area 0**
R3(config-if)#**exit**
R3(config)#**interface fastethernet 0/0**
R3(config-if)#**ipv6 ospf 3 area 3**
R3(config-if)#**exit**
R3(config)#**ipv6 router ospf 3**
R3(config-rtr)#**router-id 3.3.3.3**
R3(config-rtr)#**exit**

Following this, verify your Tunnel states using the **show interfaces** and **show ipv6 interface** commands on both of the routers:

R2#**show interfaces tunnel 0**
Tunnel0 is up, line protocol is up
Hardware is Tunnel
MTU 1514 bytes, BW 9 Kbit/sec, DLY 500000 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation TUNNEL, loopback not set
Keepalive not set
Tunnel source 2.2.2.2 (Loopback0), destination 3.3.3.3

https://t.me/learningnets

Technet24

Tunnel protocol/transport IPv6/IP
Tunnel TTL 255
Fast tunneling enabled
Tunnel transmit bandwidth 8000 (kbps)
Tunnel receive bandwidth 8000 (kbps)

[Truncated Output]

R2#**show ipv6 interface tunnel 0**
Tunnel0 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::202:202
No global unicast address is configured
Joined group address(es):
FF02::1
FF02::2
FF02::5
FF02::1:FF02:202
MTU is 1480 bytes
ICMP error messages limited to one every 100 milliseconds
ICMP redirects are enabled
ND DAD is enabled, number of DAD attempts: 1
ND reachable time is 30000 milliseconds
Hosts use stateless autoconfig for addresses.

Verify OSPFv3 adjacency states using the **show ipv6 ospf neighbor** command:

R2#**show ipv6 ospf neighbor**

Neighbor ID Pri State Dead Time Interface ID Interface
3.3.3.3 1 FULL/ - 00:00:39 24 Tunnel0

R3#**show ipv6 ospf neighbor**

Neighbor ID Pri State Dead Time Interface ID Interface
2.2.2.2 1 FULL/ - 00:00:37 10 Tunnel0

Verify IPv6 routing using the **show ipv6 route** commands:

R2#**show ipv6 route ospf**
IPv6 Routing Table - 5 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2

https://t.me/learningnets

OI 3FFE:3333:3333:3333::/64 [110/11112]
via FE80::303:303, Tunnel0

R3#**show ipv6 route ospf**
IPv6 Routing Table - 5 entries
Codes: C - Connected, L - Local, S - Static, R - RIP, B - BGP
U - Per-user Static route
I1 - ISIS L1, I2 - ISIS L2, IA - ISIS interarea, IS - ISIS summary
O - OSPF intra, OI - OSPF inter, OE1 - OSPF ext 1, OE2 - OSPF ext 2
ON1 - OSPF NSSA ext 1, ON2 - OSPF NSSA ext 2
OI 3FFE:2222:2222:2222::/64 [110/11112]
via FE80::202:202, Tunnel0

Finally, verify LAN-to-LAN connectivity between the IPv6 subnets using an extended ping:

R2#**$333:3333:3333::3 source 3FFE:2222:2222:2222::2 repeat 10 size 1500**

Type escape sequence to abort.
Sending 10, 1500-byte ICMP Echos to 3FFE:3333:3333:3333::3, timeout is 2 seconds:
Packet sent with a source address of 3FFE:2222:2222:2222::2
!!!!!!!!!!
Success rate is 100 percent (10/10), round-trip min/avg/max = 208/208/212 ms

Task 11

OSPFv3 supports both authentication and encryption for security. To configure OSPFv3 area authentication, you need to use the **area <area> authentication ipsec spi <size> [md5|sha1] <key>** OSPFv3 configuration command. This task is completed as follows:

R2(config)#**ipv6 router ospf 2**
R2(config-rtr)#**$entication ipsec spi 678 md5 1234567890abcdef1234567890abcdef**
R2(config-rtr)#**exit**

R3(config)#**ipv6 router ospf 3**
R3(config-rtr)#**$entication ipsec spi 678 md5 1234567890abcdef1234567890abcdef**
R3(config-rtr)#**exit**
Verify OSPFv3 area authentication using the **show ipv6 ospf** command:

R3#**show ipv6 ospf**
Routing Process “ospfv3 3” with ID 3.3.3.3
It is an area border router
SPF schedule delay 5 secs, Hold time between two SPFs 10 secs
Minimum LSA interval 5 secs. Minimum LSA arrival 1 secs
LSA group pacing timer 240 secs

https://t.me/learningnets
Technet24

Interface flood pacing timer 33 msecs
Retransmission pacing timer 66 msecs
Number of external LSA 0. Checksum Sum 0x000000
Number of areas in this router is 2. 2 normal 0 stub 0 nssa
Reference bandwidth unit is 100 mbps
Area BACKBONE(0)
Number of interfaces in this area is 1
MD5 Authentication, SPI 678
SPF algorithm executed 3 times
Number of LSA 6. Checksum Sum 0x032E78
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0
Area 3
Number of interfaces in this area is 1
SPF algorithm executed 2 times
Number of LSA 4. Checksum Sum 0x01CA07
Number of DCbitless LSA 0
Number of indication LSA 0
Number of DoNotAge LSA 0
Flood list length 0

By default, because IPv6 uses built-in IPsec functions, Cisco IOS software automatically creates IPsec policies for the configured authentication. The policy can be viewed using the **show crypto ipsec sa [interface <name>]** command on the router(s). Authentication Header (AH) is used. If you configure encryption, then Encapsulating Security Payload (ESP) will be used instead. Check the relevant SA states based on your configuration:

R3#**show crypto ipsec sa interface tunnel 0**

interface: Tunnel0
Crypto map tag: (none), local addr FE80::303:303

IPsecv6 policy name: OSPFv3-3-678
IPsecv6-created ACL name: Tunnel0-ipsecv6-ACL

protected vrf: (none)
local ident (addr/mask/prot/port): (FE80::/10/89/0)
remote ident (addr/mask/prot/port): (::/0/89/0)
current_peer :: port 500

https://t.me/learningnets

PERMIT, flags={origin_is_acl,}
#**pkts encaps: 12, #pkts encrypt: 0, #pkts digest: 12**
#pkts decaps: 12, #pkts decrypt: 0, #pkts verify: 12
#pkts compressed: 0, #pkts decompressed: 0
#pkts not compressed: 0, #pkts compr. failed: 0
#pkts not decompressed: 0, #pkts decompress failed: 0
#send errors 0, #recv errors 0

local crypto endpt.: FE80::303:303, remote crypto endpt.: ::
path mtu 1514, ip mtu 1514, ip mtu idb Tunnel0
current outbound spi: 0x2A6(678)

inbound esp sas:

inbound ah sas:
spi: 0x2A6(678)
transform: ah-md5-hmac ,
in use settings ={Transport, }
conn id: 2001, flow_id: SW:1, crypto map: (none)
no sa timing
replay detection support: N
Status: ACTIVE

inbound pcp sas:

outbound esp sas:

outbound ah sas:
spi: 0x2A6(678)
transform: ah-md5-hmac ,
in use settings ={Transport, }
conn id: 2002, flow_id: SW:2, crypto map: (none)
no sa timing
replay detection support: N
Status: ACTIVE

outbound pcp sas:

Additionally, you can also view the configuration parameters for the applied policy using the **show crypto ipsec policy** command on the router. The policy name, by default, will be OSPFv3-<process ID>-<SPI>. For example, on R1, the applied policy name will be OSPFv3-R1-678. This is validated and illustrated in the following output:

R3#**show crypto ipsec policy**
Crypto IPsec client security policy data

https://t.me/learningnets

Technet24

Policy name: OSPFv3-3-678
Policy refcount: 1
Inbound AH SPI: 678 (0x2A6)
Outbound AH SPI: 678 (0x2A6)
Inbound AH Key: 1234567890ABCDEF1234567890ABCDEF
Outbound AH Key: 1234567890ABCDEF1234567890ABCDEF
Transform set: ah-md5-hmac

Task 12

To complete this task, you need to enable the protected port feature on these ports. In addition, VMPS on the switch. This task is completed as follows:

ALS1(config)#**vmps server 150.1.1.254**
ALS1(config)#**$thernet 0/2 , fastethernet 0/5 - 6, fastethernet 0/9 - 10**
ALS1(config-if-range)#**switchport mode access**
ALS1(config-if-range)#**switchport access vlan dynamic**
ALS1(config-if-range)#**switchport protected**
ALS1(config-if-range)#**exit**

Verify basic Layer 2 parameters using the **show interfaces switchport** command:

ALS1#**show interfaces fastethernet 0/2 switchport**
Name: Fa0/2
Switchport: Enabled
Administrative Mode: dynamic access
Operational Mode: down
Administrative Trunking Encapsulation: dot1q
Negotiation of Trunking: Off
Access Mode VLAN: unassigned
Trunking Native Mode VLAN: 1 (default)
Voice VLAN: none
Administrative private-vlan host-association: none
Administrative private-vlan mapping: none
Administrative private-vlan trunk native VLAN: none
Administrative private-vlan trunk encapsulation: dot1q
Administrative private-vlan trunk normal VLANs: none
Administrative private-vlan trunk private VLANs: none
Operational private-vlan: none
Trunking VLANs Enabled: ALL
Pruning VLANs Enabled: 2-1001
Capture Mode Disabled

https://t.me/learningnets

Capture VLANs Allowed: ALL
Protected: true
Appliance trust: none

Verify VMPS configuration and operation using the **show vmps** commands:

ALS1#**show vmps**
VQP Client Status:

VMPS VQP Version: 1
Reconfirm Interval: 60 min
Server Retry Count: 3
VMPS domain server: 150.1.1.254 (primary, current)

Reconfirmation status

VMPS Action: other

Task 13

To complete this task, you need to enable storm control (port-based traffic control) and then enable SNMP so that traps are sent to server 150.1.1.254. This task is completed as follows:

ALS2(config)#**interface range fastethernet 0/1 - 9**
ALS2(config-if-range)#**storm-control broadcast level 5**
ALS2(config-if-range)#**storm-control multicast level 20**
ALS2(config-if-range)#**storm-control unicast level 80**
ALS2(config-if-range)#**storm-control action trap**
ALS2(config-if-range)#**exit**
ALS2(config)#**snmp-server community CCNP2011 RO**
ALS2(config)#**snmp-server host 150.1.1.254 traps CCNP2011**
ALS2(config)#**snmp-server enable traps**

Verify storm control configuration using the **show storm-control** commands:

ALS2#**show storm-control**
Interface Filter State Trap State Upper Lower Current Traps Sent
--- --- --- --- --- --- ---
Fa0/1 Forwarding Below rising 5.00% 5.00% 0.00% 0
Fa0/2 Forwarding Below rising 5.00% 5.00% 0.00% 0
Fa0/3 Forwarding Below rising 5.00% 5.00% 0.00% 0
Fa0/4 Forwarding Below rising 5.00% 5.00% 0.00% 0
Fa0/5 Forwarding Below rising 5.00% 5.00% 0.00% 0

https://t.me/learningnets
Technet24

Fa0/6 Forwarding Below rising 5.00% 5.00% 0.00% 0
Fa0/7 Forwarding Below rising 5.00% 5.00% 0.00% 0
Fa0/8 Forwarding Below rising 5.00% 5.00% 0.00% 0
Fa0/9 Forwarding Below rising 5.00% 5.00% 0.00% 0
Fa0/10 inactive inactive 100.00% 100.00% N/A 0
Fa0/11 inactive inactive 100.00% 100.00% N/A 0
Fa0/12 inactive inactive 100.00% 100.00% N/A 0

Verify SNMP configuration using the **show snmp** commands:

ALS2#**show snmp**
Chassis: FOC0620Y1FR
0 SNMP packets input
0 Bad SNMP version errors
0 Unknown community name
0 Illegal operation for community name supplied
0 Encoding errors
0 Number of requested variables
0 Number of altered variables
0 Get-request PDUs
0 Get-next PDUs
0 Set-request PDUs
0 SNMP packets output
0 Too big errors (Maximum packet size 1500)
0 No such name errors
0 Bad values errors
0 General errors
0 Response PDUs
0 Trap PDUs
SNMP global trap: enabled
SNMP logging: enabled
Logging to 150.1.1.254.162, 0/10, 0 sent, 0 dropped.
SNMP agent enabled

https://t.me/learningnets

CCNP Lab 086: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the https://ww.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

https://t.me/learningnets

You have received a problem report indicating that switch DLS2 is unable to reach any other device within VLAN 100. Troubleshoot and resolve this issue. Verify your solution using a simple ping from switch DLS2 to any other device within this VLAN.

Trouble Ticket # 2

You have received a problem report indicating that switch DLS2 is not receiving any routing information for external networks. Troubleshoot and resolve this issue. You can NOT modify the configurations on any routers when resolving this issue. Following the resolution, verify that DLS2 has external EIGRP routes in its routing table.

Trouble Ticket # 3

You have received a problem report indicating that users on the 150.4.4.0/24 subnet are unable to reach the 150.1.1.0/24 and 172.16.1.0/24 subnets. Troubleshoot and resolve this issue. Verify your solution issuing a ping from the 150.4.4.0/24 subnets to the 150.1.1.0/24 and 172.16.1.0/24 subnets. You are only allowed to change the configuration on ONE device when implementing a resolution for this issue. Verify by pinging between the subnets.

Trouble Ticket # 4

You have received a problem report indicating that the corporate NOC is unable to ping half of the devices that reside on the 172.16.1.0/24 subnet from the 150.4.4.0/24 subnet. Troubleshoot and resolve this issue. Validate your resolution by pinging all of the devices that reside on the subnet from the 150.4.4.0/24 subnet.

Lab Solutions

Solution # 1

The VLAN Access Control List (VACL) on switch DLS2 is misconfigured as follows:

vlan access-map FORWARD-ALL 10
action drop

The result of this configuration is all packets and frames within this VLAN will be dropped by the switch. To resolve this issue, the switch VACL needs to be reconfigured as follows:

DLS2(config)#**vlan access-map FORWARD-ALL 10**
DLS2(config-access-map)#**action forward**

Solution # 2

Switch DLS1 has been configured with a duplicate EIGRP router ID (the same as R2):

DLS1#**show run | begin router eigrp**
router eigrp 254

https://t.me/learningnets

Technet24

no auto-summary
eigrp router-id 1.0.0.2
network 0.0.0.0

By default, a router running EIGRP will NOT accept external routes from another router that has the same router ID. This is designed to prevent loops. In order to resolve this issue, the EIGRP router ID needs to be configured as follows:

DLS1(config)#**router eigrp 254**
DLS1(config-router)#**eigrp router-id 1.0.0.3**
DLS1(config-router)#**end**

NOTE: You can use any other value or completely remove the RID to complete this task.

Solution # 3

R2 has been configured to redistribute an EIGRP process that does not exist:

R2#**show running-config | section bgp**
no synchronization
bgp router-id 2.2.2.2
bgp log-neighbor-changes
redistribute eigrp 252
neighbor 10.0.0.10 remote-as 253
no auto-summary

To resolve this issue, you need to configure BGP to redistribute EIGRP AS 254 instead:

R2(config)#**router bgp 252**
R2(config-router)#**redistribute eigrp 254**

Solution # 4

The issue is that switches ALS1 and ALS2 have no default gateway, which prevents them from forwarding packets beyond their local subnet. Configure a default gateway as follows:

ALS1(config)#**ip default-gateway 172.16.1.1**

ALS2(config)#**ip default-gateway 172.16.1.1**

https://t.me/learningnets

CCNP Lab 087: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

https://t.me/learningnets

Trouble Ticket # 1

You have received a problem report indicating that switch ALS2 is inaccessible and cannot be reached even from devices residing on the 172.16.1.0/24 subnet. Troubleshoot and resolve this issue. Verify your solution by pinging DLS2 from any device on the 172.16.1.0/24 subnet.

Trouble Ticket # 2

You have received a problem report indicating slow convergence on the switched network. A co-worker has recently implemented 802.1w to speed up convergence, but it appears that the change did not resolve this issue. Troubleshoot and resolve this issue.

Trouble Ticket # 3

You have received a problem report indicating that users connected to the 172.16.1.0/24 and the 150.1.1.0/24 subnets are unable to reach the 150.4.4.0/24 subnet. Troubleshoot and resolve this issue. You are allowed to use only ONE command on any two routers in the network. You are NOT allowed to use any static routes. Verify your solution by pinging between these subnets.

Trouble Ticket # 4

You have received a problem report indicating that users are unable to receive Multicast traffic being sent from R4s LAN subnet. The NOC has joined the LAN interface of this router to Multicast group 227.4.4.4 but you cannot ping it from any other router. Troubleshoot and resolve this issue. Test your solution by pinging this address from all other routers.

Lab Solutions

Solution # 1

Even though an SVI for VLAN 172 exists, VLAN 172 itself is not configured on switch ALS2.

ALS2#**show vlan brief**

VLAN Name Status Ports

---- -------------------------------- --------- -------------------------

1 default active Fa0/1, Fa0/2, Fa0/3, Fa0/4
Fa0/5, Fa0/6, Fa0/11, Fa0/12
1002 fddi-default act/unsup
1003 trcrf-default act/unsup
1004 fddinet-default act/unsup
1005 trbrf-default act/unsup

https://t.me/learningnets

Technet24

The result of this configuration is that the switch will be inaccessible from all other devices. To resolve this issue, configure VLAN 172 on switch ALS2:

ALS2(config)#**vlan 172**
ALS2(config-vlan)#**name SWITCH-VLAN**

Solution # 2

The issue is that all switches, EXCEPT for switch DLS1, are running Rapid STP. RSTP is an IEEE standard and is therefore able to interoperate with traditional STP. However, it is important to realize that RSTP loses its ability to provide sub-second re-convergence when implemented in a network that also contains switches that are only 802.1D capable. Verify the STP mode using the **show spanning-tree summary** command on all switches:

DLS1#**show spanning-tree summary**
Switch is in pvst mode

[Truncated Output]

DLS2#**show spanning-tree summary**
Switch is in rapid-pvst mode

[Truncated Output]

ALS1#**show spanning-tree summary**
Switch is in rapid-pvst mode

[Truncated Output]

ALS2#**show spanning-tree summary**
Switch is in rapid-pvst mode

[Truncated Output]

To resolve this issue, implement Rapid STP on switch DLS1:

DLS1(config)#**spanning-tree mode rapid-pvst**

Solution # 3

The issue is that iBGP has not been configured to redistribute routes into OSPF or EIGRP on routers R2 and R3 as can be seen in the configuration:

R2#**show running-config | section bgp**
redistribute bgp 252 subnets
router bgp 252
no synchronization
bgp log-neighbor-changes
network 150.2.2.0 mask 255.255.255.0

https://t.me/learningnets

redistribute ospf 2 match internal external 2
neighbor 10.0.0.10 remote-as 252
no auto-summary

R3#**show running-config | section bgp**
redistribute bgp 252
router bgp 252
no synchronization
bgp router-id 3.3.3.3
bgp log-neighbor-changes
network 150.3.3.0 mask 255.255.255.0
redistribute eigrp 254
neighbor 10.0.0.9 remote-as 252
no auto-summary

To resolve this issue, configure iBGP redistribution into IGPs using the **bgp redistribute-internal** command on routers R2 and R3:

R2(config)#**router bgp 252**
R2(config-router)#**bgp redistribute-internal**

R3(config)#**router bgp 252**
R3(config-router)#**bgp redistribute-internal**

Solution # 4

The issue is that R1 and R2 have IP Multicast interfaces configured for Sparse mode forwarding. In order to use Auto RP, you need to enable Sparse-Dense mode:

R1#**show ip pim interface**

Address Interface Ver/ Nbr Query DR DR
Mode Count Intvl Prior
1.1.1.1 Loopback0 v2/S 0 30 1 1.1.1.1
10.0.0.1 Serial0/0 v2/S 1 30 1 0.0.0.0

R2#**show ip pim interface**

Address Interface Ver/ Nbr Query DR DR
Mode Count Intvl Prior
10.0.0.2 Serial0/0 v2/S 1 30 1 0.0.0.0
10.0.0.9 Serial0/1 v2/S 1 30 1 0.0.0.0

To resolve this issue, you need to enable Sparse-Dense mode forwarding:

R1(config)#**interface loopback 0**
R1(config-if)#**ip pim sparse-dense-mode**

https://t.me/learningnets

Technet24

```
R1(config-if)#exit
R1(config)#interface serial 0/0
R1(config-if)#ip pim sparse-dense-mode
R2(config)#interface serial 0/0
R2(config-if)#ip pim sparse-dense-mode
R2(config-if)#exit
R2(config)#interface serial 0/1
R2(config-if)#ip pim sparse-dense-mode
```

https://t.me/learningnets

CCNP Lab 088: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

https://t.me/learningnets

You have received a problem report indicating that users on the 150.2.2.0/24 subnet are unable to reach users on the 172.16.1.0/24 subnet and vice-versa. Troubleshoot and resolve this issue. Verify your solution by pinging between these two subnets.

Trouble Ticket # 2

You have received a problem report indicating that users on the 150.3.3.0/24 subnet are also unable to reach users on the 172.16.1.0/24 subnet and vice-versa. Troubleshoot and resolve this issue. Verify your solution by pinging between these two subnets.

Trouble Ticket # 3

You have received a problem report indicating that users no users on the network can reach the 150.4.4.0/24 subnet. Troubleshoot and resolve this issue. Test your solution by pinging this subnet from any one of the other LAN subnets.

Trouble Ticket # 4

You have received a problem report indicating users connected to the 150.4.4.0/24 subnet are unable to receive IP addressing information via DHCP. Troubleshoot and resolve this issue.

Lab Solutions

Solution # 1

The static route on R1 has been misconfigured. It is pointing to 150.1.1.22 instead of 150.1.1.2:

R1#**show ip route 172.16.1.0 255.255.255.0**
Routing entry for 172.16.1.0/24
Known via “static”, distance 1, metric 0
Advertised by bgp 100
Routing Descriptor Blocks:
*** 150.1.1.22, via FastEthernet0/0**
Route metric is 0, traffic share count is 1

The result of this configuration is that the subnet will be inaccessible from all other devices. To resolve this issue, remove this static route and configure a correct next-hop address:

R1(config)#**no ip route 172.16.1.0 255.255.255.0 FastEthernet0/0 150.1.1.22**
R1(config)#**ip route 172.16.1.0 255.255.255.0 FastEthernet0/0 150.1.1.2**

Solution # 2

By default, the NEXT_HOP attribute is not modified when routes are sent from a BGP speaker to an internal peer. This can be resolved in one of two ways:

https://t.me/learningnets

- Redistribute the 10.0.0.0/30 subnet into OSPF on R2
- Change the NEXT_HOP attribute for BGP on R2

The following shows the latter solution. Either option is acceptable when completing this task.

R2(config)#**router bgp 252**
R2(config-router)#**neighbor 10.0.0.10 next-hop-self**
R2(config-router)#**exit**

Solution # 3

The issue is that R4 has been configured as a receive-only EIGRP stub router. This prevents the router from advertising the 150.4.4.0/24 subnet via EIGRP to R3:

R4#**show running-config | section eigrp**
router eigrp 254
network 0.0.0.0
no auto-summary
eigrp stub receive-only

To resolve this issue, configure R4 as an EIGRP stub. By default, this will cause the router to advertise connected subnets:

R4(config)#**router eigrp 254**
R4(config-router)#**no eigrp stub receive-only**
R4(config-router)#**eigrp stub**

Solution # 4

There are two issues here. First, the DHCP service is disabled on R2 , the Cisco IOS DHCP Server. The second issue is that the Cisco IOS DHCP Relay Agent is not configured on R4. Resolve this issue by enabling Cisco IOS DHCP Server functionality on R2 and then also configuring the Cisco IOS DHCP Relay Agent on R4s LAN interface:

R2(config)#**service dhcp**

R4(config)#**interface fastethernet 0/0**
R4(config-if)#**ip helper-address 10.0.0.9**
R4(config-if)#**exit**

https://t.me/learningnets

CCNP Lab 089: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

https://t.me/learningnets

Trouble Ticket # 1

You have received a problem report indicating that following a change on the 172.16.1.0/24 subnet, switches DLS1 and DLS2 are no longer able to establish an OSPF adjacency. Troubleshoot and resolve this issue. You are only allowed to makes changes to ONE of these devices, but not both.

Trouble Ticket # 2

You have received a problem report indicating that the Level 1 Network staff cannot see the OSPF neighbor adjacency between router R1 and switch DLS1. Troubleshoot and resolve this issue. You are only allowed to issue ONE command to resolve this issue.

Trouble Ticket # 3

Recently Quality of Service was implemented on the R2-R3 link. However, the NOC calls to report that packets are not getting marked as configured. Troubleshoot and resolve the issue.

Trouble Ticket # 4

You have received a problem report indicating that users on the 150.4.4.0/24 subnet are unable to reach any other subnet. Troubleshoot and resolve this issue.

Trouble Ticket # 5

Recently, IPv6 was integrated into the network. However, some test users connected to the 3FFE:ABCD:1111:1/64 (R1s LAN) and the 3FFE:ABCD:3333:3/64 (R4s LAN) subnets are complaining that they are unable to reach each other. Troubleshoot and resolve this issue.

Trouble Ticket # 6

You receive a call from the Level 1 NOC located on the 172.16.1.0/24 subnet stating that they have lost connectivity to R4. Troubleshoot and resolve this issue.

Lab Solutions

Solution # 1

The issue is that DLS1 (and all the other switches) are running MSTP. While switch DLS2 does have the MST configuration, it is actually running RSTP:

DLS1#**show running-config | begin spanning-tree mode**
spanning-tree mode mst
spanning-tree extend system-id
!
spanning-tree mst configuration

https://t.me/learningnets

Technet24

name CCNP
instance 1 vlan 172, 272
instance 2 vlan 372, 472
instance 3 vlan 572, 672
instance 4 vlan 772, 872
!
spanning-tree mst 2 priority 0

DLS2#**show running-config | begin spanning-tree mode**
spanning-tree mode rapid-pvst
spanning-tree extend system-id
!
spanning-tree mst configuration
name CCNP
instance 1 vlan 172, 272
instance 2 vlan 372, 472
instance 3 vlan 572, 672
instance 4 vlan 772, 872
!
spanning-tree mst 3 priority 0

To resolve this issue, configure DLS2 to also run MSTP:

DLS2(config)#**spanning-tree mode mst**

Solution # 2

The issue is NOT with the OSPF configuration itself. Again, keep in mind that OSPF will also form an adjacency as long as parameters, such as timers, are the same. The issue is actually because of the mismatched OSPF network statement and the IP address assigned to the SVI configured on switch DLS2. To resolve this issue, perform one of the following actions:

- Change the IP address on interface VLAN 100 to match the OSPF network statement
- Change the OSPF network statement to match the IP assigned to interface VLAN 100

The solution below illustrates the first option:

DLS1(config-if)#**interface vlan 100**
DLS1(config-if)#**ip add 150.1.1.2 255.255.255.0**

https://t.me/learningnets

Solution # 3

When implementing QoS, Class-Based Packet Marking changes values in a packet header with the **set** command. Cisco IOS confirms that your router runs CEF before you attach a service policy with the **set** command. To resolve this issue, configure you must enable IOS CEF on R2:

R2(config)#**ip cef**

Solution # 4

When implementing ODR, only the hub router should be configured with the **router odr** global configuration command. All that is required on the spoke(s) is that CDP is enabled. Correct this issue by disabling this command from router R4:

R4(config)#**no router odr**

Solution # 5

There are two issues here: first, the tunnel source and destination addresses on R1 are incorrect:

R1#**show running-config interface tunnel 0**
Building configuration...

Current configuration : 161 bytes
!
interface Tunnel0
no ip address
ipv6 address 2001:ABCD:1111:A::1/64
ipv6 enable
tunnel source 4.4.4.4
tunnel destination 1.1.1.1
tunnel mode ipv6ip
end

Second, the tunnel mode configured on R4 is incorrect:

R4#**show running-config interface tunnel 0**
Building configuration...

Current configuration : 161 bytes
!
interface Tunnel0
no ip address
ipv6 address 2001:ABCD:1111:A::4/64
ipv6 enable

https://t.me/learningnets

Technet24

tunnel source Loopback0
tunnel destination 1.1.1.1
tunnel mode ipip
end

Resolve this issue on R1 by implementing the following configuration:

R1(config)#**interface tunnel 0**
R1(config-if)#**tunnel destination 4.4.4.4**
R1(config-if)#**tunnel source 1.1.1.1**

Resolve this issue on R4 by implementing the following configuration:

R4(config)#**interface tunnel 0**
R4(config-if)#**tunnel mode ipv6ip**

Solution # 6

The issue is that the subnet between R3 and R4 is not advertised via EIGRP. This is the default behavior when running ODR.

R3#**show running-config | section eigrp**
router eigrp 254
redistribute odr
network 10.0.0.10 0.0.0.0
network 150.3.3.3 0.0.0.0
default-metric 1544 20000 255 1 1500
no auto-summary

To resolve this issue, redistribute or advertise the connected subnet via EIGRP:

R3(config)#**router eigrp 254**
R3(config-router)#**redistribute connected**

https://t.me/learningnets

CCNP Lab 090: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the

https://t.me/learningnets

order listed.

Trouble Ticket # 1

You have received a problem report indicating that no one is able to reach switch DLS2. Troubleshoot and resolve this issue.

Trouble Ticket # 2

The NOC calls you to advise that they are unable to reach the 172.16.1.0/24 subnet from the 150.2.2.0/24 subnet. Troubleshoot and resolve this issue. However, ensure that your solution does NOT include advertising the 150.1.1.0/24 subnet via BGP or using static routes.

Trouble Ticket # 3

There is a secure tunnel between R1 and R4 that protects traffic between the 150.1.1.0/24 and 150.4.4.0/24 subnets. For some reason, this tunnel is not working and you are unable to ping between these subnets. Troubleshoot and resolve this issue.

Trouble Ticket # 4

A Multicast video solution is being tested between the 150.2.2.0/24 and the 150.3.3.0/24 subnets. However, the users are reporting that this is not working. Troubleshoot and resolve this issue. For proprietary reasons, the company does not allow RPs within the network.

Lab Solutions

Solution # 1

The issue is that DLS2 is running RIPv1 while switch DLS2 is running RIPv2. Switch DLS2 will therefore not receive any routing information from switch DLS1:

DLS2#**show ip protocols**
*** IP Routing is NSF aware ***

Routing Protocol is “rip”
Outgoing update filter list for all interfaces is not set
Incoming update filter list for all interfaces is not set
Sending updates every 30 seconds, next due in 6 seconds
Invalid after 180 seconds, hold down 180, flushed after 240
Redistributing: rip
Default version control: send version 1, receive version 1
Interface Send Recv Triggered RIP Key-chain
Vlan172 1 1
Automatic network summarization is not in effect

https://t.me/learningnets

Technet24

Maximum path: 4
Routing for Networks:
172.16.0.0
Routing Information Sources:
Gateway Distance Last Update
Distance: (default is 120)

To resolve this issue, configure switch DLS2 to also run RIPv2:

DLS2(config)#**router rip**
DLS2(config-router)#**version 2**

Solution # 2

There are two issues here: the first issue is that R1 has been configured with the incorrect AS number for its peer, switch DLS1:

R1#**show ip bgp summary**
BGP router identifier 1.1.1.1, local AS number 254
BGP table version is 12, main routing table version 12
6 network entries using 702 bytes of memory
6 path entries using 312 bytes of memory
5/4 BGP path/bestpath attribute entries using 620 bytes of memory
0 BGP route-map cache entries using 0 bytes of memory
0 BGP filter-list cache entries using 0 bytes of memory
BGP using 1634 total bytes of memory
BGP activity 7/1 prefixes, 7/1 paths, scan interval 60 secs

Neighbor V AS MsgRcvd MsgSent TblVer InQ OutQ Up/Down State/PfxRcd
10.0.0.2 4 254 80 77 12 0 0 01:05:34 5
150.1.1.2 4 56500 74 88 0 0 0 00:01:13 Active

To resolve this issue, implement the following configuration on router R1:

R1(config)#**router bgp 254**
R1(config-router)#**neighbor 150.1.1.2 remote-as 65500**

The second issue is that the NEXT_HOP for this subnet will be unknown to R2. R2 will not be able to reach this subnet because of this. Resolve this issue on R1 as follows:

R1(config)#**router bgp 254**
R1(config-router)#**neighbor 10.0.0.2 next-hop-self**

Solution # 3

There issue actually resides on R2, which has an ACL applied in the inbound direction. This ACL needs to be modified to permit ESP (protocol number 50):

https://t.me/learningnets

R2#**show ip access-lists**
Extended IP access list INTERNET-PROTECTION
10 permit tcp any any eq bgp (27 matches)
20 permit tcp any eq bgp any
30 deny ospf any any
40 deny eigrp any any
50 deny udp any any eq rip
60 deny 41 any any
70 permit tcp any any eq www
80 permit tcp any any eq 443
90 deny tcp any any eq telnet
100 deny tcp any eq telnet any
110 permit icmp any any
120 permit gre any any
130 permit udp any eq 50 any
140 permit udp any any eq 50
150 permit udp any eq isakmp any
160 permit udp any any eq isakmp
200 deny ip any any (83 matches)

To resolve this issue, implement the following configuration on R2:

R2(config)#**ip access-list extended INTERNET-PROTECTION**
R2(config-ext-nacl)#**170 permit esp any any**

Solution # 4

The issue is that Sparse Mode forwarding is being used and there is no Rendezvous Point configured on the network:

R2#**show ip pim interface**

Address Interface Ver/ Nbr Query DR DR
Mode Count Intvl Prior
150.2.2.2 FastEthernet0/0 v2/S 1 30 1 150.2.2.2
10.0.0.9 Serial0/1 v2/S 1 30 1 0.0.0.0

R3#**show ip pim interface**

Address Interface Ver/ Nbr Query DR DR
Mode Count Intvl Prior
10.0.0.10 Serial1/1 v2/S 1 30 1 0.0.0.0
150.3.3.3 FastEthernet0/0 v2/S 1 30 1 150.3.3.3

To resolve this issue, without using an RP, configure Dense Mode forwarding instead:

https://t.me/learningnets
Technet24

R2(config)#**int f0/0**
R2(config-if)#**ip pim dense-mode**
R2(config-if)#**exit**
R2(config)#**int s0/1**
R2(config-if)#**ip pim dense-mode**

R3(config)#**int f0/0**
R3(config-if)#**ip pim dense-mode**
R3(config-if)#**exit**
R3(config)#**int s1/1**
R3(config-if)#**ip pim dense-mode**

https://t.me/learningnets

CCNP Lab 091: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

You have received a problem report indicating that HSRP is not working between switches DLS1 and DLS1. Troubleshoot and resolve this issue.

Trouble Ticket # 2

The NOC has called you advising that they are unable to ping switch ALS1 from any of the devices. Troubleshoot and resolve this issue.

Trouble Ticket # 3

Users connected to the 150.100.1.0/24 subnet has complained that they are unable to reach devices on the 150.200.1.0/24 subnet and vice-versa. Troubleshoot and resolve

https://t.me/learningnets

this issue.

Trouble Ticket # 4

You have received an urgent call from the NOC stating that following some configuration changes on switches DLS1 and DLS2, their monitoring servers are no longer receiving any Spanning-Tree Protocol notifications from the devices. Troubleshoot and resolve this issue.

Lab Solutions

Solution # 1

The issue is that both switch DLS1 and DLS2 have been configured with the same IP addresses for the SVIs for VLANs 100 and 200:

DLS1#**show running-config interface vlan 100**
Building configuration...

Current configuration : 138 bytes
!
interface Vlan100
ip address 150.100.1.2 255.255.255.0
standby 100 ip 150.100.1.1
standby 100 priority 105
standby 100 preempt
end

DLS1#**show running-config interface vlan 200**
Building configuration...

Current configuration : 112 bytes
!
interface Vlan200
ip address 150.200.1.2 255.255.255.0
standby 200 ip 150.200.1.1
standby 200 preempt
end

DLS2#**show running-config interface vlan 100**
Building configuration...

Current configuration : 112 bytes
!
interface Vlan100
ip address 150.100.1.2 255.255.255.0

https://t.me/learningnets

Technet24

standby 100 ip 150.100.1.1
standby 100 preempt
end

DLS2#**show running-config interface vlan 200**
Building configuration...

Current configuration : 138 bytes
!
interface Vlan200
ip address 150.200.1.2 255.255.255.0
standby 200 ip 150.200.1.1
standby 200 priority 105
standby 200 preempt
end

To resolve this issue, change the configuration on switch DLS2s SVIs to a different IP address:

DLS2(config)#**interface vlan 100**
DLS2(config-if)#**ip address 150.100.1.3 255.255.255.0**
DLS2(config-if)#**exit**
DLS2(config)#**interface vlan 200**
DLS2(config-if)#**ip address 150.200.1.3 255.255.255.0**
DLS2(config-if)#**exit**

Solution # 2

The issue is that the EtherChannels between switch ALS1 and switches DLS1 and DLS2 are set to passive mode. This will prevent the LACP channel from forming.

DLS1#**show etherchannel 1 port | include Mode**
Channel group = 1 Mode = Passive Gcchange = -
Channel group = 1 Mode = Passive Gcchange = -

DLS2#**show etherchannel 2 port | include Mode**
Channel group = 2 Mode = Passive Gcchange = -
Channel group = 2 Mode = Passive Gcchange = -

ALS1#**show etherchannel 1 port | include Mode**
Channel group = 1 Mode = Passive Gcchange = -
Channel group = 1 Mode = Passive Gcchange = -

ALS1#**show etherchannel 2 port | include Mode**
Channel group = 2 Mode = Passive Gcchange = -
Channel group = 2 Mode = Passive Gcchange = -

https://t.me/learningnets

To resolve this issue, configure at least one end of the EtherChannel in active mode:

DLS1(config)#**interface range fastethernet 0/7 - 8**
DLS1(config-if-range)#**channel-group 1 mode active**

DLS2(config)#**interface range fastethernet 0/9 - 10**
DLS2(config-if-range)#**channel-group 2 mode active**

Solution # 3

The issue is that both IP routing is disabled on both DLS1 and DLS2:

DLS1#**show ip route**
Default gateway is not set

Host Gateway Last Use Total Uses Interface
ICMP redirect cache is empty

DLS2#**show ip route**
Default gateway is not set

Host Gateway Last Use Total Uses Interface
ICMP redirect cache is empty

To resolve this issue, enable IP routing on both of the switches:

DLS1(config)#**ip routing**

DLS2(config)#**ip routing**

Solution # 4

The issue is that both Spanning Tree logging has been disabled (default) on both switches. To resolve this issue, enable logging globally and on all trunk links:

DLS1(config)#**interface port-channel 1**
DLS1(config-if)#**logging event spanning-tree**
DLS1(config-if)#**exit**
DLS1(config)#**interface port-channel 2**
DLS1(config-if)#**logging event spanning-tree**
DLS1(config-if)#**exit**
DLS1(config)#**interface port-channel 5**
DLS1(config-if)#**logging event spanning-tree**
DLS1(config-if)#**exit**
DLS1(config)#**spanning-tree logging**

DLS2(config)#**interface port-channel 1**
DLS2(config-if)#**logging event spanning-tree**
DLS2(config-if)#**exit**

https://t.me/learningnets

Technet24

DLS2(config)#**interface port-channel 2**
DLS2(config-if)#**logging event spanning-tree**
DLS2(config-if)#**exit**
DLS2(config)#**interface port-channel 5**
DLS2(config-if)#**logging event spanning-tree**
DLS2(config-if)#**exit**
DLS2(config)#**spanning-tree logging**

https://t.me/learningnets

CCNP Lab 092: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

The NOC has called to report that they are unable to see any prompts when they are trying to configure switches DLS1 and DLS2. Troubleshoot and resolve this issue.

Trouble Ticket # 2

You have received a problem report indicating that switch DLS1 is unable to ping any other device on the network, including its default gateway. Troubleshoot and resolve this issue.

Trouble Ticket # 3

The NOC has recently configured OSPF between switches DLS1 and DLS2. However,

https://t.me/learningnets

they advise that the OSPF adjacency is not coming up. Troubleshoot and resolve this issue.

Trouble Ticket # 4

The NOC has recently called you to advise that they are unable to ping between switches ALS1 and ALS2. Both switches can ping the HSRP VIPs. Troubleshoot and resolve this issue.

Lab Solutions

Solution # 1

The issue is that the prompt service for configuration mode has been disabled on the switches:

DLS1#**show running-config | include service**
no service pad
service timestamps debug datetime msec
service timestamps log datetime msec
no service password-encryption
no service prompt config
DLS1#**configure terminal**
Enter configuration commands, one per line. End with CNTL/Z.

end
DLS1#

DLS2#**show running-config | include service**
no service pad
service timestamps debug datetime msec
service timestamps log datetime msec
no service password-encryption
no service prompt config
DLS2#**configure terminal**
Enter configuration commands, one per line. End with CNTL/Z.

end
DLS2#

To resolve this issue, enable the configuration prompt service:

DLS1#**config t**
Configuring from terminal, memory, or network [terminal]?
Enter configuration commands, one per line. End with CNTL/Z.
service prompt config

https://t.me/learningnets

Technet24

DLS1(config)#exit

DLS2#**config t**
Enter configuration commands, one per line. End with CNTL/Z.
service prompt config
DLS2(config)#**exit**

Solution # 2

The issue is that switch DLS1 has a misconfigured VACL which is denying all ARP frames. ARP frames use the Ethernet protocol type of value 0x806:

DLS1#**show vlan access-map**
Vlan access-map "SECURITY" 10
Match clauses:
mac address: ARP
Action:
drop

DLS1#**show running-config | begin mac**
mac access-list extended ARP
permit any any 0x806 0x0

To resolve this issue, configure the VACL to forward ARP frames:

DLS1(config)#**vlan access-map SECURITY 10**
DLS1(config-access-map)#**action forward**

Solution # 3

The issue is that switch DLS2 has IP routing disabled even though OSPF has been configured.

DLS2#**show ip route**
Default gateway is not set

Host Gateway Last Use Total Uses Interface
ICMP redirect cache is empty

To resolve this issue, enable IP routing on switch DLS2:

DLS2(config)#**ip routing**

Solution # 4

The issue is that switch ALS2 has a misconfigured default gateway:

ALS2#**show ip redirects**
Default gateway is 150.100.1.1

Host Gateway Last Use Total Uses Interface

https://t.me/learningnets

ICMP redirect cache is empty

To resolve this issue, configure the correct default gateway:

ALS2(config)#**ip default-gateway 150.200.1.1**

https://t.me/learningnets

CCNP Lab 093: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

You have received a call from Level 1 support indicating that following some scheduled changes, they have lost connectivity to router R2. Troubleshoot and resolve this issue.

Trouble Ticket # 2

Users are complaining about excessive latency between the 150.1.1.0/24 and

https://t.me/learningnets

Technet24

150.3.3.0/24 subnet. Previously, this traffic was load-shared across R2 because of the low-bandwidth 512Kbps connecting R1 and R3. Troubleshoot and resolve this issue.

Trouble Ticket # 3

You have received several complaints that the NOC is unable to reach some Loopback subnets configured on R1 from the other routers. Management has forbidden the modification of the EIGRP configuration on R1. With this restriction in mind, troubleshoot and resolve this issue.

Trouble Ticket # 4

You have received an urgent call from the NOC stating that while they were troubleshooting TCP connectivity issues between the 150.4.4.0/24 and 150.1.1.0/24 subnets they lost all connectivity to R4. Troubleshoot and resolve this issue.

Lab Solutions

Solution # 1

The issue is that R2 has been configured with all interfaces, except for FastEthernet0/0, as passive under EIGRP. This prevents the router from forming neighbor relationships with routers running EIGRP in the same autonomous system:

R2#**show running-config | section eigrp**
router eigrp 254
passive-interface default
no passive-interface FastEthernet0/0
network 10.0.0.2 0.0.0.0
network 10.0.0.9 0.0.0.0
network 150.2.2.2 0.0.0.0
no auto-summary

To resolve this issue, modify the configuration on R2 as follows:

R2(config)#**router eigrp 254**
R2(config-router)#**passive-interface fastethernet 0/0**
R2(config-router)#**no passive-interface serial 0/0**
R2(config-router)#**no passive-interface serial 0/1**
R2(config-router)#**exit**

Solution # 2

The issue is that while R1 and R3 have been configured to use unequal cost load sharing, they have been configured to forward packets using only the lowest metric (cost) path:

https://t.me/learningnets

R3#**show running-config | section eigrp**
router eigrp 254
variance 4
traffic-share min across-interfaces
passive-interface FastEthernet0/0
network 10.0.0.6 0.0.0.0
network 10.0.0.10 0.0.0.0
network 10.0.0.13 0.0.0.0
network 150.3.3.3 0.0.0.0
no auto-summary

R1#**show running-config | section eigrp**
router eigrp 254
variance 4
traffic-share min across-interfaces
redistribute static
passive-interface FastEthernet0/0
network 10.0.0.1 0.0.0.0
network 10.0.0.5 0.0.0.0
network 150.1.1.1 0.0.0.0
no auto-summary

To resolve this issue, modify the configuration on these routers as follows:

R1(config)#**router eigrp 254**
R1(config-router)#**no traffic-share min across-interfaces**

R3(config)#**router eigrp 254**
R3(config-router)#**no traffic-share min across-interfaces**

Solution # 3

The issue is that the unreachable subnets are not covered in any of the advertised aggregate prefixes. To resolve this, without modifying the EIGRP configuration, do one of two things:

- Configure and advertise a summary route
- Configure and advertise a default route

R1(config)#**ip route 172.30.48.0 255.255.240.0 null 0**

OR

R1(config)#**ip route 0.0.0.0 0.0.0.0 null 0**

https://t.me/learningnets

Technet24

Solution # 4

The issue is that the clocking has been removed from the Serial1/2 interface on R3. The interface will therefore not come up:

R3#**show controllers serial 1/2**
CD2430 Slot 1, Port 2, Controller 0, Channel 2, Revision 19
Channel mode is synchronous serial
idb 0x84D4D7D8, buffer size 1524, V.35 DCE cable

R4#**show controllers serial 0/0**
Interface Serial0/0
Hardware is PowerQUICC MPC860
DTE V.35 clocks stopped.

To resolve this issue, configure R3s Serial1/2 interface to provide clocking:

R3(config)#**interface serial 1/2**
R3(config-if)#**clock rate 128000**

https://t.me/learningnets

CCNP Lab 094: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

You have received a call from Level 1 support indicating that following some scheduled WAN changes, connectivity from the 150.3.3.0/24 subnet to the 150.1.1.0/24 and 150.2.2.0/24 subnets has been lost. Troubleshoot and resolve this issue.

Trouble Ticket # 2

https://t.me/learningnets

You have received a call from the NOC indicating that the EIGRP neighbor relationship between R3 and R4 failed following some scheduled routing configuration changes. Troubleshoot and resolve this issue.

Trouble Ticket # 3

You have received calls from users connected to the 150.4.4.0/24 subnet advising that every time there is a report of a failed network link, they lose connectivity to the 150.1.1.0/24 and 150.2.2.0/24 subnets. Troubleshoot and resolve this issue.

Trouble Ticket # 4

You have received a call from Level 1 support indicating that users connected to the 150.4.4.0/24 subnet cannot connect to a server with the IP address 150.3.3.254. The NOC has also stated that they are unable to ping R3s LAN interface IP address from R4. Troubleshoot and resolve this.

Lab Solutions

Solution # 1

The issue is that EIGRP authentication is misconfigured on R1 and R2. EIGRP authentication has been configured for AS 254 instead of AS 354:

R1#**show running-config interface serial 0/1**
Building configuration...

Current configuration : 148 bytes
!
interface Serial0/1
ip address 10.0.0.5 255.255.255.252
ip authentication mode eigrp 254 md5
ip authentication key-chain eigrp 254 SECURE
end

R2#**show running-config interface serial 0/1**
Building configuration...

Current configuration : 148 bytes
!
interface Serial0/1
ip address 10.0.0.9 255.255.255.252
ip authentication mode eigrp 254 md5
ip authentication key-chain eigrp 254 SECURE
end

To resolve this issue, implement authentication for AS 354 under these interfaces on R1

https://t.me/learningnets

Technet24

and R2:

R2(config-if)#**interface serial 0/1**
R2(config-if)#**no ip authentication mode eigrp 254 md5**
R2(config-if)#**no ip authentication key-chain eigrp 254 SECURE**
R2(config-if)#**ip authentication mode eigrp 354 md5**
R2(config-if)#**ip authentication key-chain eigrp 354 SECURE**

R3(config-if)#**interface serial 0/1**
R3(config-if)#**no ip authentication mode eigrp 254 md5**
R3(config-if)#**no ip authentication key-chain eigrp 254 SECURE**
R3(config-if)#**ip authentication mode eigrp 354 md5**
R3(config-if)#**ip authentication key-chain eigrp 354 SECURE**

Solution # 2

The issue is that the EIGRP K values are mismatched on routers R3 and R4:

R3#**show running-config | section eigrp**
redistribute eigrp 354
network 10.0.0.13 0.0.0.0
network 150.3.3.3 0.0.0.0
metric weights 0 0 1 1 1 0
no auto-summary

R4#**show running-config | section eigrp**
router eigrp 454
network 10.0.0.14 0.0.0.0
network 150.1.1.4 0.0.0.0
metric weights 0 1 1 1 0 0
no auto-summary

To resolve this issue, configure the K values using the same variables on both routers. This task can be completed by changing the K values on R3 to match those on R4, or vice-versa:

R3(config)#**router eigrp 454**
R3(config-router)#**metric weights 0 1 1 1 0 0**

Solution # 3

There are two issues here: the first is that the EIGRP 254 is not being redistributed by EIGRP 354 on R2. Therefore, if the R1-R3 link were to fail, the 150.1.1.0/24 and 150.2.2.0/24 subnets would never be advertised. The second issue is that EIGRP 254 is not redistributing EIGRP 354. Therefore, if either the R1-R3 or R2-R3 links failed, routers R1 or R2, respectively, would never have connectivity to the rest of the

https://t.me/learningnets

network:

R2#**show running-config | section eigrp**
ip authentication mode eigrp 254 md5
ip authentication key-chain eigrp 254 SECURE
router eigrp 254
network 10.0.0.2 0.0.0.0
network 150.2.2.2 0.0.0.0
no auto-summary
router eigrp 354
timers active-time 30
network 10.0.0.9 0.0.0.0
no auto-summary

To resolve this issue, implement route redistribution correctly on all routers:

R1(config)#**router eigrp 254**
R1(config-router)#**redistribute eigrp 354**

R2(config)#**router eigrp 254**
R2(config-router)#**redistribute eigrp 354**
R2(config-router)#**exit**
R2(config)#**router eigrp 354**
R2(config-router)#**redistribute eigrp 254**

Solution # 4

The issue here is that the 150.3.3.0/24 subnet has been configured as a secondary subnet on R4s LAN interface, which means that the received EIGRP route from R3 will be ignored:

R4#**show running-config interface fastethernet 0/0**
Building configuration...

Current configuration : 140 bytes
!
interface FastEthernet0/0
ip address 150.3.3.4 255.255.255.0 secondary
ip address 150.4.4.4 255.255.255.0
duplex auto
speed auto
end

To resolve this issue, remove this subnet from the LAN interface of R4:

R4(config)#**interface fastethernet 0/0**

https://t.me/learningnets

Technet24

R4(config-if)#**no ip address 150.3.3.4 255.255.255.0 secondary**

https://t.me/learningnets

CCNP Lab 095: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

You have received a call from Level 1 stating that following some configuration changes, the OSPF neighbor adjacency between R1 and R2 has failed. Troubleshoot and resolve this issue.

Trouble Ticket # 2

https://t.me/learningnets

You have received a call stating that users connected R1 and R2 do not have any routing information for the 150.4.4.0/24 subnet. Troubleshoot and resolve this issue.

Trouble Ticket # 3

You have received a call from Level 1 support stating that while all of the users connected to the 150.3.3.0/24 subnets are able to reach the 150.4.4.0/24 subnet, and vice-versa, the support operatives are unable to ping the 150.4.4.4/24 address from any other device within the network. Troubleshoot and resolve this issue.

Lab Solutions

Solution # 1

The issue is that the routers are on different subnets. R1s Serial 0/0 interface is on the 10.0.0.0/30 subnet while R2s Serial0/0 interface is on the 10.0.0.0/29 subnet:

R1#**show running-config interface serial 0/0**
Building configuration...

Current configuration : 84 bytes
!
interface Serial0/0
ip address 10.0.0.1 255.255.255.252
ip ospf network point-to-multipoint
ip ospf hello-interval 10
clock rate 2000000
end

R2#**show running-config interface serial 0/0**
Building configuration...

Current configuration : 64 bytes
!
interface Serial0/0
ip address 10.0.0.2 255.255.255.248
ip ospf network point-to-multipoint
ip ospf hello-interval 10
end

To resolve this issue, correct the IP addressing misconfiguration on R2s Serial 0/0 interface:

R2(config)#**interface serial 0/0**
R2(config-if)#**ip address 10.0.0.2 255.255.255.252**

Solution # 2

https://t.me/learningnets

Technet24

The issue is that OSPF virtual link configuration on all three routers is incorrect. On routers R1 and R2, the virtual links are using the link IP addresses instead of the RID of R3. On R3, the virtual links are using an incorrect transit area:

R1#**show running-config | section ospf**
ip ospf network broadcast
ip ospf hello-interval 5
router ospf 1
router-id 1.1.1.1
log-adjacency-changes
area 1 virtual-link 10.0.0.6
network 10.0.0.1 0.0.0.0 area 0
network 10.0.0.5 0.0.0.0 area 1
network 150.1.1.1 0.0.0.0 area 0

R2#**show running-config | section ospf**
ip ospf network broadcast
ip ospf hello-interval 5
router ospf 2
router-id 2.2.2.2
log-adjacency-changes
area 1 virtual-link 10.0.0.10
network 10.0.0.2 0.0.0.0 area 0
network 10.0.0.9 0.0.0.0 area 1
network 150.2.2.2 0.0.0.0 area 0

R3#**show running-config | section ospf**
ip ospf authentication message-digest
ip ospf message-digest-key 1 md5 CCNP2011
router ospf 3
router-id 3.3.3.3
log-adjacency-changes
area 2 virtual-link 3.3.3.3
area 2 virtual-link 2.2.2.2
network 10.0.0.6 0.0.0.0 area 1
network 10.0.0.10 0.0.0.0 area 1
network 10.0.0.13 0.0.0.0 area 2
network 150.3.3.3 0.0.0.0 area 2

To resolve this issue, implement the following configurations on these three routers:

R1(config-router)#**router ospf 1**

https://t.me/learningnets

R1(config-router)#**no area 1 virtual-link 10.0.0.6**
R1(config-router)#**area 1 virtual-link 3.3.3.3**

R2(config)#**router ospf 2**
R2(config-router)#**no area 1 virtual-link 10.0.0.10**
R2(config-router)#**area 1 virtual-link 3.3.3.3**

R3(config)#**router ospf 3**
R3(config-router)#**no area 2 virtual-link 2.2.2.2**
R3(config-router)#**no area 2 virtual-link 3.3.3.3**
R3(config-router)#**area 1 virtual-link 2.2.2.2**
R3(config-router)#**area 1 virtual-link 1.1.1.1**

Solution # 3

The issue is the local PBR configuration, which is sending any ICMP packets originated by R4 to the Null0 interface - effectively sink-holing this type of traffic:

R4#**show ip policy**
Interface Route map
local LOCAL

R4#**show route-map LOCAL**
route-map LOCAL, permit, sequence 10
Match clauses:
ip address (access-lists): 100
Set clauses:
ip precedence immediate
interface Null0
Policy routing matches: 10 packets, 1040 bytes
route-map LOCAL, deny, sequence 20
Match clauses:
Set clauses:
Policy routing matches: 0 packets, 0 bytes

R4#**show ip access-lists 100**
Extended IP access list 100
10 permit icmp any any (10 matches)

To resolve this issue, remove the incorrect NEXT_HOP configuration from R4s PBR policy:

4(config)#**route-map LOCAL permit 10**
R4(config-route-map)#**no set interface null 0**

https://t.me/learningnets

Technet24

https://t.me/learningnets

CCNP Lab 096: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

You have received a call from Level 1 stating that following some configuration changes, the OSPF neighbor adjacency between R1 and R2 has failed. Troubleshoot and resolve this issue.

Trouble Ticket # 2

https://t.me/learningnets

You have received a call from Level 1 stating that following some basic network configuration changes, the OSPF adjacency between R2 and R3 is down. Troubleshoot and resolve this issue.

Trouble Ticket # 3

You have received a call from Level 1 stating that the OSPF adjacency between R3 and R4 is down. Troubleshoot and resolve this issue.

Trouble Ticket # 4

You have received a call from Level 1 stating that there is intermittent connectivity between the 150.1.1.0/24 and 150.2.2.0/24 subnets and the 150.4.4.0/24 subnet. Due to a current configuration freeze on R3, Management allows you to only make changes to ONE device. With this restriction in mind, troubleshoot and resolve this issue.

Lab Solutions

Solution # 1

The issue is that there is no clocking on the WAN link between R1 and R2:

R1#**show controllers serial 0/0**
Interface Serial0/0
Hardware is PowerQUICC MPC860
DCE V.35, no clock

R2#**show controllers serial 0/0**
Interface Serial0/0
Hardware is PowerQUICC MPC860
DTE V.35 clocks stopped.

To resolve this issue, configure clocking on R1s WAN interface:

R1(config)#**interface serial 0/0**
R1(config-if)#**clock rate 2000000**

Solution # 2

The issue here is that there is an MTU mismatch between R2 and R3:

R2#**show running-config interface serial 0/1**
Building configuration...

Current configuration : 95 bytes
!
interface Serial0/1
ip address 10.0.0.9 255.255.255.252
ip mtu 1492

https://t.me/learningnets

Technet24

```
ip ospf 2 area 1
end
```

R3#**show running-config interface serial 1/1**

```
Building configuration...

Current configuration : 102 bytes
!
interface Serial1/1
ip address 10.0.0.10 255.255.255.252
ip ospf 3 area 1
clock rate 128000
end
```

To resolve this issue, you can do one of the following:

- Apply the same configuration to R3s WAN interface
- Remove this configuration on R2s WAN interface

This solution shows the latter of the acceptable solutions:

R2(config)#**interface serial 0/0**
R2(config-if)#**no ip mtu 1492**

Solution # 3

The issue here is that the interface configuration on R4 has been applied to the wrong interface. While R4 is connected to R3 via Serial 0/0, the configuration has been applied to Serial 0/1:

R4#**show running-config interface serial 0/1**

```
Building configuration...

Current configuration : 83 bytes
!
interface Serial0/1
ip address 10.0.0.14 255.255.255.252
ip ospf 4 area 2
end
```

To resolve this issue, remove this configuration from Serial 0/1 and apply it instead to Serial 0/0:

R4(config)#**default interface serial 0/1**

```
Building configuration...

Interface Serial0/1 set to default configuration
```

https://t.me/learningnets

R4(config)#**interface serial 0/0**
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**ip ospf 4 area 2**
R4(config-if)#**exit**

Solution # 4

The issue here is that the configuration applied to R2 causes a recursive routing issue because the tunnel source address is learned via the tunnel interface itself:

R2#**show running-config interface loopback 0**
Building configuration...

Current configuration : 81 bytes
!
interface Loopback0
ip address 2.2.2.2 255.255.255.255
ip ospf 2 area 0
end

This can be validated by looking at the contents of the routing table on R3:

R3#**show ip route 2.2.2.2 255.255.255.255**
Routing entry for 2.2.2.2/32
Known via "ospf 3", distance 110, metric 11112, type intra area
Last update from 192.168.1.2 on Tunnel0, 00:00:02 ago
Routing Descriptor Blocks:
*** 192.168.1.2, from 2.2.2.2, 00:00:02 ago, via Tunnel0**
Route metric is 11112, traffic share count is 1

Given this issue, if logging was enabled, you would see the following printed on the console:

R3(config)#**logging console**
R3(config)#
*Jul 10 04:34:34.091: %OSPF-5-ADJCHG: Process 3, Nbr 2.2.2.2 on Serial1/1 from LOADING to FULL, Loading Done
*Jul 10 04:34:49.955: %LINEPROTO-5-UPDOWN: Line protocol on Interface Tunnel0, changed state to up
*Jul 10 04:34:50.067: %OSPF-5-ADJCHG: Process 3, Nbr 2.2.2.2 on Tunnel0 from LOADING to FULL, Loading Done
***Jul 10 04:34:58.955: %TUN-5-RECURDOWN: Tunnel0 temporarily disabled due to recursive routing**
*Jul 10 04:34:59.955: %LINEPROTO-5-UPDOWN: Line protocol on Interface

https://t.me/learningnets
Technet24

Tunnel0, changed state to down
*Jul 10 04:34:59.955: %OSPF-5-ADJCHG: Process 3, Nbr 2.2.2.2 on Tunnel0 from FULL to DOWN, Neighbor Down: Interface down or detached
*Jul 10 04:35:59.955: %LINEPROTO-5-UPDOWN: Line protocol on Interface Tunnel0, changed state to up
*Jul 10 04:36:00.067: %OSPF-5-ADJCHG: Process 3, Nbr 2.2.2.2 on Tunnel0 from LOADING to FULL, Loading Done
***Jul 10 04:36:08.955: %TUN-5-RECURDOWN: Tunnel0 temporarily disabled due to recursive routing**
*Jul 10 04:36:09.955: %LINEPROTO-5-UPDOWN: Line protocol on Interface Tunnel0, changed state to down
*Jul 10 04:36:09.955: %OSPF-5-ADJCHG: Process 3, Nbr 2.2.2.2 on Tunnel0 from FULL to DOWN, Neighbor Down: Interface down or detached

Recursive routing issues are common when implementing tunneling. It is important to have a solid understanding of routing to avoid these issues. To resolve this issue, assign the Loopback interface to area 1 on R2:

R2(config)#**interface loopback 0**
R2(config-if)#**ip ospf 2 area 1**

https://t.me/learningnets

CCNP Lab 097: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

You have received a call from the ISP indicating that the BGP adjacency between them and your edge router (R1) has gone down. Troubleshoot and resolve this issue.

https://t.me/learningnets

Trouble Ticket # 2

You have received a call from the NOC indicating that users on all the 150.0.3.0/24 subnet are unable to reach the 198.1.1.0/24 subnet. At the moment, depart policy stipulates that IGP configurations cannot be modified until further notice. While adhering to the current restriction, troubleshoot and resolve this issue.

Trouble Ticket # 3

The NOC has called you to advise that after they enable BGP on R4, they failed to establish an adjacency with R3. Troubleshoot and resolve this issue.

Trouble Ticket # 4

You have received notification that users within AS 65500 are unable to reach the 150.4.4.0/24 subnet and vice-versa. Troubleshoot and resolve this issue.

Lab Solutions

Solution # 1

The issue is that the BGP peer IP address has been mis-configured on R2:

R2#**show running-config | include neighbor**
bgp log-neighbor-changes
neighbor 10.0.0.10 remote-as 65500
neighbor 10.0.0.10 next-hop-self
neighbor 201.0.0.1 remote-as 254

To resolve this issue, configure the correct BGP peer IP address on R2:

R2(config)#**router bgp 65500**
R2(config-router)#**no neighbor 201.0.0.1 remote-as 254**
R2(config-router)#**neighbor 210.0.0.1 remote-as 254**

Solution # 2

The issue is that the BGP NEXT_HOP attribute is unchanged when routes are advertised from an iBGP speaker to another iBGP speaker. Therefore, because the 210.0.0.0/30 subnet is unknown to the routers in AS 65500, the 198.1.1.0/24 prefix will be marked as inaccessible. To resolve this issue, while adhering to the restrictions, implement the following on R2:

R2(config)#**router bgp 65500**
R2(config-router)#**neighbor 10.0.0.10 next-hop-self**

Solution # 3

The issue is that there is a BGP password mismatch between R3 and R4:

https://t.me/learningnets

Technet24

R3#**show running-config | section bgp**
router bgp 65500
no synchronization
bgp router-id 3.3.3.3
bgp log-neighbor-changes
network 150.0.3.0 mask 255.255.255.0
neighbor INTERNAL peer-group
neighbor INTERNAL remote-as 65500
neighbor INTERNAL password CCNP2011
neighbor INTERNAL route-reflector-client
neighbor 10.0.0.9 peer-group INTERNAL
neighbor 10.0.0.14 peer-group INTERNAL
no auto-summary

R4#**show running-config | section bgp**
router bgp 65500
no synchronization
bgp router-id 4.4.4.4
bgp log-neighbor-changes
network 150.0.4.0 mask 255.255.255.255
neighbor 10.0.0.13 remote-as 65500
neighbor 10.0.0.13 password CCNP2O11
no auto-summary

This password mis-configuration will cause the following error messages on these routers:

R3#
*Jul 10 05:22:23.507: %TCP-6-BADAUTH: Invalid MD5 digest from 10.0.0.14(32321) to 10.0.0.13(179)
*Jul 10 05:22:25.507: %TCP-6-BADAUTH: Invalid MD5 digest from 10.0.0.14(32321) to 10.0.0.13(179)
*Jul 10 05:22:29.507: %TCP-6-BADAUTH: Invalid MD5 digest from 10.0.0.14(32321) to 10.0.0.13(179)

R4#
*Jul 10 04:01:39.919: %TCP-6-BADAUTH: Invalid MD5 digest from 10.0.0.13(14756) to 10.0.0.14(179)
*Jul 10 04:01:43.919: %TCP-6-BADAUTH: Invalid MD5 digest from 10.0.0.13(14756) to 10.0.0.14(179)
*Jul 10 04:01:51.919: %TCP-6-BADAUTH: Invalid MD5 digest from

https://t.me/learningnets

10.0.0.13(14756) to 10.0.0.14(179)

To resolve this issue, configure the correct password on R4:

R4(config)#**router bgp 65500**
R4(config-router)#**neighbor 10.0.0.13 password CCNP2011**

Solution # 4

The issue is that the BGP **network** command configured on R4 is incorrect:

R4#**show running-config | section bgp**
router bgp 65500
no synchronization
bgp router-id 4.4.4.4
bgp log-neighbor-changes
network 150.0.4.0 mask 255.255.255.255
neighbor 10.0.0.13 remote-as 65500
no auto-summary

To resolve this issue, configure the correct **network** statement under BGP:

4(config)#**router bgp 65500**
R4(config-router)#**no network 150.0.4.0 mask 255.255.255.255**
R4(config-router)#**network 150.0.4.0 mask 255.255.255.255**

https://t.me/learningnets

Technet24

CCNP Lab 098: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

You have configured BGP on R1 and R2 and notice that the adjacency is not established. Troubleshoot and resolve this issue.

https://t.me/learningnets

Technet24

Trouble Ticket # 2

You have received a call from the NOC stating that they are unable to reach the 198.1.1.0/24 subnet from the 150.3.3.0/24 subnet. Troubleshoot and resolve this issue.

Trouble Ticket # 3

You have received complaints stating that users connected to the 150.3.3.0/24 subnet are not able to communicate with users on the 150.2.2.0/24 subnet. Troubleshoot and resolve this.

Trouble Ticket # 4

The NOC has called you to advise that the 150.4.4.0/24 subnet is only able to reach devices on the 150.3.3.0/24 subnet, but nothing else. Troubleshoot and resolve this issue.

Lab Solutions

Solution # 1

When configuring indirectly connected external BGP peers, you need to modify the IP TTL of the BGP packets using the **neighbor <address> ebgp-multihop <1-254>** command:

R1#**show running-config | section bgp**
router bgp 254
no synchronization
bgp router-id 1.1.1.1
bgp log-neighbor-changes
network 198.1.1.0
neighbor 2.2.2.2 remote-as 65500
neighbor 2.2.2.2 update-source Loopback0
no auto-summary

R2#**show running-config | section bgp**
router bgp 65500
no synchronization
bgp router-id 2.2.2.2
bgp log-neighbor-changes
network 150.0.2.0 mask 255.255.255.0
neighbor 1.1.1.1 remote-as 254
neighbor 1.1.1.1 update-source Loopback0
neighbor 10.0.0.10 remote-as 65500
neighbor 10.0.0.10 route-map NEXT_HOP out

https://t.me/learningnets

no auto-summary

To resolve this issue, implement the following configuration on R1 and R2:

R1(config)#**router bgp 254**
R1(config-router)#**neighbor 2.2.2.2 ebgp-multihop 2**

R2(config)#**router bgp 65500**
R2(config-router)#**neighbor 1.1.1.1 ebgp-multihop 2**

NOTE: You do NOT have to specify a value of '2' with this command to resolve this issue.

Solution # 2

The issue is that the outbound route-map configured on R2 is incorrect as it specifies a NEXT_HOP address of R3 instead of R2 for all advertised BGP prefixes:

R2#**show route-map**
route-map NEXT_HOP, permit, sequence 10
Match clauses:
Set clauses:
ip next-hop 10.0.0.10
Policy routing matches: 0 packets, 0 bytes

To resolve this issue, implement the following configuration on R2:

R2(config)#**route-map NEXT_HOP permit 10**
R2(config-route-map)#**no set ip next-hop 10.0.0.10**
R2(config-route-map)#**set ip next-hop 10.0.0.9**

Solution # 3

The issue is that the FastEthernet0/0 interface on R2 is shut down, which prevents this subnet from being advertised by R2 via BGP:

R2#**show interfaces fastethernet 0/0**
FastEthernet0/0 is administratively down, line protocol is down
Hardware is AmdFE, address is 000d.289e.f940 (bia 000d.289e.f940)
Internet address is 150.0.2.2/24
MTU 1500 bytes, BW 100000 Kbit/sec, DLY 100 usec,
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation ARPA, loopback not set
Keepalive set (10 sec)
Auto-duplex, Auto Speed, 100BaseTX/FX

[Truncated Output]

To resolve this issue, simply bring up the FastEthernet0/0 interface:

https://t.me/learningnets

Technet24

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**no shutdown**

Solution # 4

The issue arises from the fact that R3 is not configured as a route reflector for R2 and R4:

R3#**show running-config | section bgp**
router bgp 65500
no synchronization
bgp router-id 3.3.3.3
bgp log-neighbor-changes
network 150.0.3.0 mask 255.255.255.0
neighbor 10.0.0.9 remote-as 65500
neighbor 10.0.0.9 route-map R2-NEXT-HOP out
neighbor 10.0.0.14 remote-as 65500
neighbor 10.0.0.14 route-map R4-NEXT-HOP out
no auto-summary

To resolve this issue, configure R3 as a route reflector for R2 and R4:

R3(config)#**router bgp 65500**
R3(config-router)#**neighbor 10.0.0.9 route-reflector-client**
R3(config-router)#**neighbor 10.0.0.14 route-reflector-client**

https://t.me/learningnets

CCNP Lab 099: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

You have received a call stating that users connected to the 172.16.1.0/24 subnet are unable to reach devices connected to the 150.4.4.0/24 subnet. Troubleshoot and resolve this issue.

https://t.me/learningnets

Trouble Ticket # 2

You have received multiple complaints from the users on the 172.16.1.0/24 subnet that they commonly experience poor connectivity to a Web server with the IP address 150.4.4.254/24. Troubleshoot and resolve this issue.

Trouble Ticket # 3

Cisco IOS DHCP server has been configured on R3 to service clients located on the 150.4.4.0/24 subnet. However, you receive complaints that clients located on this subnet are unable to acquire IP addresses. Troubleshoot and resolve this issue.

Lab Solutions

Solution # 1

There are multiple issues that need to be addressed to resolve this problem: the first issue is that R1 has no routing (reachability) information for this subnet:

R1#**show ip route**
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

172.16.0.0/24 is subnetted, 1 subnets
C 172.16.1.0 is directly connected, FastEthernet0/0
10.0.0.0/30 is subnetted, 1 subnets
C 10.0.0.0 is directly connected, Serial0/0

The second issue is that the NAT configuration on R2 is incorrect in that NAT is applied to the FastEthernet interface instead of the Dialer interface:

R2#**show ip nat statistics**
Total active translations: 0 (0 static, 0 dynamic; 0 extended)
Outside interfaces:
FastEthernet0/0
Inside interfaces:
Serial0/0
Hits: 22 Misses: 3
CEF Translated packets: 25, CEF Punted packets: 0

https://t.me/learningnets
Technet24

Expired translations: 2
Dynamic mappings:
-- Inside Source
[Id: 3] access-list 100 interface FastEthernet0/0 refcount 0
Appl doors: 0
Normal doors: 0
Queued Packets: 0

And finally, the third issue that is causing this problem is that R2 is not advertising the 150.2.2.0/24 subnet, or even a default route, to router R4:

R3#**show running-config | section eigrp**
router eigrp 1
network 10.0.0.13 0.0.0.0
no auto-summary

To resolve the first issue, perform one of the following actions:

- Manually configure a static route on R1 pointing to R2
- Advertise a default route dynamically via OSPF on R2

The solution below shows the latter option:

R2(config)#**router ospf 2**
R2(config-router)#**default-information originate**
To resolve the second issue, reconfigure NAT on R2 as follows:

R2(config)#**no ip nat inside source list 100 interface fastethernet0/0 over**
R2(config)#**ip nat inside source list 100 interface Dialer1 overload**
R2(config)#**interface dialer 1**
R2(config-if)#**ip nat outside**
R2(config-if)#**interface fastethernet 0/0**
R2(config-if)#**no ip nat outside**

To resolve the third issue, perform one of the following actions on R3:

- Advertise the 150.2.2.0/24 subnet via EIGRP so R4 knows about this subnet
- Redistribute the 150.2.20/24 subnet into EIGRP so R4 knows about this subnet

The solution below shows the latter option:

R3(config)#**router eigrp 1**
R3(config-router)#**redistribute connected**

https://t.me/learningnets

Solution # 2

While you may not have the hosts to perform such testing, from the description, you should be able to determine that this is a TCP issue - primarily due to MTU issues with the PPPoE implementation. MTU issues are a common cause for Layer 3 issues when using PPPoE. When a client attempts to connect to a web site, for example, the MTU size is negotiated during session negotiation between the client and the server. Typically the client and server negotiate an MTU of 1500 bytes (Ethernet). To resolve this, you can use one of the following solutions:

- Adjust the workstation Maximum MTU Value
- Adjust the TCP MSS Size on the DSL Router

On the Cisco router, you can change the TCP MSS size via the **ip tcp adjust-mss <size>** interface configuration command. This command is used to specify maximum segment size (MSS) for transient packets that traverse a router, specifically TCP segments in the SYN bit set, when PPP over Ethernet (PPPoE) is being used in the network.

This command helps prevent TCP sessions from being dropped by adjusting the MSS value of the TCP SYN packets. It is effective only for TCP connections passing through the router. In most cases, the optimum value for the max-segment-size argument is 1452 bytes. This value plus the 20-byte IP header, the 20-byte TCP header, and the 8-byte PPPoE header add up to a 1500-byte packet that matches the MTU size for the Ethernet link.

It is important to remember that the TCP MSS command must specify a value of 1452 and not 1492, which is specified using the **ip mtu <size>** interface configuration command. To resolve this issue, implement the following configuration on R2:

R2(config)#**interface serial 0/0**
R2(config-if)#**ip tcp adjust-mss 1452**

Solution # 3

The issue is that R4 has been configured to NOT forward DHCP packets:

R4#**show running-config | include forward**
ip forward-protocol nd
no ip forward-protocol udp bootps

To resolve this issue, implement the following configuration on R4:

R4(config)#**ip forward-protocol udp bootps**

https://t.me/learningnets

Technet24

https://t.me/learningnets

CCNP Lab 100: Troubleshooting Lab

Lab Objective:

The focus of this lab is to hone your trouble isolation and resolution skills. This lab will include Layer 2 and Layer 3 technologies which fall within the scope of the current CCNP curriculum.

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please download and paste the troubleshooting lab configurations. If you are using your own rack or lab, please modify this configuration to reflect the actual interface types, etc, that you have on your devices. Prior to beginning all labs, apply the pre-lab configuration for each individual device.

When completing these labs, it is important to resolve the trouble tickets in the order in which they are listed because they build on each other. For example, if you begin with Trouble Ticket # 3, you might not get the expected resolution or result if you have not completed Trouble Ticket # 1 and Trouble Ticket # 2. It is very important to follow the order listed.

Trouble Ticket # 1

Your co-worker has advised that after some configuration changes were made, they are now no longer able to reach any devices on the 3FFE:1111:1111:1111::/64 subnet from R2. Troubleshoot and resolve this issue.

Trouble Ticket # 2

https://t.me/learningnets

Your co-worker has completed configuring MP-BGP on R2 and R3; however, they are unable to get the adjacency to be established. Troubleshoot and resolve this issue.

Trouble Ticket # 3

You have received a problem report that Level 1 is unable to reach the 3FFE:1111:1111:1111::/64 subnet from R3. Troubleshoot and resolve this issue.

Trouble Ticket # 4

You have received a problem report that the OSPF adjacency between R3 and R4 has gone down following some routine changes and will not re-establish. Troubleshoot and resolve.

Lab Solutions

Solution # 1

The issue is that RIPng has been configured to use different IPv6 Multicast groups:

R1#**show running-config | section ipv6 router**
ipv6 router rip CCNP2011
port 521 multicast-group FF02::8

R2#**show running-config | section ipv6 router**
ipv6 router rip CCNP2011
redistribute connected metric 2
redistribute bgp 254 metric 2 include-connected

To resolve this issue, remove the configuration applied to R1 or implement the same configuration applied to R1 on R2. The solution below shows the former option:

R1(config)#**ipv6 router rip CCNP2011**
R1(config-rtr)#**no port 521 multicast-group FF02::8**

Solution # 2

The issue is that MP-BGP still requires an IPv4 RID. Because there are no interfaces configured with an IPv4 address, you must manually configure the MP-BGP RID:

R2#**show running-config | section bgp**
router bgp 254
no bgp default ipv4-unicast
bgp log-neighbor-changes
neighbor 2001:1111:1111:2222::3 remote-as 254

R3#**show running-config | section bgp**
router bgp 254
no bgp default ipv4-unicast

https://t.me/learningnets

Technet24

bgp log-neighbor-changes
neighbor 2001:1111:1111:2222::2 remote-as 254

To resolve this, manually configure a RID under MP-BGP on both R2 and R3:

R2(config)#**router bgp 254**
R2(config-router)#**bgp router-id 2.2.2.2**

R3(config)#**router bgp 254**
R3(config-router)#**bgp router-id 3.3.3.3**

Solution # 3

The issue is that the default route advertised via RIPng (from R1 to R2) is not automatically redistributed into MP-BGP. Instead, MP-BGP must be configured to advertise a default - allowing R3 to reach the 3FFE:1111:1111:1111::/64 subnet. To resolve this issue, you should implement the following configuration on R2:

R2(config)#**router bgp 254**
R2(config-router)#**address-family ipv6**
R2(config-router-af)#**neighbor 2001:1111:1111:2222::3 default-originate**

Solution # 4

The issue is that the Serial0/0 interface has been assigned to the incorrect OSPF area:

R4#**show running-config interface serial 0/0**
Building configuration...

Current configuration : 102 bytes
!
interface Serial0/0
no ip address
ipv6 address 2001:1111:1111:4444::4/64
ipv6 ospf 4 area 1
end

To resolve this issue, assign the Serial0/0 interface to the correct OSPF area:

R4(config-if)#**interface serial 0/0**
R4(config-if)#**ipv6 ospf 4 area 0**

https://t.me/learningnets

CCNP Lab 101: EIGRP and OSPF VRF Lite Lab

Lab Objective:

The focus of this lab is to understand Virtual Routing and Forwarding Lite implementation and verification in Cisco IOS Software using EIGRP and OSPF. Additional technologies tested also include VRF-aware Network Address Translation (NAT).

Lab Topology:

The lab network topology is illustrated below:

https://t.me/learningnets

Technet24



IMPORTANT NOTE

If you are using the www.101labs.net racks, please bring up the LAN interfaces connected to the routers by issuing the **no shutdown** command on the connected switches. If you are using a home lab with no Switches, you can bring up the LAN interfaces using the following configurations on your routers:

interface fastethernet 0/0
no keepalive
loopback
no shutdown

Alternately, you can simply connect the interfaces to a hub or switch if you have one available in your own lab.

Task 1

Configure hostnames, IP addressing on all routers as illustrated in the network topology.

Task 2

Configure the following VRFs on the devices in the network:

- R1: VRF Name - VRFONE: RD - 100:100

https://t.me/learningnets

- R2: VRF Name - VRFTWO: RD - 200:200
- R3: VRF Name - VRFONE: RD - 100:100
- R3: VRF Name - VRFTWO: RD - 200:200
- R4: VRF Name - VRFONE: RD - 100:100
- R4: VRF Name - VRFTWO: RD - 200:200

Verify your configuration using the appropriate commands:

Task 3

Configure EIGRP using AS 254 on R1 and assign interface Serial0/1 and LAN interfaces to VRF VRFONE. Verify your configuration using the appropriate commands.

Task 4

Configure OSPF on R2 and assign interface Serial0/1 and LAN interfaces to VRF VRFTWO. Verify your configuration using the appropriate commands.

Task 5

Configure EIGRP and OSPF for VRFONE and VRFTWO on R3. Verify your configuration using the appropriate commands.

Task 6

Configure EIGRP and OSPF for VRFONE and VRFTWO on R4. Verify your configuration using the appropriate commands.

Task 7

Configure two additional Loopback interfaces on R4 as follows:

- Loopback 100: IP Address 100.4.4.4/32 - VRF: VRFONE
- Loopback 200: IP Address 100.4.4.4/32 - VRF: VRFTWO

Do NOT advertise these Loopbacks via OSPF or EIGRP. However, ensure that R4 is able to ping the 150.1.1.0/24 subnet in VRFONE from the Loopback100 interface and R4 is able to ping the 150.2.2.0/24 subnet in VRFTWO from the Loopback200 interface.

Lab Validation:

Task 1

Please refer to previous labs for basic IPv4 addressing and hostname configuration. This will not be included in this section to avoid being redundant.

Task 2

https://t.me/learningnets

Technet24

In Cisco IOS software, the configuration of VRF Lite is a simple and straightforward task. First, the VRF name must be defined using the **ip vrf [name]** global configuration command. Next, a route distinguisher is assigned to the VRF using the **rd [route distinguisher]** VRF configuration command. The route distinguisher is used to identify the VPN and is used to distinguish multiple VPN routes that have an identical prefix. The route distinguisher can be configured using either ASN:nn or IP-address:nn format.

NOTE: The n simply represents an integer. You can use specify one integer or two integers.

This task is completed on all routers as follows:

R1(config)#**ip vrf VRFONE**
R1(config-vrf)#**rd 100:100**
R1(config-vrf)#**exit**

R2(config)#**ip vrf VRFTWO**
R2(config-vrf)#**rd 200:200**
R2(config-vrf)#**exit**

R3(config)#**ip vrf VRFONE**
R3(config-vrf)#**rd 100:100**
R3(config-vrf)#**exit**
R3(config)#**ip vrf VRFTWO**
R3(config-vrf)#**rd 200:200**
R3(config-vrf)#**exit**

R4(config)#**ip vrf VRFONE**
R4(config-vrf)#**rd 100:100**
R4(config-vrf)#**exit**
R4(config)#**ip vrf VRFTWO**
R4(config-vrf)#**rd 200:200**
R4(config-vrf)#**exit**

Following this, verify your solution using the **show ip vrf** command on all routers:

R1#**show ip vrf**
Name Default RD Interfaces

R2#**show ip vrf**
Name Default RD Interfaces
VRFTWO 200:200

R3#**show ip vrf**
Name Default RD Interfaces
VRFONE 100:100

https://t.me/learningnets

VRFTWO 200:200

R4#**show ip vrf**
Name Default RD Interfaces
VRFONE 100:100
VRFTWO 200:200

Task 3

The requirements for this task are straightforward. For EIGRP and RIPv2, VRF configuration is implemented using the **address-family ipv4 vrf [name]** router configuration command. In addition, for EIGRP, the **autonomous-system [number]** VRF configuration subcommand must be used to specify the autonomous system number. Static routes for each VRF can be configured using the **ip route vrf [prefix] [mask] [interface | address]** global configuration command. This task is completed as follows:

R1(config)#**interface fastethernet 0/0**
R1(config-if)#**ip vrf forwarding VRFONE**
% Interface FastEthernet0/0 IP address 150.1.1.1 removed due to enabling VRF VRFONE
R1(config-if)#**ip address 150.1.1.1 255.255.255.0**
R1(config-if)#**exit**
R1(config)#**interface serial 0/1**
R1(config-if)#**ip vrf forwarding VRFONE**
% Interface Serial0/1 IP address 10.0.0.5 removed due to enabling VRF VRFONE
R1(config-if)#**ip address 10.0.0.5 255.255.255.252**
R1(config-if)#**exit**
R1(config)#**router eigrp 1**
R1(config-router)#**address-family ipv4 vrf VRFONE**
R1(config-router-af)#**network 150.1.1.1 0.0.0.0**
R1(config-router-af)#**network 10.0.0.5 0.0.0.0**
R1(config-router-af)#**no auto-summary**
R1(config-router-af)#**autonomous-system 254**
R1(config-router-af)#**exit**

Verify your configuration using the **show ip eigrp vrf <name>** commands:

R1#**show ip eigrp vrf VRFONE interfaces**
IP-EIGRP interfaces for process 254
Xmit Queue Mean Pacing Time Multicast Pending
Interface Peers Un/Reliable SRTT Un/Reliable Flow Timer Routes
Se0/1 0 0/0 0 0/1 0 0
Fa0/0 0 0/0 0 0/1 0 0

https://t.me/learningnets
Technet24

Task 4

The requirements for this task are straightforward. In Cisco IOS software VRF Lite using OSPF is configured using the **router ospf [process ID] vrf [name]** global configuration command followed by the **capability vrf-lite** router configuration command. The remainder of the configuration, e.g. **network** statements, is performed in a similar manner to when VRF Lite is not being used. This task is completed as follows:

R2(config)#**interface fastethernet 0/0**
R2(config-if)#**ip vrf forwarding VRFTWO**
% Interface FastEthernet0/0 IP address 150.2.2.2 removed due to enabling VRF VRFTWO
R2(config-if)#**ip address 150.2.2.2 255.255.255.0**
R2(config-if)#**exit**
R2(config)#**interface serial 0/1**
R2(config-if)#**ip vrf forwarding VRFTWO**
% Interface Serial0/1 IP address 10.0.0.9 removed due to enabling VRF VRFTWO
R2(config-if)#**ip address 10.0.0.9 255.255.255.252**
R2(config-if)#**exit**
R2(config)#**router ospf 2**
R2(config-router)#**exit**
R2(config)#**router ospf 2 vrf VRFTWO**
R2(config-router)#**capability vrf-lite**
R2(config-router)#**router-id 2.2.2.2**
R2(config-router)#**network 150.2.2.2 0.0.0.0 area 0**
R2(config-router)#**network 10.0.0.9 0.0.0.0 area 0**
R2(config-router)#**exit**

Verify your configuration using the **show ip ospf** commands:

R2#**show ip ospf interface brief**
Interface PID Area IP Address/Mask Cost State Nbrs F/C
Se0/1 2 0 10.0.0.9/30 64 P2P 0/0
Fa0/0 2 0 150.2.2.2/24 1 DR 0/0

Task 5

The requirements of this task are straightforward. Following the same logic used in the previous tasks, this task is completed as follows:

R3(config)#**interface serial 1/0**
R3(config-if)#**ip vrf forwarding VRFONE**
% Interface Serial1/0 IP address 10.0.0.6 removed due to enabling VRF VRFONE

https://t.me/learningnets

R3(config-if)#**ip address 10.0.0.6 255.255.255.252**
R3(config-if)#**exit**
R3(config)#**interface serial 1/1**
R3(config-if)#**ip vrf forwarding VRFTWO**
% Interface Serial1/1 IP address 10.0.0.10 removed due to enabling VRF VRFTWO
R3(config-if)#**ip address 10.0.0.10 255.255.255.252**
R3(config-if)#**exit**
R3(config)#**interface serial 1/2**
R3(config-if)#**ip vrf forwarding VRFONE**
% Interface Serial1/2 IP address 10.0.0.13 removed due to enabling VRF VRFONE
R3(config-if)#**ip address 10.0.0.13 255.255.255.252**
R3(config-if)#**exit**
R3(config)#**interface serial 1/3**
R3(config-if)#**ip vrf forwarding VRFTWO**
% Interface Serial1/3 IP address 10.0.0.17 removed due to enabling VRF VRFTWO
R3(config-if)#**ip address 10.0.0.17 255.255.255.252**
R3(config-if)#**exit**
R3(config)#**router eigrp 1**
R3(config-router)#**address-family ipv4 vrf VRFONE**
R3(config-router-af)#**no auto-summary**
R3(config-router-af)#**network 10.0.0.6 0.0.0.0**
R3(config-router-af)#**network 10.0.0.13 0.0.0.0**
R3(config-router-af)#**autonomous-system 254**
R3(config-router-af)#**exit**
R3(config-router)#**exit**
R3(config)#**router ospf 3 vrf VRFTWO**
R3(config-router)#**capability vrf-lite**
R3(config-router)#**router-id 3.3.3.3**
R3(config-router)#**network 10.0.0.10 0.0.0.0 area 0**
R3(config-router)#**network 10.0.0.17 0.0.0.0 area 0**
R3(config-router)#**exit**

Verify your EIGRP configuration using the **show ip eigrp vrf <name>** commands:

R3#**show ip eigrp vrf VRFONE interfaces**
IP-EIGRP interfaces for process 254
Xmit Queue Mean Pacing Time Multicast Pending
Interface Peers Un/Reliable SRTT Un/Reliable Flow Timer Routes
Se1/0 1 0/0 9 5/190 226 0
Se1/2 0 0/0 0 5/5 0 0

https://t.me/learningnets
Technet24

R3#**show ip eigrp vrf VRFONE neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.5 Se1/0 11 00:03:07 9 1140 0 3

Verify your configuration using the **show ip ospf** commands:

R3#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
2.2.2.2 0 FULL/ - 00:00:31 10.0.0.9 Serial1/1

Task 6

Following the same logic applied in previous tasks, this task is completed as follows:

R4(config)#**interface serial 0/0**
R4(config-if)#**ip vrf forwarding VRFONE**
% Interface Serial0/0 IP address 10.0.0.14 removed due to enabling VRF VRFONE
R4(config-if)#**ip address 10.0.0.14 255.255.255.252**
R4(config-if)#**exit**
R4(config)#**interface serial 0/1**
R4(config-if)#**ip vrf forwarding VRFTWO**
% Interface Serial0/1 IP address 10.0.0.18 removed due to enabling VRF VRFTWO
R4(config-if)#**ip address 10.0.0.18 255.255.255.252**
R4(config-if)#**exit**
R4(config)#**router eigrp 1**
R4(config-router)#**address-family ipv4 vrf VRFONE**
R4(config-router-af)#**no auto-summary**
R4(config-router-af)#**network 10.0.0.14 0.0.0.0**
R4(config-router-af)#**autonomous-system 254**
R4(config-router-af)#**exit**
R4(config-router)#**exit**
R4(config)#**router ospf 4 vrf VRFTWO**
R4(config-router)#**capability vrf-lite**
R4(config-router)#**router-id 4.4.4.4**
R4(config-router)#**network 10.0.0.18 0.0.0.0 area 0**
R4(config-router)#**exit**

Verify your EIGRP configuration using the **show ip eigrp vrf <name>** commands:

R4#**show ip eigrp vrf VRFONE interfaces**
IP-EIGRP interfaces for process 254

https://t.me/learningnets

Xmit Queue Mean Pacing Time Multicast Pending
Interface Peers Un/Reliable SRTT Un/Reliable Flow Timer Routes
Se0/0 1 0/0 23 0/15 127 0

R4#**show ip eigrp vrf VRFONE neighbors**
IP-EIGRP neighbors for process 254
H Address Interface Hold Uptime SRTT RTO Q Seq
(sec) (ms) Cnt Num
0 10.0.0.13 Se0/0 13 00:02:19 23 200 0 8

Verify your configuration using the **show ip ospf** commands:

R4#**show ip ospf neighbor**

Neighbor ID Pri State Dead Time Address Interface
3.3.3.3 0 FULL/ - 00:00:39 10.0.0.17 Serial0/1

At this point, verify VRF routing tables using the **show ip route vrf <name>** command:

R1#**show ip route vrf VRFONE**

Routing Table: VRFONE
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 2 subnets
D 10.0.0.12 [90/21024000] via 10.0.0.6, 00:10:26, Serial0/1
C 10.0.0.4 is directly connected, Serial0/1
150.1.0.0/24 is subnetted, 1 subnets
C 150.1.1.0 is directly connected, FastEthernet0/0

R2#**show ip route vrf VRFTWO**

Routing Table: VRFTWO
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route

https://t.me/learningnets

Technet24

o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.8 is directly connected, Serial0/1
O 10.0.0.16 [110/845] via 10.0.0.10, 00:03:18, Serial0/1
150.2.0.0/24 is subnetted, 1 subnets
C 150.2.2.0 is directly connected, FastEthernet0/0

R3#**show ip route vrf VRFONE**

Routing Table: VRFONE
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.12 is directly connected, Serial1/2
C 10.0.0.4 is directly connected, Serial1/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/20514560] via 10.0.0.5, 00:10:49, Serial1/0

R3#**show ip route vrf VRFTWO**

Routing Table: VRFTWO
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.8 is directly connected, Serial1/1
C 10.0.0.16 is directly connected, Serial1/3
150.2.0.0/24 is subnetted, 1 subnets

https://t.me/learningnets

O 150.2.2.0 [110/782] via 10.0.0.9, 00:03:29, Serial1/1

R4#**show ip route vrf VRFONE**

Routing Table: VRFONE
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 2 subnets
C 10.0.0.12 is directly connected, Serial0/0
D 10.0.0.4 [90/21024000] via 10.0.0.13, 00:04:15, Serial0/0
150.1.0.0/24 is subnetted, 1 subnets
D 150.1.1.0 [90/21026560] via 10.0.0.13, 00:04:15, Serial0/0

R4#**show ip route vrf VRFTWO**

Routing Table: VRFTWO
Codes: C - connected, S - static, R - RIP, M - mobile, B - BGP
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
E1 - OSPF external type 1, E2 - OSPF external type 2
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
ia - IS-IS inter area, * - candidate default, U - per-user static route
o - ODR, P - periodic downloaded static route

Gateway of last resort is not set

10.0.0.0/30 is subnetted, 2 subnets
O 10.0.0.8 [110/845] via 10.0.0.17, 00:03:39, Serial0/1
C 10.0.0.16 is directly connected, Serial0/1
150.2.0.0/24 is subnetted, 1 subnets
O 150.2.2.0 [110/846] via 10.0.0.17, 00:03:39, Serial0/1

Task 7

Simply because we have introduced VRF Lite into the network does not mean that the basic or core fundamentals do not apply. If VRF Lite was not used, we would use NAT to complete this task. Fortunately, Cisco IOS NAT is VRF-aware. This task is therefore completed as follows:

https://t.me/learningnets

Technet24

R4(config)#**interface loopback 100**
R4(config-if)#**ip vrf forwarding VRFONE**
R4(config-if)#**ip address 100.4.4.4 255.255.255.255**
R4(config-if)#**ip nat inside**
R4(config-if)#**exit**
R4(config)#**interface loopback 200**
R4(config-if)#**ip vrf forwarding VRFTWO**
R4(config-if)#**ip address 100.4.4.4 255.255.255.255**
R4(config-if)#**ip nat inside**
R4(config-if)#**exit**
R4(config)#**interface serial 0/0**
R4(config-if)#**ip nat outside**
R4(config-if)#**exit**
R4(config)#**interface serial 0/1**
R4(config-if)#**ip nat outside**
R4(config-if)#**exit**
R4(config)#**access-list 100 permit ip host 100.4.4.4 any**
R4(config)#**$de source list 100 interface serial 0/0 vrf VRFONE overload**
R4(config)#**$de source list 100 interface serial 0/1 vrf VRFTWO overload**

Following this configuration, test VRFONE NAT by pinging 150.1.1.1 from R4s Loopback100:

R4#**ping vrf VRFONE 150.1.1.1 source loopback 100**

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.1.1.1, timeout is 2 seconds:
Packet sent with a source address of 100.4.4.4
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

Verify VRFONE NAT translations using the **show ip nat translations** command:

R4#**show ip nat translations vrf VRFONE verbose**
Pro Inside global Inside local Outside local Outside global
icmp 10.0.0.14:1 100.4.4.4:1 150.1.1.1:1 150.1.1.1:1
create 00:00:20, use 00:00:20 timeout:60000, left 00:00:39, Map-Id(In): 1,
flags:
extended, use_count: 0, VRF : VRFONE, entry-id: 1, lc_entries: 0

Next, test VRFONE NAT by pinging 150.2.2.2 from R4s Loopback100:

R4#**ping vrf VRFTWO 150.2.2.2 source loopback 200**

https://t.me/learningnets

Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 150.2.2.2, timeout is 2 seconds:
Packet sent with a source address of 100.4.4.4
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 28/30/32 ms

Finally, verify VRFTWO NAT operation using the **show ip nat translations** command:

R4#**show ip nat translations vrf VRFTWO verbose**
Pro Inside global Inside local Outside local Outside global
icmp 10.0.0.18:3 100.4.4.4:3 150.2.2.2:3 150.2.2.2:3
create 00:00:09, use 00:00:09 timeout:60000, left 00:00:50, Map-Id(In): 2,
flags:
extended, use_count: 0, VRF : VRFTWO, entry-id: 3, lc_entries: 0

https://t.me/learningnets